



National Electrical Contractors Association

# Manual of Labor Units 2015-2016



© 2015 National Electrical Contractors Association, Inc,  
3 Bethesda Metro Center, Suite 1100, Bethesda, MD 20814  
[www.necanet.org/MLU](http://www.necanet.org/MLU)  
[education@necanet.org](mailto:education@necanet.org)

Printed in the United States of America

This publication, in whole or in part, unless expressly noted, may not be reproduced, stored in a retrieval system or transmitted in any form or by any means, electronic, mechanical, photocopying, recording, or otherwise, without the prior written consent of The National Electrical Contractors Association, Inc.

Within this document, select forms or tables may be replicated to perform the calculations or analysis described within. The permission to reproduce these documents will be noted and copies will be available at [www.necanet.org/MLU](http://www.necanet.org/MLU).

This publication is intended as a reference to assist electrical contractors in identifying the duration of work tasks for the purposes of estimation. NECA makes no warranty to the accuracy of these numbers.

# FOREWORD

The National Electrical Contractors Association (NECA) is the voice of the \$130 billion industry responsible for bringing electrical power, lighting, and communications to buildings and communities across the United States.

NECA members are electrical contractors who work in all aspects of electrical construction. While most qualify as small businesses, large, multi-area electrical contracting firms are also members of the association.

NECA contractors are the technical professionals responsible for the most innovative and safest electrical construction in the U.S. and they hold a high standard for superior performance and are committed to delivering quality results.

The NECA Manual of Labor Units (MLU) has been developed, published and utilized by electrical contractors since 1923. The MLU provides an experience-based reference for estimating the electrical construction labor required to install typical electrical and communications systems. The data is intended to serve as a general guide to the labor necessary for the installation of specified items under the project conditions defined in the manual. The extent of the applicability of the data to any particular project situation is entirely at the discretion of each user.

Selected sections of the manual are reviewed and updated bi-annually estimating experts chosen from among the NECA electrical contractors located across the country. These individuals represent many years of experience in estimating, tracking the applications of labor units to construction projects and the installation of materials for a broad range of conditions and locations. The resulting labor unit determinations represent a national consensus baseline of estimated labor requirements for each item under the conditions stated.

**In each revision of the NECA Manual of Labor Units changes to labor unit data and material listings are indicated with an “X” in the column titled “Rev”.**



# TABLE OF CONTENTS

<b>Introduction to the NECA Manual of Labor Units</b> .....	<b>vii</b>	<b>1</b>
Purpose .....	vii	<b>2</b>
Source of the Data in This Manual .....	vii	<b>3</b>
Arrangement of the Labor Unit Tables .....	vii	<b>3</b>
Electrical Condition of Equipment Covered By These Labor Units.....	vii	<b>4</b>
Additional Information .....	vii	<b>4</b>
<b>Labor Units Defined</b> .....	<b>vii</b>	<b>4</b>
Scope of the Manual of Labor Units .....	viii	<b>5</b>
Items Not Included in Labor Units.....	ix	<b>5</b>
How to Select Basic Labor Units .....	ix	<b>5</b>
Increasing Estimating Accuracy.....	x	<b>5</b>
<b>Adjusting Labor Units for Project Conditions</b> .....	<b>x</b>	<b>6</b>
Description of a Typical Project .....	x	<b>6</b>
Description of Normal Project and Site Conditions.....	x	<b>6</b>
Adjusting Labor for Non-Typical Conditions.....	xi	<b>7</b>
Labor Adjustments Due to Working Conditions .....	xi	<b>7</b>
Labor Adjustments for the Type of Project .....	xi	<b>8</b>
Labor Adjustments Due to Building Height .....	xii	<b>8</b>
Labor Adjustments for Project Sizes .....	xii	<b>8</b>
Labor Adjustments for Hours Worked and Shifts .....	xii	<b>9</b>
Labor Adjustments for Crew Density.....	xii	<b>9</b>
Labor Adjustments for Project Durations .....	xiii	<b>9</b>
Labor Adjustments for Non-Productive Labor .....	xiii	<b>10</b>
Labor Adjustments for Project Location .....	xiii	<b>10</b>
Labor Adjustments for Project Planning and Pre-Planning .....	xiv	<b>10</b>
Labor Adjustments Due to the General Contractor .....	xiv	<b>11</b>
Labor Adjustments for Project Work Schedules.....	xiv	<b>11</b>
Labor Adjustments for Labor Availability .....	xv	<b>12</b>
Labor Adjustments for Other Factors .....	xv	<b>12</b>
Summary of Labor Adjustments .....	xvi	<b>12</b>
NECA Labor Factor Score Sheet .....	xvii	<b>13</b>
<b>Labor Unit Data</b>		
Section 1 – Integrated Building Systems .....	1-1	
Section 2 – Conduit, Raceways, Fittings and Related Items .....	2-1	<b>14</b>
Section 3 – Wire, Cable, Lugs, Terminations, Busway and Bus Duct.....	3-1	
Section 4 – Switchboards, MCC’s, Panelboards, and Power Equipment.....	4-1	
Section 5 – Lighting Fixtures, Poles, Parking Lot Lighting.....	5-1	<b>R</b>
Section 6 – Wiring Devices.....	6-1	
Section 7 – Hazardous Systems.....	7-1	
Section 8 – Grounding and Lightning Protection Systems .....	8-1	

Section 9 – Heating Equipment Connections .....	9-1
Section 10 – Temporary Power and Lighting .....	10-1
Section 11 – Outdoor Overhead and Underground Systems .....	11-1
Section 11 (A) – Outdoor Overhead and Underground Systems..... (Primarily intended for use by outside contractors)	11-31
Section 12 – Equipment Installation and Connections .....	12-1
Section 13 – Industrial Control and Instrumentation.....	13-1
Section 14 – Alternative Energy Systems.....	14-1

## References

Electrical Construction Abbreviations .....	R-1
Electrical Construction Definitions .....	R-2
Appendix A: Technical Data Tables.....	R-6
Table 1: Conversion of Minutes to Decimal Hours .....	R-6
Table 2: Metric Conversions .....	R-6
Table 3: Rigid Metal Conduit Inside Diameters .....	R-6
Table 4: Electrical Contractor Areas.....	R-7
Table 5: Conduit Weight Comparisons.....	R-7
Table 6: Estimating the Effects of Extended Duration .....	R-8
Appendix B: Electrical Formulas.....	R-9
Appendix C: Additional Costs of Change Orders.....	R-10
Change Order Costs Form.....	R-14
Appendix D: Estimating the Cost of Supervision .....	R-15
Appendix E: Suggested Labor Factor Percentage to Use With Multiple Runs .....	R-16
Appendix F: Equipment Startup Checklist Resources.....	R-17
Appendix G: Additional NECA Resources .....	R-18
Index of Electrical Materials.....	R-19

# INTRODUCTION TO THE *MANUAL OF LABOR UNITS*

## Purpose

The purpose of this labor unit manual is to give the user a source of labor data for estimating the labor required to install the electrical and communications systems shown on electrical construction drawings.

The NECA *Manual of Labor Units* provides the user with the national average amount of labor hours required to install a given quantity of each item under typical conditions on a typical project. The labor units in this manual are basic labor units because they represent the normal amount of labor required on a typical project under typical site conditions. These conditions are defined in the section adjusting labor units for project conditions. Suggestions are also included in that section to assist in the adjustment of the labor data in this manual for a specific project and for each project's unique site conditions.

## Source of the Data in This Manual

Since 1923 this Association's member electrical contractors have been the sole source of the labor data in this manual. Bi-annually, NECA updates and revises the labor data in the manual by soliciting the latest labor units from its member contractors with the goal of providing the latest labor data, based on the average productivity being experienced in this industry.

## Arrangement of the Labor Unit Tables

This manual is arranged in fourteen sections of related items. Each of the sections has a detailed table of contents at the beginning of the section. Section 11: Outdoor Overhead and Underground Systems is broken into two components, one which includes labor units for "inside" electrical contractors who install small quantities of outdoor overhead systems and one that includes labor units for "outside" or "line" electrical contractors who install substantially greater quantities of outdoor overhead systems with specially trained line electricians.

## Electrical Condition of Equipment Covered By These Labor Units

The condition of these labor units are based on new material. The cost of working with used or existing equipment needs to be factored, as it usually requires additional labor steps.

The power condition that applies to these labor units is de-energized, the additional labor required to work on energized equipment is defined by NFPA 70E and OSHA. Always assess your company's policies and procedures to factor this additional labor.

## Additional Information

For additional information concerning the data in this manual, estimating training courses, qualified local electrical contractors, or any other of the services provided by NECA, contact your local NECA Chapter or visit [www.necanet.org](http://www.necanet.org).

## LABOR UNITS DEFINED

All labor data in this manual are in units of man-hours. Each table of labor units indicates whether the labor units are for the installation of:

- E = One, or per each item
- C = Per hundred items
- C = Per hundred linear feet of the item
- M = Per thousand linear feet of the item
- LF = Linear Foot
- CY = Cubic Yard

## Scope of the Manual of Labor Units

All labor units in this manual include varying amounts of four basic components outlined below. These components are used in developing and evaluating each of the labor unit items published in this manual. The portion of each component in the basic labor units varies from item to item, and NECA does not attempt to quantify these portions or percentages.

It is well established that the material installation portion of some labor units represent a much larger part of some labor units than for others. For example, the actual installation portion of labor units for duplex receptacles is greater than many other items because the material handling is easy and the layout and measurement is almost non-existent. The installation of the box for the duplex receptacle usually includes all of the layout and measurement labor.

The four components included in the labor units are:

- **Normal Material Handling** – Before any electrical material is installed, it must be handled two or more times. All material must be unloaded from the delivery truck, inspected for shipping damage, carried to the storage area, transported to the floor where it will be installed, and distributed to the final installation location. Conduit bundles must be broken apart, equipment removed from cartons, lighting fixtures removed from pallets, wrappings cut from coils, etc. In addition, empty cartons, pallets, boxes, reels, skids, packing, etc., must be removed from the work area. This effort consumes labor without any electrical material actually being installed; however, this time must be included in the labor units.
- **Drawing Study, Measurement and Layout** – The installation of electrical materials cannot begin until the type and size of material is determined, the installation location is verified, the electricians are directed, the fastening devices are identified, a measurement is made to insure the proper installation location, the installation location is marked, etc. This effort consumes labor without any electrical materials being installed; however, this time must be included in the labor units.
- **Material Installation** – This effort includes both the procurement (and return) of all tools other than hand tools carried in the tool belt and the actual installation of the electrical materials. Separate labor units are necessary for the installation of all fasteners, hangers, and supports.

In the beginning of each section of this manual there is additional information regarding the scope of the labor units for particular items such as cutting, threading, bending, drilling, etc. **It is of the utmost importance that every user of this manual read the first page of each section before selecting any labor units from a particular section.**

- **Normal Non-Productive Labor** – Every labor unit in this manual includes a pro-rated amount of the normal non-productive labor. The magnitude of the non-productive labor in each labor unit is unknown.

The normal non-productive labor in the labor units includes:

- Personal comfort breaks
- Normal time to obtain drinking water
- Minimum breaks for coffee carried to the work area
- Walking time between the gang shed and the work area
- Minimal walking time to obtain tools and electrical materials
- Minimal lost time due to interference by other crafts

Some normal non-productive labor items that are not included are:

- Time waiting for material or personnel hoists or cranes
- Time due to strikes, work stoppages, or jurisdictional disputes



- Time due to egress, job site security, or physical obstructions
- Time related to safety compliance, this is to be added per contractors' experience and policies

Through good project planning and management, electrical contractors generally can keep such things as loitering, interruptions, late starting, early quitting, etc., to a minimum. When these conditions are beyond the control of the electrical contractor, then additional non-productive labor must be allowed.

## Items Not Included in Labor Units

The introduction for each section notes specific items that are not included in the labor units for that section.

Throughout the entire manual, the labor units **do not include any labor for supervision of any type**. All electrical construction requires more than one level of supervision, and the magnitude of supervision depends on the complexity, type, and size of each project. In addition, many labor agreements include special requirements related to supervision. Because each project is unique, it is the opinion of most electrical contractors that the labor for supervision is best estimated as a separate cost item and that no part of the supervision labor be included in the material installation labor units. Estimating the costs of supervision is discussed in an appendix to this manual.

## How to Select Basic Labor Units

Estimating electrical material installation labor is best accomplished by the application of a labor unit to each item on a list of materials prepared from the takeoff of the bid contract drawings. Along with the type and size of each item, it is essential that an abbreviated description of the installation conditions be noted. The necessity of the type and size of each item is obvious, but of equal necessity are the abbreviated notes regarding the installation conditions so that an appropriate selection may be made from a choice of labor units.

The NECA labor unit tables include three different labor units for each item:

- **Normal Installation Conditions** – When all of the conditions associated with the installation of an item will permit the maximum productivity of the electricians on a project, these “normal” column labor units are applicable.

Examples of these normal conditions might include the installation of surface mounted items up to a height of eight feet above the floor, the use of a rolling scaffold or six-foot ladders, a repetitive layout, a minimum of required measurements, a minimum of interference by structural or mechanical obstacles, etc.

Occasionally there are unusual installation conditions when a labor unit that is less than the “normal” column labor unit is justified. For example, when an abnormally large quantity of parallel conduits, without bends or offsets, are to be installed on trapeze hangers, labor units slightly smaller than the “normal” column labor units might be more appropriate.

- **Difficult Installation Conditions** – When one or more of the conditions associated with the installation of an item will permit less than maximum productivity of the electricians on a typical project, these “difficult” column labor units are applicable.

Examples of the difficult conditions might include the installation of surface mounted items up to a height of twelve feet from the floor, the use of fixed scaffolding installed by others, the use of ten-foot ladders, a non-repetitive layout, a moderate amount of interference by structural or mechanical obstacles, etc.

Users of this manual are also encouraged to consider using labor units whose magnitude are somewhere between the normal column labor units and the difficult column labor units when conditions justify this consideration.

- **Very Difficult Installation Conditions** – When one or more of the conditions associated with the installation of an item will permit substantially less than maximum productivity of the electricians on a typical project, these “very difficult” column labor units are applicable.

Examples of the very difficult conditions might include the installation of surface mounted items up to a height of twenty feet above the floor, the use of fixed scaffolding installed by others, the use of eighteen-foot ladders, a single location of each item, a substantial amount of interference by structural or mechanical items, a difficult fastening method, etc.

Users of this manual are also encouraged to consider using labor units whose magnitude are somewhere between the difficult column labor units and the very difficult column labor units when the conditions justify this consideration. It is also essential that users of this manual select labor units that are greater than the very difficult column labor unit when conditions justify the need.

## Increasing Estimating Accuracy

On most typical projects there are several identical items whose installation labor should be determined separately due to significantly different installation conditions. For example, different labor units should be used for estimating the installation labor for conduit located in concrete floor slabs as compared to the identical type and size of conduit installed exposed on walls or ceilings. Conduit in concrete floor slabs is usually installed by the shortest route possible and therefore requires a lesser amount for point-to-point distances. Identical exposed conduit installed on walls, on ceilings, or parallel to concrete column lines requires a greater quantity of conduit, and the labor required per foot of conduit is greater because of the additional effort to maintain the alignment, elevation, and appearance. The labor for installing identical items should be determined separately whenever a significant quantity of the item is required in situations where two or more different installation conditions exist.

The best assurance that a construction contractor will continue in business is to bid projects based on the contract documents which include the specifications and the installation drawings. A realistic evaluation of all the anticipated project conditions based on the contract documents is the only justifiable reason for modifying the estimated labor costs in the bid estimates. The adjustment of estimated labor costs based on who the competitors are and how they would estimate the project is not only foolish and unjustifiable but will, without exception, eventually lead to financial disaster.

## ADJUSTING LABOR UNITS FOR PROJECT CONDITIONS

When adjusting the estimated labor for a specific project it is clearly more practical to adjust sub-totals or totals of labor man-hours for each portion of the project rather than to adjust individual labor units. The estimated labor adjusting is usually most effectively accomplished on an estimate summary sheet designed for that purpose. In computerized estimating this estimated labor adjustment is easily accomplished by appropriate programming (software) and corresponding computer operator instructions. It is the opinion of most electrical contractors that the best material and labor estimates are produced by listing every material item required, by listing the exact quantity of each item required, by applying an appropriate labor unit for each item to establish the basic quantity of labor required, and by adjusting the basic quantity of labor to reflect the specific project.

## Description of a Typical Project

The following general description defines a typical project for the purposes of estimating using this manual. This description may need to be altered for electrical contractors who perform low voltage, voice-data-video, or other types of specialty electrical work.

- Building Size and Shape
  - Up to three floors above street level
  - Approximately 20,000 to 100,000 square feet per floor
  - A standard rectangular or square floor plan
  - New construction
- Location
  - In or near a metropolitan area
  - Outside of a controlled access or high security area
  - A single building, facility, or activity
  - Unused, native soil with no unforeseen obstructions
- Construction and Work Schedule
  - Standard workday hours
  - 40 hours per workweek
  - All work on daylight shift
  - Sufficient time to eliminate scheduled overtime
- Electrical and Communications Systems
  - Up to 600-volt (and Medium voltage as indicated) power distribution
  - The electrical service by the local utility company
  - All standard UL listed electrical materials
  - All layout and specifications comply with the local and National Electrical Code
  - All new material and new construction
  - All systems to be installed 20 feet or less above a solid floor

## Description of Normal Project and Site Conditions

The following general description defines the typical site conditions for the purposes of estimating using this manual:

- Complete engineering, well coordinated design, drawings, and specifications
- Familiar type of building design and standard materials
- Crane furnished by owner or general contractors
- Adequate security for material and tool storage on the jobsite
- All electrical material furnished by the electrical contractor
- Sufficient supply of qualified journeymen electricians
- Overall job progress based on a realistic CPM project schedule
- Minimum quantity and magnitude of change orders
- No joint or beneficial occupancy
- All new material and new construction
- No interruptions, delays, or jurisdictional disputes
- Optimum job coordination of all crafts
- Work area temperature environment
  - Minimum equivalent temperature of plus 35 degrees Fahrenheit
  - Maximum temperature and humidity 88 degrees Fahrenheit and 50% RH or its equivalent

## **Adjusting Labor for Non-Typical Conditions**

It is universally recognized that individual labor units should **not** be adjusted when making allowances for non-typical projects and non-typical project conditions. A faster, more accurate procedure is to make labor adjustments using percentages applied to different categories of the work. Perhaps the most difficult operation in estimating is the evaluation of the applicability and magnitude of the labor increases or decreases due to non-typical conditions. The following pages contain guidelines and references which may be helpful in selecting estimated labor adjustments due to non-typical projects and non-typical project conditions.

In order to assist the users of this manual in evaluating the impact on labor productivity due to the conditions relating to the project, the following pages describe various labor factors to be considered when evaluating the degree of difficulty for the particular project. Following the labor factor descriptions is the "Labor Factor Score Sheet" to be used by the estimator to score the various labor factors present on the project. The estimator should review each project situation and determine the category that relates best to that situation. Most projects will have job situations that fall into various categories. When those situations exist, you may want to utilize the project grading system provided in the Labor Factor Score Sheet.

### ***Labor Adjustments Due to Working Conditions***

The basic labor units in this manual are based on environmental (weather) conditions, which do not reduce the labor productivity. As a result of labor data research by NECA it was determined that electrician labor productivity does not decrease until the effective temperature (wind chill factor included) drops below 35 degrees Fahrenheit. The same research developed the combinations of high temperature and humidity limits that do not impair the productivity of installation labor. In addition, the productivity loss due to extreme environmental conditions is available.

This labor data along with the details of its development, electrician labor productivity loss percentages for extremes of environmental conditions and suggestions on how to use the data is available from NECA in the report *The Effect of Temperature on Productivity* (Index # 5072-04).

### ***Labor Adjustments for the Type of Project***

It is recognized in the construction industry that different types of buildings and projects may require either more or less labor to install identical electrical materials than the average labor units in this manual. There are many reasons for these differences in productivity, but the major reasons include:

- Structural differences
- Special requirements in the construction contract
- The magnitude of the electrical power requirements
- The quantities of identical electrical materials
- The differences in typical ceiling heights
- The differences in lighting requirements
- The complexity of the electrical systems
- The complexity of the communications systems
- The differences in the rate at which the construction can progress
- The special requirements of the National Electrical Code
- The differences in soil conditions
- Other equally important elements

### ***Labor Adjustments Due to Building Height***

The basic labor units in this manual are based on buildings and projects with up to three floors above grade or street level. For taller buildings or projects, a labor adjustment must be made to the estimated labor sub-totals developed from the labor units in this manual. To evaluate additional labor required due to the height of a building, a cumulative range of 1% to 2% per floor reflects the rate of productivity loss experienced by our member contractors.

NECA's *The Effects of Multi-Story Buildings on Productivity* (Index # 5071-04) includes a summary of the data researched to produce the findings, factors that cause the productivity loss, tables of productivity loss percentages for buildings up to 50 stories tall, and suggestions on how to use these tables.

### ***Labor Adjustments for Project Sizes***

The basic labor units in this manual are based on typical projects whose size will require the full time assignment of electricians for normal workweeks on small projects and on typical projects whose maximum electrician peak workforce will not exceed one hundred persons.

On abnormally small projects, the estimated labor based on the labor units in this manual must be substantially increased to reflect the actual labor that will be required. On abnormally large projects, the estimated labor units should be substantially increased for numerous reasons such as the additional supervision required, the additional labor for handling material or for controlling tools, time lost walking to and from assigned work areas, the additional labor required to coordinate the electrical work with other crafts, the increased difficulty in obtaining the use of hoisting equipment and in coordination of material delivery and material storage, the increased productivity loss due to personnel turnover, and the basic psychological impact of a large project.

### ***Labor Adjustments for Hours Worked and Shifts***

The basic labor units in this manual are based on projects that did not include any scheduled overtime. Occasional or unscheduled overtime of a few electricians working a minimum amount of overtime once or twice a month in support of other crafts is not unusual and is included in the scope of a typical project. However, when the contract documents require scheduled overtime, when the bid documents or project schedule suggest that scheduled overtime will be required, and when the project does not proceed as originally anticipated, there is a substantial loss of productivity if scheduled overtime is initiated. The loss of productivity is experienced not only during the overtime hours worked, but also during the normal hours preceding overtime. As a result of labor data research by NECA, it was determined that the loss of productivity due to scheduled overtime increases in magnitude as the duration of the scheduled overtime is increased.

Additional information can be found in the report *Impact of Overtime on Electrical Labor Productivity: A Measured Mile Approach* (Index # F3101).

### ***Labor Adjustments for Crew Density***

The basic labor units in this manual are based on normal peak work force of electricians. When abnormal peak work force is experienced, there is a loss of productivity. Contract bid documents and the scope of work to be completed in the time available may indicate that varying sizes of work crews will be necessary. Likewise, unanticipated changes in the progress of the construction or other changed conditions may require the use of larger than normal work crews. For estimating the impact of having to over-man a project before the work is actually completed, only the judgment of an experienced electrical contractor is reliable. In most situations, the after-the-facts labor records are the best method to assess the productivity loss due to over-manning.

To assist the industry in assessing this type of loss, the use of other than optimum crew sizes, or the use of constantly changing crew sizes, NECA developed data from the records of its member electrical contractors to establish the normal peak electrician workforce for numerous types and sizes of electrical construction projects. This normal peak workforce data is available from NECA in the report *Project Peak Workforce* (Index # 5074-04).

## ***Labor Adjustments for Project Durations***

The basic labor units in this manual are based on normal project durations. When the contract documents indicate abnormal project progress schedules, abnormal project completion dates, and when the project progress schedule is substantially revised there is a loss of productivity due to these conditions. Additionally the overall continuity of the project schedule has an effect on the production. Starting and stopping work prevents the workforce from establishing a productive workflow. The magnitude of the productivity loss is in proportion to the circumstances of the particular project involved. In most situations, the after-the-facts labor records provide the best source to assess the productivity loss. For estimating the impact of these conditions before the work is actually completed, only the judgment of an experienced electrical contractor is completely reliable.

To assist the industry in assessing the productivity loss due to abnormal project durations and productivity loss due to changed project progress schedules, NECA developed data from the records of its member electrical contractors to establish the normal project duration for numerous types and sizes of electrical construction projects. This normal project duration data is available from NECA within the report *Normal Project Duration* (Index # 5076-04).

## ***Labor Adjustments for Non-Productive Labor***

The basic labor units in this manual include a prorated amount of the normal non-productive labor experienced on a typical project. On some projects the non-productive labor is greater than the normal amount, and the estimated labor for the installation of the electrical systems must be increased accordingly. For example, the owner or general contractor may allow or require all construction crafts to take coffee breaks at a specific time and for a specific duration. Other non-productive labor to consider are mandatory stretch and flex, added safety measures required or clean-up required beyond the normal scope or work to name a few. A description of the normal non-productive labor is included in the foregoing discussion of the scope of the NECA labor units. The evaluation and determination of the magnitude of abnormal productivity is extremely difficult because there are no standard percentages, mathematical formulas, or guidelines that can be used. The evaluation of the cause and effect of abnormal non-productive situations can only be determined by the judgment of an experienced person.

In the bid estimating of the project labor requirements, the electrical contractor must evaluate all the known and anticipated project conditions that will affect the labor productivity and then adjust the estimated labor man-hours accordingly. A substantially different condition exists when estimating the labor for change orders. The electrical contractor not only must evaluate the magnitude of the non-productive labor before any change order is received, but the change order itself always increases the non-productive labor and the supervisory labor to some degree. The issuance of a single typical small change order does increase the nonproductive labor, but usually not in measurable amounts. However, after several change orders are issued, or when a single change order of substantial size is issued, the electrical contractor will always experience a major increase in lost productivity.

For additional information on cost factors involved in change orders, see *Change Order Guidelines For Electrical and Low Voltage Contractors* (Index # F3405a), *Impact of Change Orders on Labor Efficiency* (Index # F9901) and *Quantifying the Cumulative Impact of Change Orders for Electrical Contractors* (Index # F2004).

## ***Labor Adjustments for Project Location***

The basic labor units in this manual are based on typical project locations that do not include any unusual problems. When the project location creates unusual material and tool handling problems, other types of physical obstructions, or administrative obstructions, the additional labor (productivity loss) caused by these conditions must be considered. Some of the conditions that may cause productivity losses include:

- Material and tool delivery and unloading restrictions
- Material availability from local suppliers
- Material and tool storage restrictions
- Material and tool hoisting restrictions

- Material and tool security problems
- Potential flooding, fire hazards, or dust storms
- Lack of space for subcontractor field office or job shed
- Security area restrictions
- Widely dispersed work areas
- Craft parking restrictions and availability
- Disruptions due to nearby demolition, rock blasting, chemical fumes, etc.

The loss of productivity due to any of these abnormal conditions cannot be determined from any tables or charts. Each situation must be evaluated independently, and the productivity loss must be determined by judgment, logic, and common sense. The most frequent method of determining the additional labor hours which will be required as a result of the project location is to multiply the total estimated man-hours times a productivity loss percentage to produce the number of additional man-hours required.

### ***Labor Adjustments for Project Planning and Pre-Planning***

The process of planning the installation of the material prior to the actual project construction is an excellent method of reducing the labor required to perform the actual installation. Detailing the assembly of material including the method and location of the final installation will help reduce the need for layout time on the job. Some companies devote hours of drafting and research time to planning the final installation of the material. In many cases these companies find that one hour spent in pre-planning will save as many as seven hours of project installation time.

### ***Labor Adjustments Due to the General Contractor***

The basic labor units in this manual are based on the effective coordination and management of the project by the contractor or construction manager. If the project is not managed effectively, the electrical contractor experiences a loss of productivity.

Occasionally the owner's actions are the cause of the general contractor's problems, and ultimately additional electrician labor may be required to complete an installation. The owner's redesign of any part of a project after construction has started, beginning construction without complete or coordinated construction drawings, electrical materials furnished by the owner, an excessive number of change orders, delays in the project due to the lack of financing, owners accelerating the construction schedule, and other disruptive actions by owners may contribute to the general contractor's ineffectiveness.

However, there are numerous other elements that are within the control of general contractors and construction managers that have a direct impact on the loss of productivity by electricians. Some general contractors are substantially less effective in coordinating the work of the subcontractors, in sequencing the structural components, in resolving problems, in controlling the operation of material and personnel hoists, in using overtime to maintain the construction schedule, in administering change orders, and numerous other activities that directly impact the productivity of the electricians.

Electrical contractors must take the general contractor's management effectiveness into consideration when bidding each project and must include an appropriate labor adjustment when necessary. Likewise, an adjustment for the general contractor's or construction manager's effectiveness must be included, when appropriate, for estimating change orders, accelerated schedule impact costs, delay impact costs, and all other changed conditions impact costs. The magnitude of the productivity loss must be determined by an independent evaluation of the circumstances associated with each project.

### ***Labor Adjustments for Project Work Schedules***

The basic labor units in this manual are based on normal work schedules. A normal work schedule includes eight daylight hours per day, five days per week and forty total hours per week. Any deviation from the normal work schedule will have an impact on the labor productivity and the quantity of supervision necessary.

Some of the elements that may affect the productivity change due to abnormal work schedules include but are not limited to:

- Weather, climate and geographical location
- Duration of the abnormal work schedule
- Daylight versus nighttime hours
- Availability of sufficient qualified electricians
- The level of construction worker unemployment
- Type and size of project
- Project owner's special requirements
- Historical labor practices
- Other psychological influences

### ***Labor Adjustments for Labor Availability***

The basic labor units in this manual are based on having an adequate supply of qualified electricians. When an adequate supply of qualified electricians is not available during any portion of the electrical construction, there is a loss of productivity that must be taken into consideration. It is extremely difficult when preparing a bid estimate to precisely determine the loss of productivity due to a shortage of qualified electricians that may occur at some future date. However, this situation does occur frequently, and some rationale must be employed to produce the total labor required during the bid preparation process. Experience, judgment, and common sense are the only tools available to assess these situations.

In other situations, such as labor estimating for accelerated construction schedules, change orders, and after-the-fact labor cost analysis, the loss of productivity due to a shortage of qualified electricians is more easily determinable. In these situations the loss of productivity is usually estimated by multiplying the total man-hours that would have been required under normal conditions by a productivity loss percentage to produce the number of additional man-hours required. The productivity loss percentage in this calculation cannot be obtained from any published table, but must be determined by the careful analysis of all the elements for each individual situation. Electrical contractors are contractually responsible to include the productivity loss due to a shortage of qualified electricians in their original bid price based on the information available in the bid documents. However, when the project conditions change after construction has started, and for many change order situations, the electrical contractor is clearly entitled to recover the additional labor costs resulting from a shortage of qualified electricians.

In the electrical construction industry it is not the individual electrical contractor's responsibility to select and train electricians. The JATC program under the joint guidance of NECA and the IBEW makes every effort possible to anticipate the need for electricians and to train an adequate supply of qualified people in every part of the country.

### ***Labor Adjustments for Other Factors***

The users of this manual must recognize that other conditions not specifically mentioned on these pages can have a substantial impact-either positive or negative-on the productivity of electricians. Worker motivation is one example of a condition that could be either positive or negative and could change either rapidly or slowly after a project is started.

For additional information on issues of this type, see *Factors Affecting Labor Productivity for Electrical Contractors* (Index # F3000).

Another consideration is for prefabricated assemblies of electrical materials. The process of prefabricating repetitive assemblies in a controlled environment with optimum access to material and tooling is an extremely effective way of reducing the amount of labor required during construction. It is not uncommon to realize upwards of 30% labor saving when assembling the individual material items into these prefabricated units. Obviously, the greater the number of identical assemblies that are prefabricated offsite, the greater the labor savings however there may be justification for prefabricating as few as five or six when appropriate.



## **Summary of Labor Adjustments**

It is well recognized that the most effective and least error prone method of estimating is to use a standard or basic set of labor units applied to a complete list of all materials that will be required and to adjust the total estimated electrician labor to reflect the unique conditions on each project. For budget purposes it may be necessary, because of the absence of completed installation drawings, to estimate the installed costs of electrical or communications systems using some other method of estimating cost.

It is the intent of this manual to furnish realistic labor units which represent the average amount of labor required for a typical project located anywhere in the United States. In order to tailor the estimated labor required for a specific project, the estimated labor calculated with the labor units in this manual may be adjusted either upward or downward to take into consideration all condition that would differ from a typical. The adjustment of the estimated labor for a project's special condition is not an exact science, but the experience of many electrical contractors over a long period of time has demonstrated that this manual does accurately reflect the amount of labor required for a typical project.

## **NECA Labor Factor Score Sheet**

To assist the users of this manual in evaluating the impact on labor productivity due to the conditions relating to the project, the "Labor Factor Score Sheet" lists situations that may be encountered on projects, and must be considered when determining the degree of difficulty for that particular project. The estimator should review each project situation and determine the category that relates best to that situation. Most projects will have job situations that fall into various categories and when those situations exist, you may want to utilize the project grading system provided in the Labor Factor Score Sheet.

*The purpose of the Labor Factor Score Sheet is to identify the appropriate labor column to be used due to the conditions of project. Labor adjustments will still be needed for building height, weather conditions, overtime, abnormal project durations, abnormal peak work forces, abnormal work schedules, abnormal project sizes, and shortage of qualified electricians, project location, general contractor, abnormal non-productive labor, and other conditions in addition to the selection of the correct rating column.*

## NECA Labor Factor Score Sheet

Within the Labor Factor Score Sheet, score each condition between 1 and 5, with 1 being normal working conditions and 5 being the most difficult working conditions. For scores between 36 and 75 use the Normal column, between 76 and 134 use the Difficult column, and use the Very Difficult column for scores between 135 and 175.

Conditions	Considerations	Score
Working conditions	Indoor, Controlled environment, Extreme conditions	
Working height	Up to 10', 10'-20', 20' +, Ladders/lifts/scaffold, Below grade	
Building height	Number of floors 1-3, 4-7, High-rise	
Building sq. ft.	Manageable, Moderate, Excessive	
Project size in dollars	Normal, Moderate, Extreme	
Site size	Urban setting, Ample laydown space	
Job conditions	New construction, Remodel, Work while occupied	
Type of construction	Frame, Block, Concrete or exposed	
Hours worked	40 hours/week; 5, 6 or 7 day work week; 8, 10 or 12 hour work day	
Shifts	Day, 2nd, 3rd	
Crew density	Normal, Moderate, Extreme	
Project duration	Normal, Compressed, Delayed, Fast track	
Safety	Standard OSHA guidelines, Customer directives, Project specific	
Clean-up	Routine, No dust, Clean room condition	
Installation	Repetitive, Moderate repetitive, No repetition	
Systems	Common systems, Special, Complex	
Conduit type	PVC, EMT, Flex or GRC, IMC, Aluminum, PVC coated GRC	
Accessibility of work area	Unlimited, Limited, Escorted	
Voltage	0-600V, 600-5Kv, Over 5Kv	
Inventory of local supplier	Adequate, Moderate, Limited	
Proximity of stored materials	On site, In general area of project, Remote	
Project continuity	Interruptions: None, Moderate, Extreme	
Construction	Standard, Poor, None	
Drawings/plans	% Complete, 100%, 95%, 50%, 35%, Less	
Information	Timely, Delayed, Limited	
Change order quantity	Minimal, Moderate, Excessive	
Craft coordination required	Minimum, Moderate, Extensive	
Authority having jurisdiction	Experience with type of project: Considerable, Moderate, Limited	
Decision making	Timely, Delayed, Limited	
Change order timing	Prior to installation, During, After	
Project schedule	As planned, Compressed/extended, Moderately, Extreme	
General contractors on same jobsite	Single prime, Two primes, Three + primes	
Job meetings	Regularly scheduled, Crisis meetings, Minimal	
Shared responsibility for project	One EC, Two EC's, Three + EC's on site	
Tools/equipment	Standard, Non-standard, Specialty	
Labor availability	Readily, Moderately, Limited, Non-available	
<b>Total Score</b>		

The NECA Labor Factor Score Sheet may be duplicated by purchasers of the Manual of Labor Units for the purposes of calculating project score. This document is also available online at [www.necanet.org/MLU](http://www.necanet.org/MLU).

# SECTION 1

## INTEGRATED BUILDING SYSTEMS

### General Information

The labor units in this section are applicable for the installation of various IBS systems including: fire alarm, security, clock, sound, audio visual, signaling, nurse call, computer, telephone and television. In addition, this section contains components of structured cabling systems including fiber optic cable and terminations, UTP cable and terminations, various electronic cable and cable terminations and other premises cabling items. See Section 13 for temperature controls.

### Scope of These Labor Units

The Introduction section includes details on the scope of labor units across the manual. Some items included are:

- Material unloading, jobsite storage and delivery to the installation area
- Drawing and specification study
- Layout, measuring and marking the installation location
- Tool acquisition and return to storage
- Material assembly and installation
- Clean-up of electrical contractor furnished excess material
- Normal non-productive labor

### Work Operations Not Included In These Labor Units

- Field supervision
- Programming
- Hanger or fastener installation
- Welding or painting
- Measurements and alignment more precise than normal industry standards
- Testing of any type unless specifically noted
- Cutting holes or openings in walls or floors
- Warranty

### Labor Adjustments for Non-Typical Conditions

See the Introduction section for details.

### Application Instructions

- Labor units under the “Normal” column are for heights up to ten feet above a smooth, hard floor. Labor units under the “Difficult” column are for heights up to twelve feet. Labor units under the “Very Difficult” column are for heights up to twenty feet.
- Labor units in this section do not include the installation of cable tray, outlet boxes, conduit, conduit connectors, supports or fasteners. See Section 2 for support, fastener and anchor labor units.
- Labor unit tables do not include every type and size of items available. When labor units are required for items not listed, an approximate labor unit may be obtained from the tables for a similar item of about the same weight, dimensions and conductor terminations.
- All the labor units in this section are based on using the most efficient tools and equipment available. When the anticipated jobsite conditions will prevent the optimum use of tools and equipment, an appropriate additional labor allowance in proportion to the anticipated difficulties is necessary.
- Labor units in this manual are for new work only and for a complete electrical installation. For remodeling or change order situations these labor units need to be substantially increased.



**Section 1  
Table of Contents**

<b>Fire Alarm</b>	1-7
Fire Alarm Control Panels Hardwired	1-7
Hardwire Annunciator	1-7
Addressable Control Panels - Modules Mounted in Control Panel	1-7
Fire Alarm Initiating Devices	1-7
Fire Alarm - Signaling	1-7
Fire Alarm - Miscellaneous Devices	1-7
Fire Alarm - Aspirating Smoke Detection	<b>(Updated)</b> 1-7
<b>Security &amp; Access Control</b>	1-8
Security Systems - Control Panels	1-8
Security Systems - Wireless	1-8
Security Systems - Peripherals	1-8
Security Systems - Detection Devices	1-8
Security Systems - Signaling Devices	1-8
Access Control	1-9
Access Field Devices	1-9
Access Control - Misc. Items	1-9
<b>Clock</b>	1-10
Clock Systems	1-10
<b>Audio Visual</b>	1-11
Sound Systems - Signal Generators	1-11
Sound Systems - Signal Processing Equip.	1-11
Sound Systems - Sound Generating Equip.	1-11
Sound Systems - Pro-Sound - Theatrical Systems	1-11
Sound Systems - Pro-Sound - Theatrical Systems - Patch Bays	1-12
Sound Systems - Pro-Sound - Theatrical Systems - Electronics	1-12
Sound Systems - Pro-Sound - Theatrical Systems - Consoles, Mixers	1-12
Sound Systems - Sound Masking	1-12
Audio Visual Systems - Source Equipment	1-12
Audio Visual Systems - Programming and Switching	1-13
Audio Visual Systems - Playback	1-13
Audio Visual Systems - Remote Control	1-13
Audio Visual Systems - Interface Devices	1-13
Audio Visual Systems - Teleconference	1-13
Audio Visual Systems - Patching	1-13
Audio Visual Systems - Roll Down Screens	1-13
Audio Visual Systems - Miscellaneous	1-13
Electronic Equipment - Miscellaneous Components - Power Supplies	1-13
Electronic Equipment - Miscellaneous Components - Speakers	1-13
<b>Nurse Call</b>	1-14
Nurse Call System - Head End	1-14
Nurse Call System - Field Devices	1-14
Code Blue Systems	1-14
Patient Monitoring System	<b>(Updated)</b> 1-14
<b>Computer Equipment</b>	1-15
Computer Equipment	1-15
Computer Equipment - Miscellaneous	1-15
Computer Equipment - Network Devices	<b>(Updated)</b> 1-15
Computer Equipment - Printers	1-15

## Section 1 Table of Contents

<b>Telephone / Television</b>	1-16
Telephone Equipment	1-16
Telephone Equipment - Small System Programming	1-16
Telephone Equipment Paging System	1-16
Specific Use Items	1-16
Electronic Equipment - Miscellaneous Components - Jacks, Wall Plates	1-16
Television System	1-16
<b>Closed Circuit Television</b>	1-17
CCTV Systems - Controllers and Recorders	1-17
Television Systems - Camera and Enclosure	1-17
Television Systems - Camera Lenses	1-17
<b>Cabling System</b>	1-18
Innerduct in Conduit - Indoor PVC/Plenum	1-18
Innerduct in Conduit - Outdoor PVC/Plenum	1-18
Innerduct: Not In Conduit - Indoor PVC / Plenum	1-18
Innerduct: Not In Conduit - Outdoor Buried (Reels) (Not Including Trenching)	1-18
Innerduct: Not In Conduit - Outdoor Aerial	1-18
Innerduct: Not In Conduit -Multi Duct (Not Incl. Trenching)	1-18
Innerduct	1-18
Optical Fiber Cable - Indoor in Conduit	1-18
Optical Fiber Cable - Indoor W/O Conduit	1-18
Fabric Inter Duct	1-18
Optical Fiber Cable - Outdoor Underground in Conduit	1-19
Optical Fiber Cable - Outdoor Direct Burial (Not Including Trenching)	1-19
Optical Fiber Cable - Outdoor Aerial	1-19
Cable Prep of Fiber - Gel Filled	1-19
Cable Prep of Fiber - Unfilled	1-19
Cable Prep of Fiber - Fanouts	1-19
Splicing	1-19
Splice Enclosure Indoor	1-19
Splice Cables - Outdoor	1-19
Terminations Anaerobic	1-20
Hot Melt / Heat Cure / UV	1-20
Termination Boxes / Cabinets - Wall Mounted	1-20
Termination Boxes / Cabinets - Rack Mount	1-20
Termination Boxes / Cabinets - Misc	1-20
Fiber Optic Cable - Patch Cords (Premade)	1-20
Fiber Optic Cable - Fiber Testing (one wave length)	1-20
Fiber Optic Cable - Fiber Labeling	1-20
Copper Cable - UTP - PVC / Plenum Indoor In Conduit	1-20
Copper Cable - UTP - PVC / Plenum Indoor w/o Conduit	1-21
Copper Cable - STP - PVC / Plenum Indoor In Conduit	1-21
Copper Cable - STP - PVC / Plenum Indoors w/o Conduit	1-21
Coaxial Cable - Indoor In Conduit PVC / Plenum	1-21
Coaxial Cable - Indoor Not In Conduit PVC / Plenum	1-21
Twisted Pair Cable - Riser Cable (Metal Jacket in Conduit)	1-22
Twisted Pair Cable - Riser Cable Metal Jacket w/o Conduit	1-22
Twisted Pair Cable - Outdoor Underground In Conduit (OSP)	1-22
Twisted Pair Cable - Outdoor Direct Burial (OSP) Not Including Trenching	1-22
Twisted Pair Cable - Outdoor Aerial (OSP)	1-22
Copper Splice Enclosures	1-22
Splice Enclosures	1-22
Copper Termination Hardware	1-22
Patch Panel Mounting Only	1-23
Patch Panel Termination	1-23

## Section 1 Table of Contents

Wire Managers	1-23
Wall Mounted Racks / Cabinets (Assemble and Mount)	1-23
Floor Mount (Assemble and Mount)	1-23
Work Area Terminations	1-24
Miscellaneous Connectors	1-24
Patch Cords	1-24
Cross Connects	1-24
Copper Testing	1-25
Copper Labeling	1-25
Firestopping	1-25
Cable Supports	1-25
Electronic Equipment - Miscellaneous Components - Switches	1-25
Electronic Equipment - Miscellaneous Components - Terminals	1-25
Electronic Equipment - Miscellaneous Components - Meters	1-25
Electronic Equipment - Miscellaneous Components - Jacks, Wall Plates	1-25
Lighting Controls	1-25
Electronic Equipment	1-25
<b>Low Voltage Lighting Control</b>	1-26
Lighting Control Systems	1-26





Section 1 - Fire Alarm

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Fire Alarm Control Panels Hardwired</b>						
Up to 8 Zone		4.00	5.00	6.00		E
Integrated Digital Communicator		1.00	1.25	1.50		E
Remote Trouble Test Switch		0.30	0.35	0.40		E
<b>Hardwire Annunciator</b>						
Up to 8 Zone		4.00	5.00	6.25		E
<b>Addressable Control Panels - Modules Mounted in Control Panel</b>						
Relay Module		0.90	1.15	1.35		E
4 Circuit Signal Module		0.90	1.15	1.35		E
Panel Mount Control Switch		1.10	1.38	1.72		E
Power Supply 6 Amps		2.00	2.50	3.00		E
Voice Telephone Command		2.00	2.50	3.00		E
Master Firefighter Telephone		2.00	2.50	3.00		E
Amplifier		2.00	2.50	3.00		E
Add. Address. Loop Modules		1.00	1.25	1.50		E
Audio Message Generator		1.00	1.25	1.50		E
Remote LCD Annunciator		2.00	2.50	3.00		E
<b>Fire Alarm Initiating Devices</b>						
Manual Station Non-Coded		0.50	0.63	0.78		E
Manual Station Coded		0.50	0.63	0.78		E
Manual Station Addressable		0.50	0.63	0.78		E
Guard for Devices		0.60	0.75	0.94		E
Detector Base		0.65	0.81	1.02		E
Detector Head		0.20	0.25	0.31		E
Addressable Base		0.65	0.81	1.02		E
Addressable Head		0.20	0.25	0.31		E
Duct Smoke Detector		2.00	2.50	3.00		E
Duct Smoke Detector Test Station		0.80	1.00	1.20		E
Duct Smoke Detector Remote Light		0.40	0.50	0.63		E
Beam Detector Transmitter/Receiver		4.00	5.00	6.25		E
Addressable Point ID Module		0.60	0.75	0.94		E
Explosion proof Heat Detector w/Box		1.30	1.63	2.03		E
Explosion proof Smoke Detector w/Box		1.30	1.63	2.03		E
Explosion proof Manual Station w/Box		1.10	1.38	1.72		E
Flow Switch, No Plumbing		1.20	1.50	1.88		E
Tamper Switch, No Plumbing		1.20	1.50	1.88		E
Pressure Switch, No Plumbing		1.20	1.50	1.88		E
<b>Fire Alarm - Signaling</b>						
Bell		0.75	1.00	1.25		E
Strobe Light		0.75	1.00	1.25		E
Bell/Strobe		0.75	1.00	1.25		E
Chime		0.75	1.00	1.25		E
Chime/Strobe		0.75	1.00	1.25		E
Speaker, 8 Inch Ceiling		1.00	1.25	1.50		E
Speaker, 4 Inch Wall		0.75	1.00	1.25		E
Speaker/Strobe		0.75	1.00	1.25		E
Fire Fighters Phone		1.25	1.60	2.00		E
Fire Fighters Jack		0.50	0.75	1.00		E
Remote Power Supply		3.00	3.75	4.50		E
Mass Notification - Speaker / Strobe		0.75	1.00	1.25		E
Mass Notification - Strobe		0.75	1.00	1.25		E
<b>Fire Alarm - Miscellaneous Devices</b>						
Waterproof Black box		0.50	0.63	0.75		E
Semi-Flush Control Relay		0.75	1.00	1.25		E
Addressable Control Relay		0.75	1.00	1.25		E
Magnetic Door Holder		1.00	1.25	1.50		E
4 Single Pole Double Throw Relay Surface Mtd. w/enclosure		0.90	1.15	1.35		E
Printer		1.50	1.90	2.25		E
Remote Power Supply		2.50	3.15	3.75		E
<b>Fire Alarm - Aspirating Smoke Detection</b>						
Aspirating Smoke Detector	X	4.000	5.000	6.000		E
Aspirating Pipe 3/4"	X	5.000	6.200	7.500		C
Aspirating Tubing 1/4"	X	14.00	17.50	21.00		M
Aspirating Socket Coupling	X	0.050	0.060	0.070		E
Aspirating Socket Union	X	0.050	0.060	0.070		E
Aspirating Pipe 90 Long Radius	X	0.100	0.125	0.150		E
Aspirating Pipe 45	X	0.100	0.125	0.150		E
Aspirating End Cap	X	0.120	0.150	0.180		E
Aspirating Pipe Clip	X	0.083	0.104	1.240		E
Aspirating Pipe Entrance Point w/Label	X	0.100	0.125	0.150		E
Aspirating Flush Sample Point Kit	X	0.25	0.31	0.38		E

Section 1 - Security & Access Control
















































Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Security Systems - Control Panels</b>						
 Control Panel - Commercial		4.00	5.00	6.00		E
Control Panel - Industrial		6.00	7.25	8.50		E
LCD Remote Keypad		2.50	3.25	4.00		E
Zone Expansion Module - 8 Zone		1.00	1.25	1.50		E
Zone Expansion Module - 16 Zone		2.00	2.50	3.00		E
Relay Logic Module		1.20	1.50	1.80		E
AC Failure Module		0.80	1.00	1.20		E
<b>Security Systems - Wireless</b>						
 Wireless Receiver		3.00	3.75	4.50		E
Wireless Remote Keypad		0.50	0.63	0.75		E
Wireless Door Contact		0.50	0.63	0.75		E
Wireless Motion Detector		0.50	0.63	0.75		E
Wireless Thermostat		0.50	0.63	0.75		E
Wireless Smoke Detector		0.50	0.63	0.75		E
<b>Security Systems - Peripherals</b>						
 Remote Digital Comm.		1.50	2.00	2.25		E
Cellular Phone Link		3.00	4.00	5.00		E
Internet Communicator		1.50	2.00	2.25		E
Digital Keypad		1.00	1.25	1.50		E
<b>Security Systems - Detection Devices</b>						
 Magnetic Switch*		0.75	0.95	1.15		E
Glass Break Detector		0.80	1.00	1.20		E
Seismic Detector		0.80	1.00	1.20		E
Heat Sensor		0.80	1.00	1.20		E
Temperature Sensor		0.80	1.00	1.20		E
Water Sensor		0.80	1.00	1.20		E
Motion Detectors		0.80	1.00	1.20		E
 Panic Button		0.80	1.00	1.20		E
Key Switch		0.70	0.90	1.10		E
Overhead Door Contact		1.00	1.25	1.50		E
Driveway Sensor		4.00	5.00	6.00		E
*Includes drilling, mounting and termination						
<b>Security Systems - Signaling Devices</b>						
 Horn - Indoor		0.60	0.75	0.90		E
Horn - Outdoor		0.80	1.00	1.20		E
Wireless Siren		0.60	0.75	0.90		E
Indoor Strobe		0.50	0.65	0.75		E

**Section 1 - Security & Access Control**




































	Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit	
	<b>Access Control</b>							
	Controller/CPU (in enclosure)		4.00	5.00	6.00		E	
	Two Door Controller		2.00	2.50	3.00		E	
	Four Door Controller		4.00	5.00	6.00		E	
	Eight Door Controller		6.00	7.50	9.00		E	
	Elevator Interface Panel		5.00	6.25	7.50		E	
	Card Reader, Wall Mounted		0.80	1.00	1.20		E	
	Card Reader, Post Mounted		1.00	1.25	1.50		E	
	Reader Controller		2.00	2.50	3.00		E	
	Palm Print Identifier		2.00	2.50	3.00		E	
	Touchpad Door Lock, New		2.00	2.50	3.00		E	
	Touchpad Door Lock, Refit		3.00	3.75	4.50		E	
		<b>Access Field Devices</b>						
		Door Lock Protector		1.00	1.25	1.50		E
		Key Switch		0.70	0.90	1.10		E
Emergency Door Release			1.00	1.25	1.50		E	
Door Closer, Hydraulic			2.00	2.50	3.00		E	
Electric Door Strike, New			2.00	2.50	3.00		E	
Electric Door Strike, Refit			2.50	3.15	3.75		E	
Electric Mortise Lock, New			2.00	2.50	3.00		E	
Electric Mortise Lock, Refit			3.00	3.75	4.50		E	
Electric Hinge			2.00	2.50	3.00		E	
Magnetic Lock			2.50	3.25	3.75		E	
Request To Exit			1.00	1.25	1.50		E	
Door Contact			1.00	1.25	1.50		E	
Door Management Device			1.25	1.50	1.75		E	
Door Lock Power Supply		3.00	3.75	4.50		E		
	<b>Access Control - Misc. Items</b>							
	Intercom - Master Station		2.00	2.50	3.00		E	
	Intercom - Remote Station		1.50	1.90	2.25		E	
	Telephone Entry System		10.00	12.00	16.00		E	



Section 1 - Audio Visual

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Sound Systems - Signal Generators</b>						
 CD player		1.00	1.25	1.50		E
 AV Receiver		1.00	1.25	1.50		E
 Microphone		0.40	0.50	0.60		E
 Wireless Microphone & Rec		1.25	1.60	1.90		E
 Audio Cart Player		1.00	1.25	1.50		E
<b>Sound Systems - Signal Processing Equip.</b>						
 Power Amp		2.50	3.15	3.75		E
 Pre-Amp		2.00	2.50	3.00		E
 Equalizer - Install		1.00	1.20	1.50		E
 Equalizer - Set		2.00	2.50	3.00		E
 4-12 Channel Mixer		2.00	2.50	3.00		E
 12+ Channel Mixer		4.00	5.00	6.00		E
 Volume Control		0.40	0.50	0.60		E
 Programmable Switch		0.80	1.00	1.20		E
 Speaker Selection Switch		0.80	1.00	1.20		E
 Noise Reduction Unit		2.00	2.50	3.00		E
 Filters, Various Types		0.80	1.00	1.20		E
 Delay Unit		1.00	1.25	1.50		E
 VU Meters		0.80	1.00	1.20		E
 Synch Generator		1.00	1.25	1.50		E
 Computer Interface		4.00	5.00	6.00		E
 Routing System		2.50	3.15	3.75		E
<b>Sound Systems - Sound Generating Equip.</b>						
 Speaker - Ceiling (includes cutting hole)		0.75	0.95	1.15		E
 Speaker - Wall (Surface)		0.50	0.65	0.75		E
 Speaker - Wall (Flush)		0.75	0.95	1.15		E
 Speaker - Outdoor Column Mount		3.00	3.75	4.50		E
 Horn		0.50	0.65	0.75		E
 Microphone Outlet, Flush		0.80	1.00	1.20		E
 Intercom, Central Unit		8.00	10.00	12.00		E
 Intercom, Satellite Unit		0.80	1.00	1.20		E
 Wireless Speaker System		3.00	3.75	4.50		E
 Antenna		6.00	7.50	9.00		E
 19" Rack Adapter		0.50	0.65	0.75		E
 Microphone Stand		0.30	0.40	0.45		E
<b>Sound Systems - Pro-Sound - Theatrical Systems</b>						
 Rack buildup, transport, seismic bracing		16.00	20.00	24.00		E
 Single channel rack-mount power amplifier		2.00	2.50	3.00		E
 Dual-channel rack-mounted power amplifier		2.25	2.80	3.40		E
 Amplifier with internal processing module		2.50	3.15	3.75		E
 Install and set up module for amplifier		0.50	0.65	0.75		E
 Wall mount amplifier with 6 input modules		4.00	5.00	6.00		E
 Production intercom master station		3.50	4.40	5.25		E
 Production intercom wall station, surface mount		1.50	1.90	2.25		E
 Production intercom belt-pack station		0.50	0.65	0.75		E
 Wireless microphone receiver, rack mount		1.50	1.90	2.25		E
 Hearing impaired transmitter, IR-based, rack mount		1.75	2.20	2.60		E
 Hearing impaired transmitter, RF-based, rack mount		1.75	2.20	2.60		E
 RF antenna for hearing impaired or wireless mic, wall mount		0.50	0.65	0.75		E
 Hearing impaired IR emitter unit with power supply		2.00	2.50	3.00		E






















Section 1 - Audio Visual

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Sound Systems - Pro-Sound - Theatrical Systems - Patch Bays</b>						
 Patch bay, punch down TRS, non-normalled, balanced 48 pt		24.00	30.00	36.00		E
 Patch bay, punch down TRS, normalled, balanced 48 pt		24.00	30.00	36.00		E
 Patch bay, punch down TT, non-normalled balanced 96 pt		48.00	60.00	72.00		E
 Patch bay, punch down TT, normalled, balanced 96 pt		48.00	60.00	72.00		E
<b>Sound Systems - Pro-Sound - Theatrical Systems - Electronics</b>						
 MIDI / SMPTE interface, rack mount		0.75	0.95	1.15		E
 DBX / Dolby Noise reduction unit, rack mount		0.60	0.75	0.90		E
 Phantom power supply, rack mount		0.50	0.65	0.75		E
 Digital multi-track recorder / ADAT, rack mount		1.50	1.90	2.25		E
 DAT unit, MP3, soave rack mount		1.00	1.25	1.50		E
 CD player/changer, rack mount on shelf		1.00	1.25	1.50		E
 AM/FM Tuner, rack mount		1.00	1.25	1.50		E
 FM Antenna, rack mounted whip		0.40	0.50	0.60		E
 FM Antenna, roof mounted yagi on 10 foot mast w/ tripod		4.00	5.00	6.00		E
<b>Sound Systems - Pro-Sound - Theatrical Systems - Consoles, Mixers</b>						
 8 Channel desk console, multi-bus including hookup		1.25	1.60	1.90		E
 12 Channel desk mixing console, multi-bus, including hookup		1.50	1.90	2.25		E
 16 Channel desk mixing console, multi-bus including hookup		1.50	1.90	2.25		E
 24 Channel desk mixing console, multi-bus including hookup		2.00	2.50	3.00		E
 36 Channel desk mixing console, multi-bus including hookup		2.50	3.15	3.75		E
 Rack mount line, line/mic mixer		0.80	1.00	1.20		E
 4-channel auto mic mixer		3.00	3.75	4.50		E
 8-channel auto mic mixer		6.00	7.50	9.00		E
 Frame based automixer, 8 to 24 mic inputs		6.00	7.50	9.00		E
 Frame based automixer, 25-100 mic inputs		8.00	10.00	12.00		E
 Mixer-to-computer interface		1.00	1.25	1.50		E
 Remote Volume Control, Master Panel		1.25	1.60	1.90		E
 Remote Volume Control, wall mounted		0.75	0.95	1.15		E
 Custom rack panel (switches, controls, jacks)		3.00	3.75	4.50		E
 Rack mount VU monitor panel		1.25	1.60	1.90		E
 I/O Plates per connection		0.25	0.30	0.40		E
<b>Sound Systems - Sound Masking</b>						
 Stand-alone masking generator / amp / speaker unit		2.00	2.50	3.00		E
 Masking generator, rack mount		1.25	1.60	1.90		E
 Masking speaker, hanging above ceiling grid		1.00	1.25	1.50		E
 Step attenuator, mounted to masking back box		0.25	0.30	0.40		E
 Amplifier		2.00	2.50	3.00		E
<b>Audio Visual Systems - Source Equipment</b>						
 Playback Device (VCR / DVD / BluRay Player)		1.00	1.25	1.50		E
 Media Server / Computer Interface		2.00	2.50	3.00		E

Section 1 - Audio Visual

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Audio Visual Systems - Programming and Switching</b>						
 Line doubler		2.00	2.50	3.00		E
Video distribution amp.		1.00	1.25	1.50		E
Time code		2.00	2.50	3.00		E
Matrix switcher programming per I/O point		2.00	2.50	3.00		E
Matrix switcher (video) input/output per I/O point		2.00	2.50	3.00		E
Automatic Patching		2.00	2.50	3.00		E
<b>Audio Visual Systems - Playback</b>						
13" monitor (rack)		1.00	1.25	1.50		E
<25" monitor (wall)		2.00	2.50	3.00		E
27" to 42" monitor (wall)		2.50	3.15	3.75		E
42" to 60" monitor (wall)		3.00	3.75	4.50		E
Wall Mount Monitor Bracket		2.00	2.50	3.00		E
LCD Projector - Conference Room		2.50	3.15	4.50		E
LCD Projector - Auditorium		8.00	10.00	12.00		E
Projector Mounting Bracket - Conference Room		1.50	1.90	2.25		E
Projector Mounting Bracket - Auditorium		4.00	5.00	6.00		E
<b>Audio Visual Systems - Remote Control</b>						
Main CPU cage		4.00	5.00	6.00		E
Input/output cards		0.75	0.95	1.15		E
Power supply		0.75	0.95	1.15		E
Volume control		0.75	0.95	1.15		E
Relay cards (4)		1.00	1.25	1.50		E
Relay cards (8)		2.00	2.50	3.00		E
Hard button panel (8-12)		2.00	2.50	3.00		E
Hard button panel (12-24)		2.00	2.50	3.00		E
Programming Per Screen		4.00	5.00	6.00		E
System Programming Per I/O Point		4.00	5.00	6.00		E
<b>Audio Visual Systems - Interface Devices</b>						
Lighting (Communication Cable Connection)		1.00	1.25	1.56		E
Lighting (relay)		2.00	2.50	3.13		E
Dark out drapes (Communication Cable Connection)		1.00	1.25	1.56		E
Dark out drapes (relay)		2.00	2.50	3.13		E
<b>Audio Visual Systems - Teleconference</b>						
Teleconference bridge		2.00	2.50	3.00		E
Bridge programming		4.00	5.00	6.00		E
CODEX		4.00	5.00	6.00		E
<b>Audio Visual Systems - Patching</b>						
BNC 24 port		16.00	20.00	24.00		E
BNC 48 port		24.00	30.00	36.00		E
BNC 96 port		48.00	60.00	72.00		E
Twisted Pair 48 port		48.00	60.00	72.00		E
<b>Audio Visual Systems - Roll Down Screens</b>						
Manual		2.50	3.15	3.75		E
Motorized		4.00	5.00	6.00		E
Seismic support		4.00	5.00	6.00		E
Motorized Screen Control Switch		1.00	1.25	1.50		E
<b>Audio Visual Systems - Miscellaneous</b>						
Keyboard extender		0.50	0.65	0.75		E
Wireless mouse		0.50	0.65	0.75		E
Wireless keyboard		0.50	0.65	0.75		E
Infrared repeater		1.00	1.25	1.50		E
<b>Electronic Equipment - Miscellaneous Components - Power Supplies</b>						
Power supplies 50 watt		0.40	0.50	0.60		E
Power supplies 100 watt		0.50	0.65	0.75		E
Power supplies 200 watt		0.60	0.75	0.90		E
<b>Electronic Equipment - Miscellaneous Components - Speakers</b>						
Speakers 18 watt		0.75	0.95	1.15		E
Speakers 30 watt		0.75	0.95	1.15		E
Speakers 50 watt		1.00	1.25	1.56		E
Speakers 80 watt		2.00	2.50	3.13		E

Section 1 - Nurse Call

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Nurse Call System - Head End</b>						
 Nurse Call - Master Station		8.00	10.00	12.50		E
 Nurse Call - Nurse Station Annunciator		6.00	7.50	9.38		E
Power supply with back box		1.00	1.25	1.50		E
Monitor and keyboard		2.00	2.50	3.00		E
Printer		1.50	1.90	2.25		E
<b>Nurse Call System - Field Devices</b>						
 Single Bed Station		0.75	0.95	1.15		E
 Dual Bed Station		1.00	1.25	1.50		E
 Bed Station Call-In Cord		0.50	0.63	0.78		E
 Pull Cord		0.50	0.63	0.78		E
 Pillow Speaker		0.50	0.63	0.78		E
 Dome Light		0.50	0.65	0.81		E
 Zone Light		0.50	0.65	0.81		E
 Staff Station		0.50	0.65	0.81		E
 Duty Station		0.50	0.65	0.81		E
 Utility Station		0.50	0.65	0.81		E
 Emergency Station		0.50	0.63	0.78		E
 Toilet/Shower Station		0.50	0.63	0.78		E
 Code Blue Station		0.50	0.63	0.78		E
 Relay Module - Lighting Control		0.50	0.63	0.78		E
<b>Code Blue Systems</b>						
 Central Equipment		6.00	7.50	9.00		E
 Nurse's Station		4.00	5.00	6.00		E
 Annunciator		3.00	3.75	4.50		E
 Zone Light		0.50	0.65	0.75		E
 Pull Cord		0.25	0.30	0.40		E
 Power Supply		1.00	1.25	1.50		E
 Call Station		0.50	0.65	0.75		E
 Corridor Light		0.50	0.65	0.75		E
<b>Patient Monitoring System</b>						
 Patient Wandering Egress Panel	X					
 Patient Wandering Antenna	X	4.00	5.00	6.00		E
	X	2.00	2.50	3.00		E










Section 1 - Cabling System

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>Innerduct in Conduit - Indoor PVC/Plenum</b>						
1"		3.00	3.75	4.50		C
1 1/4"		4.00	5.00	6.00		C
1 1/2"		5.00	6.25	7.50		C
2"		6.00	7.50	9.00		C
 <b>Innerduct in Conduit - Outdoor PVC/Plenum</b>						
1"		3.00	3.75	4.50		C
1 1/4"		4.00	5.00	6.00		C
1 1/2"		5.00	6.25	7.50		C
2"		6.00	7.50	9.00		C
 <b>Innerduct: Not In Conduit - Indoor PVC / Plenum</b>						
1"		4.00	5.00	6.00		C
1 1/4"		5.00	6.25	7.50		C
1 1/2"		6.00	7.50	9.00		C
2"		7.00	8.75	10.50		C
 <b>Innerduct: Not In Conduit - Outdoor Buried (Reels) (Not Including Trenching)</b>						
1"		2.00	2.50	3.00		C
1 1/4"		3.00	3.75	4.50		C
1 1/2"		4.00	5.00	6.00		C
2"		5.00	6.25	7.50		C
 <b>Innerduct: Not In Conduit - Outdoor Aerial</b>						
1"		5.00	6.25	7.50		C
1 1/4"		6.00	7.50	9.00		C
1 1/2"		7.00	8.75	10.50		C
2"		8.00	10.00	12.00		C
 <b>Innerduct: Not In Conduit -Multi Duct (Not Incl. Trenching)</b>						
1 X 4		5.50	6.90	8.25		C
 <b>Innerduct</b>						
1" Innerduct w/Tape - Indoor Tray		3.25	4.10	4.90		C
1 1/4" Innerduct w/Tape - Indoor Tray		3.50	4.40	5.25		C
1 1/2" Innerduct w/Tape - Indoor Tray		3.75	4.70	5.60		C
2" Innerduct w/Tape - Indoor Tray		4.00	5.00	6.00		C
1" Innerduct w/Rope - In Conduit		2.50	3.15	3.75		C
1 1/2" Innerduct w/Tape - In Conduit		3.00	3.75	4.50		C
 <b>Optical Fiber Cable - Indoor in Conduit</b>						
2-12 Strand PVC / Plenum		6.00	7.50	9.00		M
12-96 Strand PVC / Plenum		7.00	8.75	10.50		M
96-144 Strand PVC / Plenum		8.00	10.00	12.00		M
 <b>Optical Fiber Cable - Indoor W/O Conduit</b>						
2-12 Strand PVC / Plenum		8.00	10.00	12.00		M
12-96 Strand PVC / Plenum		9.00	11.25	13.50		M
96-144 Strand PVC / Plenum		10.00	12.50	15.00		M
 <b>Fabric Inter Duct</b>						
3" 3 cell		8.00	10.00	12.00		M
2" 3 cell		8.00	10.00	12.00		M

Section 1 - Cabling System






Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>Optical Fiber Cable - Outdoor Underground in Conduit</b>						
12 - 144 Strand		12.00	15.00	18.00		M
144 - 288 Strand		14.00	17.50	21.00		M
288 - 432 Strand		18.00	22.50	27.00		M
432 & Above		20.00	25.00	30.00		M
<b>Optical Fiber Cable - Outdoor Direct Burial (Not Including Trenching)</b>						
12 - 144 Strand		11.00	13.75	16.50		M
144 - 288 Strand		13.00	16.25	19.50		M
288 - 432 Strand		17.00	21.25	25.50		M
432 & Above		19.00	23.75	28.50		M
<b>Optical Fiber Cable - Outdoor Aerial</b>						
12 - 144 Strand		60.00	75.00	90.00		M
144 - 288 Strand		65.00	81.25	97.50		M
288 - 432 Strand		70.00	87.50	105.00		M
432 & Above		76.00	95.00	114.00		M
<b>Cable Prep of Fiber - Gel Filled</b>						
Up to 12		2.00	2.50	3.00		E
12 - 24		2.50	3.13	3.75		E
24 - 48		3.00	3.75	4.50		E
48 - 72		3.50	4.40	5.25		E
72 - 96		4.00	5.00	6.00		E
96 - 144		6.00	7.50	9.00		E
<b>Cable Prep of Fiber - Unfilled</b>						
Up to 12		1.00	1.25	1.50		E
12 - 24		1.50	1.90	2.25		E
24 - 48		2.00	2.50	3.00		E
48 - 72		2.50	3.15	3.75		E
72 - 96		3.00	3.75	4.50		E
96 - 144		4.00	5.00	6.00		E
<b>Cable Prep of Fiber - Fanouts</b>						
Up to 12		2.00	2.50	3.00		E
12 - 24		3.00	3.75	4.50		E
24 - 48		4.00	5.00	6.00		E
<b>Splicing</b>						
Fusion - Single Strand		0.30	0.40	0.45		E
Fusion - Ribbon - 12 Strand		1.00	1.25	1.50		E
Mechanical - Single Strand		0.40	0.50	0.60		E
Mechanical - Array		1.00	1.25	1.50		E
<b>Splice Enclosure Indoor</b>						
Splice Cabinet		1.00	1.25	1.50		E
Splice Tray		0.25	0.30	0.40		E
<b>Splice Cables - Outdoor</b>						
Pedestal		2.00	2.50	3.00		E
Aerial		4.00	5.00	6.00		E
Underground		4.00	5.00	6.00		E




Section 1 - Cabling System

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Terminations Anaerobic</b>						
 SC		0.25	0.30	0.40		E
ST		0.25	0.30	0.40		E
LC		0.25	0.30	0.40		E
MTRJ		0.25	0.30	0.40		E
Crimp		0.25	0.30	0.40		E
<b>Hot Melt / Heat Cure / UV</b>						
SC		0.30	0.40	0.45		E
ST		0.30	0.40	0.45		E
LC		0.30	0.40	0.45		E
MTRJ		0.40	0.50	0.60		E
<b>Termination Boxes / Cabinets - Wall Mounted</b>						
6 Port LIU		0.40	0.50	0.60		E
8 Port LIU		0.40	0.50	0.60		E
12 Port LIU		0.40	0.50	0.60		E
16 Port LIU		0.40	0.50	0.60		E
24 Port LIU		1.00	1.25	1.50		E
48 Port LIU		1.00	1.25	1.50		E
<b>Termination Boxes / Cabinets - Rack Mount</b>						
24 Port		0.75	0.95	1.15		E
72 Port		0.75	0.95	1.15		E
<b>Termination Boxes / Cabinets - Misc</b>						
Connector Panel		0.10	0.13	0.15		E
Coupler		0.10	0.13	0.15		E
<b>Fiber Optic Cable - Patch Cords (Premade)</b>						
1M Simplex		0.10	0.13	0.15		E
3M Simplex		0.10	0.13	0.15		E
7M Simplex		0.15	0.19	0.23		E
1MDuplex		0.10	0.13	0.15		E
3M Duplex		0.10	0.13	0.15		E
7M Duplex		0.15	0.19	0.23		E
<b>Fiber Optic Cable - Fiber Testing (one wave length)</b>						
Light Source / Continuity		0.20	0.25	0.30		E
Power Meter - Single Direction		0.20	0.25	0.30		E
Power Meter - Bi-Directional		0.30	0.40	0.45		E
OTDR - Single Direction		0.20	0.25	0.30		E
OTDR Bi-Directional		0.30	0.40	0.45		E
OTDR - Single Direction W/ Documentation		0.50	0.65	0.75		E
OTDR - Bi-Directional W/ Documentation		0.75	0.95	1.15		E
<b>Fiber Optic Cable - Fiber Labeling</b>						
(4) ID Points Per Strand		0.20	0.25	0.30		E
<b>Copper Cable - UTP - PVC / Plenum Indoor In Conduit</b>						
4 Pair *		7.00	8.75	10.50		M
25 Pair *		8.00	10.00	12.00		M
50 Pair		10.00	12.50	15.00		M
100 Pair		12.00	15.00	18.00		M
200 Pair		16.00	20.00	24.00		M
300 Pair		24.00	30.00	36.00		M
*Note: Includes CAT 3, 5, 5E and 6						
*Note: Add 25% for CAT 6E, CAT 6A, CAT 9						

Section 1 - Cabling System

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Copper Cable - UTP - PVC / Plenum Indoor w/o Conduit</b>						
 4 Pair *		14.00	17.50	21.00		M
25 Pair *		16.00	20.00	24.00		M
50 Pair		20.00	25.00	30.00		M
100 Pair		24.00	30.00	36.00		M
200 Pair		32.00	40.00	48.00		M
300 Pair		48.00	60.00	72.00		M
*Note: Includes CAT 3, 5, 5E and 6						
*Note: Add 25% for CAT 6E, CAT 6A, CAT 9						
<b>Copper Cable - STP - PVC / Plenum Indoor In Conduit</b>						
 IBM Type 1, 2 and 9		10.00	12.50	15.00		M
2 Conductor Shielded 18 Ga		7.00	8.75	10.50		M
2 Pair Individually Shield (T-1)		10.00	12.50	15.00		M
4 Pair Shielded 24 Ga		8.00	10.00	12.00		M
25 Conductor (RS232)		12.00	15.00	18.00		M
<b>Copper Cable - STP - PVC / Plenum Indoors w/o Conduit</b>						
 IBM Type 1, 2 and 9		20.00	25.00	30.00		M
2 Conductor Shielded 18 Ga		14.00	17.50	21.00		M
2 Pair Individually Shield (T-1)		20.00	25.00	30.00		M
4 Pair Shielded 24 Ga		16.00	20.00	24.00		M
25 Conductor (RS232)		24.00	30.00	36.00		M
<b>Coaxial Cable - Indoor In Conduit PVC / Plenum</b>						
 RG 58 Thinnet		7.00	8.75	10.50		M
RG 59/U		7.00	8.75	10.50		M
RG 62/U		7.00	8.75	10.50		M
RG 6/U		8.00	10.00	12.00		M
RG 11/U		10.00	12.50	15.00		M
<b>Coaxial Cable - Indoor Not In Conduit PVC / Plenum</b>						
 RG 58 Thinnet		14.00	17.50	21.00		M
RG 59/U		14.00	17.50	21.00		M
RG 62/U		14.00	17.50	21.00		M
RG 6/U		16.00	20.00	24.00		M
RG 11/U		20.00	25.00	30.00		M

Section 1 - Cabling System

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Twisted Pair Cable - Riser Cable (Metal Jacket in Conduit)</b>						
 100 Pair		16.00	20.00	24.00		M
200 Pair		20.00	25.00	30.00		M
300 Pair		28.00	35.00	42.00		M
600 Pair		48.00	60.00	72.00		M
900 Pair		96.00	120.00	144.00		M
1200 Pair		144.00	180.00	216.00		M
<b>Twisted Pair Cable - Riser Cable Metal Jacket w/o Conduit</b>						
100 Pair		24.00	30.00	36.00		M
200 Pair		30.00	37.50	45.00		M
300 Pair		42.00	52.50	63.00		M
600 Pair		72.00	90.00	108.00		M
900 Pair		144.00	180.00	216.00		M
1200 Pair		216.00	270.00	324.00		M
<b>Twisted Pair Cable - Outdoor Underground In Conduit (OSP)</b>						
Up to 100 Pair		14.00	17.50	21.00		M
200 Pair		18.00	22.50	27.00		M
300 Pair		26.00	32.50	39.00		M
600 Pair		46.00	57.50	69.00		M
900 Pair		92.00	115.00	138.00		M
1200 Pair		136.00	170.00	204.00		M
<b>Twisted Pair Cable - Outdoor Direct Burial (OSP) Not Including Trenching</b>						
Up to 100 Pair		11.00	13.75	16.50		M
200 Pair		16.00	20.00	24.00		M
300 Pair		20.00	25.00	30.00		M
600 Pair		24.00	30.00	36.00		M
900 Pair		32.00	40.00	48.00		M
1200 Pair		48.00	60.00	72.00		M
<b>Twisted Pair Cable - Outdoor Aerial (OSP)</b>						
Up to 100 Pair		40.00	50.00	60.00		M
200 Pair		44.00	55.00	66.00		M
300 Pair		48.00	60.00	72.00		M
600 Pair		65.00	81.25	97.50		M
900 Pair		70.00	87.50	105.00		M
1200 Pair		75.00	93.75	112.50		M
<b>Copper Splice Enclosures</b>						
Pedestal		2.00	2.50	3.00		E
Buried		4.00	5.00	6.00		E
Aerial		4.00	5.00	6.00		E
Underground		4.00	5.00	6.00		E
Riser		3.00	3.75	4.50		E
<b>Splice Enclosures</b>						
710 25 Pr Module		0.50	0.65	0.75		E
Pic-A-Bond Single Pair Module		0.25	0.30	0.40		E
Scotch-lock Single Conductor Module		0.15	0.19	0.23		E
<b>Copper Termination Hardware</b>						
100 Pr 110 Block Mount Only		0.25	0.30	0.40		E
300 Pr 110 Block Mount Only		0.25	0.30	0.40		E
C4/C5 Clip		5.00	6.25	7.50		C
110 Termination		2.00	2.50	3.00		C
110 Designation Strip (25 Pr)		0.10	0.13	0.15		E
66 Block Mount Only		0.25	0.30	0.40		E
66 Termination		2.00	2.50	3.00		C
66 Block Designation Strip		0.10	0.13	0.15		E
89 B Bracket		0.25	0.30	0.40		E
BIX Block Mount Only		0.25	0.30	0.40		E
BIX Terminations		2.00	2.50	3.00		C
BIX Block Designation Strips		0.10	0.13	0.15		E
100 Pr Lightning Protector (Direct Termination) Mo		1.00	1.25	1.50		E
100 Pr Lightning Protector (With Splice Tails) Mou		2.00	2.50	3.00		E
Protector Modules		2.00	2.50	3.00		C



Section 1 - Cabling System

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Patch Panel Mounting Only</b>						
 12, 24, 48 Port Wall Mount		1.00	1.25	1.50		E
12, 24, 48 Port Rack Mount		1.00	1.25	1.50		E
<b>Patch Panel Termination</b>						
RJ-11 Jack		0.10	0.13	0.15		E
RJ-45 Jack		0.20	0.25	0.30		E
Coax Jack		0.20	0.25	0.30		E
<b>Wire Managers</b>						
110 Stand Off Bracket		0.20	0.25	0.30		E
Split D Ring		0.10	0.13	0.15		E
Horizontal Rack Mount		0.20	0.25	0.30		E
Horizontal Wall Mount		0.20	0.25	0.30		E
Vertical Rack Mount		0.30	0.40	0.45		E
Vertical Wall Mount		0.30	0.40	0.45		E
Brackets For Wall Mount		0.30	0.40	0.45		E
Cable Dressing (Velcro)		8.00	10.00	12.00		C
<b>Wall Mounted Racks / Cabinets (Assemble and Mount)</b>						
4' Rack (Fixed)		2.00	2.50	3.00		E
4' Rack (Hinged)		2.00	2.50	3.00		E
4' Cabinet		4.00	5.00	6.00		E
<b>Floor Mount (Assemble and Mount)</b>						
7' Open Rack		3.00	3.75	4.50		E
7' Cabinet (Fully Equipped, Includes Power Strips,		12.00	15.00	18.00		E
72" no doors		12.00	15.00	18.75		E
Doors front		2.00	2.50	3.13		E
Doors		2.00	2.50	3.13		E
AC power strip		1.00	1.25	1.56		E

## Section 1 - Cabling System

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Work Area Terminations</b>						
		0.20	0.25	0.30		E
Double Gang Box Eliminator		0.20	0.25	0.30		E
RJ-11 Jack Surface Mount		0.25	0.30	0.40		E
RJ-45 Jack Surface Mount		0.30	0.40	0.45		E
1 Gang Face Plate		0.10	0.13	0.15		E
1 Gang Surface Mount Box		0.25	0.30	0.40		E
		0.10	0.13	0.15		E
2 Gang Surface Mount Box		0.25	0.30	0.40		E
RJ-11 Modular Jack		0.10	0.13	0.15		E
RJ-45 Modular Jack		0.20	0.25	0.30		E
Type F Modular Jack		0.20	0.25	0.30		E
BNC Modular Jack		0.20	0.25	0.30		E
RCA Module		0.50	0.65	0.75		E
Blank Module		0.10	0.13	0.15		E
<b>Miscellaneous Connectors</b>						
RCA Connector		0.50	0.65	0.75		E
		0.20	0.25	0.30		E
Coax BNC Connector		0.20	0.25	0.30		E
F Terminator		0.10	0.13	0.15		E
DB-9 Connector		0.50	0.65	0.75		E
DB-15 Connector		0.50	0.65	0.75		E
DB-25 Connector		0.75	0.95	1.15		E
		1.00	1.25	1.50		E
IBM Type A Connector		0.50	0.65	0.75		E
Inline Coupler		0.10	0.13	0.15		E
Male/Female Adapter		0.10	0.13	0.15		E
Balun		0.10	0.13	0.15		E
<b>Patch Cords</b>						
		0.10	0.13	0.15		E
5' Patch Cord		0.10	0.13	0.15		E
7' Patch Cord		0.10	0.13	0.15		E
10' Patch Cord		0.10	0.13	0.15		E
14' Patch Cord		0.10	0.13	0.15		E
25' Patch Cord		0.10	0.13	0.15		E
<b>Cross Connects</b>						
		0.20	0.25	0.30		E
2Pr 20' Max		0.30	0.40	0.45		E
3Pr 20' Max		0.40	0.50	0.60		E
4Pr 20' Max		0.50	0.65	0.75		E

Section 1 - Cabling System

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Copper Testing</b>						
 4 Pair Continuity Test		0.20	0.25	0.30		E
25 Pair Continuity Test		0.50	0.65	0.75		E
4 Pair Certification		0.40	0.50	0.60		E
4 Pair Certification w/ Documentation		0.50	0.65	0.75		E
<b>Copper Labeling</b>						
4 ID Points Per Cable		0.20	0.25	0.30		E
<b>Firestopping</b>						
<i>Grounding: See Grounding Section 8</i>						
Cable Penetration up to 1"		0.50	0.65	0.75		E
Sleeving Up To 4"		1.00	1.25	1.50		E
Cable Tray Up To 18"		2.00	2.50	3.00		E
Plywood Backboard 4' X 8' Fire Rated		1.50	1.90	2.25		E
<b>Cable Supports</b>						
J - Hooks		5.00	6.25	7.50		C
Beam Clamps		5.00	6.25	7.50		C
Concrete Anchor		10.00	12.50	15.00		C
Hollow Wall Anchor		10.00	12.50	15.00		C
D - Rings		5.00	6.25	7.50		C
<b>Electronic Equipment - Miscellaneous Components - Switches</b>						
Toggle switches SPST		0.15	0.19	0.23		E
Toggle switches DPDT		0.20	0.25	0.30		E
Toggle switches 3PDT		0.20	0.25	0.30		E
Toggle switches 4PDT		0.20	0.25	0.30		E
Snap switches SPST		0.15	0.19	0.23		E
Snap switches SPDT		0.15	0.19	0.23		E
<b>Electronic Equipment - Miscellaneous Components - Terminals</b>						
Solderless terminals #22-18		0.10	0.13	0.15		E
Solderless terminals #16-14		0.10	0.13	0.15		E
Solderless terminals #12-10		0.10	0.13	0.15		E
Terminal blocks 2 circuit		0.15	0.19	0.23		E
Terminal blocks 4 circuit		0.15	0.19	0.23		E
Terminal blocks 8 circuit		0.20	0.25	0.30		E
Terminal blocks 12 circuit		0.20	0.25	0.30		E
Terminal blocks 20 circuit		0.25	0.30	0.40		E
<b>Electronic Equipment - Miscellaneous Components - Meters</b>						
Panel meters, 2-1/2" sq.		0.40	0.50	0.60		E
<b>Electronic Equipment - Miscellaneous Components - Jacks, Wall Plates</b>						
Standard phone jack		0.15	0.19	0.23		E
Shielded phone jack		0.20	0.25	0.30		E
<b>Lighting Controls</b>						
Light Level Sensor		0.30	0.40	0.45		E
Lighting Controller		2.50	3.15	3.75		E
4 Pole Lighting Contactor		2.00	2.50	3.00		E
8 Pole Lighting Contactor		3.00	3.75	4.50		E
12 Pole Lighting Contactor		4.00	5.00	6.00		E
2400 W Dimming Controller		1.00	1.25	1.50		E
<b>Electronic Equipment</b>						
Plug-in relay		0.20	0.25	0.30		E
Relay socket		0.20	0.25	0.30		E

Section 1 - Low Voltage Lighting Control

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
The labor units are based on Lutron Grafik Eye, Ecosys and Quantum systems. Visit www.lutron.com for all component specifications						
<b>Lighting Control Systems</b>						
*** Note - Add additional labor to test and start-up these systems ***						
**** Note - For Line Voltage see Section 6	X					
Control Panel		8.00	10.00	12.50		E
Control Panel - w/ Electric Shade Control		10.00	12.50	15.63		E
2C #16AWG Cable (Plenum/Non-Plenum) w/o Conduit		16.00	20.00	25.00		M
2C #18, 2#22AWG Cable (Plenum/Non-Plenum) w/o Conduit		17.00	21.25	26.56		M
5C #22AWG Cable (Plenum/Non-Plenum) w/o Conduit		18.00	22.50	28.13		M
2C #12, 2C #22, 1C#18, 1c #24 AWG (Plenum/Non-Plenum) w/o Conduit		20.00	25.00	31.25		M
Termination of LV Digital Bus - Pre-Installed Ballast		0.30	0.38	0.47		E
Termination of LV Digital Bus - Pre-Installed LED Driver		0.30	0.38	0.47		E
Bus Supply Module		0.80	1.00	1.25		E
Dimming Power Module for 3-wire Lutron Dimming Ballasts		0.80	1.00	1.25		E
Emergency Lighting Interface Module		0.80	1.00	1.25		E
Motor Group Controller		1.25	1.56	1.95		E
Timeclock		1.50	1.88	2.34		E
Sensor Module		0.80	1.00	1.25		E
4-Button Wall Control with Raise/Lower		0.75	0.94	1.17		E
Wireless Control and Mounting Accessories		0.35	0.44	0.55		E
PicoR Wired Control		0.60	0.75	0.94		E
Level Remote Control		0.25	0.31	0.39		E
Fixture Mountable Infrared Sensor		0.50	0.63	0.78		E
Fixture Mountable Daylight Sensor with IR Receiver		0.50	0.63	0.78		E
Wireless Ceiling Mount Sensor		0.35	0.44	0.55		E
Wireless Daylight Ceiling Mount Sensor		0.35	0.44	0.55		E
Wireless Wall-Mount Sensor		0.35	0.44	0.55		E
Dual Technology Ceiling Mount Sensor		0.50	0.63	0.79		E
Infrared Ceiling Mount Sensor		0.50	0.63	0.79		E
Ultrasonic Ceiling Mount Sensor		0.50	0.63	0.79		E
Power Pack 120/277V-24V		0.50	0.63	0.79		E
Auxiliary Power Pack 120/277V-24V		0.50	0.63	0.79		E
AV Control Interface		0.80	1.00	1.25		E
Ethernet Lighting and Shade Control Interface		0.75	0.94	1.17		E
Lighting and Shade Control Interface		0.75	0.94	1.17		E
Programming Control Interface		0.75	0.94	1.17		E
DMX Control Interface		0.75	0.94	1.17		E
DMX 512 Control Interface		1.25	1.56	1.95		E
Control Interface for Misc Points		0.75	0.94	1.17		E
Infrared Transmitter/Receiver Pair		1.00	1.25	1.56		E
2-Button Scene/Pushbutton Wallstation		0.65	0.81	1.02		E
3-Button Scene/Pushbutton Wallstation		0.85	1.06	1.33		E
4-Button Scene/Pushbutton Wallstation		1.05	1.31	1.64		E
5-Button Scene/Pushbutton Wallstation		1.30	1.63	2.03		E
6-Button Scene/Pushbutton Wallstation		1.80	2.25	2.81		E
7-Button Scene/Pushbutton Wallstation		2.00	2.50	3.13		E
8-Button Scene/Pushbutton Wallstation		2.25	2.81	3.52		E
10-Button Scene/Pushbutton Wallstation		2.50	3.13	3.91		E
Keyswitch Wallstation		0.45	0.56	0.70		E
Wall Mount 120v Main Unit - 3 Zone		4.00	5.00	6.25		E
Wall Mount 120v Main Unit - 4 Zone		5.00	6.25	7.81		E
Wall Mount 120v Main Unit - 6 Zone		6.00	7.50	9.38		E
Wall Mount LV Main Unit - 2 Zone		4.00	5.00	6.25		E
Wall Mount LV Main Unit - 3 Zone		4.00	5.00	6.25		E
Wall Mount LV Main Unit - 4 Zone		5.00	6.25	7.81		E
Wall Mount LV Main Unit - 6 Zone		6.00	7.50	9.38		E
Wall Mount LV Main Unit - 8 Zone		7.00	8.75	10.94		E
Wall Mount LV Main Unit - 16 Zone		10.00	12.50	15.63		E
Wall Mount LV Main Unit - 24 Zone		12.00	15.00	18.75		E
Slider Control Unit		4.00	5.00	6.25		E







# SECTION 2

## CONDUIT, RACEWAYS, FITTINGS AND RELATED ITEMS

### General Information

This section includes labor units for conduit, conduit fittings, conduit bending, boxes, enclosures, surface metal raceways, underfloor duct, cable trays, anchors, fasteners, supports, fireproofing material and related items.

### Scope of These Labor Units

The Introduction section includes details on the scope of labor units across the manual. Some items included are:

- Material unloading, jobsite storage and delivery to the installation area
- Drawing and specification study
- Layout, measuring and marking the installation location
- Tool acquisition and return to storage
- Measuring, cutting, threading and handling conduit
- Material assembly and installation
- Conduit offset bending
- Normal non-productive labor

### Work Operations Not Included In These Labor Units

- Field supervision
- Hoisting above three floors
- Welding or painting
- Fasteners for conduit (List separately and apply fastener labor units)
- Rerouting conduit due to structural or mechanical obstacles

### Labor Adjustments for Non-Typical Conditions

See the Introduction section for details.

### Application Instructions

- Labor units for conduit termination material include installing the locknuts and bushings as well as measuring, cutting, offset bending of sizes ½"-1", threading and installing a less than full length of conduit, which is normally required on one end of each circuit run.
- Labor for terminating conduit in threaded hub fittings and threaded hub boxes is included in the hub fitting or hub box labor units.
- The labor units for conduit terminations with ground bushings include the labor for connecting the grounding conductor.
- Labor units for conduit factory elbows include the coupling and elbow installation labor as well as the measuring, cutting, threading and installation of a less than full length of conduit, which is normally required on one end of each elbow.
- For installations more than 20 feet above a smooth hard floor, these labor units need to be increased in proportion to the additional height above 20 feet and the degree of installation difficulty.
- Labor units in this manual are for new work only and for a complete electrical installation. For remodeling or change order situations these labor units need to be substantially increased.
- Labor units for buried plastic conduit outside of buildings may be found in Section 11.
- Reducing the estimated labor due to multiple parallel runs is a common practice as installing multiple parallel runs of similar raceway material will increase efficiency and productivity. Caution should be taken and all other installation conditions should be considered before applying such factoring as there is no safe way to predict a factor amount and its relationship with the number of runs and assume that it would apply to all job conditions. Appendix E contains a chart to help address this impact.





## Section 2 - Conduit, Raceways, Fittings & Related Items Table of Contents

<b>Rigid Steel Conduit (GRC or GRS) and Fittings</b>		2-15	<b>2</b>
Rigid Steel Conduit with Threaded Couplings		2-15	
Rigid Steel Factory Elbows		2-15	
Field Bending Steel Conduit & Installation		2-15	
Plastic Bushing Only		2-15	
Rigid Conduit Locknut Only		2-16	
Lock Nut & Ground Bushing Sets - Field Cut & Thread Included		2-16	
Factory Cut Rigid Steel Nipples		2-16	
Field Cut Rigid Steel Nipples & Installation		2-16	
Steel Chase Nipples - Includes Locknut & Bushing		2-16	
Steel Offset Nipples - Includes Locknut & Bushings		2-16	
Steel Threaded Reducers		2-17	
Steel Compression Couplings		2-17	
Steel Split Couplings		2-17	
Rigid Steel Expansion / Deflection Couplings	<i>(Updated)</i>	2-17	
Steel Erickson Couplings		2-17	
Steel Threaded Entrance Elbows		2-17	
Steel Threadless Box Connectors		2-17	
Steel Threaded Box Connectors (Myers Hub)		2-18	
Steel Threaded Service Entrance Caps		2-18	
Steel Threaded Capped Elbows		2-18	
Steel Pipe Caps or Capped Bushings		2-18	
Steel Threaded Conduit Bodies-One Hub		2-18	
Steel Threaded Conduit Bodies-Two Hubs		2-18	
Steel Threaded Conduit Bodies-Three Hubs		2-19	
Steel Threaded Conduit Bodies-Four Hubs		2-19	
Steel Mogul Conduit Bodies-Two Hubs		2-19	
Steel Mogul Conduit Bodies-Three Hubs		2-19	
Steel Mogul Conduit Bodies-Four Hubs		2-19	
Iron FS & FD Threaded 1-Gang Boxes		2-19	
Iron FS & FD Threaded 2-Gang Boxes		2-19	
Iron FS & FD Threaded 3-Gang Boxes		2-20	
Iron FS & FD Box Covers		2-20	
Knockout Type Steel Boxes	<i>(Updated)</i>	2-20	
Knockout Type Steel Boxes - Masonry		2-20	
Knockout Type Steel Boxes - Wall Boxes		2-20	
Knockout Type Steel Boxes - Accessories		2-20	
Threaded Cast Round Outlet Boxes		2-21	
Knockout Type Steel Boxes		2-21	
Threaded Cast Floor Boxes		2-21	
Floor Boxes		2-21	
Cast Iron Junction Boxes		2-21	
<b>Electrical Metallic Tubing (EMT) and Fittings</b>		2-22	
Electrical Metallic Tubing (EMT)	<i>(Updated)</i>	2-22	
EMT Set Screw Couplings		2-22	
EMT Factory Elbows		2-22	
Field Bending EMT Conduit and Installation		2-22	
EMT Set Screw Box Connectors		2-22	
EMT Compression Box Connectors		2-22	
EMT Compression Couplings		2-23	
EMT Service Elbows		2-23	
EMT Service Entrance Caps		2-23	
EMT to Rigid Conduit Adapters		2-23	
EMT to Flexible Conduit Couplings		2-23	
EMT to EMT Reducing Couplings		2-23	
EMT Expansion/Deflection Coupling	<i>(Updated)</i>	2-23	

## Section 2 - Conduit, Raceways, Fittings & Related Items Table of Contents

Steel Set Screw Conduit Bodies	2-24
Threadless Conduit Bodies for EMT & Rigid Steel Conduit	2-24
<b>Intermediate Metal Conduit (IMC) and Fittings</b>	2-25
Intermediate Metal Conduit (IMC) with Couplings	2-25
IMC Factory Elbows	2-25
Field Bending IMC Conduit and Installation	2-25
IMC Field Cut Nipples and Installation	2-25
<b>Rigid Aluminum Conduit and Fittings</b>	2-26
Rigid Aluminum Conduit with Couplings	2-26
Rigid Aluminum Factory Elbows	2-26
Field Bending Rigid Aluminum Conduit and Installation	2-26
Aluminum Lock Nut & Bushing Sets	2-26
Aluminum Lock Nut & Ground Bushing Sets	2-26
Aluminum Factory Cut Nipples	2-27
Aluminum Field Cut Nipples and Installation	2-27
Aluminum Chase Nipples	2-27
Aluminum Offset Nipples	2-27
Aluminum Female Threaded Reducers	2-27
Aluminum Compression Couplings	2-27
Aluminum Split Couplings	2-28
Aluminum Expansion Couplings	2-28
Aluminum Erickson Couplings	2-28
Aluminum Threaded Entrance Elbows	2-28
Aluminum Threadless Box Connectors	2-28
Aluminum Threaded Service Entrance Caps	2-28
Aluminum Threaded Capped Elbows	2-29
Aluminum Pipe Caps or Capped Bushings	2-29
Aluminum Threaded Conduit Bodies-One Hub	2-29
Aluminum Threaded Conduit Bodies-Two Hubs	2-29
Aluminum Threaded Conduit Bodies-Three Hubs	2-29
Aluminum Threaded Conduit Bodies-Four Hubs	2-29
Aluminum Mogul Conduit Bodies-Two Hubs	2-29
Aluminum Mogul Conduit Bodies-Three Hubs	2-30
Aluminum FS & FD Threaded 1-Gang Boxes	2-30
Aluminum FS & FD Threaded 2-Gang Boxes	2-30
Weatherproof Aluminum Boxes 1-Gang	2-30
<b>Flexible Steel Conduit (FSC or Greenfield) and Fittings</b>	2-31
Flexible Steel Conduit (FSC)	2-31
FSC to Box Connectors	2-31
FSC to Rigid Steel Conduit Couplings	2-31
FSC to EMT Couplings	2-31
FSC Duplex Box Converters	2-31
<b>Sealtite Flexible Conduit and Fittings</b>	2-32
Liquidtight Flexible Steel Conduit (LFSC)	2-32
LFSC to Box Connectors	2-32
LFSC to Rigid Steel Conduit Couplings	2-32
LFSC to EMT Couplings	2-32
<b>PVC Coated Rigid Steel Conduit</b>	2-33
PVC Coated Rigid Steel Conduit	2-33
PVC Coated Rigid Steel Elbows	2-33
PVC Coated Rigid Steel Elbows - 48" Radius	2-33
PVC Coated Termination Sets	2-33

## Section 2 - Conduit, Raceways, Fittings & Related Items Table of Contents

PVC Coated Steel Factory Nipples	2-33	
PVC Coated Steel Field Cut Nipples	2-34	
PVC Coated Steel Offset Nipples	2-34	
PVC Coated Couplings	2-34	
PVC Coated Steel Split Couplings	2-34	
PVC Coated Expansion Couplings	2-34	
<b>PVC Rigid Conduit</b>	2-35	
PVC Rigid Conduit - Schedule 40 with Couplings	2-35	
PVC Factory Elbows-Sch 40	2-35	
Field Bent PVC Conduit and Installation	2-35	
PVC Conduit Adapters-All Types	2-35	
PVC Expansion Couplings-Sch 40	2-35	
PVC Bell Ends-Sch 40	2-36	
PVC Conduit End Caps-Sch 40	2-36	
PVC Rigid Conduit - Schedule 80 with Couplings	2-36	<i>(Updated)</i>
PVC Factory Elbows-Sch 80	2-36	
Field Bent Schedule 80 PVC Conduit and Installation	2-36	
Schedule 80 PVC Conduit Adapters-All Types	2-36	
PVC Expansion Couplings-Sch 80	2-37	
PVC Junction Boxes & Pull Boxes	2-37	
PVC Conduit Bodies	2-37	
PVC Boxes	2-37	
PVC Handy Boxes	2-37	
<b>Fiberglass Conduit</b>	2-38	
Fiberglass Conduit - 10Ft & 20Ft Len. w/ Glued Couplings	2-38	
Fiberglass Conduit Glued Couplings	2-38	
Fiberglass Conduit 90 Degree Elbows	2-38	
Fiberglass Conduit Threaded Adapters	2-38	
Fiberglass Conduit Expansion Couplings	2-38	
<b>ENT Conduit</b>	2-39	
Electrical Non-Metallic Flexible Tubing (ENT)	2-39	
ENT Couplings	2-39	
ENT Box Connectors-Threaded Type	2-39	
ENT Box Connectors-Threaded Elbows	2-39	
ENT Box Connectors-Snap In Type	2-39	
<b>LNT Conduit</b>	2-40	
Liquidtight Non-Metallic Flexible Tubing (LNT)	2-40	
LNT Box Connectors-Threaded Type	2-40	
LNT Box Connectors-Threaded Elbows	2-40	
NEMA 1 Screw cover J-Boxes & Pull Boxes with Knockouts	2-40	<i>(Updated)</i>
NEMA 3R Rain-tight J-Boxes & Pull Boxes	2-40	<i>(Updated)</i>
NEMA 12 Hinged Cover J-Boxes & Pull Boxes	2-40	<i>(Updated)</i>
NEMA 4 J-Boxes & Pull Boxes	2-40	<i>(Updated)</i>
NEMA 13 J-Boxes & Pull Boxes	2-41	<i>(Updated)</i>
CT Cabinets	2-41	<i>(Updated)</i>
Field Cut Knockouts in J-Boxes & Pull Boxes	2-41	<i>(Updated)</i>
Custom Made #10 Gage Steel Pull Boxes WxHxD	2-41	
<b>Surface Metal Raceways</b>	2-42	

## Section 2 - Conduit, Raceways, Fittings & Related Items Table of Contents

<b>Nonmetallic Surface Raceways</b>	2-46
Wiremold Product - Available in 6' and 8' lengths	2-46
Device boxes for 2700/2800/2900	2-46
Wiremold product - 5' lengths only	2-46
Device boxes for 400/800/2300 Selected Series	2-47
Wiremold Product - 8' Lengths only	2-47
Device boxes for NM2000	2-47
Wiremold product - 8' Lengths only	2-47
Wiremold product - Power and low voltage applications - Available in 8' and 10' lengths	2-48
Device boxes for PN05A/PN10A series raceways	2-48
Wiremold Product - Power and low voltage applications - 8' lengths only	2-48
Device boxes for PN20A series raceways	2-48
Wiremold product - Cablesmart series for power and low voltage applications - 8' lengths only	2-48
Wiremold product - Large cable capacity for power and low voltage applications - 8' lengths only	2-49
<b>Metal Wireway</b>	2-50
Hinged Cover Lay-In Wireways	2-50
Hinged Cover Lay-In Wireways - Fittings	2-50
Hinged Cover Lay-In Wireways - Accessories	2-50
Hinged Cover Lay-In Wireways - Brackets	2-50
Hinged Cover Lay-In Wireways - Miscellaneous	2-50
Screwed Cover Lay-In Wireways	2-50
Screwed Cover Lay-In Wireways - Fittings	2-51
Screwed Cover Lay-In Wireways - Adapters	2-51
Screwed Cover Lay-In Wireways - Brackets	2-51
Screwed Cover Lay-In Wireways - Miscellaneous	2-51
Flanged End Wireways with Knockouts	2-51
Flanged End Wireways with Knockouts - Fittings	2-52
Flanged End Wireways with Knockouts - Connectors	2-52
Flanged End Wireways with Knockouts - Brackets	2-52
Flanged End Wireways with Knockouts - Miscellaneous	2-52
Flanged End Wireways with Knockouts - End Caps	2-52
J.I.C. Type Wireways without Knockouts	2-53
J.I.C. Type Wireways without Knockouts - Connectors & Brackets	2-53
Channel Type Raceways & Fixture Supports	2-53
<b>Underfloor Duct</b>	2-54
Steel Underfloor Duct & Fittings	2-54
Cellular Underfloor Duct-3 Cell	2-54
3-Cell Junction Boxes	2-54
3-Cell Elbows	2-54
3-Cell Duct Support & Couplings	2-54
Header Sections	2-54
Field Installed Preset Inserts	2-54
Duct End Closures	2-54
Duct Marker Items	2-55
Header Items	2-55
3 1/4" x 1 1/4" Flushduct	2-55
Underfloor Duct Accessories	2-55
Underfloor Duct Outlet Receptacles	2-55
<b>Trench Duct</b>	2-56
Solid Bottom Trench Duct	2-56
Cellular Trench Duct	2-56
Trench Duct Elbows	2-56
Trench Duct Tees	2-56
Trench Duct Crosses	2-56

## Section 2 - Conduit, Raceways, Fittings & Related Items Table of Contents

Trench Duct Wall Elbows & Panel Risers	2-56
Trench Duct Cover Plates	2-56
<b>Cable Tray</b>	2-57
<b>Steel Tray 3" Depth</b>	2-57
Steel Ladder Cable Tray - 6" Rung Spacing - 3" Depth	2-57
Steel Ladder Cable Tray - 9" Rung Spacing - 3" Depth	2-57
Steel Ladder Cable Tray - 12" Rung Spacing - 3" Depth	2-57
Steel Ladder Cable Tray - 18" Rung Spacing - 3" Depth	2-57
Steel - 45 Degree Elbow - 3" Depth	2-57
Steel - 90 Degree Elbow - 3" Depth	2-57
Steel - Tee - 3" Depth	2-57
Steel - Cross - 3" Depth	2-57
Steel - Reducer - 3" Depth	2-58
Steel - Vertical 45 Degree Elbow - 3" Depth	2-58
Steel - Vertical 90 Degree Elbow - 3" Depth	2-58
Steel - Vertical Tee - 3" Depth	2-58
<b>Steel Tray 4" Depth</b>	2-59
Steel Ladder Cable Tray - 6" Rung Spacing - 4" Depth	2-59
Steel Ladder Cable Tray - 9" Rung Spacing - 4" Depth	2-59
Steel Ladder Cable Tray - 12" Rung Spacing - 4" Depth	2-59
Steel Ladder Cable Tray - 18" Rung Spacing - 4" Depth	2-59
Steel - 45 Degree Elbow - 4" Depth	2-59
Steel - 90 Degree Elbow - 4" Depth	2-59
Steel - Tee - 4" Depth	2-59
Steel - Cross - 4" Depth	2-59
Steel - Reducer - 4" Depth	2-60
Steel - Vertical 45 Degree Elbow - 4" Depth	2-60
Steel - Vertical 90 Degree Elbow - 4" Depth	2-60
Steel - Vertical Tee - 4" Depth	2-60
<b>Steel Tray 6" Depth</b>	2-61
Steel Ladder Cable Tray - 6" Rung Spacing - 6" Depth	2-61
Steel Ladder Cable Tray - 9" Rung Spacing - 6" Depth	2-61
Steel Ladder Cable Tray - 12" Rung Spacing - 6" Depth	2-61
Steel Ladder Cable Tray - 18" Rung Spacing - 6" Depth	2-61
Steel - 45 Degree Elbow - 6" Depth	2-61
Steel - 90 Degree Elbow - 6" Depth	2-61
Steel - Tee - 6" Depth	2-61
Steel - Cross - 6" Depth	2-61
Steel - Reducer - 6" Depth	2-62
Steel - Vertical 45 Degree Elbow - 6" Depth	2-62
Steel - Vertical 90 Degree Elbow - 6" Depth	2-62
Steel - Vertical Tee - 6" Depth	2-62
<b>Steel Cable Tray Fittings &amp; Accessories</b>	2-63
Combination Hold-Down Clamp and Expansion Guide	2-63
Steel Cable Tray - Solid Covers	2-63
Steel Cable Tray - Solid Cover Clamps (Per Pair)	2-63
Steel - 45 Degree Elbow - Solid Covers	2-63
Steel - 90 Degree Elbow - Solid Covers	2-63
Steel - Tee - Solid Covers	2-63
Steel - Cross - Solid Covers	2-63
Steel - Reducer - Solid Covers	2-63
Steel - Vertical 45 Degree Elbow - Solid Covers	2-63
Steel - Vertical 90 Degree Elbow - Solid Covers	2-64

## Section 2 - Conduit, Raceways, Fittings & Related Items Table of Contents

2

Steel - Vertical Tee - Solid Covers	2-64
Steel - Enclosure Connectors	2-64
Steel - End Plates	2-64
Steel - Ladder Drop-Outs	2-64
Steel - Splice Plates Pair	2-64
Steel Cable Tray Barrier Strips	2-64
Steel Cable Tray Fitting Barrier Strips	2-64
Steel Conduit To Cable Tray Adapters	2-64
Bonding Jumpers	2-64
<b>Aluminum Tray 3" Depth</b>	2-65
Aluminum Ladder Cable Tray - 6" Rung Spacing - 3" Depth	2-65
Aluminum Ladder Cable Tray - 9" Rung Spacing - 3" Depth	2-65
Aluminum Ladder Cable Tray - 12" Rung Spacing - 3" Depth	2-65
Aluminum Ladder Cable Tray - 18" Rung Spacing - 3" Depth	2-65
Aluminum - 45 Degree Elbow - 3" Depth	2-65
Aluminum - 90 Degree Elbow - 3" Depth	2-65
Aluminum - Tee - 3" Depth	2-65
Aluminum - Cross - 3" Depth	2-65
Aluminum - Reducer - 3" Depth	2-65
Aluminum - Vertical 45 Degree Elbow - 3" Depth	2-66
Aluminum - Vertical 90 Degree Elbow - 3" Depth	2-66
Aluminum - Vertical Tee - 3" Depth	2-66
<b>Aluminum Tray 4" Depth</b>	2-67
Aluminum Ladder Cable Tray - 6" Rung Spacing - 4" Depth	2-67
Aluminum Ladder Cable Tray - 9" Rung Spacing - 4" Depth	2-67
Aluminum Ladder Cable Tray - 12" Rung Spacing - 4" Depth	2-67
Aluminum Ladder Cable Tray - 18" Rung Spacing - 4" Depth	2-67
Aluminum - 45 Degree Elbow - 4" Depth	2-67
Aluminum - 90 Degree Elbow - 4" Depth	2-67
Aluminum - Tee - 4" Depth	2-67
Aluminum - Cross - 4" Depth	2-67
Aluminum - Reducer - 4" Depth	2-68
Aluminum - Vertical 45 Degree Elbow - 4" Depth	2-68
Aluminum - Vertical 90 Degree Elbow - 4" Depth	2-68
Aluminum - Vertical Tee - 4" Depth	2-68
<b>Aluminum Tray 6" Depth</b>	2-69
Aluminum Ladder Cable Tray - 6" Rung Spacing - 6" Depth	2-69
Aluminum Ladder Cable Tray - 9" Rung Spacing - 6" Depth	2-69
Aluminum Ladder Cable Tray - 12" Rung Spacing - 6" Depth	2-69
Aluminum Ladder Cable Tray - 18" Rung Spacing - 6" Depth	2-69
Aluminum - 45 Degree Elbow - 6" Depth	2-69
Aluminum - 90 Degree Elbow - 6" Depth	2-69
Aluminum - Tee - 6" Depth	2-69
Aluminum - Cross - 6" Depth	2-69
Aluminum - Reducer - 6" Depth	2-70
Aluminum - Vertical 45 Degree Elbow - 6" Depth	2-70
Aluminum - Vertical 90 Degree Elbow - 6" Depth	2-70
Aluminum - Vertical Tee - 6" Depth	2-70
<b>Aluminum Cable Tray Fittings &amp; Accessories</b>	2-71
Combination Hold - Down Clamp and Expansion Guide	2-71
Aluminum Cable Tray - Solid Covers	2-71
Aluminum Cable Tray - Solid Cover Clamps (Per Pair)	2-71
Aluminum - 45 Degree Elbow - Solid Covers	2-71

## Section 2 - Conduit, Raceways, Fittings & Related Items Table of Contents

Aluminum - 90 Degree Elbow - Solid Covers	2-71
Aluminum - Tee - Solid Covers	2-71
Aluminum - Cross - Solid Covers	2-71
Aluminum - Reducer - Solid Covers	2-71
Aluminum - Vertical 45 Degree Elbow - Solid Covers	2-71
Aluminum - Vertical 90 Degree Elbow - Solid Covers	2-72
Aluminum - Vertical Tee - Solid Covers	2-72
Aluminum - Enclosure Connectors	2-72
Aluminum - End Plates	2-72
Aluminum - Ladder Drop-Outs	2-72
Aluminum - Splice Plates Pair	2-72
Aluminum Cable Tray Barrier Strips	2-72
Aluminum Cable Tray Fitting Barrier Strips	2-72
Aluminum Conduit To Cable Tray Adapters	2-72
Bonding Jumpers	2-72
<b>Fiberglass Tray 3" Depth</b>	2-73
Fiberglass Cable Tray - 6" Rung Spacing - 3" Depth	2-73
Fiberglass Cable Tray - 6" Rung Spacing - 3" Depth	2-73
Fiberglass Cable Tray - 12" Rung Spacing - 3" Depth	2-73
Fiberglass Cable Tray - 18" Rung Spacing - 3" Depth	2-73
Fiberglass - 45 Degree Elbow - 3" Depth	2-73
Fiberglass - 90 Degree Elbow - 3" Depth	2-73
Fiberglass - Tee - 3" Depth	2-73
Fiberglass - Cross - 3" Depth	2-73
Fiberglass - Reducer - 3" Depth	2-74
Fiberglass - Vertical 45 Degree Elbow - 3" Depth	2-74
Fiberglass - Vertical 90 Degree Elbow - 3" Depth	2-74
Fiberglass - Vertical Tee - 3" Depth	2-74
<b>Fiberglass Tray 4" Depth</b>	2-75
Fiberglass Cable Tray- 6" Rung Spacing - 4" Depth	2-75
Fiberglass Cable Tray- 9" Rung Spacing - 4" Depth	2-75
Fiberglass Cable Tray- 12" Rung Spacing - 4" Depth	2-75
Fiberglass Cable Tray- 18" Rung Spacing - 4" Depth	2-75
Fiberglass - 45 Degree Elbow - 4" Depth	2-75
Fiberglass - 90 Degree Elbow - 4" Depth	2-75
Fiberglass - Tee - 4" Depth	2-75
Fiberglass - Cross - 4" Depth	2-75
Fiberglass - Reducer - 4" Depth	2-76
Fiberglass - Vertical 45 Degree Elbow - 4" Depth	2-76
Fiberglass - Vertical 90 Degree Elbow - 4" Depth	2-76
Fiberglass - Vertical Tee - 4" Depth	2-76
<b>Fiberglass Tray 6" Depth</b>	2-77
Fiberglass Cable Tray - 6" Rung Spacing - 6" Depth	2-77
Fiberglass Cable Tray - 9" Rung Spacing - 6" Depth	2-77
Fiberglass Cable Tray - 12" Rung Spacing - 6" Depth	2-77
Fiberglass Cable Tray - 18" Rung Spacing - 6" Depth	2-77
Fiberglass - 45 Degree Elbow - 6" Depth	2-77
Fiberglass - 90 Degree Elbow - 6" Depth	2-77
Fiberglass - Tee - 6" Depth	2-77
Fiberglass - Cross - 6" Depth	2-77
Fiberglass - Reducer - 6" Depth	2-78
Fiberglass - Vertical 45 Degree Elbow - 6" Depth	2-78
Fiberglass - Vertical 90 Degree Elbow - 6" Depth	2-78
Fiberglass - Vertical Tee - 6" Depth	2-78

## Section 2 - Conduit, Raceways, Fittings & Related Items Table of Contents

<b>Fiberglass Cable Tray Fittings &amp; Accessories</b>	2-79
Combination Hold-Down Clamp and Expansion Guide	2-79
Fiberglass Cable Tray - Solid Covers	2-79
Fiberglass Cable Tray - Solid Covers Clamps (Per Pair)	2-79
Fiberglass - 45 Degree Elbow - Solid Covers	2-79
Fiberglass - 90 Degree Elbow - Solid Covers	2-79
Fiberglass - Tee - Solid Covers	2-79
Fiberglass - Cross - Solid Covers	2-79
Fiberglass - Reducer - Solid Covers	2-79
Fiberglass - Vertical 45 Degree Elbow - Solid Covers	2-79
Fiberglass - Vertical 90 Degree Elbow - Solid Covers	2-80
Fiberglass - Vertical Tee - Solid Covers	2-80
Fiberglass - End Plates	2-80
Fiberglass - Ladder Drop-Outs	2-80
Fiberglass - Splice Plates Pair	2-80
Fiberglass Cable Tray Barrier Strips	2-80
Fiberglass Cable Tray Fitting Barrier Strips	2-80
Fiberglass Conduit to Cable Tray Adapters	2-80
<b>Solid/Ventilated Steel Tray 3" Depth</b>	2-81
Solid/Ventilated Steel - Cable Tray - 3" Depth	2-81
Solid/Ventilated Steel - 45 Degree Elbow - 3" Depth	2-81
Solid/Ventilated Steel - 90 Degree Elbow - 3" Depth	2-81
Solid/Ventilated Steel - Tee - 3" Depth	2-81
Solid/Ventilated Steel - Cross - 3" Depth	2-81
Solid/Ventilated Steel - Reducer - 3" Depth	2-81
Solid/Ventilated Steel - Vertical 45 Degree Elbow - 3" Depth	2-81
Solid/Ventilated Steel - Vertical 90 Degree Elbow - 3" Depth	2-81
Solid/Ventilated Steel - Vertical Tee - 3" Depth	2-81
<b>Solid/Ventilated Steel Tray 4" Depth</b>	2-82
Solid/Ventilated Steel- Cable Tray - 4" Depth	2-82
Solid/Ventilated Steel - 45 Degree Elbow - 4" Depth	2-82
Solid/Ventilated Steel - 90 Degree Elbow - 4" Depth	2-82
Solid/Ventilated Steel - Tee - 4" Depth	2-82
Solid/Ventilated Steel - Cross - 4" Depth	2-82
Solid/Ventilated Steel - Reducer - 4" Depth	2-82
Solid/Ventilated Steel - Vertical 45 Degree Elbow - 4" Depth	2-82
Solid/Ventilated Steel - Vertical 90 Degree Elbow - 4" Depth	2-82
Solid/Ventilated Steel - Vertical Tee - 4" Depth	2-82
<b>Solid/Ventilated Steel Tray 6" Depth</b>	2-83
Solid/Ventilated Steel - Cable Tray - 6" Depth	2-83
Solid/Ventilated Steel - 45 Degree Elbow - 6" Depth	2-83
Solid/Ventilated Steel - 90 Degree Elbow - 6" Depth	2-83
Solid/Ventilated Steel - Tee - 6" Depth	2-83
Solid/Ventilated Steel - Cross - 6" Depth	2-83
Solid/Ventilated Steel - Reducer - 6" Depth	2-83
Solid/Ventilated Steel - Vertical 45 Degree Elbow - 6" Depth	2-83
Solid/Ventilated Steel - Vertical 90 Degree Elbow - 6" Depth	2-83
Solid/Ventilated Steel - Vertical Tee - 6" Depth	2-83
<b>Solid/Ventilated Steel Cable Tray Fittings &amp; Accessories</b>	2-84
Seismic Hold-Down Clamp and Expansion Guide	2-84
Solid/Ventilated Steel Cable Tray - Solid Covers	2-84
Solid/Ventilated Steel Cable Tray - Solid Cover Clamps (Per Pair)	2-84



## Section 2 - Conduit, Raceways, Fittings & Related Items Table of Contents

Solid/Ventilated Steel - 45 Degree Elbow - Solid Covers	2-84
Solid/Ventilated Steel - 90 Degree Elbow - Solid Covers	2-84
Solid/Ventilated Steel - Tee - Solid Covers	2-84
Solid/Ventilated Steel - Cross - Solid Covers	2-84
Solid/Ventilated Steel - Reducer - Solid Covers	2-84
Solid/Ventilated Steel - Vertical 45 Degree Elbow - Solid Covers	2-84
Solid/Ventilated Steel - Vertical 90 Degree Elbow - Solid Covers	2-84
Solid/Ventilated Steel - Vertical Tee - Solid Covers	2-85
Solid/Ventilated Steel - Enclosure Connectors	2-85
Solid/Ventilated Steel - End Plates	2-85
Solid/Ventilated Steel - Ladder Drop-Outs	2-85
Solid/Ventilated Steel - Splice Plates Pair	2-85
Solid/Ventilated Steel Cable Tray Barrier Strips	2-85
Solid/Ventilated Steel Cable Tray Fitting Barrier Strips	2-85
Solid/Ventilated Steel Conduit to Cable Tray Adapters	2-85
Bonding Jumpers	2-85
<b>Solid/Ventilated Aluminum Tray 3" Depth</b>	2-86
Solid/Ventilated Aluminum - Cable Tray - 3" Depth	2-86
Solid/Ventilated Aluminum - 45 Degree Elbow - 3" Depth	2-86
Solid/Ventilated Aluminum - 90 Degree Elbow - 3" Depth	2-86
Solid/Ventilated Aluminum - Tee - 3" Depth	2-86
Solid/Ventilated Aluminum - Cross - 3" Depth	2-86
Solid/Ventilated Aluminum - Reducer - 3" Depth	2-86
Solid/Ventilated Aluminum - Vertical 45 Degree Elbow - 3" Depth	2-86
Solid/Ventilated Aluminum - Vertical 90 Degree Elbow - 3" Depth	2-86
Solid/Ventilated Aluminum - Vertical Tee - 3" Depth	2-86
<b>Solid/Ventilated Aluminum Tray 4" Depth</b>	2-87
Solid/Ventilated Aluminum - Cable Tray - 4" Depth	2-87
Solid/Ventilated Aluminum - 45 Degree Elbow - 4" Depth	2-87
Solid/Ventilated Aluminum - 90 Degree Elbow - 4" Depth	2-87
Solid/Ventilated Aluminum - Tee - 4" Depth	2-87
Solid/Ventilated Aluminum - Cross - 4" Depth	2-87
Solid/Ventilated Aluminum - Reducer - 4" Depth	2-87
Solid/Ventilated Aluminum - Vertical 45 Degree Elbow - 4" Depth	2-87
Solid/Ventilated Aluminum - Vertical 90 Degree Elbow - 4" Depth	2-87
Solid/Ventilated Aluminum - Vertical Tee - 4" Depth	2-87
<b>Solid/Ventilated Aluminum Tray 6" Depth</b>	2-88
Solid/Ventilated Aluminum - Cable Tray - 6" Depth	2-88
Solid/Ventilated Aluminum - 45 Degree Elbow - 6" Depth	2-88
Solid/Ventilated Aluminum - 90 Degree Elbow - 6" Depth	2-88
Solid/Ventilated Aluminum - Tee - 6" Depth	2-88
Solid/Ventilated Aluminum - Cross - 6" Depth	2-88
Solid/Ventilated Aluminum - Reducer - 6" Depth	2-88
Solid/Ventilated Aluminum - Vertical 45 Degree Elbow - 6" Depth	2-88
Solid/Ventilated Aluminum - Vertical 90 Degree Elbow - 6" Depth	2-88
Solid/Ventilated Aluminum - Vertical Tee - 6" Depth	2-88
<b>Solid/Ventilated Aluminum Cable Tray Fittings &amp; Accessories</b>	2-89
Seismic Hold-Down Clamp and Expansion Guide	2-89
Solid/Ventilated Aluminum Cable Tray - Solid Covers	2-89
Solid/Ventilated Aluminum Cable Tray - Solid Cover Clamps (Per Pair)	2-89
Solid/Ventilated Aluminum - 45 Degree Elbow - Solid Covers	2-89
Solid/Ventilated Aluminum - 90 Degree Elbow - Solid Covers	2-89
Solid/Ventilated Aluminum - Tee - Solid Covers	2-89

## Section 2 - Conduit, Raceways, Fittings & Related Items Table of Contents

2






Solid/Ventilated Aluminum - Cross - Solid Covers	2-89
Solid/Ventilated Aluminum - Reducer - Solid Covers	2-89
Solid/Ventilated Aluminum - Vertical 45 Degree Elbow - Solid Covers	2-89
Solid/Ventilated Aluminum - Vertical 90 Degree Elbow - Solid Covers	2-89
Solid/Ventilated Aluminum - Vertical Tee- Solid Covers	2-90
Solid/Ventilated Aluminum - Enclosure Connectors	2-90
Solid/Ventilated Aluminum - End Plates	2-90
Solid/Ventilated Aluminum - Ladder Drop - Outs	2-90
Solid/Ventilated Aluminum - Splice Plates Pair	2-90
Solid/Ventilated Aluminum Cable Tray Barrier Strips	2-90
Solid/Ventilated Aluminum Cable Tray Fitting Barrier Strips	2-90
Solid/Ventilated Aluminum Conduit to Cable Tray Adapters	2-90
Bonding Jumpers	2-90
Cable Tray Insulator Blocks	2-91
Cable Clamps	2-91
Cable Tray Lay-in Ground Clamp	2-91
Cable Rollers For Tray Setup	2-91
Cable Pulleys/Bull Wheels-Setup	2-91
Chanel Cable Tray	2-91
Basket Type Wire Tray-Steel	2-91
Center-R-Rail Spline Cable Tray- Aluminum	2-91
Fittings	<b>(Updated)</b> 2-91
Cable Tray Fire Barrier	2-91
<b>Fasteners / Hangers / Supports</b>	2-92
Toggle Bolts	2-92
Drop-in Anchors	2-92
Expansion Shields	2-92
Self Drill Anchors	2-92
Concrete Anchor Bolts	2-92
Hollow Wall Anchors	2-92
Fiber & Plastic Anchors	2-92
Powder Activated Fasteners - All Types	2-92
Hammer Drive Anchors	2-92
Anchor Bolts Set in Concrete	2-92
Concrete Channel Inserts	2-93
Threaded Concrete Inserts	2-93
Concrete Channel End Plates	2-93
Concrete Channel Nuts	2-93
Concrete Channel Studs	<b>(Updated)</b> 2-93
Pre-cut Strut Hanger Channels	<b>(Updated)</b> 2-93
Field Cut Strut Hanger Channels	2-93
Pre-cut Hanger Rods	2-93
Field-cut All-thread Hanger Rods	2-93
Hanger Channel Conduit Clamps	2-93
One Hole Conduit Straps	2-93
Two Hole Conduit Straps	2-93
Conduit Ring Hangers	2-94
Adjustable Ring Hangers	2-94
Conduit Clamps	2-94
Minerallic Straps	2-94
Clevis Ring Hangers	2-94
Conduit Riser Clamps	2-94
U-Bolts	2-94
Conduit and Box Supports	2-94
Beam Clamps	2-95
Trapeze Hangers without Beam Clamps or Inserts	2-95

## Section 2 - Conduit, Raceways, Fittings & Related Items Table of Contents

Drill Holes in Steel (up to 1/4" Thick)		2-95
Drill Holes in Wood Stud	<i>(Updated)</i>	2-95
<b>Misc Bolts, Washers, Nuts &amp; Screws</b>		2-96
Bolt, Washer, and Nut		2-96
Sheet Metal Screw		2-97
Machine Screw-Drill & Tap		2-97
Self Tapping Screws		2-97
Cones		2-97
<b>Hole Drilling and Coring</b>		2-98
Roto-Hammer Concrete		2-98
Core-Drill Concrete With Lay-out	<i>(Updated)</i>	2-98
<b>Firestop Material</b>		2-98
Fire Stop Pillows		2-98
Fire Proof Wall Penetrations		2-98
Multi Cable/Tray Firestop		2-98
Speed Sleeve		2-98
Firestop Collar		2-98
Floor Firestop		2-98









## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Rigid Steel Conduit (GRC or GRS) and fittings</b>						
<b>Rigid Steel Conduit with Threaded Couplings</b>						
		5.50	6.80	8.20		C
1/2"		6.00	7.50	9.00		C
3/4"		7.00	8.70	10.50		C
1"		8.00	10.00	12.00		C
1 1/4"		9.00	11.20	13.50		C
1 1/2"		11.00	13.70	16.50		C
2"		15.00	18.70	22.50		C
2 1/2"		20.00	25.00	30.00		C
3"		25.00	31.20	37.50		C
3 1/2"		30.00	37.50	45.00		C
4"		38.00	47.50	57.00		C
5"		48.00	60.00	72.00		C
6"						
<i>For Stainless Steel Conduit &amp; Fittings Add 25%</i>						
<b>Rigid Steel Factory Elbows</b>						
<b>Add 20% For Wide Sweep Elbows</b>						
		0.35	0.43	0.52		E
1/2"		0.40	0.50	0.60		E
3/4"		0.50	0.62	0.75		E
1"		0.60	0.75	0.90		E
1 1/4"		0.75	0.93	1.12		E
1 1/2"		1.00	1.25	1.50		E
2"		1.50	1.85	2.25		E
2 1/2"		2.00	2.50	3.00		E
3"		2.50	3.10	3.75		E
3 1/2"		3.00	3.75	4.50		E
4"		4.00	5.00	6.00		E
5"		5.00	6.25	7.50		E
6"						
<i>For Stainless Steel Conduit &amp; Fittings Add 25%</i>						
<b>Field Bending Steel Conduit &amp; Installation</b>						
<b>Add approx 20% for each field cut &amp; thread</b>						
<b>Add 50% For Wide Sweep Segment Bend</b>						
		1.20	1.50	1.80		E
1 1/4"		1.50	1.90	2.25		E
1 1/2"		2.00	2.50	3.00		E
2"		2.75	3.40	4.05		E
2 1/2"		3.50	4.35	5.25		E
3"		4.25	5.25	6.35		E
3 1/2"		5.00	6.25	7.50		E
4"		7.00	8.75	10.50		E
5"		9.00	11.25	13.50		E
6"						
<i>For Stainless Steel Conduit &amp; Fittings Add 25%</i>						
<b>Lock Nut &amp; Bushing Sets - Field Cut &amp; Thread Included</b>						
		0.30	0.37	0.45		E
1/2"		0.35	0.43	0.52		E
3/4"		0.40	0.50	0.60		E
1"		0.50	0.62	0.75		E
1 1/4"		0.60	0.75	0.90		E
1 1/2"		0.80	1.00	1.20		E
2"		1.00	1.25	1.50		E
2 1/2"		1.20	1.50	1.80		E
3"		1.40	1.75	2.10		E
3 1/2"		1.60	2.00	2.40		E
4"		1.90	2.40	2.90		E
5"		2.30	2.90	3.50		E
6"						
<i>For Stainless Steel Conduit &amp; Fittings Add 25%</i>						
<b>Plastic Bushing Only</b>						
		0.10	0.12	0.15		E
1/2"		0.12	0.14	0.17		E
3/4"		0.13	0.17	0.20		E
1"		0.17	0.21	0.25		E
1 1/4"		0.20	0.25	0.30		E
1 1/2"		0.27	0.33	0.40		E
2"		0.33	0.42	0.50		E
2 1/2"		0.40	0.50	0.60		E
3"		0.47	0.58	0.70		E
3 1/2"		0.53	0.67	0.80		E
4"		0.63	0.80	0.97		E
5"		0.77	0.97	1.17		E
6"						

## Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Rigid Conduit Locknut Only</b>						
 1/2"		0.10	0.12	0.15		E
3/4"		0.12	0.14	0.17		E
1"		0.13	0.17	0.20		E
1 1/4"		0.17	0.21	0.25		E
1 1/2"		0.20	0.25	0.30		E
2"		0.27	0.33	0.40		E
2 1/2"		0.33	0.42	0.50		E
3"		0.40	0.50	0.60		E
3 1/2"		0.47	0.58	0.70		E
4"		0.53	0.67	0.80		E
5"		0.63	0.80	0.97		E
6"		0.77	0.97	1.17		E
<b>Lock Nut &amp; Ground Bushing Sets</b>						
<b>Field Cut &amp; Thread Included</b>						
 1/2"		0.40	0.50	0.60		E
3/4"		0.45	0.56	0.67		E
1"		0.50	0.62	0.75		E
1 1/4"		0.60	0.75	0.90		E
1 1/2"		0.80	1.00	1.20		E
2"		1.00	1.25	1.50		E
2 1/2"		1.20	1.50	1.80		E
3"		1.40	1.75	2.10		E
3 1/2"		1.60	2.00	2.40		E
4"		1.90	2.35	2.85		E
5"		2.20	2.75	3.30		E
6"		2.70	3.40	4.00		E
<i>For Stainless Steel Conduit &amp; Fittings Add 25%</i>						
<b>Factory Cut Rigid Steel Nipples - Up to 12" Length Maximum</b>						
 1/2"		0.25	0.31	0.37		E
3/4"		0.30	0.37	0.45		E
1"		0.35	0.43	0.52		E
1 1/4"		0.40	0.50	0.60		E
1 1/2"		0.50	0.62	0.75		E
2"		0.60	0.75	0.90		E
2 1/2"		0.75	0.94	1.12		E
3"		0.90	1.12	1.35		E
3 1/2"		1.10	1.37	1.65		E
4"		1.30	1.62	1.95		E
5"		1.50	1.87	2.25		E
6"		1.80	2.25	2.70		E
<i>For Stainless Steel Conduit &amp; Fittings Add 25%</i>						
<b>Field Cut Rigid Steel Nipples &amp; Installation</b>						
<b>Up to 12" Length Maximum</b>						
 1/2"		0.50	0.62	0.74		E
3/4"		0.60	0.74	0.90		E
1"		0.70	0.86	1.04		E
1 1/4"		0.80	1.00	1.20		E
1 1/2"		1.00	1.24	1.50		E
2"		1.20	1.50	1.80		E
2 1/2"		1.45	1.81	2.17		E
3"		1.75	2.17	2.60		E
3 1/2"		2.10	2.62	3.15		E
4"		2.50	3.12	3.75		E
5"		3.40	4.22	5.10		E
6"		4.10	5.15	6.20		E
<i>For Stainless Steel Conduit &amp; Fittings Add 25%</i>						
<b>Steel Chase Nipples - Includes Locknut &amp; Bushing</b>						
 1/2"		0.12	0.15	0.18		E
3/4"		0.14	0.17	0.21		E
1"		0.17	0.21	0.25		E
1 1/4"		0.20	0.25	0.30		E
1 1/2"		0.25	0.31	0.37		E
2"		0.30	0.37	0.45		E
2 1/2"		0.35	0.43	0.52		E
3"		0.40	0.50	0.60		E
3 1/2"		0.45	0.56	0.67		E
4"		0.50	0.62	0.75		E
<i>For Stainless Steel Conduit &amp; Fittings Add 25%</i>						
<b>Steel Offset Nipples - Includes Locknut &amp; Bushings</b>						
 1/2"		0.25	0.31	0.37		E
3/4"		0.30	0.37	0.45		E
1"		0.35	0.43	0.52		E
1 1/4"		0.40	0.50	0.60		E
1 1/2"		0.45	0.56	0.67		E
2"		0.50	0.62	0.75		E
<i>For Stainless Steel Conduit &amp; Fittings Add 25%</i>						

## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Steel Threaded Reducers</b>						
 1/2"		0.15	0.18	0.22		E
3/4"		0.17	0.21	0.26		E
1"		0.20	0.25	0.30		E
1 1/4"		0.23	0.28	0.34		E
1 1/2"		0.26	0.32	0.39		E
2"		0.30	0.37	0.45		E
2 1/2"		0.35	0.43	0.52		E
3"		0.40	0.50	0.60		E
3 1/2"		0.45	0.56	0.67		E
4"		0.50	0.62	0.75		E
<b>Steel Compression Couplings</b>						
1/2"		0.20	0.25	0.30		E
3/4"		0.25	0.31	0.37		E
1"		0.30	0.37	0.45		E
1 1/4"		0.40	0.50	0.60		E
1 1/2"		0.50	0.62	0.75		E
2"		0.60	0.75	0.90		E
2 1/2"		0.70	0.87	1.05		E
3"		0.80	1.00	1.20		E
3 1/2"		0.90	1.12	1.35		E
4"		1.00	1.25	1.50		E
<b>Steel Split Couplings</b>						
1/2"		0.25	0.31	0.37		E
3/4"		0.30	0.37	0.45		E
1"		0.40	0.50	0.60		E
1 1/4"		0.50	0.62	0.75		E
1 1/2"		0.60	0.75	0.90		E
2"		0.70	0.87	1.05		E
2 1/2"		0.80	1.00	1.20		E
3"		0.90	1.12	1.35		E
3 1/2"		1.05	1.30	1.57		E
4"		1.20	1.50	1.80		E
<b>Rigid Steel Expansion / Deflection Couplings - Includes Bonding Jumper</b>						
1/2"	X	0.60	0.75	0.90		E
3/4"		0.70	0.87	1.05		E
1"		0.80	1.00	1.20		E
1 1/4"		1.00	1.25	1.50		E
1 1/2"		1.25	1.55	1.85		E
2"		1.50	1.85	2.25		E
2 1/2"		1.75	2.15	2.60		E
3"		2.00	2.50	3.00		E
3 1/2"		2.50	3.10	3.75		E
4"		3.00	3.75	4.50		E
<b>Steel Erickson Couplings</b>						
1/2"		0.60	0.75	0.90		E
3/4"		0.70	0.87	1.05		E
1"		0.80	1.00	1.20		E
1 1/4"		0.90	1.12	1.35		E
1 1/2"		1.05	1.30	1.57		E
2"		1.25	1.55	1.85		E
2 1/2"		1.50	1.85	2.25		E
3"		1.75	2.15	2.60		E
3 1/2"		2.00	2.50	3.00		E
4"		2.25	2.80	3.40		E
<b>Steel Threaded Entrance Elbows</b>						
1/2"		0.50	0.62	0.75		E
3/4"		0.60	0.75	0.90		E
1"		0.75	0.93	1.12		E
1 1/4"		1.00	1.25	1.50		E
1 1/2"		1.25	1.55	1.85		E
2"		1.50	1.85	2.25		E
2 1/2"		2.00	2.50	3.00		E
3"		2.50	3.10	3.75		E
3 1/2"		3.00	3.75	4.50		E
4"		4.00	5.00	6.00		E
5"		5.00	6.25	7.50		E
6"		6.00	7.50	9.00		E

## Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Steel Threadless Box Connectors</b>						
 1/2"		0.30	0.37	0.45		E
3/4"		0.40	0.50	0.60		E
1"		0.50	0.62	0.75		E
1 1/4"		0.60	0.75	0.90		E
1 1/2"		0.70	0.85	1.00		E
2"		0.80	1.00	1.20		E
2 1/2"		0.90	1.10	1.35		E
3"		1.00	1.25	1.50		E
3 1/2"		1.10	1.35	1.60		E
4"		1.20	1.45	1.70		E
<b>Steel Threaded Box Connectors (Myers Hub)</b>						
 1/2"		0.35	0.44	0.55		E
3/4"		0.45	0.56	0.70		E
1"		0.55	0.69	0.86		E
1 1/4"		0.65	0.81	1.02		E
1 1/2"		0.75	0.94	1.17		E
2"		0.85	1.06	1.33		E
2 1/2"		0.95	1.19	1.48		E
3"		1.05	1.31	1.64		E
3 1/2"		1.15	1.44	1.80		E
4"		1.25	1.56	1.95		E
<b>Steel Threaded Service Entrance Caps</b>						
 1/2"		0.60	0.75	0.90		E
3/4"		0.70	0.87	1.05		E
1"		0.80	1.00	1.20		E
1 1/4"		0.90	1.12	1.35		E
1 1/2"		1.00	1.25	1.50		E
2"		1.25	1.55	1.85		E
2 1/2"		1.50	1.85	2.25		E
3"		2.00	2.50	3.00		E
3 1/2"		2.50	3.10	3.75		E
4"		3.00	3.75	4.50		E
5"		4.00	5.00	6.00		E
6"		5.00	6.25	7.50		E
<b>Steel Threaded Capped Elbows</b>						
 1/2"		0.50	0.62	0.75		E
3/4"		0.60	0.75	0.90		E
1"		0.70	0.87	1.05		E
1 1/4"		0.80	1.00	1.20		E
1 1/2"		1.00	1.25	1.50		E
2"		1.20	1.50	1.80		E
<b>Steel Pipe Caps or Capped Bushings</b>						
 1/2"		0.15	0.18	0.22		E
3/4"		0.16	0.20	0.24		E
1"		0.18	0.22	0.27		E
1 1/4"		0.20	0.25	0.30		E
1 1/2"		0.25	0.31	0.37		E
2"		0.30	0.37	0.45		E
2 1/2"		0.35	0.43	0.52		E
3"		0.40	0.50	0.60		E
3 1/2"		0.45	0.56	0.67		E
4"		0.50	0.62	0.75		E
5"		0.55	0.68	0.82		E
6"		0.60	0.75	0.90		E
<b>Steel Threaded Conduit Bodies-One Hub</b>						
 1/2"		0.40	0.50	0.60		E
3/4"		0.50	0.62	0.75		E
1"		0.60	0.75	0.90		E
<b>Steel Threaded Conduit Bodies-Two Hubs</b>						
 1/2"		0.50	0.62	0.75		E
3/4"		0.65	0.80	0.95		E
1"		0.80	1.00	1.20		E
1 1/4"		1.00	1.25	1.50		E
1 1/2"		1.50	1.85	2.25		E
2"		2.00	2.50	3.00		E
2 1/2"		2.75	3.40	4.10		E
3"		3.50	4.35	5.25		E
3 1/2"		4.25	5.30	6.35		E
4"		5.00	6.25	7.50		E
						




## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Steel Threaded Conduit Bodies-Three Hubs</b>						
 1/2"		0.80	1.00	1.20		E
3/4"		1.00	1.25	1.50		E
1"		1.25	1.55	1.85		E
1 1/4"		1.50	1.85	2.25		E
1 1/2"		2.00	2.50	3.00		E
2"		2.75	3.40	4.10		E
2 1/2"		3.50	4.35	5.25		E
3"		4.50	5.60	6.75		E
3 1/2"		5.50	6.85	8.25		E
4"		6.50	8.10	9.75		E
<b>Steel Threaded Conduit Bodies-Four Hubs</b>						
1/2"		1.00	1.25	1.50		E
3/4"		1.25	1.55	1.85		E
1"		1.50	1.85	2.25		E
1 1/4"		2.25	2.80	3.35		E
1 1/2"		3.00	3.75	4.50		E
2"		4.00	5.00	6.00		E
2 1/2"		5.00	6.25	7.50		E
3"		6.00	7.50	9.00		E
3 1/2"		7.00	8.75	10.50		E
4"		8.00	10.00	12.00		E
<b>Steel Mogul Conduit Bodies-Two Hubs</b>						
 1"		1.00	1.25	1.50		E
1 1/4"		1.50	1.85	2.25		E
1 1/2"		2.00	2.50	3.00		E
2"		2.50	3.10	3.75		E
2 1/2"		3.00	3.75	4.50		E
3"		3.50	4.35	5.25		E
3 1/2"		4.25	5.30	6.35		E
4"		5.00	6.25	7.50		E
<b>Steel Mogul Conduit Bodies-Three Hubs</b>						
 1"		1.50	1.85	2.25		E
1 1/4"		2.00	2.50	3.00		E
1 1/2"		2.50	3.10	3.75		E
2"		3.00	3.75	4.50		E
2 1/2"		3.50	4.35	5.25		E
3"		4.00	5.00	6.00		E
3 1/2"		5.00	6.25	7.25		E
4"		6.00	7.50	9.00		E
<b>Steel Mogul Conduit Bodies-Four Hubs</b>						
 1"		2.50	3.10	3.75		E
1 1/4"		3.00	3.75	4.50		E
1 1/2"		3.50	4.35	5.25		E
2"		4.00	5.00	6.00		E
2 1/2"		4.50	5.60	6.75		E
3"		5.00	6.25	7.50		E
3 1/2"		6.00	7.50	9.00		E
4"		7.00	8.75	10.50		E
<b>Iron FS &amp; FD Threaded 1-Gang Boxes</b>						
 1/2" One Hub		0.60	0.75	0.90		E
3/4" One Hub		0.70	0.85	1.05		E
1" One Hub		0.85	1.05	1.25		E
1/2" Two Hubs		0.80	1.00	1.20		E
3/4" Two Hubs		0.95	1.15	1.40		E
1" Two Hubs		1.15	1.40	1.70		E
1/2" Three Hubs		1.00	1.25	1.50		E
3/4" Three Hubs		1.20	1.50	1.80		E
1" Three Hubs		1.45	1.80	2.15		E
1/2" Four Hubs		1.20	1.50	1.80		E
3/4" Four Hubs		1.45	1.80	2.15		E
1" Four Hubs		1.75	2.15	2.60		E
<b>Iron FS &amp; FD Threaded 2-Gang Boxes</b>						
 1/2" One Hub		0.65	0.80	1.00		E
3/4" One Hub		0.75	0.90	1.10		E
1" One Hub		0.90	1.10	1.35		E
1/2" Two Hubs		0.85	1.05	1.25		E
3/4" Two Hubs		1.00	1.25	1.50		E
1" Two Hubs		1.20	1.50	1.80		E
1/2" Three Hubs		1.05	1.30	1.55		E
3/4" Three Hubs		1.25	1.55	1.85		E
1" Three Hubs		1.50	1.85	2.25		E

Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Iron FS &amp; FD Threaded 3-Gang Boxes</b>						
 1/2" One Hub		0.70	0.85	1.05		E
3/4" One Hub		0.80	1.00	1.20		E
1" One Hub		0.95	1.15	1.40		E
1/2" Two Hubs		0.90	1.10	1.35		E
3/4" Two Hubs		1.05	1.30	1.55		E
1" Two Hubs		1.25	1.55	1.85		E
1/2" Three Hubs		1.10	1.35	1.65		E
3/4" Three Hubs		1.30	1.60	1.95		E
1" Three Hubs		1.55	1.90	2.30		E
<b>Iron FS &amp; FD Box Covers</b>						
Blank Covers		0.08	0.09	0.10		E
Receptacle Covers		0.10	0.12	0.15		E
Single Gang Switch Covers		0.10	0.12	0.15		E
Two Gang Switch Covers		0.15	0.18	0.21		E
Three Gang Switch Covers		0.20	0.25	0.30		E
<b>Knockout Type Steel Boxes</b>						
4" Square Boxes		30.00	35.00	40.00		C
4" Octagon Boxes		30.00	35.00	40.00		C
4 11/16" Square Boxes		30.00	35.00	40.00		C
4" Concrete Boxes		40.00	45.00	50.00		C
4" Handy Boxes		25.00	30.00	35.00		C
4" Switch Boxes		25.00	30.00	35.00		C
2-Gang Solid Boxes		25.00	30.00	35.00		C
3-Gang Solid Boxes		27.00	32.00	37.00		C
4-Gang Solid Boxes		30.00	35.00	40.00		C
5-Gang Solid Boxes		33.00	38.00	43.00		C
6-Gang Solid Boxes		36.00	41.00	46.00		C
7-Gang Solid Boxes		40.00	45.00	50.00		C
8-Gang Solid Boxes		45.00	50.00	55.00		C
4" Hung Ceiling Boxes		45.00	50.00	55.00		C
6" Square Boxes-Blank/Customizable	X	0.40	0.45	0.50		E
6" Square Boxes -with ko's	X	0.40	0.45	0.50		E
6" Flat cover	X	0.10	0.12	0.15		E
6" 1 Gang Mud Ring	X	0.15	0.20	0.25		E
6" 2 Gang Mud Ring	X	0.15	0.20	0.25		E
6" Three Gang Mud Ring	X	0.15	0.20	0.25		E
Add for KO in Blank Box	X					E
Ceiling Fan Box with Adjustable Stud Bracket	X	0.50	0.75	1.00		E
Ceiling Fan Box-Direct Mount to Rafter	X	0.40	0.50	0.65		E
<b>Knockout Type Steel Boxes - Masonry</b>						
1-Gang Masonry & Tile Boxes		35.00	40.00	45.00		C
2-Gang Masonry & Tile Boxes		37.00	42.00	47.00		C
3-Gang Masonry & Tile Boxes		40.00	45.00	50.00		C
4-Gang Masonry & Tile Boxes		45.00	50.00	55.00		C
<b>Knockout Type Steel Boxes - Wall Boxes</b>						
1-Gang Thru-Wall Boxes		35.00	40.00	45.00		C
2-Gang Thru-Wall Boxes		37.00	42.00	47.00		C
3-Gang Thru-Wall Boxes		40.00	45.00	50.00		C
<b>Knockout Type Steel Boxes - Accessories</b>						
Box Extensions-All Types		20.00	25.00	30.00		C
Plaster Rings-All Sizes		15.00	20.00	25.00		C
Tile Rings-All Sizes		17.50	22.00	27.50		C
Box Covers-All Types		8.00	9.00	10.00		C

## Section 2 - Conduit, Raceways, Fittings & Related Items






Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Threaded Cast Round Outlet Boxes</b>						
 1/2" One Hub		0.40	0.50	0.60		E
 3/4" One Hub		0.50	0.62	0.75		E
 1" One Hub		0.65	0.80	0.95		E
 1 1/4" One Hub		0.80	1.00	1.20		E
 1 1/2" One Hub		1.00	1.25	1.50		E
 1/2" Two Hubs		0.60	0.75	0.90		E
 3/4" Two Hubs		0.80	1.00	1.20		E
 1" Two Hubs		1.00	1.25	1.50		E
 1 1/4" Two Hubs		1.20	1.50	1.80		E
 1 1/2" Two Hubs		1.45	1.80	2.15		E
 1/2" Three Hubs		0.80	1.00	1.20		E
 3/4" Three Hubs		1.00	1.25	1.50		E
 1" Three Hubs		1.25	1.55	1.90		E
 1 1/4" Three Hubs		1.50	1.85	2.25		E
 1 1/2" Three Hubs		1.80	2.25	2.70		E
 1/2" Four Hubs		1.00	1.25	1.50		E
 3/4" Four Hubs		1.25	1.55	1.90		E
 1" Four Hubs		1.50	1.85	2.25		E
 1 1/4" Four Hubs		1.80	2.25	2.70		E
 1 1/2" Four Hubs		2.20	2.75	3.30		E
Cast Round Blank Covers		0.20	0.25	0.30		E
Cast Round Cover with 1/2" Hub		0.25	0.31	0.37		E
Cast Round Cover with 3/4" Hub		0.30	0.37	0.45		E
Swivel Hanger Cover with 1/2" Hub		0.35	0.43	0.52		E
Swivel Hanger Cover with 3/4" Hub		0.40	0.50	0.60		E
<b>Knockout Type Steel Boxes</b>						
<b>Floor Boxes W/O Trim Covers</b>						
<b>See Section 6 for Trim Covers</b>						
 Square Floor Boxes non-adjustable		80.00	90.00	100.00		C
 Octagon Floor Boxes non-adjustable		80.00	90.00	100.00		C
 Square Floor Boxes adjustable		100.00	112.00	125.00		C
 Octagon Floor Boxes adjustable		100.00	112.00	125.00		C
<b>Threaded Cast Floor Boxes</b>						
 Round Boxes without Legs		1.25	1.55	1.90		E
 Round Boxes with Legs		1.50	1.85	2.25		E
 1-Gang with Cover		1.20	1.65	1.95		E
 2-Gang with Cover		1.40	1.75	2.10		E
 3-Gang with Cover		1.50	1.85	2.25		E
 4-Gang with Cover		1.60	2.00	2.40		E
<b>Floor Boxes</b>						
 Poke-Thru Floor Box Single Serv		1.00	1.50	2.00		E
Excludes Core						
 Poke-Thru Floor Box Dual Service		1.25	1.75	2.25		E
Excludes Core						
 P.V.C. Floor Box Cut-off type		1.00	1.50	2.00		E
 Raised Floor Box		1.00	2.00	3.00		E
 Cutting Raised Floor		1.50	2.00	3.00		E
<b>Cast Iron Junction Boxes</b>						
 6 x 4 x 4 7 lbs		1.50	1.85	2.25		E
 6 x 6 x 6 12 lbs		1.55	1.90	2.30		E
 6 x 6 x 8 19 lbs		1.60	2.00	2.40		E
 8 x 8 x 4 22 lbs		1.70	2.15	2.55		E
8 x 8 x 6 25 lbs		1.80	2.25	2.70		E
8 x 8 x 8 29 lbs		1.90	2.35	2.85		E
12 x 12 x 4 34 lbs		2.00	2.50	3.00		E
12 x 12 x 6 38 lbs		2.25	2.80	3.35		E
12 x 12 x 8 42 lbs		2.50	3.10	3.75		E
18 x 8 x 6 52 lbs		3.00	3.75	4.50		E
18 x 12 x 6 60 lbs		4.00	5.00	6.00		E
18 x 18 x 6 80 lbs		5.00	6.25	7.50		E
24 x 12 x 6 100 lbs		6.00	7.50	9.00		E

Section 2 - Conduit, Raceways, Fittings & Related Items

2



Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Electrical Metallic Tubing (EMT) and Fittings</b>						
<b>Electrical Metallic Tubing (EMT)</b>						
	X					
1/2"		4.50	5.60	6.70		C
3/4"		5.00	6.20	7.50		C
1"		5.50	6.80	8.20		C
1 1/4"		6.20	7.80	9.30		C
1 1/2"		7.00	8.70	10.50		C
2"		8.00	10.00	12.00		C
2 1/2"		9.50	11.80	14.20		C
3"		11.00	13.70	16.50		C
3 1/2"		13.00	16.20	19.50		C
4"		16.00	20.00	24.00		C
Add 10% for colored conduit (handling, layout, design)	X					
<b>EMT Set Screw Couplings</b>						
1/2"		0.04	0.05	0.06		E
3/4"		0.05	0.06	0.07		E
1"		0.06	0.07	0.08		E
1 1/4"		0.08	0.09	0.10		E
1 1/2"		0.10	0.11	0.13		E
2"		0.12	0.14	0.16		E
2 1/2"		0.14	0.16	0.18		E
3"		0.16	0.18	0.20		E
3 1/2"		0.20	0.22	0.24		E
4"		0.22	0.24	0.26		E
<b>EMT Factory Elbows</b>						
1/2"		0.20	0.25	0.30		E
3/4"		0.22	0.27	0.33		E
1"		0.25	0.31	0.37		E
1 1/4"		0.32	0.40	0.48		E
1 1/2"		0.40	0.50	0.60		E
2"		0.50	0.62	0.75		E
2 1/2"		0.60	0.75	0.90		E
3"		0.70	0.87	1.05		E
3 1/2"		0.85	1.05	1.25		E
4"		1.00	1.25	1.50		E
<b>Field Bending EMT Conduit and Installation</b>						
Add approx 10% for each field cut & ream						
1 1/4"		0.64	0.80	0.96		E
1 1/2"		0.80	1.00	1.20		E
2"		1.00	1.24	1.50		E
2 1/2"		1.20	1.50	1.80		E
3"		1.40	1.74	2.10		E
3 1/2"		1.70	2.10	2.50		E
4"		2.00	2.50	3.00		E
<b>EMT Set Screw Box Connectors</b>						
1/2"		0.08	0.10	0.12		E
3/4"		0.10	0.12	0.15		E
1"		0.12	0.15	0.18		E
1 1/4"		0.16	0.20	0.24		E
1 1/2"		0.20	0.25	0.30		E
2"		0.25	0.31	0.37		E
2 1/2"		0.30	0.37	0.45		E
3"		0.35	0.45	0.50		E
3 1/2"		0.40	0.50	0.60		E
4"		0.45	0.60	0.75		E
<b>EMT Compression Box Connectors</b>						
1/2"		0.25	0.31	0.37		E
3/4"		0.30	0.37	0.45		E
1"		0.35	0.43	0.52		E
1 1/4"		0.40	0.50	0.60		E
1 1/2"		0.45	0.56	0.67		E
2"		0.50	0.62	0.75		E
2 1/2"		0.60	0.75	0.90		E
3"		0.70	0.87	1.05		E
3 1/2"		0.80	1.00	1.20		E
4"		0.90	1.12	1.35		E

## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>EMT Compression Couplings</b>						
	1/2"	0.12	0.15	0.18		E
	3/4"	0.14	0.17	0.21		E
	1"	0.16	0.20	0.24		E
	1 1/4"	0.20	0.25	0.30		E
	1 1/2"	0.25	0.31	0.37		E
	2"	0.30	0.37	0.45		E
	2 1/2"	0.40	0.50	0.60		E
	3"	0.45	0.56	0.67		E
	3 1/2"	0.50	0.62	0.75		E
	4"	0.60	0.75	0.90		E
<b>EMT Service Elbows</b>						
	1/2"	0.40	0.50	0.60		E
	3/4"	0.45	0.56	0.67		E
	1"	0.50	0.62	0.75		E
	1 1/4"	0.60	0.75	0.90		E
	1 1/2"	0.70	0.87	1.05		E
	2"	0.80	1.25	1.50		E
<b>EMT Service Entrance Caps</b>						
	1/2"	0.50	0.62	0.75		E
	3/4"	0.55	0.68	0.82		E
	1"	0.60	0.75	0.90		E
	1 1/4"	0.70	0.87	1.05		E
	1 1/2"	0.85	1.05	1.25		E
	2"	1.00	1.25	1.50		E
	2 1/2"	1.25	1.55	1.85		E
	3"	1.50	1.85	2.25		E
3 1/2"	1.75	2.15	2.60		E	
4"	2.00	2.50	3.00		E	
<b>EMT to Rigid Conduit Adapters</b>						
	1/2"	0.15	0.20	0.25		E
	3/4"	0.20	0.25	0.30		E
	1"	0.25	0.31	0.37		E
	1 1/4"	0.30	0.37	0.45		E
	1 1/2"	0.35	0.43	0.52		E
	2"	0.40	0.50	0.60		E
<b>EMT to Flexible Conduit Couplings</b>						
	1/2"	0.12	0.15	0.18		E
	3/4"	0.15	0.18	0.22		E
	1"	0.20	0.25	0.30		E
	1 1/4"	0.25	0.31	0.37		E
	1 1/2"	0.30	0.37	0.45		E
	2"	0.40	0.50	0.60		E
	2 1/2"	0.50	0.62	0.75		E
	3"	0.60	0.75	0.90		E
	3 1/2"	0.75	0.93	1.12		E
	4"	1.00	1.25	1.50		E
<b>EMT to EMT Reducing Couplings</b>						
	1/2" to 3/4"	0.06	0.07	0.08		E
	3/4" to 1"	0.08	0.09	0.10		E
	1" to 1 1/4"	0.10	0.11	0.13		E
	1 1/4" to 1 1/2"	0.12	0.14	0.16		E
	1 1/2" to 2"	0.14	0.16	0.18		E
	2" to 2 1/2"	0.16	0.18	0.20		E
	2 1/2" to 3"	0.20	0.22	0.24		E
	3" to 3 1/2"	0.22	0.24	0.26		E
3 1/2" to 4"	0.24	0.26	0.28		E	
<b>EMT Expansion/Deflection Coupling-Includes Bonding Jumper</b>						
	1/2"	X	0.50	0.65	0.80	E
	3/4"	X	0.55	0.70	0.85	E
	1"	X	0.60	0.75	0.90	E
	1 1/4"	X	0.65	0.80	0.95	E
	1 1/2"	X	0.70	0.85	1.00	E
	2"	X	0.85	1.00	1.15	E
	2 1/2"	X	0.95	1.15	1.30	E
	3"	X	1.10	1.25	1.40	E
	3 1/2"	X	1.30	1.50	1.75	E
	4"	X	1.50	1.75	2.25	E

Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Steel Set Screw Conduit Bodies</b>						
 1/2" One Hub		0.30	0.37	0.45		E
 3/4" One Hub		0.35	0.43	0.52		E
 1" One Hub		0.40	0.50	0.60		E
 1/2" Two Hubs		0.40	0.50	0.60		E
 3/4" Two Hubs		0.50	0.62	0.75		E
 1" Two Hubs		0.70	0.87	1.05		E
 1 1/4" Two Hubs		0.90	1.12	1.35		E
 1 1/2" Two Hubs		1.10	1.37	1.65		E
 2" Two Hubs		1.35	1.68	2.00		E
 2 1/2" Two Hubs		1.60	1.75	1.90		E
 3" Two Hubs		2.00	2.25	2.50		E
 3 1/2" Two Hubs		2.50	2.75	3.00		E
 4" Two Hubs		3.25	3.75	4.25		E
 1/2" Three Hubs		0.60	0.75	0.90		E
 3/4" Three Hubs		0.75	0.93	1.12		E
 1" Three Hubs		0.90	1.12	1.35		E
1 1/4" Three Hubs		1.10	1.37	1.65		E
1 1/2" Three Hubs		1.35	1.68	2.00		E
2" Three Hubs		1.60	2.00	2.40		E
1/2" Four Hubs		0.80	1.00	1.20		E
3/4" Four Hubs		1.00	1.25	1.50		E
1" Four Hubs		1.20	1.50	1.80		E
1 1/4" Four Hubs		1.40	1.75	2.10		E
1 1/2" Four Hubs		1.60	2.00	2.40		E
2" Four Hubs		1.90	2.35	2.85		E
<b>Threadless Conduit Bodies for EMT &amp; Rigid Steel Conduit</b>						
 1/2" One Hub		0.35	0.43	0.52		E
 3/4" One Hub		0.40	0.50	0.60		E
 1" One Hub		0.50	0.62	0.75		E
 1/2" Two Hubs		0.50	0.62	0.75		E
 3/4" Two Hubs		0.60	0.75	0.90		E
 1" Two Hubs		0.75	0.93	1.12		E
 1 1/4" Two Hubs		1.00	1.25	1.50		E
 1 1/2" Two Hubs		1.25	1.55	1.85		E
 2" Two Hubs		1.50	1.85	2.25		E
 1/2" Three Hubs		0.70	0.87	1.05		E
 3/4" Three Hubs		0.85	1.05	1.25		E
 1" Three Hubs		1.00	1.25	1.50		E
1 1/4" Three Hubs		1.20	1.50	1.80		E
1 1/2" Three Hubs		1.50	1.85	2.25		E
2" Three Hubs		1.80	2.25	2.70		E
1/2" Four Hubs		1.00	1.25	1.50		E
3/4" Four Hubs		1.15	1.40	1.70		E
1" Four Hubs		1.30	1.60	1.95		E
1 1/4" Four Hubs		1.50	1.85	2.25		E
1 1/2" Four Hubs		1.75	2.15	2.60		E
2" Four Hubs		2.00	2.50	3.00		E

## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Intermediate Metal Conduit (IMC) and Fittings</b>						
<b>Intermediate Metal Conduit (IMC) with Couplings</b>						
1/2"		5.00	6.20	7.50		C
3/4"		5.50	6.80	8.20		C
1"		6.00	7.50	9.00		C
1 1/4"		7.00	8.70	10.50		C
1 1/2"		8.00	10.00	12.00		C
2"		9.00	11.20	13.50		C
2 1/2"		12.00	15.00	18.00		C
3"		15.00	18.70	22.50		C
3 1/2"		18.00	22.50	27.00		C
4"		21.00	26.20	31.50		C
<b>IMC Factory Elbows</b>						
1/2"		0.35	0.43	0.52		E
3/4"		0.40	0.52	0.60		E
1"		0.50	0.60	0.75		E
1 1/4"		0.60	0.75	0.90		E
1 1/2"		0.75	0.93	1.15		E
2"		0.90	1.15	1.35		E
2 1/2"		1.30	1.60	1.95		E
3"		1.70	2.10	2.55		E
3 1/2"		2.10	2.60	3.15		E
4"		2.50	3.10	3.75		E
<b>Field Bending IMC Conduit and Installation</b>						
<b>Add approx 20% for each field cut &amp; thread</b>						
1 1/4"		1.20	1.50	1.80		E
1 1/2"		1.50	1.86	2.30		E
2"		1.80	2.30	2.70		E
2 1/2"		2.55	3.15	3.80		E
3"		3.20	3.95	4.80		E
3 1/2"		3.85	4.75	5.75		E
4"		4.50	5.60	6.75		E
<b>IMC Field Cut Nipples and Installation - 12" Length Maximum</b>						
1/2"		0.50	0.62	0.74		E
3/4"		0.60	0.74	0.90		E
1"		0.70	0.86	1.04		E
1 1/4"		0.80	1.00	1.20		E
1 1/2"		1.00	1.24	1.50		E
2"		1.20	1.50	1.80		E
2 1/2"		1.45	1.81	2.17		E
3"		1.75	2.17	2.60		E
3 1/2"		2.10	2.62	3.15		E
4"		2.50	3.12	3.75		E






## Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Rigid Aluminum Conduit and Fittings</b>						
<b>Rigid Aluminum Conduit with Couplings</b>						
1/2"		5.00	6.20	7.50		C
3/4"		5.50	6.80	8.20		C
1"		6.00	7.50	9.00		C
1 1/4"		6.50	8.10	9.70		C
1 1/2"		7.00	8.70	10.50		C
2"		8.00	10.00	12.00		C
2 1/2"		10.00	12.50	15.00		C
3"		12.00	15.00	18.00		C
3 1/2"		15.00	18.70	22.50		C
4"		19.00	23.70	28.50		C
5"		24.00	30.00	36.00		C
6"		30.00	37.50	45.00		C
<i>Note: Add 25% for PVC Coated Aluminum</i>						
<b>Rigid Aluminum Factory Elbows</b>						
1/2"		0.25	0.31	0.37		E
3/4"		0.30	0.37	0.45		E
1"		0.35	0.43	0.52		E
1 1/4"		0.40	0.50	0.60		E
1 1/2"		0.50	0.62	0.75		E
2"		0.75	0.93	1.12		E
2 1/2"		1.00	1.25	1.50		E
3"		1.30	1.60	1.95		E
3 1/2"		1.60	2.00	2.40		E
4"		2.00	2.50	3.00		E
5"		2.50	3.10	3.75		E
6"		3.00	3.75	4.50		E
<i>Note: Add 25% for PVC Coated Aluminum</i>						
<b>Field Bending Rigid Aluminum Conduit and Installation</b>						
<b>Add approx 20% for each field cut &amp; thread</b>						
1 1/4"		0.80	1.00	1.20		E
1 1/2"		1.00	1.24	1.50		E
2"		1.50	1.86	2.24		E
2 1/2"		2.00	2.50	3.00		E
3"		2.50	3.10	3.75		E
3 1/2"		3.00	3.75	4.50		E
4"		3.75	4.65	5.60		E
5"		4.75	5.80	7.10		E
6"		6.00	7.50	9.00		E
<i>Note: Add 25% for PVC Coated Aluminum</i>						
<b>Aluminum Lock Nut &amp; Bushing Sets</b>						
<b>Field Cut &amp; Thread Included</b>						
1/2"		0.30	0.37	0.45		E
3/4"		0.35	0.43	0.52		E
1"		0.40	0.50	0.60		E
1 1/4"		0.50	0.62	0.75		E
1 1/2"		0.60	0.75	0.90		E
2"		0.80	1.00	1.20		E
2 1/2"		1.00	1.25	1.50		E
3"		1.20	1.50	1.80		E
3 1/2"		1.40	1.75	2.10		E
4"		1.60	2.00	2.40		E
5"		1.80	2.25	2.70		E
6"		2.00	2.50	3.00		E
<b>Aluminum Lock Nut &amp; Ground Bushing Sets</b>						
<b>Field Cut &amp; Thread Included</b>						
1/2"		0.40	0.50	0.60		E
3/4"		0.45	0.56	0.67		E
1"		0.50	0.62	0.75		E
1 1/4"		0.60	0.75	0.90		E
1 1/2"		0.80	1.00	1.20		E
2"		1.00	1.25	1.50		E
2 1/2"		1.20	1.50	1.80		E
3"		1.40	1.75	2.10		E
3 1/2"		1.60	2.00	2.40		E
4"		1.80	2.25	2.70		E
5"		2.10	2.60	3.15		E
6"		2.40	3.00	3.60		E



## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Aluminum Factory Cut Nipples - 12" Length Maximum</b>						
 1/2"		0.25	0.31	0.37		E
3/4"		0.30	0.37	0.45		E
1"		0.35	0.43	0.52		E
1 1/4"		0.40	0.50	0.60		E
1 1/2"		0.50	0.62	0.75		E
2"		0.60	0.75	0.90		E
2 1/2"		0.75	0.93	1.12		E
3"		0.90	1.12	1.35		E
3 1/2"		1.10	1.37	1.65		E
4"		1.30	1.62	1.95		E
5"		1.50	1.85	2.25		E
6"		1.80	2.25	2.70		E
<b>Aluminum Field Cut Nipples and Installation - 12" Length Maximum</b>						
1/2"		0.60	0.74	0.89		E
3/4"		0.70	0.87	1.05		E
1"		0.80	0.99	1.19		E
1 1/4"		0.90	1.12	1.35		E
1 1/2"		1.10	1.37	1.65		E
2"		1.40	1.75	2.10		E
2 1/2"		1.75	2.19	2.62		E
3"		2.10	2.62	3.15		E
3 1/2"		2.50	3.12	3.75		E
4"		2.90	3.62	4.35		E
5"		3.30	4.12	4.95		E
6"		3.90	4.85	5.85		E
<b>Aluminum Chase Nipples - Includes Locknut &amp; Bushing</b>						
 1/2"		0.12	0.15	0.18		E
3/4"		0.14	0.17	0.21		E
1"		0.17	0.21	0.25		E
1 1/4"		0.20	0.25	0.30		E
1 1/2"		0.25	0.31	0.37		E
2"		0.30	0.37	0.45		E
2 1/2"		0.35	0.43	0.52		E
3"		0.40	0.50	0.60		E
3 1/2"		0.40	0.50	0.60		E
4"		0.50	0.62	0.75		E
<b>Aluminum Offset Nipples - Includes Locknut &amp; Bushings</b>						
 1/2"		0.25	0.31	0.37		E
3/4"		0.30	0.37	0.45		E
1"		0.35	0.43	0.52		E
1 1/4"		0.40	0.50	0.60		E
1 1/2"		0.45	0.56	0.67		E
2"		0.50	0.62	0.75		E
<b>Aluminum Female Threaded Reducers - Includes Locknut &amp; Bushing</b>						
 1/2"		0.15	0.18	0.22		E
3/4"		0.17	0.21	0.26		E
1"		0.20	0.25	0.30		E
1 1/4"		0.23	0.28	0.34		E
1 1/2"		0.25	0.32	0.39		E
2"		0.30	0.37	0.45		E
2 1/2"		0.35	0.43	0.52		E
3"		0.40	0.50	0.60		E
3 1/2"		0.45	0.56	0.67		E
4"		0.50	0.62	0.75		E
<b>Aluminum Compression Couplings</b>						
 1/2"		0.20	0.25	0.30		E
3/4"		0.25	0.31	0.37		E
1"		0.30	0.37	0.45		E
1 1/4"		0.40	0.50	0.60		E
1 1/2"		0.50	0.62	0.75		E
2"		0.60	0.75	0.90		E
2 1/2"		0.70	0.87	1.05		E
3"		0.80	1.00	1.20		E
3 1/2"		0.90	1.12	1.35		E
4"		1.00	1.25	1.50		E

Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Aluminum Split Couplings</b>						
 1/2"		0.30	0.37	0.45		E
3/4"		0.40	0.50	0.60		E
1"		0.50	0.62	0.75		E
1 1/4"		0.60	0.75	0.90		E
1 1/2"		0.70	0.87	1.05		E
2"		0.80	1.00	1.20		E
2 1/2"		0.90	1.12	1.35		E
3"		1.00	1.25	1.50		E
3 1/2"		1.15	1.38	1.70		E
4"		1.30	1.60	1.95		E
<b>Aluminum Expansion Couplings - Includes Bonding Jumper</b>						
1/2"		0.60	0.75	0.90		E
3/4"		0.70	0.87	1.05		E
1"		0.80	1.00	1.20		E
1 1/4"		1.00	1.25	1.50		E
1 1/2"		1.25	1.55	1.85		E
2"		1.50	1.85	2.25		E
2 1/2"		1.75	2.15	2.60		E
3"		2.00	2.50	3.00		E
3 1/2"		2.50	3.10	3.75		E
4"		3.00	3.75	4.50		E
<b>Aluminum Erickson Couplings</b>						
1/2"		0.60	0.75	0.90		E
3/4"		0.70	0.87	1.05		E
1"		0.80	1.00	1.20		E
1 1/4"		0.90	1.12	1.35		E
1 1/2"		1.05	1.30	1.57		E
2"		1.25	1.55	1.85		E
2 1/2"		1.50	1.85	2.25		E
3"		1.75	2.15	2.60		E
3 1/2"		2.00	2.50	3.00		E
4"		2.25	2.80	3.35		E
<b>Aluminum Threaded Entrance Elbows</b>						
1/2"		0.50	0.62	0.75		E
3/4"		0.60	0.75	0.90		E
1"		0.75	0.93	1.12		E
1 1/4"		1.00	1.25	1.50		E
1 1/2"		1.25	1.55	1.85		E
2"		1.50	1.85	2.25		E
2 1/2"		2.00	2.50	3.00		E
3"		2.50	3.10	3.75		E
3 1/2"		3.00	3.75	4.50		E
4"		4.00	5.00	6.00		E
5"		5.00	6.25	7.50		E
6"		6.00	7.50	9.00		E
<b>Aluminum Threadless Box Connectors</b>						
1/2"		0.30	0.37	0.45		E
3/4"		0.40	0.50	0.60		E
1"		0.50	0.62	0.75		E
1 1/4"		0.60	0.75	0.90		E
1 1/2"		0.70	0.85	1.00		E
2"		0.80	1.00	1.20		E
2 1/2"		0.90	1.10	1.35		E
3"		1.00	1.25	1.50		E
3 1/2"		1.10	1.35	1.60		E
4"		1.20	1.45	1.70		E
<b>Aluminum Threaded Service Entrance Caps</b>						
1/2"		0.60	0.75	0.90		E
3/4"		0.70	0.87	1.05		E
1"		0.80	1.00	1.20		E
1 1/4"		0.90	1.12	1.35		E
1 1/2"		1.00	1.25	1.50		E
2"		1.25	1.55	1.85		E
2 1/2"		1.50	1.85	2.25		E
3"		2.00	2.50	3.00		E
3 1/2"		2.50	3.10	3.75		E
4"		3.00	3.75	4.50		E
5"		4.00	5.00	6.00		E
6"		5.00	6.25	7.50		E

## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Aluminum Threaded Capped Elbows</b>						
 1/2"		0.50	0.62	0.75		E
3/4"		0.60	0.75	0.90		E
1"		0.70	0.87	1.05		E
1 1/4"		0.80	1.00	1.20		E
1 1/2"		1.00	1.25	1.50		E
2"		1.20	1.50	1.80		E
<b>Aluminum Pipe Caps or Capped Bushings</b>						
1/2"		0.15	0.18	0.22		E
3/4"		0.16	0.20	0.24		E
1"		0.18	0.22	0.27		E
1 1/4"		0.20	0.25	0.30		E
1 1/2"		0.25	0.31	0.37		E
2"		0.30	0.37	0.45		E
2 1/2"		0.35	0.43	0.52		E
3"		0.40	0.50	0.60		E
3 1/2"		0.45	0.56	0.67		E
4"		0.50	0.62	0.75		E
5"		0.55	0.68	0.82		E
6"		0.60	0.75	0.90		E
<b>Aluminum Threaded Conduit Bodies-One Hub</b>						
1/2"		0.35	0.43	0.52		E
3/4"		0.45	0.56	0.67		E
1"		0.60	0.75	0.90		E
<b>Aluminum Threaded Conduit Bodies-Two Hubs</b>						
1/2"		0.60	0.75	0.90		E
3/4"		0.70	0.87	1.05		E
1"		0.90	1.12	1.35		E
1 1/4"		1.10	1.37	1.65		E
1 1/2"		1.25	1.56	1.87		E
2"		1.65	2.05	2.47		E
2 1/2"		2.50	3.12	3.75		E
3"		3.25	4.05	4.85		E
3 1/2"		3.75	4.65	5.60		E
4"		4.50	5.60	6.75		E
<b>Aluminum Threaded Conduit Bodies-Three Hubs</b>						
1/2"		0.75	0.93	1.12		E
3/4"		0.90	1.12	1.35		E
1"		1.15	1.43	1.72		E
1 1/4"		1.40	1.75	2.10		E
1 1/2"		1.65	2.05	2.47		E
2"		2.15	2.68	3.22		E
2 1/2"		3.25	4.05	4.85		E
3"		4.10	5.10	6.15		E
3 1/2"		4.90	6.15	7.35		E
4"		5.70	7.10	8.50		E
<b>Aluminum Threaded Conduit Bodies-Four Hubs</b>						
1/2"		0.90	1.12	1.35		E
3/4"		1.15	1.43	1.72		E
1"		1.40	1.75	2.10		E
1 1/4"		1.70	2.10	2.55		E
1 1/2"		2.00	2.50	3.00		E
2"		3.00	3.75	4.50		E
2 1/2"		4.00	5.00	6.00		E
3"		5.00	5.75	7.50		E
4"		7.00	8.75	10.50		E
<b>Aluminum Mogul Conduit Bodies-Two Hubs</b>						
1"		0.90	1.12	1.35		E
1 1/4"		1.20	1.50	1.80		E
1 1/2"		1.60	2.00	2.40		E
2"		2.00	2.50	3.00		E
2 1/2"		2.50	3.12	3.75		E
3"		3.00	3.75	4.50		E
3 1/2"		3.50	4.35	5.25		E
4"		4.00	5.00	6.00		E

Section 2 - Conduit, Raceways, Fittings & Related Items

2




Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Aluminum Mogul Conduit Bodies-Three Hubs</b>						
 1"		1.25	1.55	1.85		E
1 1/4"		1.75	2.15	2.60		E
1 1/2"		2.00	2.50	3.00		E
2"		2.25	2.80	3.35		E
2 1/2"		2.50	3.10	3.75		E
3"		3.25	4.05	4.85		E
3 1/2"		4.00	5.00	6.00		E
4"		5.00	6.25	7.50		E
<b>Aluminum FS &amp; FD Threaded 1-Gang Boxes</b>						
 1/2" One Hub		0.50	0.62	0.75		E
3/4" One Hub		0.60	0.75	0.90		E
1" One Hub		0.75	0.94	1.12		E
1/2" Two Hubs		0.70	0.87	1.05		E
3/4" Two Hubs		0.85	1.05	1.25		E
1" Two Hubs		1.05	1.30	1.55		E
1/2" Three Hubs		0.90	1.12	1.35		E
3/4" Three Hubs		1.10	1.35	1.65		E
1" Three Hubs		1.35	1.65	2.00		E
1/2" Four Hubs		1.10	1.35	1.65		E
3/4" Four Hubs		1.35	1.65	2.00		E
1" Four Hubs		1.60	2.00	2.40		E
<b>Aluminum FS &amp; FD Threaded 2-Gang Boxes</b>						
 1/2" One Hub		0.55	0.68	0.82		E
3/4" One Hub		0.65	0.81	0.97		E
1" One Hub		0.80	1.00	1.20		E
1/2" Two Hubs		0.75	0.94	1.12		E
3/4" Two Hubs		0.90	1.12	1.35		E
1" Two Hubs		1.10	1.35	1.65		E
1/2" Three Hubs		0.95	1.15	1.40		E
3/4" Three Hubs		1.15	1.40	1.70		E
1" Three Hubs		1.35	1.65	2.00		E
1/2" Four Hubs		1.15	1.40	1.70		E
3/4" Four Hubs		1.35	1.65	2.00		E
1" Four Hubs		1.60	2.00	2.40		E
<b>Weatherproof Aluminum Boxes 1-Gang</b>						
 1/2" One Hub		0.50	0.62	0.75		E
1/2" Two Hubs		0.70	0.87	1.05		E
1/2" Three Hubs		0.90	1.12	1.35		E
1/2" Four Hubs		1.10	1.35	1.65		E
3/4" One Hub		0.60	0.75	0.90		E
3/4" Two Hubs		0.85	1.05	1.25		E
3/4" Three Hubs		1.10	1.35	1.65		E
3/4" Four Hubs		1.35	1.65	2.00		E

## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Flexible Steel Conduit (FSC or Greenfield) and Fittings</b>						
<b>Flexible Steel Conduit (FSC)</b>						
<b>For flex Alum, reduce the Steel Labor by 10%</b>						
		3/8"	3.50	4.30	5.20	C
		1/2"	4.00	5.00	6.00	C
		3/4"	5.00	6.20	7.50	C
		1"	7.50	9.30	11.20	C
		1 1/4"	10.00	12.50	15.00	C
		1 1/2"	15.00	18.70	22.50	C
		2"	20.00	25.00	30.00	C
		2 1/2"	25.00	31.20	37.50	C
		3"	30.00	37.50	45.00	C
		3 1/2"	40.00	50.00	60.00	C
		4"	50.00	62.00	75.00	C
<b>FSC to Box Connectors - Add 20% for angled fittings</b>						
		3/8"	0.10	0.12	0.15	E
		1/2"	0.12	0.15	0.18	E
		3/4"	0.14	0.17	0.21	E
		1"	0.17	0.21	0.25	E
		1 1/4"	0.20	0.25	0.30	E
		1 1/2"	0.25	0.31	0.37	E
		2"	0.30	0.37	0.45	E
		2 1/2"	0.40	0.50	0.60	E
		3"	0.50	0.62	0.75	E
		3 1/2"	0.60	0.75	0.90	E
		4"	0.70	0.87	1.05	E
<b>FSC to Rigid Steel Conduit Couplings</b>						
		1/2"	0.15	0.18	0.22	E
		3/4"	0.20	0.25	0.30	E
		1"	0.25	0.31	0.37	E
		1 1/4"	0.30	0.37	0.45	E
		1 1/2"	0.40	0.50	0.60	E
		2"	0.55	0.68	0.82	E
		2 1/2"	0.75	0.93	1.12	E
		3"	1.00	1.25	1.50	E
		3 1/2"	1.25	1.55	1.85	E
		4"	1.50	1.85	2.25	E
<b>FSC to EMT Couplings</b>						
		1/2"	0.12	0.15	0.18	E
		3/4"	0.15	0.18	0.22	E
		1"	0.20	0.25	0.30	E
		1 1/4"	0.25	0.31	0.37	E
		1 1/2"	0.30	0.37	0.45	E
		2"	0.40	0.50	0.60	E
		2 1/2"	0.50	0.62	0.75	E
		3"	0.60	0.75	0.90	E
		3 1/2"	0.75	0.93	1.12	E
		4"	1.00	1.25	1.50	E
<b>FSC Duplex Box Converters</b>						
		3/8"	0.15	0.17	0.18	E
		1/2"	0.15	0.17	0.18	E

## Section 2 - Conduit, Raceways, Fittings & Related Items

2






Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Sealtite Flexible Conduit and Fittings</b>						
<b>Liquidtight Flexible Steel Conduit (LFSC)</b>						
						
3/8"		3.50	4.30	5.20		C
1/2"		4.00	5.00	6.00		C
3/4"		5.00	6.20	7.50		C
1"		7.50	9.30	11.20		C
1 1/4"		10.00	12.50	15.00		C
1 1/2"		15.00	18.70	22.50		C
2"		20.00	25.00	30.00		C
2 1/2"		25.00	31.20	37.50		C
3"		30.00	37.50	45.00		C
3 1/2"		40.00	50.00	60.00		C
4"		50.00	62.00	75.00		C
<b>LFSC to Box Connectors - Add 20% for angled fittings</b>						
						
3/8"		0.12	0.15	0.18		E
1/2"		0.15	0.18	0.22		E
3/4"		0.18	0.22	0.27		E
1"		0.24	0.30	0.36		E
1 1/4"		0.30	0.37	0.45		E
1 1/2"		0.36	0.45	0.54		E
2"		0.42	0.52	0.63		E
2 1/2"		0.48	0.60	0.72		E
3"		0.60	0.75	0.90		E
3 1/2"		0.72	0.90	1.08		E
4"		0.96	1.20	1.44		E
<b>LFSC to Rigid Steel Conduit Couplings</b>						
						
1/2"		0.20	0.25	0.30		E
3/4"		0.25	0.31	0.37		E
1"		0.30	0.37	0.45		E
1 1/4"		0.40	0.50	0.60		E
1 1/2"		0.55	0.68	0.82		E
2"		0.75	0.93	1.12		E
2 1/2"		1.00	1.25	1.50		E
3"		1.25	1.55	1.85		E
3 1/2"		1.50	1.85	2.25		E
4"		1.75	2.15	2.60		E
<b>LFSC to EMT Couplings</b>						
						
1/2"		0.16	0.20	0.24		E
3/4"		0.20	0.25	0.30		E
1"		0.25	0.31	0.37		E
1 1/4"		0.30	0.37	0.45		E
1 1/2"		0.40	0.50	0.60		E
2"		0.50	0.62	0.75		E
2 1/2"		0.65	0.80	0.95		E
3"		0.80	1.00	1.20		E
3 1/2"		1.00	1.25	1.50		E
4"		1.25	1.55	1.85		E

## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>PVC Coated Rigid Steel Conduit</b>						
<b>PVC Coated Rigid Steel Conduit</b>						
 1/2"		7.00	8.70	10.50		C
3/4"		8.00	10.00	12.00		C
1"		10.00	12.50	15.00		C
1 1/4"		12.00	15.00	18.00		C
1 1/2"		15.00	18.70	22.50		C
2"		18.00	22.50	27.00		C
2 1/2"		21.00	26.20	31.50		C
3"		26.00	32.50	39.00		C
3 1/2"		32.00	40.00	48.00		C
4"		38.00	47.00	57.00		C
5"		45.00	56.20	67.50		C
6"		60.00	75.00	90.00		C
<i>PVC Coating Repair Not Included.</i>						
<b>PVC Coated Rigid Steel Elbows</b>						
1/2"		0.50	0.62	0.74		E
3/4"		0.60	0.74	0.90		E
1"		0.70	0.86	1.04		E
1 1/4"		0.80	1.00	1.20		E
1 1/2"		1.00	1.24	1.50		E
2"		1.20	1.50	1.80		E
2 1/2"		1.75	2.05	2.35		E
3"		2.25	2.75	3.20		E
3 1/2"		2.75	3.25	3.75		E
4"		3.25	3.75	4.25		E
5"		4.50	5.50	6.50		E
6"		5.50	6.50	7.50		E
<i>PVC Coating Repair Not Included.</i>						
<b>PVC Coated Rigid Steel Elbows</b>						
48" Radius						
1"		0.75	0.90	1.10		E
1 1/4"		0.85	1.05	1.25		E
1 1/2"		1.10	1.30	1.55		E
2"		1.30	1.60	1.90		E
2 1/2"		1.85	2.15	2.45		E
3"		2.45	2.95	3.45		E
3 1/2"		2.95	3.45	3.95		E
4"		3.45	3.95	4.45		E
5"		4.90	5.90	6.90		E
6"		6.00	7.00	8.00		E
<i>PVC Coating Repair Not Included.</i>						
<b>PVC Coated Termination Sets</b>						
1/2"		0.40	0.50	0.60		E
3/4"		0.45	0.56	0.67		E
1"		0.55	0.68	0.82		E
1 1/4"		0.65	0.81	0.97		E
1 1/2"		0.80	1.00	1.20		E
2"		1.00	1.25	1.50		E
2 1/2"		1.25	1.55	1.85		E
3"		1.50	1.85	2.25		E
3 1/2"		1.75	2.15	2.60		E
4"		2.00	2.50	3.00		E
5"		2.35	2.90	3.50		E
6"		2.70	3.35	4.00		E
<i>PVC Coating Repair Not Included.</i>						
<b>PVC Coated Steel Factory Nipples - 12" Length Maximum</b>						
1/2"		0.25	0.31	0.37		E
3/4"		0.30	0.37	0.45		E
1"		0.35	0.43	0.52		E
1 1/4"		0.40	0.50	0.60		E
1 1/2"		0.50	0.62	0.75		E
2"		0.60	0.75	0.90		E
2 1/2"		0.75	0.94	1.12		E
3"		0.90	1.12	1.35		E
3 1/2"		1.10	1.37	1.65		E
4"		1.30	1.62	1.95		E
5"		1.50	1.87	2.25		E
6"		1.80	2.25	2.70		E
<i>PVC Coating Repair Not Included.</i>						






Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>PVC Coated Steel Field Cut Nipples - 12" Length Maximum</b>						
 1/2"		0.50	0.62	0.74		E
3/4"		0.60	0.74	0.90		E
1"		0.70	0.86	1.04		E
1 1/4"		0.80	1.00	1.20		E
1 1/2"		1.00	1.24	1.50		E
2"		1.20	1.50	1.80		E
2 1/2"		1.45	1.81	2.17		E
3"		1.75	2.17	2.60		E
3 1/2"		2.10	2.62	3.15		E
4"		2.50	3.12	3.75		E
5"		3.40	4.22	5.10		E
6"		4.10	5.15	6.20		E
<i>PVC Coating Repair Not Included.</i>						
<b>PVC Coated Steel Offset Nipples</b>						
 1/2"		0.25	0.31	0.27		E
3/4"		0.30	0.37	0.45		E
1"		0.35	0.43	0.52		E
1 1/4"		0.40	0.50	0.60		E
1 1/2"		0.45	0.56	0.67		E
2"		0.50	0.62	0.75		E
<i>PVC Coating Repair Not Included.</i>						
<b>PVC Coated Couplings</b>						
 1/2"		0.30	0.37	0.45		E
3/4"		0.35	0.43	0.52		E
1"		0.40	0.50	0.60		E
1 1/4"		0.50	0.62	0.75		E
1 1/2"		0.60	0.75	0.90		E
2"		0.70	0.87	1.05		E
2 1/2"		0.80	1.00	1.20		E
3"		1.00	1.25	1.50		E
3 1/2"		1.20	1.50	1.80		E
4"		1.50	1.85	2.25		E
<i>PVC Coating Repair Not Included.</i>						
<b>PVC Coated Steel Split Couplings</b>						
 1/2"		0.30	0.37	0.45		E
3/4"		0.35	0.43	0.52		E
1"		0.40	0.50	0.60		E
1 1/4"		0.50	0.62	0.75		E
1 1/2"		0.60	0.75	0.90		E
2"		0.70	0.87	1.05		E
2 1/2"		0.80	1.00	1.20		E
3"		1.00	1.25	1.50		E
3 1/2"		1.20	1.50	1.80		E
4"		1.50	1.85	2.25		E
<i>PVC Coating Repair Not Included.</i>						
<b>PVC Coated Expansion Couplings - Including Bond Jumper</b>						
 1/2"		0.70	0.87	1.05		E
3/4"		0.85	1.00	1.25		E
1"		1.00	1.25	1.50		E
1 1/4"		1.25	1.55	1.85		E
1 1/2"		1.50	1.85	2.25		E
2"		1.75	2.15	2.60		E
2 1/2"		2.00	2.50	3.00		E
3"		2.50	3.10	3.75		E
3 1/2"		3.00	3.75	4.50		E
4"		3.75	4.65	5.60		E
<i>PVC Coating Repair Not Included.</i>						








## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>PVC Rigid Conduit</b>						
<b>PVC Rigid Conduit - Schedule 40 with Couplings</b>						
For installation in trench, see Section 11						
 1/2"		4.10	5.10	6.15		C
3/4"		4.50	5.60	6.75		C
1"		5.25	6.50	7.90		C
1 1/4"		6.00	7.50	9.00		C
1 1/2"		7.00	8.75	10.50		C
2"		8.00	10.00	12.00		C
2 1/2"		9.00	11.25	14.06		C
3"		10.00	12.50	15.63		C
3 1/2"		12.00	15.00	18.75		C
4"		14.00	17.50	21.88		C
5"		18.00	22.50	28.13		C
6"		24.00	30.00	37.50		C
<b>PVC Factory Elbows-Sch 40 - Add 20% for Wide Sweep</b>						
 1/2"		0.20	0.25	0.30		E
3/4"		0.22	0.28	0.33		E
1"		0.25	0.31	0.38		E
1 1/4"		0.32	0.40	0.48		E
1 1/2"		0.40	0.48	0.60		E
2"		0.50	0.63	0.75		E
2 1/2"		0.60	0.75	0.90		E
3"		0.70	0.84	1.05		E
3 1/2"		0.85	1.06	1.28		E
4"		1.00	1.25	1.50		E
5"		1.25	1.56	1.88		E
6"		1.50	1.88	2.25		E
<b>Field Bent PVC Conduit and Installation</b>						
Add approx 10% for each field cut & ream.						
 1/2"		0.40	0.50	0.60		E
3/4"		0.50	0.63	0.75		E
1"		0.60	0.75	0.90		E
1 1/4"		0.65	0.81	0.98		E
1 1/2"		0.80	1.00	1.20		E
2"		1.00	1.25	1.50		E
2 1/2"		1.20	1.50	1.80		E
3"		1.40	1.75	2.10		E
3 1/2"		1.70	2.13	2.55		E
4"		2.00	2.50	3.00		E
5"		3.15	3.94	4.73		E
6"		4.20	5.25	6.30		E
<b>PVC Conduit Adapters-All Types</b>						
 1/2"		0.14	0.17	0.21		E
3/4"		0.16	0.20	0.24		E
1"		0.18	0.22	0.27		E
1 1/4"		0.20	0.25	0.30		E
1 1/2"		0.25	0.31	0.37		E
2"		0.30	0.37	0.45		E
2 1/2"		0.40	0.50	0.60		E
3"		0.50	0.62	0.75		E
3 1/2"		0.65	0.81	0.97		E
4"		0.80	1.00	1.20		E
5"		1.00	1.25	1.50		E
6"		1.25	1.55	1.85		E
<b>PVC Expansion Couplings-Sch 40</b>						
 1/2"		0.50	0.62	0.75		E
3/4"		0.60	0.75	0.90		E
1"		0.70	0.87	1.05		E
1 1/4"		0.80	1.00	1.20		E
1 1/2"		0.90	1.12	1.35		E
2"		1.00	1.25	1.50		E
2 1/2"		1.15	1.43	1.72		E
3"		1.30	1.62	1.95		E
3 1/2"		1.50	1.85	2.25		E
4"		1.75	2.15	2.60		E




Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>PVC Bell Ends-Sch 40</b>						
 1/2"		0.12	0.15	0.18		E
3/4"		0.14	0.17	0.21		E
1"		0.16	0.20	0.24		E
1 1/4"		0.18	0.22	0.27		E
1 1/2"		0.20	0.25	0.30		E
2"		0.23	0.28	0.34		E
2 1/2"		0.26	0.32	0.39		E
3"		0.30	0.37	0.45		E
3 1/2"		0.35	0.43	0.52		E
4"		0.40	0.50	0.60		E
5"		0.45	0.56	0.67		E
6"		0.50	0.62	0.75		E
<b>PVC Conduit End Caps-Sch 40</b>						
 1/2"		0.10	0.12	0.15		E
3/4"		0.12	0.15	0.18		E
1"		0.14	0.17	0.21		E
1 1/4"		0.16	0.20	0.24		E
1 1/2"		0.18	0.22	0.27		E
2"		0.20	0.25	0.30		E
2 1/2"		0.23	0.28	0.34		E
3"		0.26	0.32	0.39		E
3 1/2"		0.29	0.36	0.43		E
4"		0.31	0.38	0.46		E
5"		0.35	0.43	0.52		E
6"		0.40	0.50	0.60		E
<b>PVC Rigid Conduit - Schedule 80 with Couplings</b> For installation in trench, see Section 11						
 1/2"		4.90	5.90	6.90		C
3/4"		5.40	6.40	7.40		C
1"		6.30	7.30	8.30		C
1 1/4"		7.20	7.70	9.20		C
1 1/2"		8.40	9.60	10.80		C
2"		9.60	10.80	12.80		C
2 1/2"		10.80	12.00	14.80		C
3"		12.00	14.50	16.50		C
4"		16.80	20.30	24.68		C
5"	X	21.60	27.00	33.75		C
6"		28.80	34.80	42.30		C
<b>PVC Factory Elbows-Sch 80 - Add 20% for Wide Sweep</b>						
1/2"		0.22	0.27	0.32		E
3/4"		0.24	0.29	0.34		E
1"		0.28	0.33	0.38		E
1 1/4"		0.35	0.40	0.45		E
1 1/2"		0.46	0.56	0.66		E
2"		0.58	0.73	0.88		E
2 1/2"		0.69	0.89	1.09		E
3"		0.84	1.09	1.34		E
4"		1.20	1.70	2.20		E
5"		1.50	2.00	2.50		E
6"		1.80	2.30	2.80		E
<b>Field Bent Schedule 80 PVC Conduit and Installation</b> Add approx 10% for each field cut & ream.						
 1/2"		0.50	0.60	0.70		E
3/4"		0.60	0.70	0.80		E
1"		0.70	0.85	1.00		E
1 1/4"		0.80	0.96	1.12		E
1 1/2"		1.00	1.20	1.40		E
2"		1.25	1.50	1.75		E
2 1/2"		1.50	1.75	2.00		E
3"		1.75	2.00	2.25		E
4"		2.00	2.25	2.50		E
5"		2.40	2.90	3.40		E
6"		3.65	4.44	5.23		E
<b>Schedule 80 PVC Conduit Adapters-All Types</b>						
 1/2"		0.16	0.19	0.23		E
3/4"		0.18	0.22	0.26		E
1"		0.20	0.24	0.28		E
1 1/4"		0.22	0.27	0.32		E
1 1/2"		0.30	0.35	0.40		E
2"		0.35	0.42	0.47		E
2 1/2"		0.45	0.55	0.65		E
3"		0.60	0.70	0.80		E
4"		0.70	0.85	0.97		E
5"		0.85	1.15	1.35		E
6"		1.20	1.40	1.70		E


## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>PVC Expansion Couplings-Sch 80</b>						
1/2"		0.25	0.30	0.35		E
3/4"		0.30	0.36	0.41		E
1"		0.40	0.48	0.55		E
1 1/4"		0.50	0.60	0.70		E
1 1/2"		0.65	0.78	0.90		E
2"		0.75	0.90	1.05		E
2 1/2"		0.85	1.02	1.17		E
3"		1.05	1.26	1.45		E
4"		1.40	1.68	1.93		E
5"		1.65	1.98	2.28		E
6"		1.90	2.28	2.62		E
<b>PVC Junction Boxes &amp; Pull Boxes</b>						
4" x 4" x 4"		0.30	0.37	0.45		E
4" x 6" x 4"		0.35	0.43	0.52		E
6" x 6" x 4"		0.40	0.50	0.60		E
6" x 8" x 4"		0.45	0.56	0.67		E
8" x 8" x 4"		0.50	0.62	0.75		E
8" x 12" x 4"		0.60	0.75	0.90		E
12" x 12" x 4"		0.70	0.87	1.05		E
12" x 12" x 6"		0.85	1.05	1.25		E
12" x 18" x 6"		1.00	1.25	1.50		E
<b>PVC Conduit Bodies</b>						
1/2" One Hub		0.30	0.37	0.45		E
3/4" One Hub		0.35	0.43	0.52		E
1/2" Two Hubs		0.40	0.50	0.60		E
3/4" Two Hubs		0.45	0.56	0.67		E
1" Two Hubs		0.50	0.62	0.75		E
1 1/4" Two Hubs		0.60	0.75	0.90		E
1 1/2" Two Hubs		0.75	0.93	1.12		E
2" Two Hubs		0.90	1.12	1.35		E
1/2" Three Hubs		0.50	0.62	0.75		E
3/4" Three Hubs		0.55	0.68	0.82		E
1" Three Hubs		0.60	0.75	0.90		E
1 1/4" Three Hubs		0.70	0.87	1.05		E
1 1/2" Three Hubs		0.85	1.05	1.25		E
2" Three Hubs		1.00	1.25	1.50		E
1/2" Four Hubs		0.65	0.81	0.97		E
3/4" Four Hubs		0.70	0.87	1.05		E
1" Four Hubs		0.75	0.93	1.12		E
1 1/4" Four Hubs		0.85	1.05	1.25		E
1 1/2" Four Hubs		1.00	1.25	1.50		E
2" Four Hubs		1.15	1.45	1.75		E
<b>PVC Boxes</b>						
PVC 4" Square Boxes		0.30	0.35	0.40		E
PVC 4" Octagon Boxes		0.30	0.35	0.40		E
<b>PVC Handy Boxes</b>						
PVC Handy Boxes		0.25	0.30	0.35		E
PVC Switch Boxes		0.25	0.30	0.35		E
PVC 4" Concrete Boxes		0.40	0.45	0.50		E
PVC 4" Hung Ceiling Boxes		0.45	0.50	0.55		E
PVC Floor Boxes		0.80	0.90	1.00		E
PVC Box Extensions		0.15	0.20	0.25		E
PVC Plaster Rings		0.15	0.20	0.25		E
PVC Box Covers-All Types		0.08	0.09	0.10		E



Section 2 - Conduit, Raceways, Fittings & Related Items








2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Fiberglass Conduit</b>						
<b>Fiberglass Conduit</b>						
<b>10Ft &amp; 20Ft Len. w/ Glued Couplings</b>						
 3/4"		5.50	6.88	8.59		C
1"		5.75	7.19	8.98		C
1 1/4"		6.00	7.50	9.38		C
1 1/2"		6.35	7.94	9.92		C
2"		6.75	8.44	10.55		C
2 1/2"		7.10	8.88	11.09		C
3"		7.50	9.38	11.72		C
3 1/2"		7.85	9.81	12.27		C
4"		8.25	10.31	12.89		C
5"		8.60	10.75	13.44		C
6"		9.00	11.25	14.06		C
<i>Note: Reduce Labor Units for 20 ft Lengths by 10%</i>						
<b>Fiberglass Conduit Glued Couplings</b>						
3/4"		14.00	17.50	21.88		C
1"		15.00	18.75	23.44		C
1 1/4"		16.50	20.63	25.78		C
1 1/2"		18.00	22.50	28.13		C
2"		21.00	26.25	32.81		C
2 1/2"		25.50	31.88	39.84		C
3"		30.00	37.50	46.88		C
3 1/2"		37.50	46.88	58.59		C
4"		45.00	56.25	70.31		C
5"		52.00	65.00	81.25		C
6"		60.00	75.00	93.75		C
<b>Fiberglass Conduit 90 Degree Elbows</b>						
3/4"		50.00	62.50	78.13		C
1"		60.00	75.00	93.75		C
1 1/4"		63.00	78.75	98.44		C
1 1/2"		67.00	83.75	104.69		C
2"		75.00	93.75	117.19		C
2 1/2"		82.00	102.50	128.13		C
3"		90.00	112.50	140.63		C
3 1/2"		105.00	131.25	164.06		C
4"		120.00	150.00	187.50		C
5"		135.00	168.75	210.94		C
6"		150.00	187.50	234.38		C
<b>Fiberglass Conduit Threaded Adapters</b>						
3/4"		25.00	31.25	39.06		C
1"		30.00	37.50	46.88		C
1 1/4"		31.00	38.75	48.44		C
1 1/2"		33.00	41.25	51.56		C
2"		36.00	45.00	56.25		C
2 1/2"		40.00	50.00	62.50		C
3"		45.00	56.25	70.31		C
3 1/2"		52.00	65.00	81.25		C
4"		60.00	75.00	93.75		C
5"		67.00	83.75	104.69		C
6"		75.00	93.75	117.19		C
<b>Fiberglass Conduit Expansion Couplings</b>						
3/4"		1.15	1.44	1.80		E
1"		1.20	1.50	1.88		E
1 1/4"		1.23	1.54	1.92		E
1 1/2"		1.27	1.59	1.98		E
2"		1.35	1.69	2.11		E
2 1/2"		1.42	1.78	2.22		E
3"		1.50	1.88	2.34		E
3 1/2"		1.57	1.96	2.45		E
4"		1.65	2.06	2.58		E
5"		1.72	2.15	2.69		E
6"		1.80	2.25	2.81		E




Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>LNT Conduit</b>						
<b>Liquidtight Non-Metallic Flexible Tubing (LNT)</b>						
 1/2"		4.00	5.00	6.00		C
3/4"		5.00	6.25	7.50		C
1"		7.50	9.38	11.25		C
1 1/4"		10.00	12.50	15.00		C
1 1/2"		15.00	18.75	22.50		C
2"		20.00	25.00	30.00		C
<b>LNT Box Connectors-Threaded Type</b>						
 1/2"		0.12	0.15	0.18		E
3/4"		0.14	0.18	0.21		E
1"		0.16	0.20	0.24		E
1 1/4"		0.20	0.25	0.30		E
1 1/2"		0.30	0.38	0.45		E
2"		0.40	0.50	0.60		E
<b>LNT Box Connectors-Threaded Elbows</b>						
 1/2"		0.15	0.19	0.23		E
3/4"		0.17	0.21	0.26		E
1"		0.20	0.25	0.30		E
1 1/4"		0.25	0.31	0.38		E
1 1/2"		0.35	0.44	0.53		E
2"		0.50	0.63	0.75		E
<b>NEMA 1 Screw cover J-Boxes &amp; Pull Boxes with Knockouts</b>						
 6" x 6" x 4"	X	1.00	1.25	1.50		E
8" x 8" x 4"	X	1.10	1.35	1.80		E
10" x 8" x 4"	X	1.10	1.35	1.80		E
12" x 8" x 4"	X	1.15	1.40	1.90		E
10" x 10" x 4"	X	1.15	1.40	1.90		E
12" x 12" x 4"	X	1.25	1.60	2.15		E
16" x 12" x 4"	X	1.35	1.75	2.20		E
16" x 16" x 4"	X	1.35	1.75	2.20		E
12" x 12" x 6"	X	1.35	1.75	2.20		E
12" x 16" x 6"	X	1.50	2.00	3.00		E
16" x 16" x 6"	X	1.50	2.00	3.00		E
24" x 24" x 6"	X	2.75	3.50	4.00		E
24" x 18" x 8"	X	2.75	3.50	4.00		E
24" x 24" x 8"	X	3.00	4.00	5.00		E
30" x 30" x 8"	X	3.50	4.50	5.50		E
<b>NEMA 3R Rain-tight J-Boxes &amp; Pull Boxes</b>						
 6" x 6" x 4"	X	1.00	1.25	1.50		E
8" x 6" x 4"	X	1.10	1.35	1.80		E
10" x 8" x 4"	X	1.10	1.35	1.80		E
12" x 8" x 4"	X	1.15	1.40	1.90		E
10" x 10" x 4"	X	1.15	1.40	1.90		E
12" x 12" x 4"	X	1.25	1.60	2.15		E
8" x 8" x 6"	X	1.35	1.75	2.20		E
10" x 10" x 6"	X	1.35	1.75	2.20		E
12" x 12" x 6"	X	1.35	1.75	2.20		E
18" x 12" x 6"	X	1.50	2.00	3.00		E
24" x 12" x 6"	X	1.50	2.00	3.00		E
18" x 12" x 8"	X	2.75	3.50	4.00		E
24" x 18" x 8"	X	2.75	3.50	4.00		E
<b>NEMA 12 Hinged Cover J-Boxes &amp; Pull Boxes</b>						
 6" x 6" x 4"	X	0.70	1.00	1.15		E
8" x 6" x 4"	X	1.00	1.30	1.50		E
10" x 8" x 4"	X	1.00	1.30	1.50		E
12" x 10" x 4"	X	1.10	1.40	1.70		E
12" x 12" x 4"	X	1.10	1.40	1.70		E
18" x 12" x 4"	X	1.25	1.55	1.85		E
18" x 16" x 4"	X	1.25	1.55	1.85		E
18" x 12" x 6"	X	1.30	1.60	2.00		E
24" x 18" x 6"	X	2.25	3.00	4.10		E
<b>NEMA 4 J-Boxes &amp; Pull Boxes</b>						
 6" x 6" x 4"	X	1.25	1.50	1.75		E
8" x 6" x 4"	X	1.30	1.60	1.85		E
10" x 8" x 6"	X	1.45	1.75	2.00		E
12" x 10" x 6"	X	1.50	1.85	2.10		E
16" x 12" x 6"	X	1.50	1.85	2.10		E
16" x 14" x 6"	X	1.60	2.00	2.50		E

## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>NEMA 13 J-Boxes &amp; Pull Boxes</b>						
12" x 12" x 6"	X					E
20" x 16" x 6"	X	2.00	3.00	4.00		E
30" x 24" x 8"	X	3.50	4.50	5.50		E
36" x 36" x 12"	X	6.00	7.00	8.00		E
<b>CT Cabinets</b>						
24" x 24" x 12"	X					E
30" x 30" x 12"	X	3.00	3.50	4.00		E
36" x 30" x 12"	X	3.50	4.00	4.50		E
36" x 36" x 12"	X	4.00	4.50	5.00		E
36" x 36" x 12"	X	4.50	5.00	6.00		E
48" x 36" x 12"	X	5.00	5.50	7.00		E
<b>Field Cut Knockouts in J-Boxes &amp; Pull Boxes</b>						
1/2"	X					E
3/4"		0.16	0.20	0.24		E
1"		0.18	0.23	0.27		E
1 1/4"		0.24	0.30	0.36		E
1 1/2"		0.30	0.38	0.45		E
2"		0.65	0.80	0.95		E
2 1/2"		0.70	0.85	1.00		E
3"		0.75	0.90	1.10		E
3 1/2"		0.80	1.00	1.20		E
4"		0.85	1.05	1.25		E
5"		0.90	1.10	1.35		E
6"		0.95	1.15	1.40		E
6"		1.00	1.25	1.50		E
Add 25% for stainless steel boxes	X					
<b>Custom Made #10 Gage Steel Pull Boxes WxHxD</b>						
12" x 12" x 12"		1.70	2.10	2.55		E
12" x 18" x 12"		1.85	2.30	2.80		E
12" x 24" x 12"		2.00	2.50	3.00		E
18" x 18" x 12"		2.15	2.70	3.20		E
18" x 24" x 12"		2.30	2.90	3.45		E
18" x 30" x 12"		2.50	3.10	3.75		E
24" x 24" x 12"		2.90	3.60	4.35		E
24" x 30" x 12"		3.05	3.80	4.60		E
24" x 36" x 12"		3.20	4.00	4.80		E
30" x 30" x 12"		3.35	4.20	5.00		E
30" x 36" x 12"		3.50	4.40	5.25		E
30" x 48" x 12"		3.75	4.70	5.60		E
36" x 36" x 12"		4.00	5.00	6.00		E
36" x 48" x 12"		6.00	7.50	9.00		E
36" x 60" x 12"		8.00	10.00	12.00		E
18" x 36" x 18"		3.25	4.06	4.90		E
18" x 48" x 18"		3.70	4.63	5.55		E
18" x 60" x 18"		6.00	7.50	9.00		E
24" x 36" x 18"		5.50	6.25	8.25		E
24" x 48" x 18"		6.25	7.81	9.40		E
24" x 60" x 18"		7.00	8.75	10.50		E



Section 2 - Conduit, Raceways, Fittings & Related Items

2



Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Surface Metal Raceways</b>						
 G3000B Raceway Base		13.00	16.25	19.50		C
G4000B Raceway Base		16.00	20.00	24.00		C
G4000C Raceway Cover		4.00	5.00	6.00		C
G4000D Raceway Divider		2.00	2.50	3.00		C
G6000B Raceway Base		18.00	22.50	27.00		C
G6000B 5 Base		17.00	21.25	25.50		C
G6000C Cover		3.00	3.75	4.50		C
G3000WC Wire Clip		5.00	6.25	7.50		C
G3001A Coupling		15.00	18.75	22.50		C
G3007C 4.5 Dev Bracket		10.00	12.50	15.00		C
G3010B Blank End Fitting		10.00	12.50	15.00		C
G3010C Entrance End Fitting		40.00	50.00	60.00		C
G3000CE Raceway Cover		3.00	3.75	4.50		C
G6001 Coupling		25.00	31.25	37.50		C
G6006 Connector Cover		5.00	6.25	7.50		C
G6007C1 1-Gang Plate		10.00	12.50	15.00		C
G6007C2 2-Gang Plate		10.00	12.50	15.00		C
G6010B Combination End Fitting		20.00	25.00	30.00		C
G6017TX Combination Elbow		50.00	62.50	75.00		C
G6011TX Combination Flat Elbow		50.00	62.50	75.00		C
G6086 Panel Connector		100.00	125.00	150.00		C
G6001TX Convert Coupling		10.00	12.50	15.00		C
G6000WC Wire Clip		5.00	6.25	7.50		C
G6008A C-Hanger Clamp		10.00	12.50	15.00		C
G4012TX 45D Elbow		40.00	50.00	60.00		C
G4000WC Wire Clip		5.00	6.25	7.50		C
G4001 Coupling		20.00	25.00	30.00		C
G4007C1 1-Gang Plate		10.00	12.50	15.00		C
G4001 D Divider Coupling		5.00	6.25	7.50		C
G4007C2 2-Gang Plate		10.00	12.50	15.00		C
G4010B Blank End		10.00	12.50	15.00		C
G4011 Flat Elbow		40.00	50.00	60.00		C
G4017 Internal Elbow		40.00	50.00	60.00		C
G4018 External Elbow		40.00	50.00	60.00		C
G4015 Tee		60.00	75.00	90.00		C
G4014A Wall Box Connector		50.00	62.50	75.00		C
G4046B Combination Cover		5.00	6.25	7.50		C
G4046T Telephone Cover		5.00	6.25	7.50		C
G4010D Entrance End Fitting		20.00	25.00	40.00		C
G4017TC Interior Corner		40.00	50.00	60.00		C
G4086A Panel Connector		100.00	125.00	150.00		C
G3010AE Entrance End Fitting		50.00	62.50	75.00		C
G3018AE Exterior Corner Coupling		5.00	6.25	7.50		C
G3011E 90D Flat Elbow		35.00	43.75	52.50		C
G3006E Cover Clip		5.00	6.25	7.50		C







## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 5781 1/2 Male Connector		5.00	6.25	7.50		C
5781A 3/4 Male Connector		7.00	8.75	10.50		C
5782 1/2 Pipe Connector		5.00	6.25	7.50		C
5784 1/2 Elbow Connector		10.00	12.50	15.00		C
5785 Combination Connector		20.00	25.00	30.00		C
5786 Adjustable Offset Connector		30.00	37.50	45.00		C
57240 SP Switch and Box		50.00	62.50	75.00		C
57242 Utility Box		25.00	31.25	37.50		C
57243G Receptacle & Box		50.00	62.50	75.00		C
T627 Plug-in Center		25.00	31.25	37.50		C
T628 Plug-in Center		25.00	31.25	37.50		C
T436 Plug-in Center		25.00	31.25	37.50		C
T637SF Surge Suppressor		25.00	31.25	37.50		C
2100B Raceway Base		7.00	8.75	10.50		C
2100C Raceway Cover		3.00	3.75	4.50		C
W30 Wire Connector		5.00	6.25	7.50		C
2100 WC Wire Clip		5.00	6.25	7.50		C
2101 1-3/4 Coupling		10.00	12.50	15.00		C
2106 Cover Clip		3.00	3.75	4.50		C
2110A Entrance End Fitting		30.00	37.50	45.00		C
2110B Blank End Fitting		10.00	12.50	15.00		C
2111 90D Flat Elbow		20.00	25.00	30.00		C
2115 Tee		30.00	37.50	45.00		C
2117TC Corner Coupling		10.00	12.50	15.00		C
2118A Corner Coupling		10.00	12.50	15.00		C
2126 Keyless Socket		25.00	31.25	37.50		C
2127DC Single Recept		25.00	31.25	37.50		C
2127G Blk Grounded Receptacle		25.00	31.25	37.50		C
2127GA 3W Grounded Receptacle		25.00	31.25	37.50		C
2127GB 3W Grounded Receptacle		25.00	31.25	37.50		C
2141 1-Gang Switch & Receptacle Box		25.00	31.25	37.50		C
2151 1-Gang External Adapter		25.00	31.25	37.50		C
2174 Take-off Connector		30.00	37.50	45.00		C
2182 End Fitting		10.00	12.50	15.00		C
2000 Raceway W/Cover		8.00	10.00	12.00		C
2001 2-In Coupling		5.00	6.25	7.50		C
2010A Entrance End Fitting		30.00	37.50	45.00		C
2010B Blank End Fitting		10.00	12.50	15.00		C
2011 90D Flat Elbow		15.00	18.75	22.50		C
2015 Tee		25.00	31.25	37.50		C
2017TC Internal Coupling		5.00	6.25	7.50		C
2018C External Cover		15.00	18.75	22.50		C
2051H Flush Plate Adapter		10.00	12.50	15.00		C
2089 Side Reducing Connector		20.00	25.00	30.00		C
2089E End Reducing Connector		20.00	25.00	30.00		C
20G306 Plugmold		50.00	62.50	75.00		C
20G606 Plugmold		50.00	62.50	75.00		C
20G506 Plugmold		50.00	62.50	75.00		C
20GB606 Plugmold		55.00	68.75	82.50		C
20GB612 Plugmold		55.00	68.75	82.50		C
20G618 Plugmold		50.00	62.50	75.00		C
20G609 Plugmold		50.00	62.50	75.00		C
20GB06 Plugmold		12.00	15.00	18.00		E
20GB12 Plugmold		8.00	10.00	12.00		E
20GB18 Plugmold		8.00	10.00	12.00		E
20GB30 Plugmold		8.00	10.00	12.00		E
20GBA30 Plugmold		8.00	10.00	12.00		E
						

## Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Nonmetallic Surface Raceways</b>						
<b>Wiremold Product</b>						
<b>Latching raceway with adhesive backing and ivory plastic finish</b>						
<b>Available in 6' and 8' lengths</b>						
2700 Latching Raceway - Base and Cover		4.00	4.80	5.60		C
2706 Joint Cover		3.00	3.60	4.20		C
2710B Blank End		3.00	3.60	4.20		C
2711 Flat Elbow		10.00	12.00	14.00		C
2717 Internal Elbow		11.00	13.20	15.40		C
2718 External Elbow		11.00	13.20	15.40		C
2715 Tee		15.00	18.00	21.00		C
2786 Drop Ceiling Connector		15.00	18.00	21.00		C
<b>Wiremold Product</b>						
<b>Latching raceway with adhesive backing and ivory plastic finish</b>						
<b>Available in 6' and 8' lengths</b>						
2800 Latching Raceway - Base and Cover		4.50	5.40	6.30		C
2806 Joint Cover		3.00	3.60	4.20		C
2810B Blank End		3.00	3.60	4.20		C
2811 Flat Elbow		10.00	12.00	14.00		C
2817 Internal Elbow		11.00	13.20	15.40		C
2818 External Elbow		11.00	13.20	15.40		C
2815 Tee		15.00	18.00	21.00		C
2886 Drop Ceiling		15.00	18.00	21.00		C
2889 Reducing Connector		10.00	12.00	14.00		E
<b>Wiremold Product</b>						
<b>Latching raceway with adhesive backing and ivory plastic finish</b>						
<b>Available in 6' and 8' lengths</b>						
2900 Latching Raceway - Base and Cover		6.00	7.20	8.40		C
2906 Joint Cover		4.00	4.80	5.60		C
2910B Blank End		4.00	4.80	5.60		C
2911 Flat Elbow		11.00	13.20	15.40		C
2917 Internal Elbow		12.00	14.40	16.80		C
2918 External Elbow		12.00	14.40	16.80		C
2915 Tee		16.00	19.20	22.40		C
2986 Drop Ceiling Connector		16.00	19.20	22.40		C
2989 Reducing Connector		10.00	12.00	14.00		C
<b>Device boxes for 2700/2800/2900</b>						
<b>Boxes are for mounting voice/data devices</b>						
NM2044 1-Gang Deep Device Box		30.00	36.00	42.00		C
NM2044 2-Gang Deep Device Box		35.00	42.00	49.00		C
CM-MMB-291 One Multimedia Box		40.00	48.00	56.00		E
CM-MMB-293 Two Multimedia Box		40.00	48.00	56.00		E
CM-MMB-293 Three Multimedia Box		45.00	54.00	63.00		E
<b>Wiremold product</b>						
<b>Two-Piece raceway, ivory or white plastic finish</b>						
<b>5' lengths only</b>						
<b>Supplied with wide adhesive tape along its entire length</b>						
400BAC 2-Piece Raceway - Base and Cover		7.00	8.40	9.80		C
400WC Wire Clip		2.50	3.00	3.50		C
406 Joint Cover		4.00	4.80	5.60		C
410B Blank End		4.00	4.80	5.60		C
411 Flat Elbow		11.00	13.20	15.40		C
417 Internal Elbow		12.00	14.40	16.80		C
418 External Elbow		12.00	14.40	16.80		C
415 Tee		16.00	19.20	22.40		C
810A2 Entrance End Fitting		16.00	19.20	22.40		C
<b>Wiremold product</b>						
<b>Two-Piece raceway, ivory or white plastic finish</b>						
<b>5' lengths only</b>						
<b>Supplied with wide adhesive tape along its entire length</b>						
<b>Requires screw fasteners in addition to the adhesive tape</b>						
800BAC 2-Piece Raceway - Base and Cover		7.50	9.00	10.50		C
800WC Wire Clip		2.50	3.00	3.50		C
806 Joint Cover		4.00	4.80	5.60		C
810B Blank End		4.00	4.80	5.60		C
811 Flat Elbow		11.00	13.20	15.40		C
817 Internal Elbow		12.00	14.40	16.80		C
818 External Elbow		12.00	14.40	16.80		C
815 Tee		16.00	19.20	22.40		C
810A2 Entrance End		16.00	19.20	22.40		C
889A Reducing Connector		10.00	12.00	14.00		C



## Section 2 - Conduit, Raceways, Fittings & Related Items

2



















Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Wiremold product</b>						
<b>Power and low voltage applications</b>						
<b>2-piece raceway with adhesive backing</b>						
<b>Ivory, white or fog plastic finish</b>						
<b>Available in 8' and 10' lengths</b>						
<b>Built-in wire retainers</b>						
PN05A08/10 2-Piece Raceway - Base and Cover		4.50	5.40	6.30		C
PN05F06 Joint Cover		3.00	3.60	4.20		C
PN05F20 Blank End		3.00	3.60	4.20		C
PN05F11 Flat Elbow		10.00	12.00	14.00		C
PN05F17 Internal Elbow		11.00	13.20	15.40		C
PN05F18 External Elbow		11.00	13.20	15.40		C
PN05F15 Tee		15.00	18.00	21.00		C
PN05F86 Drop Ceiling Connector		15.00	18.00	21.00		C
<b>Wiremold product</b>						
<b>Power and low voltage applications</b>						
<b>2-piece raceway with adhesive backing</b>						
<b>Ivory, white or fog plastic finish</b>						
<b>Available in 8' and 10' lengths</b>						
<b>Built-in wire retainers</b>						
PN10A08/10 2-Piece Raceway - Base and Cover		8.00	9.60	11.20		C
PN10F06 Joint Cover		4.00	4.80	5.60		C
PN10F20 Blank End		4.00	4.80	5.60		C
PN10F11 Flat Elbow		12.00	14.40	16.80		C
PN10F17 Internal Elbow		13.00	15.60	18.20		C
PN10F18 External Elbow		13.00	15.60	18.20		C
PN10F15 Tee		16.50	19.80	23.10		C
PN10F86 Drop Ceiling Connector		16.00	19.20	22.40		C
PN10F21 Entrance End Fitting		16.00	19.20	22.40		C
<b>Device boxes for PN05A/PN10A series raceways</b>						
<b>Boxes are for mounting power and voice/data devices</b>						
PSB1 1-Gang Device Box		30.00	36.00	42.00		C
PSB1 2-Gang Device Box		35.00	42.00	49.00		C
PSB1 3-Gang Device Box		40.00	48.00	56.00		C
PBB2S2 (2) Series II Data Box		30.00	36.00	42.00		C
PBB4TJ (4) Tracjack Data Box		35.00	42.00	49.00		C
PDB1CM (1) CM Data Box		30.00	36.00	42.00		C
PDB1S2 (1) Series II Data Box		30.00	36.00	42.00		C
PDB2TJ (2) Tracjack Data Box		35.00	42.00	49.00		C
PDB2CM (2) CM Data Box		35.00	42.00	49.00		C
PDB2S2 (2) Series II Data Box		35.00	42.00	49.00		C
PDB4TJ (J) Tracjack Data Box		40.00	48.00	56.00		C
<b>Wiremold Product</b>						
<b>Power and low voltage applications</b>						
<b>2-piece raceway with adhesive backing</b>						
<b>Ivory, white or fog plastic finish</b>						
<b>Requires screw fasteners to mount raceway</b>						
<b>8' lengths only</b>						
<b>Integral divider, two channel for power and low voltage applications</b>						
<b>Built-in wire retainers</b>						
PN20A08 2-Piece Raceway - Base and Cover		9.00	10.80	12.60		C
PN20F06 Joint Cover		4.00	4.80	5.60		C
PN20F20 Blank End		4.00	4.80	5.60		C
PN20F11 Flat Elbow		14.00	16.80	19.60		C
PN20F17 Internal Elbow		14.00	16.80	19.60		C
PN20F18 External Elbow		14.00	16.80	19.60		C
PN20F15 Tee		17.50	21.00	24.50		C
PN20F86 Drop Ceiling Connector		17.00	20.40	23.80		C
PN20F74 Transition Fitting		17.00	20.40	23.80		C
PN20F21 Entrance End Fitting		17.00	20.40	23.80		C
<b>Device boxes for PN20A series raceways</b>						
<b>Boxes are for mounting power and voice/data devices</b>						
PIB20S2 (2) Series II Data Box		30.00	36.00	42.00		C
PIB20CM (2) Cm Data Box		30.00	36.00	42.00		C
PIB20TJ (4) Tracjack Data Box		35.00	42.00	49.00		C
PIB20D Duplex Device Box		30.00	36.00	42.00		C
PIB20R Rectangular Device Box		40.00	48.00	56.00		C
PMBD20TJ Duplex and (4) Tracjack		40.00	48.00	56.00		C
PMBD20S2 Duplex and (2) Series II Data		40.00	48.00	56.00		C
PMBD20CM Duplex and (2) CM Data		40.00	48.00	56.00		C
PMBR20S2 Rect. Device and (2) Series Data		40.00	48.00	56.00		C
PMBR20CM Rect. Device and (4) Tracjack		40.00	48.00	56.00		C

## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Wiremold product</b>						
<b>Cablesmart series for power and low voltage applications</b>						
<b>2-piece raceway with multiple channel raceways</b>						
<b>Ivory or white plastic finish</b>						
<b>Requires screw fasteners to mount raceway</b>						
<b>8' lengths only</b>						
<b>Tamper-resistant where additional security is a priority</b>						
40N2 2-Piece Raceway - Base and Cover		13.00	15.60	18.20		C
40N2F06 Joint Cover		4.00	4.80	5.60		C
40N2F20 Blank End		6.00	7.20	8.40		C
40N2F11 Flat Elbow		24.00	28.80	33.60		C
40N2F17 Internal Elbow		28.00	33.60	39.20		C
40N2F19 External Elbow		28.00	33.60	39.20		C
40N2F15 Tee		24.00	28.80	33.60		C
40N2F74 Transition Fitting		24.00	28.80	33.60		C
40N2F21 Entrance End Fitting		22.00	26.40	30.80		C
40N2FWC Wire Clip		4.00	4.80	5.60		C
40N2F31 Twin Cover Device Bracket		16.00	19.20	22.40		C
40N2F55 High Capacity Device Box		20.00	24.00	28.00		C
<b>Wiremold product</b>						
<b>Cablesmart series for power and low voltage applications</b>						
<b>2-piece raceway with multiple channel raceways</b>						
<b>Ivory or white plastic finish</b>						
<b>Requires screw fasteners to mount raceway</b>						
<b>8' lengths only</b>						
<b>Tamper-resistant where additional security is a priority</b>						
60N2 2-Piece Raceway - Base and Cover		15.00	18.00	21.00		C
60N2F06 Joint Cover		6.00	7.20	8.40		C
60N2F20 Blank End		8.00	9.60	11.20		C
60N2F11 Flat Elbow		26.00	31.20	36.40		C
60N2F17 Internal Elbow		30.00	36.00	42.00		C
60N2F18 External Elbow		30.00	36.00	42.00		C
60N2F15 Tee		26.00	31.20	36.40		C
60N2F74 Transition Fitting		26.00	31.20	36.40		C
60N2F21 Entrance End Fitting		24.00	28.80	33.60		C
60N2FWC Wire Clip		5.00	6.00	7.00		C
60N2F31 Twin Cover Device Bracket		18.00	21.60	25.20		C
60N2F55 High Capacity Device Box		20.00	24.00	28.00		C
<b>Wiremold product</b>						
<b>Large cable capacity for power and low voltage applications</b>						
<b>2-piece raceway with multiple channel raceways</b>						
<b>Ivory or white plastic finish</b>						
<b>Requires screw fasteners to mount raceway</b>						
<b>8' lengths only</b>						
5400Tb 2-Piece Raceway - Base and Cover		15.00	18.00	21.00		C
5406TB Joint Cover		6.00	7.20	8.40		C
5410 Blank End		8.00	9.60	11.20		C
5411F0 Flat Elbow		26.00	31.20	36.40		C
5417 Internal Elbow		30.00	36.00	42.00		C
5418 External Elbow		30.00	36.00	42.00		C
5415 Tee		26.00	31.20	36.40		C
5474 Transition Fitting		26.00	31.20	36.40		C
5410DF0 Entrance End Fitting		24.00	28.80	33.60		C
5400TWC Wire Clip		5.00	6.00	7.00		C
5450 Device Bracket		18.00	21.60	25.20		C
5450 Orap Wireless Bracket		20.00	24.00	28.00		C
5450T Twin Snap Cover Bracket		20.00	24.00	28.00		C
5450A3 Three Device Bracket		22.00	26.40	30.80		C
<b>Wiremold product</b>						
<b>Large cable capacity for power and low voltage applications</b>						
<b>2-piece raceway with multiple channel raceways</b>						
<b>Ivory or white plastic finish</b>						
<b>Requires screw fasteners to mount raceway</b>						
<b>8' lengths only</b>						
5500 2-Piece Raceway - Base and Cover		18.00	21.60	25.20		C
5506 Joint Cover		7.00	8.40	9.80		C
5510 Blank End		9.00	10.80	12.60		C
511F0 Flat Elbow		28.00	33.60	39.20		C
5517 Internal Elbow		32.00	38.40	44.80		C
5518 External Elbow		32.00	38.40	44.80		C
5515 Tee		28.00	33.60	39.20		C
5574 Transition Fitting		28.00	33.60	39.20		C
5510D Entrance End Fitting		28.00	33.60	39.20		C
5500WC Wire Clip		6.00	7.20	8.40		C
5550 Device Bracket		18.00	21.60	25.20		C
5550 Orap Offset Mounting Bracket		20.00	24.00	28.00		C
5514A Backfeed Connector		20.00	24.00	28.00		C













## Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Metal Wireway</b>						
<b>Hinged Cover Lay-In Wireways</b>						
 2 1/2" x 2 1/2" Wireways		10.00	12.50	15.00		C
 4" x 4" Wireways		12.00	15.00	18.00		C
6" x 6" Wireways		15.00	18.75	22.50		C
8" x 8" Wireways		18.00	22.50	27.00		C
12" x 12" Wireways		22.00	27.50	33.00		C
<b>Hinged Cover Lay-In Wireways -Fittings</b>						
2 1/2" x 2 1/2" Elbows		30.00	37.50	45.00		C
4" x 4" Elbows		35.00	43.70	52.00		C
6" x 6" Elbows		40.00	50.00	60.00		C
8" x 8" Elbows		50.00	62.00	75.00		C
12" x 12" Elbows		60.00	75.00	90.00		C
2 1/2" x 2 1/2" Couplings		20.00	25.00	30.00		C
4" x 4" Couplings		25.00	31.20	37.00		C
6" x 6" Couplings		30.00	37.50	45.00		C
8" x 8" Couplings		40.00	50.00	60.00		C
12" x 12" Couplings		50.00	62.00	75.00		C
2 1/2" x 2 1/2" Tees		40.00	50.00	60.00		C
4" x 4" Tees		45.00	56.00	67.00		C
6" x 6" Tees		50.00	62.00	75.00		C
8" x 8" Tees		60.00	75.00	90.00		C
12" x 12" Tees		70.00	87.00	100.00		C
2 1/2" x 2 1/2" Crosses		50.00	62.00	75.00		C
4" x 4" Crosses		55.00	68.00	82.00		C
6" x 6" Crosses		60.00	75.00	90.00		C
8" x 8" Crosses		70.00	87.00	100.00		C
12" x 12" Crosses		80.00	100.00	120.00		C
2 1/2" x 2 1/2" End Caps		12.00	15.00	18.00		C
4" x 4" End Caps		15.00	18.70	22.50		C
6" x 6" End Caps		20.00	25.00	30.00		C
8" x 8" End Caps		25.00	31.20	37.00		C
12" x 12" End Caps		30.00	37.50	45.00		C
<b>Hinged Cover Lay-In Wireways - Accessories</b>						
2 1/2" x 2 1/2" Adapters		20.00	25.00	30.00		C
4" x 4" Adapters		25.00	31.20	37.00		C
6" x 6" Adapters		30.00	37.50	45.00		C
8" x 8" Adapters		40.00	50.00	60.00		C
12" x 12" Adapters		50.00	62.00	75.00		C
2 1/2" x 2 1/2" Panel Connectors		30.00	37.50	45.00		C
4" x 4" Panel Connectors		35.00	43.70	52.50		C
6" x 6" Panel Connectors		40.00	50.00	60.00		C
8" x 8" Panel Connectors		50.00	62.00	75.00		C
12" x 12" Panel Connectors		60.00	75.00	90.00		C
2 1/2" x 2 1/2" Slip Fittings		40.00	50.00	60.00		C
4" x 4" Slip Fittings		45.00	56.00	67.00		C
6" x 6" Slip Fittings		50.00	62.00	75.00		C
8" x 8" Slip Fittings		60.00	75.00	90.00		C
12" x 12" Slip Fittings		70.00	87.00	100.00		C
<b>Hinged Cover Lay-In Wireways - Brackets</b>						
2 1/2" Wall Brackets		8.00	10.00	12.00		C
4" Wall Brackets		10.00	12.50	15.00		C
6" Wall Brackets		12.00	15.00	18.00		C
8" Wall Brackets		14.00	17.50	21.00		C
12" Wall Brackets		16.00	20.00	24.00		C
2 1/2" Ceiling Brackets		12.00	15.00	18.00		C
4" Ceiling Brackets		14.00	17.50	21.00		C
6" Ceiling Brackets		16.00	20.00	24.00		C
8" Ceiling Brackets		18.00	22.50	27.00		C
12" Ceiling Brackets		20.00	25.00	30.00		C
<b>Hinged Cover Lay-In Wireways - Miscellaneous</b>						
4" x 4" x 2 1/2" Reducers		20.00	25.00	30.00		C
6" x 6" x 4" Reducers		25.00	31.20	37.50		C
8" x 8" x 6" Reducers		30.00	37.50	45.00		C
12" x 12" x 8" Reducers		35.00	43.70	52.50		C
7" x 7" x 7" Pull Boxes		150.00	187.00	225.00		C
7" x 12" x 12" Pull Boxes		175.00	215.00	260.00		C
<b>Screwed Cover Lay-In Wireways</b>						
2 1/2" x 2 1/2" Wireways		10.00	12.50	15.00		C
4" x 4" Wireways		12.00	15.00	18.00		C
6" x 6" Wireways		14.00	17.50	21.00		C
8" x 8" Wireways		17.00	21.20	25.50		C
12" x 12" Wireways		20.00	25.00	30.00		C











## Section 2 - Conduit, Raceways, Fittings & Related Items
















































Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Screwed Cover Lay-In Wireways - Fittings</b>						
		15.00	18.70	22.50		C
4" x 4" Couplings		17.00	21.20	25.50		C
6" x 6" Couplings		20.00	25.00	30.00		C
8" x 8" Couplings		25.00	31.20	37.50		C
12" x 12" Couplings		30.00	37.50	45.00		C
2 1/2" x 2 1/2" Elbows		35.00	43.70	52.50		C
4" x 4" Elbows		40.00	50.00	60.00		C
6" x 6" Elbows		45.00	56.00	67.00		C
8" x 8" Elbows		50.00	68.70	82.00		C
12" x 12" Elbows		55.00	81.00	97.00		C
2 1/2" x 2 1/2" Tees		45.00	56.00	67.00		C
4" x 4" Tees		50.00	62.00	75.00		C
6" x 6" Tees		55.00	68.70	82.00		C
8" x 8" Tees		65.00	81.00	97.00		C
12" x 12" Tees		75.00	93.00	110.00		C
2 1/2" x 2 1/2" Crosses		55.00	68.70	82.00		C
4" x 4" Crosses		60.00	75.00	90.00		C
6" x 6" Crosses		65.00	81.00	97.00		C
8" x 8" Crosses		75.00	93.00	110.00		C
12" x 12" Crosses		85.00	105.00	125.00		C
2 1/2" x 2 1/2" End Caps		12.00	15.00	18.00		C
4" x 4" End Caps		15.00	18.70	22.50		C
6" x 6" End Caps		20.00	25.00	30.00		C
8" x 8" End Caps		25.00	31.20	37.50		C
12" x 12" End Caps		30.00	37.50	45.00		C
<b>Screwed Cover Lay-In Wireways - Adapters</b>						
2 1/2" x 2 1/2" Adapters		30.00	37.50	45.00		C
4" x 4" Adapters		35.00	43.70	52.50		C
6" x 6" Adapters		40.00	50.00	60.00		C
8" x 8" Adapters		50.00	62.50	75.00		C
12" x 12" Adapters		60.00	75.00	90.00		C
2 1/2" x 2 1/2" Panel Connectors		35.00	43.70	52.50		C
4" x 4" Panel Connectors		40.00	50.00	60.00		C
6" x 6" Panel Connectors		45.00	56.20	67.50		C
8" x 8" Panel Connectors		55.00	68.70	82.50		C
12" x 12" Panel Connectors		65.00	81.00	97.00		C
2 1/2" x 2 1/2" Slip Fittings		45.00	56.20	67.50		C
4" x 4" Slip Fittings		50.00	62.50	75.00		C
6" x 6" Slip Fittings		55.00	68.70	82.50		C
8" x 8" Slip Fittings		65.00	81.00	97.00		C
12" x 12" Slip Fittings		75.00	93.00	110.00		C
<b>Screwed Cover Lay-In Wireways - Brackets</b>						
2 1/2" Wall Brackets		8.00	10.00	12.00		C
4" Wall Brackets		8.00	10.00	12.00		C
6" Wall Brackets		10.00	12.50	15.00		C
8" Wall Brackets		14.00	17.50	21.00		C
12" Wall Brackets		16.00	20.00	24.00		C
2 1/2" Ceiling Brackets		12.00	15.00	18.00		C
4" Ceiling Brackets		12.00	15.00	18.00		C
6" Ceiling Brackets		15.00	18.75	22.50		C
8" Ceiling Brackets		18.00	22.50	27.00		C
12" Ceiling Brackets		20.00	25.00	30.00		C
<b>Screwed Cover Lay-In Wireways - Miscellaneous</b>						
4" x 4" x 2 1/2" Reducers		25.00	31.20	37.50		C
6" x 6" x 4" Reducers		30.00	37.50	45.00		C
8" x 8" x 6" Reducers		35.00	43.70	52.50		C
12" x 12" x 6" Reducers		40.00	50.00	60.00		C
7" x 7" x 7" Pull Boxes		150.00	187.00	225.00		C
7" x 12" x 12" Pull Boxes		175.00	215.00	260.00		C
7" x 16" x 16" Pull Boxes		200.00	250.00	300.00		C
<b>Flanged End Wireways with Knockouts</b>						
2 1/2" x 2 1/2" Wireways		12.00	15.00	18.00		C
4" x 4" Wireways		14.00	17.50	21.00		C
6" x 6" Wireways		16.00	20.00	24.00		C
8" x 8" Wireways		20.00	25.00	30.00		C
12" x 12" Wireways		24.00	30.00	36.00		C
2 1/2" x 2 1/2" Gaskets		10.00	12.50	15.00		C
4" x 4" Gaskets		12.00	15.00	18.00		C
6" x 6" Gaskets		14.00	17.50	21.00		C
8" x 8" Gaskets		17.00	21.20	25.50		C
12" x 12" Gaskets		20.00	25.00	30.00		C

## Section 2 - Conduit, Raceways, Fittings & Related Items

2










































Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Flanged End Wireways with Knockouts - Fittings</b>						
 2-1/2" x 2-1/2" Flanged Elbows		40.00	50.00	60.00		C
4" x 4" Flanged Elbows		45.00	56.20	67.50		C
6" x 6" Flanged Elbows		50.00	62.50	75.00		C
8" x 8" Flanged Elbows		60.00	75.00	90.00		C
12" x 12" Flanged Elbows		70.00	87.00	100.00		C
2 1/2" x 2 1/2" Flanged Tees		50.00	62.50	75.00		C
4" x 4" Flanged Tees		55.00	68.70	82.50		C
6" x 6" Flanged Tees		60.00	75.00	90.00		C
8" x 8" Flanged Tees		70.00	87.00	100.00		C
12" x 12" Flanged Tees		80.00	100.00	120.00		C
2 1/2" x 2 1/2" Flanged Crosses		60.00	75.00	90.00		C
4" x 4" Flanged Crosses		70.00	87.00	100.00		C
6" x 6" Flanged Crosses		80.00	100.00	120.00		C
8" x 8" Flanged Crosses		90.00	110.00	135.00		C
12" x 12" Flanged Crosses		100.00	125.00	150.00		C
<b>Flanged End Wireways with Knockouts - Connectors</b>						
 2 1/2" x 2 1/2" Panel Connectors		40.00	50.00	60.00		C
4" x 4" Panel Connectors		45.00	56.20	67.50		C
6" x 6" Panel Connectors		50.00	62.00	75.00		C
8" x 8" Panel Connectors		60.00	75.00	90.00		C
12" x 12" Panel Connectors		70.00	87.00	105.00		C
 2 1/2" x 2 1/2" Slip Fittings		50.00	62.00	75.00		C
4" x 4" Slip Fittings		55.00	68.00	82.00		C
6" x 6" Slip Fittings		60.00	75.00	90.00		C
8" x 8" Slip Fittings		70.00	87.00	105.00		C
12" X 12" Slip Fittings		80.00	100.00	120.00		C
<b>Flanged End Wireways with Knockouts - Brackets</b>						
 2 1/2" Wall Brackets		20.00	25.00	30.00		C
4" Wall Brackets		25.00	31.20	37.50		C
6" Wall Brackets		30.00	37.50	45.00		C
8" Wall Brackets		35.00	43.70	52.50		C
12" Wall Brackets		40.00	50.00	60.00		C
 2 1/2" Ceiling Brackets		25.00	31.20	37.50		C
4" Ceiling Brackets		30.00	37.50	45.00		C
6" Ceiling Brackets		35.00	43.70	52.50		C
8" Ceiling Brackets		40.00	50.00	60.00		C
12" Ceiling Brackets		45.00	56.20	67.50		C
<b>Flanged End Wireways with Knockouts - Miscellaneous</b>						
 4" x 4" x 2 1/2" Reducers		25.00	31.20	37.50		C
6" x 6" x 4" Reducers		30.00	37.50	45.00		C
8" x 8" x 6" Reducers		35.00	43.70	52.50		C
12" x 12" x 8" reducers		40.00	50.00	60.00		C
7" x 7" x 7" Pull Boxes		100.00	125.00	150.00		C
7" x 12" x 12" Pull Boxes		120.00	150.00	180.00		C
7" x 16" x 16" Pull boxes		150.00	185.00	225.00		C
 2 1/2" Junction Boxes		60.00	75.00	90.00		C
4" Junction Boxes		65.00	81.00	97.00		C
6" Junction Boxes		70.00	87.00	105.00		C
8" Junction Boxes		80.00	100.00	120.00		C
12" Junction Boxes		90.00	112.00	135.00		C
<b>Flanged End Wireways with Knockouts - End Caps</b>						
 2 1/2" End Caps		10.00	12.50	15.00		C
4" End Caps		12.00	15.00	18.00		C
6" End Caps		14.00	17.50	21.00		C
8" End Caps		17.00	21.20	25.50		C
12" End Caps		20.00	25.00	30.00		C

Section 2 - Conduit, Raceways, Fittings & Related Items


























Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>J.I.C. Type Wireways without Knockouts</b>						
 2 1/2" x 2 1/2" JIC Wireways		14.00	17.50	21.00		C
 4" x 4" JIC Wireways		16.00	20.00	24.00		C
 6" x 6" JIC Wireways		19.00	23.70	28.50		C
 8" x 8" JIC Wireways		22.00	27.50	33.00		C
 12" x 12" JIC Wireways		26.00	32.50	39.00		C
 2 1/2" x 2 1/2" Gaskets		10.00	12.50	15.00		C
 4" x 4" Gaskets		12.00	15.00	18.00		C
 6" x 6" Gaskets		14.00	17.50	21.00		C
 8" x 8" Gaskets		17.00	21.20	25.50		C
 12" x 12" Gaskets		20.00	25.00	30.00		C
 2 1/2" x 2 1/2" JIC Elbows		45.00	56.20	67.50		C
 4" x 4" JIC Elbows		50.00	62.00	75.00		C
 6" x 6" JIC Elbows		60.00	75.00	90.00		C
 8" x 8" JIC Elbows		70.00	87.00	105.00		C
 12" x 12" JIC Elbows		80.00	100.00	120.00		C
 2 1/2" x 2 1/2" JIC Tees		55.00	68.00	82.00		C
 4" x 4" JIC Tees		60.00	75.00	90.00		C
 6" x 6" JIC Tees		70.00	87.00	105.00		C
 8" x 8" JIC Tees		80.00	100.00	120.00		C
 12" x 12" JIC Tees		90.00	112.00	135.00		C
 2 1/2" x 2 1/2" JIC Crosses		65.00	81.00	97.00		C
 4" x 4" JIC Crosses		70.00	87.00	100.00		C
 6" x 6" JIC Crosses		80.00	100.00	120.00		C
8" x 8" JIC Crosses		90.00	112.00	135.00		C
12" x 12" JIC Crosses		100.00	125.00	150.00		C
<b>J.I.C. Type Wireways without Knockouts - Connectors &amp; Brackets</b>						
 2 1/2" x 2 1/2" JIC Panel Connectors		45.00	56.00	67.00		C
 4" x 4" JIC Panel Connectors		50.00	62.00	75.00		C
 6" x 6" JIC Panel Connectors		60.00	75.00	90.00		C
 8" x 8" Panel Connectors		70.00	87.00	100.00		C
 12" x 12" JIC Panel Connectors		80.00	100.00	120.00		C
 2 1/2" x 2 1/2" JIC Slip Fittings		55.00	68.00	82.00		C
 4" x 4" JIC Slip Fittings		60.00	75.00	90.00		C
 6" x 6" Slip Fittings		70.00	87.00	100.00		C
 8" x 8" Slip Fittings		80.00	100.00	120.00		C
 12" x 12" Slip Fittings		90.00	112.00	135.00		C
 2 1/2" Wall Brackets		20.00	25.00	30.00		C
 4" X 4" Wall Brackets		25.00	31.00	37.00		C
 6" X 6" Wall Brackets		30.00	37.00	45.00		C
 8" X 8" Wall Brackets		35.00	43.00	52.00		C
 12" X 12" Wall Brackets		40.00	50.00	60.00		C
2-1/2" X 2-1/2" Ceiling Brackets		25.00	31.00	37.00		C
4" X 4" Ceiling Brackets		30.00	37.00	45.00		C
6" X 6" Ceiling Brackets		35.00	43.00	52.00		C
8" X 8" Ceiling Brackets		40.00	50.00	60.00		C
12" X 12" Ceiling Brackets		45.00	56.00	67.00		C
<b>Channel Type Raceways &amp; Fixture Supports</b>						
 1 5/8" x 1 5/8" Channel Raceway		12.00	15.00	18.00		C
 1 5/8" x 2 1/2" Channel Raceway		14.00	17.50	21.00		C
 1 5/8" x 3 1/4" Channel Raceway		16.00	20.00	24.00		C
 1 5/8" Channel Covers		6.00	7.50	9.00		C
 1 5/8" Splice Plates		10.00	12.50	15.00		C
 1 5/8" Channel Hanger		20.00	25.00	30.00		C
 1 5/8" J-Box 1 Channel		25.00	31.00	37.00		C
 1 5/8" J-Box 2 Channels		30.00	37.00	45.00		C
 1 5/8" J-Box 3 Channels		40.00	50.00	60.00		C
1 5/8" J-Box 4 Channels		50.00	62.00	75.00		C
1 5/8" Conduit Connector		15.00	18.70	22.50		C
1 5/8" Conduit Swivel		15.00	18.70	22.50		C
1 5/8" 15 Amp 2-wire receptacles		25.00	31.00	37.00		C
1 5/8" 15 Amp 3-wire receptacles		30.00	37.00	45.00		C
1 5/8" 20 Amp 2-wire receptacles		35.00	43.00	52.00		C
1 5/8" 20 Amp 3-wire receptacles		40.00	50.00	60.00		C

## Section 2 - Conduit, Raceways, Fittings & Related Items

2


Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Underfloor Duct</b>						
<b>Steel Underfloor Duct &amp; Fittings</b>						
 3" Standard Blank Duct		4.00	5.00	6.00		C
 6" Standard blank Duct		5.00	6.20	7.50		C
 3" Standard Insert Duct		4.50	5.60	6.70		C
 6" Standard Insert Duct		5.50	6.80	8.20		C
 3" Standard Duct Couplings		10.00	12.50	15.00		C
 6" Standard Duct Couplings		10.00	12.50	15.00		C
 3" Standard Duct Elbows & Offsets		30.00	37.50	45.00		C
 6" Standard Duct Elbows & Offsets		35.00	43.70	52.00		C
 3" Standard Duct Support-Single		10.00	12.50	15.00		C
 6" Standard Duct Support-Single		11.00	13.50	16.00		C
 3" Standard Duct Support-Double		11.00	13.50	16.00		C
 6" Standard Duct Support-Double		12.00	14.50	17.00		C
 3" Standard Duct Support-Triple		12.00	14.50	17.00		C
 6" Standard Duct Support-Triple		13.00	15.50	18.00		C
 3" Duct Tee		50.00	62.00	75.00		C
 6" Duct Tee		55.00	68.00	82.00		C
 3" Duct 1-Level Cross		55.00	68.00	82.00		C
 6" Duct 1-Level Cross		60.00	75.00	90.00		C
 3" Duct 2-Level Cross		60.00	75.00	90.00		C
6" Duct 2-Level Cross		65.00	81.00	97.00		C
3" Duct Adapters-All Types		10.00	12.50	15.00		C
6" Duct Adapters-All Types		12.00	15.00	18.00		C
3" Duct Expansion Joint		50.00	62.00	75.00		C
6" Duct Expansion Joint		55.00	68.00	82.00		C
3" Panel Connector		50.00	62.50	75.00		C
6" Panel Connector		50.00	62.50	75.00		C
3" Duct End Cap		5.00	6.20	7.50		C
6" Duct End Cap		5.50	6.80	8.20		C
10" x 10" Junction Box		100.00	125.00	150.00		C
12" x 12" Junction Box		140.00	165.00	190.00		C
14" x 14" Junction Box		180.00	210.00	235.00		C
16" x 16" Junction Box		220.00	250.00	280.00		C
18" x 18" Junction Box		240.00	275.00	300.00		C
24" x 24" Junction box		280.00	310.00	335.00		C
30" x 30" Junction box		300.00	400.00	500.00		C
Duct Marker Screw Assembly		15.00	18.70	22.50		C
Duct Joint Spot Welding		30.00	37.50	45.00		C
<b>Cellular Underfloor Duct-3 Cell</b>						
 10"		7.00	8.70	10.50		C
 13"		8.00	10.00	12.00		C
 16"		9.00	11.20	13.50		C
 24"		10.00	12.50	15.00		C
<b>3-Cell Junction Boxes</b>						
 10"		40.00	50.00	60.00		C
 13"		50.00	62.00	75.00		C
 16"		60.00	75.00	90.00		C
 24"		70.00	87.00	105.00		C
<b>3-Cell Elbows</b>						
 10"		20.00	25.00	30.00		C
 13"		30.00	37.00	45.00		C
 16"		40.00	50.00	60.00		C
 24"		50.00	62.00	75.00		C
<b>3-Cell Duct Support &amp; Couplings</b>						
 10"		8.00	10.00	12.00		C
 13"		9.00	11.20	13.50		C
 16"		10.00	12.50	15.00		C
 24"		12.00	15.00	18.00		C
<b>Header Sections</b>						
 24" x 60" Header Sections		40.00	50.00	60.00		C
 30" x 60" Header Sections		50.00	62.00	75.00		C
 36" x 60" Header Sections		60.00	75.00	90.00		C
<b>Field Installed Preset Inserts</b>						
 Field Install Preset Inserts		20.00	25.00	30.00		C
<b>Duct End Closures</b>						
 Duct End Closures		5.00	6.20	7.50		C
 J-Box Closure Caps		6.00	7.50	9.00		C

## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Duct Marker Items</b>						
 Duct Marker Screw Assembly		15.00	18.70	22.50		C
 Preset Marker Screw Plates		10.00	12.50	15.00		C
<b>Header Items</b>						
 Blank Header Duct		5.50	6.80	8.20		C
Insert Header Duct		6.00	7.50	9.00		C
Header Duct Couplings		10.00	12.50	15.00		C
Header Duct Elbows		30.00	37.50	45.00		C
Header Duct Supports		10.00	12.50	15.00		C
Header Duct Panel Risers		30.00	37.50	45.00		C
Header Duct Handhole Sections		20.00	25.00	30.00		C
Header Duct Access Tees		40.00	50.00	60.00		C
Header Duct Access Crosses		50.00	62.00	75.00		C
<b>3 1/4" x 1 1/4" Flushduct</b>						
 Single Duct		5.00	6.20	7.50		C
 Double Duct		6.00	7.50	9.00		C
 Triple Duct		7.00	9.00	11.00		C
Single Duct Elbows		30.00	37.00	45.00		C
Double Duct Elbows		32.00	40.00	48.00		C
Triple Duct Elbows		35.00	43.00	52.00		C
Single Duct Offsets		20.00	25.00	30.00		C
Double Duct Offsets		22.00	27.50	33.00		C
Triple Duct Offsets		25.00	31.20	37.50		C
Single Duct Supports		8.00	10.00	12.00		C
Double Duct Supports		9.00	11.00	13.00		C
Triple Duct Supports		10.00	12.00	15.00		C
Flushduct Adapters-All Types		10.00	12.00	15.00		C
<b>Underfloor Duct Accessories</b>						
 Afterset Insert (before concrete) Blank Duct		50.00	65.00	80.00		C
 Afterset Insert (after concrete) Blank Duct		100.00	125.00	150.00		C
 Afterset Inserts (before concrete)- Insert Type Duct		25.00	30.00	35.00		C
 Afterset Inserts (after concrete)- Insert Type Duct		50.00	65.00	80.00		C
 Afterset Insert Extensions		20.00	25.00	30.00		C
 Insert Bushings & Standpipes		15.00	18.70	22.50		C
 Snap Rings & Grommets		5.00	6.20	7.50		C
 Spot Weld Duct Joints		30.00	37.50	45.00		C
<b>Underfloor Duct Outlet Receptacles</b>						
 15 Amp Receptacle		40.00	50.00	60.00		C
 20 Amp Receptacle		45.00	56.00	67.00		C
 30 Amp Receptacle		50.00	62.00	75.00		C
 50 Amp Receptacle		65.00	81.00	97.00		C
 60 Amp Receptacle		80.00	100.00	120.00		C
 Communication Outlet Boxes		25.00	31.20	37.50		C
 Cable Outlet & Post Outlets		25.00	31.20	37.50		C
 Phone Outlets with Terminal Blocks		30.00	37.50	45.00		C
 15 Amp Receptacle W/ Communication Outlet		60.00	70.00	80.00		C
 20 Amp Receptacle W/ Communication Outlet		65.00	76.00	87.00		C
 Outlet Abandoning Assembly		20.00	25.00	30.00		C

Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Trench Duct</b>						
<b>Solid Bottom Trench Duct</b>						
 9"		40.00	50.00	60.00		C
12"		45.00	56.20	67.50		C
18"		54.00	67.50	81.00		C
24"		64.00	80.00	96.00		C
27"		68.00	85.00	102.00		C
30"		72.00	90.00	108.00		C
36"		80.00	100.00	120.00		C
<b>Cellular Trench Duct</b>						
9"		50.00	62.00	75.00		C
12"		55.00	68.70	82.50		C
18"		65.00	81.20	97.50		C
24"		75.00	93.70	112.00		C
27"		80.00	100.00	120.00		C
30"		90.00	112.00	135.00		C
36"		100.00	125.00	150.00		C
<b>Trench Duct Elbows</b>						
9"		4.00	5.00	6.00		E
12"		4.50	5.60	6.70		E
18"		5.00	6.20	7.50		E
24"		5.50	6.80	8.20		E
27"		6.00	7.50	9.00		E
30"		7.00	8.70	10.50		E
36"		8.00	10.00	12.00		E
<b>Trench Duct Tees</b>						
9"		5.00	6.20	7.50		E
12"		5.50	6.80	8.20		E
18"		6.00	7.50	9.00		E
24"		7.00	8.70	10.50		E
27"		8.00	10.00	12.00		E
30"		9.00	11.20	13.50		E
36"		10.00	12.50	15.00		E
<b>Trench Duct Crosses</b>						
9"		6.00	7.50	9.00		E
12"		6.50	8.10	9.70		E
18"		7.00	8.70	10.50		E
24"		8.00	10.00	12.00		E
27"		9.00	11.20	13.50		E
30"		10.00	12.50	15.00		E
36"		12.00	15.00	18.00		E
<b>Trench Duct Wall Elbows &amp; Panel Risers</b>						
9"		3.00	3.70	4.50		E
12"		3.50	4.30	5.20		E
18"		4.00	5.00	6.00		E
24"		4.50	5.60	6.70		E
27"		5.00	6.20	7.50		E
30"		6.00	7.50	9.00		E
36"		7.00	8.70	10.50		E
<b>Trench Duct Cover Plates</b>						
9"		4.00	5.00	6.00		C
12"		4.50	5.60	6.70		C
18"		5.00	6.20	7.50		C
24"		5.50	6.80	8.20		C
27"		6.00	7.50	9.00		C
30"		7.00	8.70	10.50		C
36"		8.00	10.00	12.00		C

Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Cable Tray</b>						
<b>Steel Tray 3" Depth</b>						
<b>Steel Ladder Cable Tray - 6" Rung Spacing - 3" Depth</b>						
	6" Wide		12.00	15.00	18.00	C
	9" Wide		13.00	16.25	19.50	C
	12" Wide		14.00	17.50	21.00	C
	18" Wide		15.00	18.75	22.50	C
	24" Wide		16.00	20.00	24.00	C
	30" Wide		18.00	22.50	27.00	C
	36" Wide		20.00	25.00	30.00	C
<b>Steel Ladder Cable Tray - 9" Rung Spacing - 3" Depth</b>						
	6" Wide		11.50	14.38	17.25	C
	9" Wide		12.25	15.31	18.38	C
	12" Wide		13.00	16.25	19.50	C
	18" Wide		13.75	17.19	20.63	C
	24" Wide		14.50	18.13	21.75	C
	30" Wide		16.00	20.00	24.00	C
	36" Wide		17.50	21.88	26.25	C
<b>Steel Ladder Cable Tray - 12" Rung Spacing - 3" Depth</b>						
	6" Wide		11.00	13.75	16.50	C
	9" Wide		11.50	14.38	17.25	C
	12" Wide		12.00	15.00	18.00	C
	18" Wide		12.50	15.63	18.75	C
	24" Wide		13.00	16.25	19.50	C
	30" Wide		14.00	17.50	21.00	C
	36" Wide		15.00	18.75	22.50	C
<b>Steel Ladder Cable Tray - 18" Rung Spacing - 3" Depth</b>						
	6" Wide		10.70	13.38	16.05	C
	9" Wide		11.20	14.00	16.80	C
	12" Wide		11.60	14.50	17.40	C
	18" Wide		12.20	15.25	18.30	C
	24" Wide		12.60	15.75	18.90	C
	30" Wide		13.50	16.88	20.25	C
	36" Wide		14.00	17.50	21.00	C
<b>Steel - 45 Degree Elbow - 3" Depth</b>						
	6" Wide		1.50	1.88	2.25	E
	9" Wide		1.65	2.06	2.48	E
	12" Wide		1.80	2.25	2.70	E
	18" Wide		2.00	2.50	3.00	E
	24" Wide		2.35	2.94	3.53	E
	30" Wide		2.65	3.31	3.98	E
	36" Wide		3.00	3.75	4.50	E
<b>Steel - 90 Degree Elbow - 3" Depth</b>						
	6" Wide		2.25	2.81	3.38	E
	9" Wide		2.50	3.13	3.75	E
	12" Wide		2.75	3.44	4.13	E
	18" Wide		3.00	3.75	4.50	E
	24" Wide		3.50	4.38	5.25	E
	30" Wide		4.00	5.00	6.00	E
	36" Wide		4.50	5.63	6.75	E
<b>Steel - Tee - 3" Depth</b>						
	6" Wide		4.00	5.00	6.00	E
	9" Wide		4.25	5.31	6.38	E
	12" Wide		4.50	5.63	6.75	E
	18" Wide		5.00	6.25	7.50	E
	24" Wide		5.50	6.88	8.25	E
	30" Wide		6.00	7.50	9.00	E
	36" Wide		6.50	8.13	9.75	E
<b>Steel - Cross - 3" Depth</b>						
	6" Wide		5.25	6.56	7.88	E
	9" Wide		5.50	6.88	8.25	E
	12" Wide		6.00	7.50	9.00	E
	18" Wide		6.50	8.13	9.75	E
	24" Wide		7.00	8.75	10.50	E
	30" Wide		7.50	9.38	11.25	E
	36" Wide		8.00	10.00	12.00	E













Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Steel Tray 4" Depth</b>						
<b>Steel Ladder Cable Tray - 6" Rung Spacing - 4" Depth</b>						
	6" Wide					C
	9" Wide	14.00	17.50	21.00		C
	12" Wide	15.00	18.75	22.50		C
	18" Wide	16.00	20.00	24.00		C
	24" Wide	17.00	21.25	25.50		C
	30" Wide	18.00	22.50	27.00		C
	36" Wide	20.00	25.00	30.00		C
	22.00	27.50	33.00		C	
<b>Steel Ladder Cable Tray - 9" Rung Spacing - 4" Depth</b>						
	6" Wide					C
	9" Wide	13.50	16.88	20.25		C
	12" Wide	13.90	17.38	20.85		C
	18" Wide	14.70	18.38	22.05		C
	24" Wide	15.50	19.38	23.25		C
	30" Wide	16.00	20.00	24.00		C
	36" Wide	18.10	22.63	27.15		C
	19.70	24.63	29.55		C	
<b>Steel Ladder Cable Tray- 12" Rung Spacing - 4" Depth</b>						
	6" Wide					C
	9" Wide	13.00	16.25	19.50		C
	12" Wide	13.50	16.88	20.25		C
	18" Wide	14.00	17.50	21.00		C
	24" Wide	14.50	18.13	21.75		C
	30" Wide	15.00	18.75	22.50		C
	36" Wide	16.00	20.00	24.00		C
	17.00	21.25	25.50		C	
<b>Steel Ladder Cable Tray - 18" Rung Spacing - 4" Depth</b>						
	6" Wide					C
	9" Wide	12.60	15.75	18.90		C
	12" Wide	13.00	16.25	19.50		C
	18" Wide	13.60	17.00	20.40		C
	24" Wide	14.00	17.50	21.00		C
	30" Wide	14.60	18.25	21.90		C
	36" Wide	15.50	19.38	23.25		C
	16.00	20.00	24.00		C	
<b>Steel - 45 Degree Elbow - 4" Depth</b>						
	6" Wide					E
	9" Wide	1.75	2.19	2.63		E
	12" Wide	1.90	2.38	2.85		E
	18" Wide	2.20	2.75	3.30		E
	24" Wide	2.40	3.00	3.60		E
	30" Wide	2.70	3.38	4.05		E
	36" Wide	3.10	3.88	4.65		E
	3.50	4.38	5.25		E	
<b>Steel - 90 Degree Elbow - 4" Depth</b>						
	6" Wide					E
	9" Wide	2.60	3.25	3.90		E
	12" Wide	2.90	3.63	4.35		E
	18" Wide	3.15	3.94	4.73		E
	24" Wide	3.50	4.38	5.25		E
	30" Wide	4.00	5.00	6.00		E
	36" Wide	4.60	5.75	6.90		E
	5.20	6.50	7.80		E	
<b>Steel - Tee - 4" Depth</b>						
	6" Wide					E
	9" Wide	4.60	5.75	6.90		E
	12" Wide	4.90	6.13	7.35		E
	18" Wide	5.20	6.50	7.80		E
	24" Wide	5.80	7.25	8.70		E
	30" Wide	6.40	8.00	9.60		E
	36" Wide	7.00	8.75	10.50		E
	7.60	9.50	11.40		E	
<b>Steel - Cross- 4" Depth</b>						
	6" Wide					E
	9" Wide	6.10	7.63	9.15		E
	12" Wide	6.40	8.00	9.60		E
	18" Wide	7.00	8.75	10.50		E
	24" Wide	7.50	9.38	11.25		E
	30" Wide	8.20	10.25	12.30		E
	36" Wide	8.70	10.88	13.05		E
	9.30	11.63	13.95		E	



Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Steel Tray 6" Depth</b>						
<b>Steel Ladder Cable Tray - 6" Rung Spacing - 6" Depth</b>						
 6" Wide		18.00	22.50	27.00		C
9" Wide		19.00	23.75	28.50		C
12" Wide		20.00	25.00	30.00		C
18" Wide		21.00	26.25	31.50		C
24" Wide		22.00	27.50	33.00		C
30" Wide		24.00	30.00	36.00		C
36" Wide		26.00	32.50	39.00		C
<b>Steel Ladder Cable Tray - 9" Rung Spacing - 6" Depth</b>						
 6" Wide		17.50	21.88	26.25		C
9" Wide		18.30	22.88	27.45		C
12" Wide		19.00	23.75	28.50		C
18" Wide		19.80	24.75	29.70		C
24" Wide		20.40	25.50	30.60		C
30" Wide		21.90	27.38	32.85		C
36" Wide		23.50	29.38	35.25		C
<b>Steel Ladder Cable Tray - 12" Rung Spacing - 6" Depth</b>						
 6" Wide		17.00	21.25	25.50		C
9" Wide		17.50	21.88	26.25		C
12" Wide		18.00	22.50	27.00		C
18" Wide		18.50	23.13	27.75		C
24" Wide		19.00	23.75	28.50		C
30" Wide		20.00	25.00	30.00		C
36" Wide		21.00	26.25	31.50		C
<b>Steel Ladder Cable Tray - 18" Rung Spacing - 6" Depth</b>						
 6" Wide		16.50	20.63	24.75		C
9" Wide		17.00	21.25	25.50		C
12" Wide		17.50	21.88	26.25		C
18" Wide		17.90	22.38	26.85		C
24" Wide		18.40	23.00	27.60		C
30" Wide		19.50	24.38	29.25		C
36" Wide		20.00	25.00	30.00		C
<b>Steel - 45 Degree Elbow - 6" Depth</b>						
 6" Wide		2.00	2.50	3.00		E
9" Wide		2.20	2.75	3.30		E
12" Wide		2.40	3.00	3.60		E
18" Wide		2.60	3.25	3.90		E
24" Wide		3.00	3.75	4.50		E
30" Wide		3.50	4.38	5.25		E
36" Wide		3.90	4.88	5.85		E
<b>Steel - 90 Degree Elbow - 6" Depth</b>						
 6" Wide		3.00	3.75	4.50		E
9" Wide		3.30	4.13	4.95		E
12" Wide		3.80	4.75	5.70		E
18" Wide		4.00	5.00	6.00		E
24" Wide		4.70	5.88	7.05		E
30" Wide		5.30	6.63	7.95		E
36" Wide		6.00	7.50	9.00		E
<b>Steel - Tee - 6" Depth</b>						
 6" Wide		5.90	7.38	8.85		E
9" Wide		6.20	7.75	9.30		E
12" Wide		6.60	8.25	9.90		E
18" Wide		7.30	9.13	10.95		E
24" Wide		8.00	10.00	12.00		E
30" Wide		8.80	11.00	13.20		E
36" Wide		9.50	11.88	14.25		E
<b>Steel - Cross - 6" Depth</b>						
 6" Wide		7.70	9.63	11.55		E
9" Wide		8.20	10.25	12.30		E
12" Wide		8.80	11.00	13.20		E
18" Wide		9.50	11.88	14.25		E
24" Wide		10.30	12.88	15.45		E
30" Wide		11.00	13.75	16.50		E
36" Wide		11.80	14.75	17.70		E









## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Steel Cable Tray Fittings &amp; Accessories</b>						
<b>Combination Hold-Down Clamp and Expansion Guide</b>						
Hold Down Clamp Pair		0.8	1.00	1.20		E
<b>Steel Cable Tray - Solid Covers</b>						
6" Wide		3.75	4.69	5.63		C
9" Wide		4.25	5.31	6.38		C
12" Wide		5.25	6.56	7.88		C
18" Wide		6.75	8.44	10.13		C
24" Wide		8.25	10.31	12.38		C
30" Wide		10.25	12.81	15.38		C
36" Wide		12.25	15.31	18.38		C
<b>Steel Cable Tray - Solid Cover Clamps (Per Pair)</b>						
6" Wide		0.50	0.63	0.75		E
9" Wide		0.55	0.69	0.83		E
12" Wide		0.60	0.75	0.90		E
18" Wide		0.65	0.81	0.98		E
24" Wide		0.70	0.88	1.05		E
30" Wide		0.75	0.94	1.13		E
36" Wide		0.80	1.00	1.20		E
<b>Steel - 45 Degree Elbow - Solid Covers</b>						
6" Wide		0.25	0.31	0.38		E
9" Wide		0.30	0.38	0.45		E
12" Wide		0.35	0.44	0.53		E
18" Wide		0.40	0.50	0.60		E
24" Wide		0.50	0.63	0.75		E
30" Wide		0.60	0.75	0.90		E
36" Wide		0.70	0.88	1.05		E
<b>Steel - 90 Degree Elbow - Solid Covers</b>						
6" Wide		0.25	0.31	0.38		E
9" Wide		0.30	0.38	0.45		E
12" Wide		0.35	0.44	0.53		E
18" Wide		0.40	0.50	0.60		E
24" Wide		0.50	0.63	0.75		E
30" Wide		0.60	0.75	0.90		E
36" Wide		0.70	0.88	1.05		E
<b>Steel - Tee - Solid Covers</b>						
6" Wide		0.35	0.44	0.53		E
9" Wide		0.40	0.50	0.60		E
12" Wide		0.45	0.56	0.68		E
18" Wide		0.50	0.63	0.75		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.70	0.88	1.05		E
36" Wide		0.80	1.00	1.20		E
<b>Steel - Cross - Solid Covers</b>						
6" Wide		0.45	0.56	0.68		E
9" Wide		0.50	0.63	0.75		E
12" Wide		0.55	0.69	0.83		E
18" Wide		0.60	0.75	0.90		E
24" Wide		0.70	0.88	1.05		E
30" Wide		0.80	1.00	1.20		E
36" Wide		0.90	1.13	1.35		E
<b>Steel - Reducer - Solid Covers</b>						
6" Wide		0.25	0.31	0.38		E
9" Wide		0.30	0.38	0.45		E
12" Wide		0.35	0.44	0.53		E
18" Wide		0.40	0.50	0.60		E
24" Wide		0.50	0.63	0.75		E
30" Wide		0.60	0.75	0.90		E
36" Wide		0.70	0.88	1.05		E
<b>Steel - Vertical 45 Degree Elbow - Solid Covers</b>						
6" Wide		0.35	0.44	0.53		E
9" Wide		0.40	0.50	0.60		E
12" Wide		0.45	0.56	0.68		E
18" Wide		0.50	0.63	0.75		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.70	0.88	1.05		E
36" Wide		0.80	1.00	1.20		E










Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Steel - Vertical 90 Degree Elbow - Solid Covers</b>						
6" Wide		0.35	0.44	0.53		E
9" Wide		0.40	0.50	0.60		E
12" Wide		0.45	0.56	0.68		E
18" Wide		0.50	0.63	0.75		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.70	0.88	1.05		E
36" Wide		0.80	1.00	1.20		E
<b>Steel - Vertical Tee - Solid Covers</b>						
6" Wide		0.45	0.56	0.68		E
9" Wide		0.50	0.63	0.75		E
12" Wide		0.55	0.69	0.83		E
18" Wide		0.60	0.75	0.90		E
24" Wide		0.70	0.88	1.05		E
30" Wide		0.80	1.00	1.20		E
36" Wide		0.90	1.13	1.35		E
<b>Steel - Enclosure Connectors</b>						
6" Wide		2.00	2.50	3.00		E
9" Wide		2.25	2.81	3.38		E
12" Wide		2.60	3.25	3.90		E
18" Wide		3.00	3.75	4.50		E
24" Wide		3.50	4.38	5.25		E
30" Wide		4.25	5.31	6.38		E
36" Wide		5.00	6.25	7.50		E
<b>Steel - End Plates</b>						
6" Wide		0.40	0.50	0.60		E
9" Wide		0.45	0.56	0.68		E
12" Wide		0.50	0.63	0.75		E
18" Wide		0.55	0.69	0.83		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.65	0.81	0.98		E
36" Wide		0.70	0.88	1.05		E
<b>Steel - Ladder Drop-Outs</b>						
6" Wide		0.40	0.50	0.60		E
9" Wide		0.45	0.56	0.68		E
12" Wide		0.50	0.63	0.75		E
18" Wide		0.55	0.69	0.83		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.65	0.81	0.98		E
36" Wide		0.70	0.88	1.05		E
<b>Steel - Splice Plates Pair</b>						
6" Wide		0.80	1.00	1.20		E
9" Wide		0.85	1.06	1.28		E
12" Wide		0.90	1.13	1.35		E
18" Wide		0.95	1.19	1.43		E
24" Wide		1.00	1.25	1.50		E
30" Wide		1.10	1.38	1.65		E
36" Wide		1.20	1.50	1.80		E
<b>Steel Cable Tray Barrier Strips</b>						
3" Depth		6.00	7.50	9.00		C
4" Depth		8.00	10.00	12.00		C
6" Depth		10.00	12.50	15.00		C
<b>Steel Cable Tray Fitting Barrier Strips</b>						
3" Depth		0.60	0.75	0.90		E
4" Depth		0.65	0.81	0.98		E
6" Depth		0.70	0.88	1.05		E
<b>Steel Conduit To Cable Tray Adapters</b>						
1/2" Conduit		0.50	0.63	0.75		E
3/4" Conduit		0.55	0.69	0.83		E
1" Conduit		0.60	0.75	0.90		E
1 1/4" Conduit		0.65	0.81	0.98		E
1 1/2" Conduit		0.70	0.88	1.05		E
2" Conduit		0.75	0.94	1.13		E
2 1/2" Conduit		0.80	1.00	1.20		E
3" Conduit		0.90	1.13	1.35		E
3 1/2" Conduit		1.00	1.25	1.50		E
4" Conduit		1.20	1.50	1.80		E
<b>Bonding Jumpers</b>						
#1/0 Copper X 15" Long		0.60	0.75	0.90		E
#4/0 Copper X 15" Long		0.80	1.00	1.20		E
#250 Copper X 15" Long		1.00	1.25	1.50		E











Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Aluminum Tray 3" Depth</b>						
	<b>Aluminum Ladder Cable Tray - 6" Rung Spacing - 3" Depth</b>					
	6" Wide		10.50	13.13	15.75	C
	9" Wide		11.25	14.06	16.88	C
	12" Wide		12.00	15.00	18.00	C
	18" Wide		12.75	15.94	19.13	C
	24" Wide		13.50	16.88	20.25	C
	30" Wide		15.00	18.75	22.50	C
36" Wide		16.50	20.63	24.75	C	
	<b>Aluminum Ladder Cable Tray - 9" Rung Spacing - 3" Depth</b>					
	6" Wide		10.20	12.75	15.30	C
	9" Wide		10.80	13.50	16.20	C
	12" Wide		11.25	14.06	16.88	C
	18" Wide		12.00	15.00	18.00	C
	24" Wide		12.75	15.94	19.13	C
	30" Wide		14.25	17.81	21.38	C
36" Wide		15.75	19.69	23.63	C	
	<b>Aluminum Ladder Cable Tray - 12" Rung Spacing - 3" Depth</b>					
	6" Wide		9.75	12.19	14.63	C
	9" Wide		10.20	12.75	15.30	C
	12" Wide		10.50	13.13	15.75	C
	18" Wide		10.80	13.50	16.20	C
	24" Wide		11.25	14.06	16.88	C
	30" Wide		12.00	15.00	18.00	C
36" Wide		12.75	15.94	19.13	C	
	<b>Aluminum Ladder Cable Tray - 18" Rung Spacing - 3" Depth</b>					
	6" Wide		9.00	11.25	13.50	C
	9" Wide		9.40	11.75	14.10	C
	12" Wide		9.75	12.19	14.63	C
	18" Wide		10.20	12.75	15.30	C
	24" Wide		10.50	13.13	15.75	C
	30" Wide		11.25	14.06	16.88	C
36" Wide		12.00	15.00	18.00	C	
	<b>Aluminum - 45 Degree Elbow - 3" Depth</b>					
	6" Wide		1.35	1.69	2.03	E
	9" Wide		1.50	1.88	2.25	E
	12" Wide		1.70	2.13	2.55	E
	18" Wide		1.80	2.25	2.70	E
	24" Wide		2.10	2.63	3.15	E
	30" Wide		2.40	3.00	3.60	E
36" Wide		2.70	3.38	4.05	E	
	<b>Aluminum - 90 Degree Elbow - 3" Depth</b>					
	6" Wide		2.00	2.50	3.00	E
	9" Wide		2.25	2.81	3.38	E
	12" Wide		2.40	3.00	3.60	E
	18" Wide		2.70	3.38	4.05	E
	24" Wide		3.20	4.00	4.80	E
	30" Wide		3.60	4.50	5.40	E
36" Wide		4.00	5.00	6.00	E	
	<b>Aluminum - Tee - 3" Depth</b>					
	6" Wide		3.60	4.50	5.40	E
	9" Wide		3.80	4.75	5.70	E
	12" Wide		4.00	5.00	6.00	E
	18" Wide		4.50	5.63	6.75	E
	24" Wide		5.00	6.25	7.50	E
	30" Wide		5.40	6.75	8.10	E
36" Wide		5.90	7.38	8.85	E	
	<b>Aluminum - Cross - 3" Depth</b>					
	6" Wide		4.70	5.88	7.05	E
	9" Wide		5.00	6.25	7.50	E
	12" Wide		5.40	6.75	8.10	E
	18" Wide		5.80	7.25	8.70	E
	24" Wide		6.30	7.88	9.45	E
	30" Wide		6.75	8.44	10.13	E
36" Wide		7.20	9.00	10.80	E	
	<b>Aluminum - Reducer - 3" Depth</b>					
	6" Wide		1.35	1.69	2.03	E
	9" Wide		1.50	1.88	2.25	E
	12" Wide		1.70	2.13	2.55	E
	18" Wide		1.80	2.25	2.70	E
	24" Wide		2.10	2.63	3.15	E
	30" Wide		2.40	3.00	3.60	E
36" Wide		2.70	3.38	4.05	E	








Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Aluminum Tray 4" Depth</b>						
	<b>Aluminum Ladder Cable Tray - 6" Rung Spacing - 4" Depth</b>					
	6" Wide		12.75	15.94	19.13	C
	9" Wide		13.50	16.88	20.25	C
	12" Wide		14.25	17.81	21.38	C
	18" Wide		15.00	18.75	22.50	C
	24" Wide		16.50	20.63	24.75	C
	30" Wide		18.00	22.50	27.00	C
36" Wide		19.50	24.38	29.25	C	
	<b>Aluminum Ladder Cable Tray - 9" Rung Spacing - 4" Depth</b>					
	6" Wide		12.20	15.25	18.30	C
	9" Wide		12.75	15.94	19.13	C
	12" Wide		13.40	16.75	20.10	C
	18" Wide		14.00	17.50	21.00	C
	24" Wide		15.00	18.75	22.50	C
	30" Wide		16.20	20.25	24.30	C
36" Wide		17.40	21.75	26.10	C	
	<b>Aluminum Ladder Cable Tray - 12" Rung Spacing - 4" Depth</b>					
	6" Wide		11.60	14.50	17.40	C
	9" Wide		12.00	15.00	18.00	C
	12" Wide		12.60	15.75	18.90	C
	18" Wide		13.00	16.25	19.50	C
	24" Wide		13.50	16.88	20.25	C
	30" Wide		14.40	18.00	21.60	C
36" Wide		15.30	19.13	22.95	C	
	<b>Aluminum Ladder Cable Tray - 18" Rung Spacing - 4" Depth</b>					
	6" Wide		11.25	14.06	16.88	C
	9" Wide		11.70	14.63	17.55	C
	12" Wide		12.30	15.38	18.45	C
	18" Wide		12.60	15.75	18.90	C
	24" Wide		13.10	16.38	19.65	C
	30" Wide		14.00	17.50	21.00	C
36" Wide		14.40	18.00	21.60	C	
	<b>Aluminum - 45 Degree Elbow - 4" Depth</b>					
	6" Wide		1.40	1.75	2.10	E
	9" Wide		1.55	1.94	2.33	E
	12" Wide		1.75	2.19	2.63	E
	18" Wide		1.85	2.31	2.78	E
	24" Wide		2.20	2.75	3.30	E
	30" Wide		2.50	3.13	3.75	E
36" Wide		2.80	3.50	4.20	E	
	<b>Aluminum - 90 Degree Elbow - 4" Depth</b>					
	6" Wide		2.10	2.63	3.15	E
	9" Wide		2.35	2.94	3.53	E
	12" Wide		2.50	3.13	3.75	E
	18" Wide		2.80	3.50	4.20	E
	24" Wide		3.30	4.13	4.95	E
	30" Wide		3.75	4.69	5.63	E
36" Wide		4.15	5.19	6.23	E	
	<b>Aluminum - Tee - 4" Depth</b>					
	6" Wide		3.75	4.69	5.63	E
	9" Wide		3.95	4.94	5.93	E
	12" Wide		4.15	5.19	6.23	E
	18" Wide		4.65	5.81	6.98	E
	24" Wide		5.15	6.44	7.73	E
	30" Wide		5.60	7.00	8.40	E
36" Wide		6.10	7.63	9.15	E	
	<b>Aluminum- Cross - 4" Depth</b>					
	6" Wide		4.90	6.13	7.35	E
	9" Wide		5.20	6.50	7.80	E
	12" Wide		5.60	7.00	8.40	E
	18" Wide		6.00	7.50	9.00	E
	24" Wide		6.55	8.19	9.83	E
	30" Wide		7.00	8.75	10.50	E
36" Wide		7.50	9.38	11.25	E	

Section 2 - Conduit, Raceways, Fittings & Related Items

2





Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Aluminum - Reducer - 4" Depth</b>						
 6" Wide		1.40	1.75	2.10		E
9" Wide		1.55	1.94	2.33		E
12" Wide		1.75	2.19	2.63		E
18" Wide		1.85	2.31	2.78		E
24" Wide		2.20	2.75	3.30		E
30" Wide		2.50	3.13	3.75		E
36" Wide		2.80	3.50	4.20		E
<b>Aluminum - Vertical 45 Degree Elbow - 4" Depth</b>						
 6" Wide		1.70	2.13	2.55		E
9" Wide		1.80	2.25	2.70		E
12" Wide		2.10	2.63	3.15		E
18" Wide		2.20	2.75	3.30		E
24" Wide		2.60	3.25	3.90		E
30" Wide		3.00	3.75	4.50		E
36" Wide		3.30	4.13	4.95		E
<b>Aluminum - Vertical 90 Degree Elbow - 4" Depth</b>						
 6" Wide		2.50	3.13	3.75		E
9" Wide		2.80	3.50	4.20		E
12" Wide		3.00	3.75	4.50		E
18" Wide		3.30	4.13	4.95		E
24" Wide		3.90	4.88	5.85		E
30" Wide		4.50	5.63	6.75		E
36" Wide		5.00	6.25	7.50		E
<b>Aluminum - Vertical Tee - 4" Depth</b>						
6" Wide		4.60	5.75	6.90		E
9" Wide		4.90	6.13	7.35		E
12" Wide		5.20	6.50	7.80		E
18" Wide		5.80	7.25	8.70		E
24" Wide		6.40	8.00	9.60		E
30" Wide		7.00	8.75	10.50		E
36" Wide		7.60	9.50	11.40		E

Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Aluminum Tray 6" Depth</b>						
<b>Aluminum Ladder Cable Tray - 6" Rung Spacing - 6" Depth</b>						
	6" Wide					C
	9" Wide	16.50	20.63	24.75		C
	12" Wide	17.25	21.56	25.88		C
	18" Wide	18.00	22.50	27.00		C
	24" Wide	18.75	23.44	28.13		C
	30" Wide	20.25	25.31	30.38		C
	36" Wide	21.75	27.19	32.63		C
	23.25	29.06	34.88		C	
<b>Aluminum Ladder Cable Tray - 9" Rung Spacing - 6" Depth</b>						
	6" Wide	16.00	20.00	24.00		C
	9" Wide	16.50	20.63	24.75		C
	12" Wide	17.10	21.38	25.65		C
	18" Wide	17.70	22.13	26.55		C
	24" Wide	18.70	23.38	28.05		C
	30" Wide	19.80	24.75	29.70		C
	36" Wide	21.00	26.25	31.50		C
<b>Aluminum Ladder Cable Tray - 12" Rung Spacing - 6" Depth</b>						
	6" Wide	15.40	19.25	23.10		C
	9" Wide	15.75	19.69	23.63		C
	12" Wide	16.20	20.25	24.30		C
	18" Wide	16.60	20.75	24.90		C
	24" Wide	17.10	21.38	25.65		C
	30" Wide	18.00	22.50	27.00		C
	36" Wide	18.90	23.63	28.35		C
<b>Aluminum Ladder Cable Tray - 18" Rung Spacing - 6" Depth</b>						
	6" Wide	14.60	18.25	21.90		C
	9" Wide	15.30	19.13	22.95		C
	12" Wide	15.75	19.69	23.63		C
	18" Wide	16.10	20.13	24.15		C
	24" Wide	16.50	20.63	24.75		C
	30" Wide	17.60	22.00	26.40		C
	36" Wide	18.00	22.50	27.00		C
<b>Aluminum - 45 Degree Elbow - 6" Depth</b>						
	6" Wide	1.50	1.88	2.25		E
	9" Wide	1.60	2.00	2.40		E
	12" Wide	1.80	2.25	2.70		E
	18" Wide	1.90	2.38	2.85		E
	24" Wide	2.40	3.00	3.60		E
	30" Wide	2.75	3.44	4.13		E
	36" Wide	3.00	3.75	4.50		E
<b>Aluminum - 90 Degree Elbow - 6" Depth</b>						
	6" Wide	2.30	2.88	3.45		E
	9" Wide	2.60	3.25	3.90		E
	12" Wide	2.75	3.44	4.13		E
	18" Wide	3.00	3.75	4.50		E
	24" Wide	3.80	4.75	5.70		E
	30" Wide	4.30	5.38	6.45		E
	36" Wide	4.80	6.00	7.20		E
<b>Aluminum - Tee - 6" Depth</b>						
	6" Wide	4.30	5.38	6.45		E
	9" Wide	4.50	5.63	6.75		E
	12" Wide	4.80	6.00	7.20		E
	18" Wide	5.40	6.75	8.10		E
	24" Wide	5.90	7.38	8.85		E
	30" Wide	6.40	8.00	9.60		E
	36" Wide	6.90	8.63	10.35		E
<b>Aluminum - Cross - 6" Depth</b>						
	6" Wide	5.60	7.00	8.40		E
	9" Wide	6.00	7.50	9.00		E
	12" Wide	6.40	8.00	9.60		E
	18" Wide	6.90	8.63	10.35		E
	24" Wide	7.50	9.38	11.25		E
	30" Wide	8.00	10.00	12.00		E
	36" Wide	8.60	10.75	12.90		E



## Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Aluminum - Reducer - 6" Depth</b>						
 6" Wide		1.50	1.88	2.25		E
9" Wide		1.60	2.00	2.40		E
12" Wide		1.80	2.25	2.70		E
18" Wide		1.90	2.38	2.85		E
24" Wide		2.40	3.00	3.60		E
30" Wide		2.75	3.44	4.13		E
36" Wide		3.00	3.75	4.50		E
<b>Aluminum - Vertical 45 Degree Elbow - 6" Depth</b>						
 6" Wide		1.80	2.25	2.70		E
9" Wide		1.90	2.38	2.85		E
12" Wide		2.20	2.75	3.30		E
18" Wide		2.30	2.88	3.45		E
24" Wide		2.90	3.63	4.35		E
30" Wide		3.30	4.13	4.95		E
36" Wide		3.60	4.50	5.40		E
<b>Aluminum - Vertical 90 Degree Elbow - 6" Depth</b>						
 6" Wide		2.70	3.38	4.05		E
9" Wide		3.20	4.00	4.80		E
12" Wide		3.30	4.13	4.95		E
18" Wide		3.60	4.50	5.40		E
24" Wide		4.50	5.63	6.75		E
30" Wide		5.20	6.50	7.80		E
36" Wide		5.70	7.13	8.55		E
<b>Aluminum - Vertical Tee - 6" Depth</b>						
 6" Wide		5.20	6.50	7.80		E
9" Wide		5.40	6.75	8.10		E
12" Wide		5.80	7.25	8.70		E
18" Wide		6.50	8.13	9.75		E
24" Wide		7.00	8.75	10.50		E
30" Wide		7.70	9.63	11.55		E
36" Wide		8.30	10.38	12.45		E

## Section 2 - Conduit, Raceways, Fittings & Related Items







Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Aluminum Cable Tray Fittings &amp; Accessories</b>						
<b>Combination Hold - Down Clamp and Expansion Guide</b>						
Hold Down Clamp Pair		0.8	1.00	1.20		E
<b>Aluminum Cable Tray - Solid Covers</b>						
6" Wide		3.50	4.38	5.25		C
9" Wide		4.00	5.00	6.00		C
12" Wide		5.00	6.25	7.50		C
18" Wide		6.50	8.13	9.75		C
24" Wide		8.00	10.00	12.00		C
30" Wide		10.00	12.50	15.00		C
36" Wide		12.00	15.00	18.00		C
<b>Aluminum Cable Tray - Solid Cover Clamps (Per Pair)</b>						
6" Wide		0.50	0.63	0.75		E
9" Wide		0.55	0.69	0.83		E
12" Wide		0.60	0.75	0.90		E
18" Wide		0.65	0.81	0.98		E
24" Wide		0.70	0.88	1.05		E
30" Wide		0.75	0.94	1.13		E
36" Wide		0.80	1.00	1.20		E
<b>Aluminum - 45 Degree Elbow - Solid Covers</b>						
6" Wide		0.25	0.31	0.38		E
9" Wide		0.30	0.38	0.45		E
12" Wide		0.35	0.44	0.53		E
18" Wide		0.40	0.50	0.60		E
24" Wide		0.50	0.63	0.75		E
30" Wide		0.60	0.75	0.90		E
36" Wide		0.70	0.88	1.05		E
<b>Aluminum - 90 Degree Elbow - Solid Covers</b>						
6" Wide		0.25	0.31	0.38		E
9" Wide		0.30	0.38	0.45		E
12" Wide		0.35	0.44	0.53		E
18" Wide		0.40	0.50	0.60		E
24" Wide		0.50	0.63	0.75		E
30" Wide		0.60	0.75	0.90		E
36" Wide		0.70	0.88	1.05		E
<b>Aluminum - Tee - Solid Covers</b>						
6" Wide		0.35	0.44	0.53		E
9" Wide		0.40	0.50	0.60		E
12" Wide		0.45	0.56	0.68		E
18" Wide		0.50	0.63	0.75		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.70	0.88	1.05		E
36" Wide		0.80	1.00	1.20		E
<b>Aluminum - Cross - Solid Covers</b>						
6" Wide		0.45	0.56	0.68		E
9" Wide		0.50	0.63	0.75		E
12" Wide		0.55	0.69	0.83		E
18" Wide		0.60	0.75	0.90		E
24" Wide		0.70	0.88	1.05		E
30" Wide		0.80	1.00	1.20		E
36" Wide		0.90	1.13	1.35		E
<b>Aluminum - Reducer - Solid Covers</b>						
6" Wide		0.25	0.31	0.38		E
9" Wide		0.30	0.38	0.45		E
12" Wide		0.35	0.44	0.53		E
18" Wide		0.40	0.50	0.60		E
24" Wide		0.50	0.63	0.75		E
30" Wide		0.60	0.75	0.90		E
36" Wide		0.70	0.88	1.05		E
<b>Aluminum - Vertical 45 Degree Elbow - Solid Covers</b>						
6" Wide		0.35	0.44	0.53		E
9" Wide		0.40	0.50	0.60		E
12" Wide		0.45	0.56	0.68		E
18" Wide		0.50	0.63	0.75		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.70	0.88	1.05		E
36" Wide		0.80	1.00	1.20		E











Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Aluminum - Vertical 90 Degree Elbow - Solid Covers</b>						
6" Wide		0.35	0.44	0.53		E
9" Wide		0.40	0.50	0.60		E
12" Wide		0.45	0.56	0.68		E
18" Wide		0.50	0.63	0.75		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.70	0.88	1.05		E
36" Wide		0.80	1.00	1.20		E
<b>Aluminum - Vertical Tee - Solid Covers</b>						
6" Wide		0.45	0.56	0.68		E
9" Wide		0.50	0.63	0.75		E
12" Wide		0.55	0.69	0.83		E
18" Wide		0.60	0.75	0.90		E
24" Wide		0.70	0.88	1.05		E
30" Wide		0.80	1.00	1.20		E
36" Wide		0.90	1.13	1.35		E
<b>Aluminum - Enclosure Connectors</b>						
6" Wide		2.00	2.50	3.00		E
9" Wide		2.25	2.81	3.38		E
12" Wide		2.60	3.25	3.90		E
18" Wide		3.00	3.75	4.50		E
24" Wide		3.50	4.38	5.25		E
30" Wide		4.25	5.31	6.38		E
36" Wide		5.00	6.25	7.50		E
<b>Aluminum - End Plates</b>						
6" Wide		0.40	0.50	0.60		E
9" Wide		0.45	0.56	0.68		E
12" Wide		0.50	0.63	0.75		E
18" Wide		0.55	0.69	0.83		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.65	0.81	0.98		E
36" Wide		0.70	0.88	1.05		E
<b>Aluminum - Ladder Drop-Outs</b>						
6" Wide		0.40	0.50	0.60		E
9" Wide		0.45	0.56	0.68		E
12" Wide		0.50	0.63	0.75		E
18" Wide		0.55	0.69	0.83		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.65	0.81	0.98		E
36" Wide		0.70	0.88	1.05		E
<b>Aluminum - Splice Plates Pair</b>						
6" Wide		0.80	1.00	1.20		E
9" Wide		0.85	1.06	1.28		E
12" Wide		0.90	1.13	1.35		E
18" Wide		0.95	1.19	1.43		E
24" Wide		1.00	1.25	1.50		E
30" Wide		1.10	1.38	1.65		E
36" Wide		1.20	1.50	1.80		E
<b>Aluminum Cable Tray Barrier Strips</b>						
3" Depth		6.00	7.50	9.00		C
4" Depth		8.00	10.00	12.00		C
6" Depth		10.00	12.50	15.00		C
<b>Aluminum Cable Tray Fitting Barrier Strips</b>						
3" depth		0.60	0.75	0.90		E
4" depth		0.65	0.81	0.98		E
6" depth		0.70	0.88	1.05		E
<b>Aluminum Conduit To Cable Tray Adapters</b>						
1/2" Conduit		0.50	0.63	0.75		E
3/4" Conduit		0.55	0.69	0.83		E
1" Conduit		0.60	0.75	0.90		E
1 1/4" Conduit		0.65	0.81	0.98		E
1 1/2" Conduit		0.70	0.88	1.05		E
2" Conduit		0.75	0.94	1.13		E
2 1/2" Conduit		0.80	1.00	1.20		E
3" Conduit		0.90	1.13	1.35		E
3 1/2" Conduit		1.00	1.25	1.50		E
4" Conduit		1.20	1.50	1.80		E
<b>Bonding Jumpers</b>						
#1/0 Copper X 15" Long		0.60	0.75	0.90		E
#4/0 Copper X 15" Long		0.80	1.00	1.20		E
#250 Copper X 15" Long		1.00	1.25	1.50		E







Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Fiberglass Tray 3" Depth</b>						
<b>Fiberglass Cable Tray - 6" Rung Spacing - 3" Depth</b>						
						
6" Wide		14.00	17.50	21.00		C
9" Wide		15.00	18.75	22.50		C
12" Wide		16.00	20.00	24.00		C
18" Wide		17.00	21.25	25.50		C
24" Wide		18.00	22.50	27.00		C
30" Wide		20.00	25.00	30.00		C
36" Wide		22.00	27.50	33.00		C
<b>Fiberglass Cable Tray - 6" Rung Spacing - 3" Depth</b>						
						
6" Wide		13.50	16.88	20.25		C
9" Wide		14.50	18.13	21.75		C
12" Wide		15.00	18.75	22.50		C
18" Wide		16.00	20.00	24.00		C
24" Wide		17.00	21.25	25.50		C
30" Wide		19.00	23.75	28.50		C
36" Wide		21.00	26.25	31.50		C
<b>Fiberglass Cable Tray - 12" Rung Spacing - 3" Depth</b>						
						
6" Wide		13.00	16.25	19.50		C
9" Wide		13.50	16.88	20.25		C
12" Wide		14.00	17.50	21.00		C
18" Wide		14.50	18.13	21.75		C
24" Wide		15.00	18.75	22.50		C
30" Wide		16.00	20.00	24.00		C
36" Wide		17.00	21.25	25.50		C
<b>Fiberglass Cable Tray - 18" Rung Spacing - 3" Depth</b>						
						
6" Wide		12.00	15.00	18.00		C
9" Wide		12.50	15.63	18.75		C
12" Wide		13.00	16.25	19.50		C
18" Wide		13.50	16.88	20.25		C
24" Wide		14.00	17.50	21.00		C
30" Wide		15.00	18.75	22.50		C
36" Wide		16.00	20.00	24.00		C
<b>Fiberglass - 45 Degree Elbow - 3" Depth</b>						
						
6" Wide		1.80	2.25	2.70		E
9" Wide		2.00	2.50	3.00		E
12" Wide		2.25	2.81	3.38		E
18" Wide		2.50	3.13	3.75		E
24" Wide		2.80	3.50	4.20		E
30" Wide		3.25	4.06	4.88		E
36" Wide		3.60	4.50	5.40		E
<b>Fiberglass - 90 Degree Elbow - 3" Depth</b>						
						
6" Wide		2.70	3.38	4.05		E
9" Wide		3.00	3.75	4.50		E
12" Wide		3.30	4.13	4.95		E
18" Wide		3.60	4.50	5.40		E
24" Wide		4.20	5.25	6.30		E
30" Wide		4.80	6.00	7.20		E
36" Wide		5.40	6.75	8.10		E
<b>Fiberglass - Tee - 3" Depth</b>						
						
6" Wide		4.80	6.00	7.20		E
9" Wide		5.10	6.38	7.65		E
12" Wide		5.40	6.75	8.10		E
18" Wide		6.00	7.50	9.00		E
24" Wide		6.60	8.25	9.90		E
30" Wide		7.20	9.00	10.80		E
36" Wide		7.80	9.75	11.70		E
<b>Fiberglass - Cross - 3" Depth</b>						
						
6" Wide		6.30	7.88	9.45		E
9" Wide		6.60	8.25	9.90		E
12" Wide		7.20	9.00	10.80		E
18" Wide		7.80	9.75	11.70		E
24" Wide		8.40	10.50	12.60		E
30" Wide		9.00	11.25	13.50		E
36" Wide		9.60	12.00	14.40		E

Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Fiberglass - Reducer - 3" Depth</b>						
 6" Wide		1.80	2.25	2.70		E
9" Wide		2.00	2.50	3.00		E
12" Wide		2.25	2.81	3.38		E
18" Wide		2.50	3.13	3.75		E
24" Wide		2.80	3.50	4.20		E
30" Wide		3.25	4.06	4.88		E
36" Wide		3.60	4.50	5.40		E
<b>Fiberglass - Vertical 45 Degree Elbow - 3" Depth</b>						
 6" Wide		2.10	2.63	3.15		E
9" Wide		2.30	2.88	3.45		E
12" Wide		2.60	3.25	3.90		E
18" Wide		2.90	3.63	4.35		E
24" Wide		3.20	4.00	4.80		E
30" Wide		3.70	4.63	5.55		E
36" Wide		4.10	5.13	6.15		E
<b>Fiberglass - Vertical 90 Degree Elbow - 3" Depth</b>						
 6" Wide		3.25	4.06	4.88		E
9" Wide		3.60	4.50	5.40		E
12" Wide		4.00	5.00	6.00		E
18" Wide		4.30	5.38	6.45		E
24" Wide		5.00	6.25	7.50		E
30" Wide		5.80	7.25	8.70		E
36" Wide		6.50	8.13	9.75		E
<b>Fiberglass - Vertical Tee - 3" Depth</b>						
 6" Wide		6.00	7.50	9.00		E
9" Wide		6.40	8.00	9.60		E
12" Wide		6.75	8.44	10.13		E
18" Wide		7.50	9.38	11.25		E
24" Wide		8.25	10.31	12.38		E
30" Wide		9.00	11.25	13.50		E
36" Wide		9.75	12.19	14.63		E






Section 2 - Conduit, Raceways, Fittings & Related Items









Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Fiberglass Tray 4" Depth</b>						
<b>Fiberglass Cable Tray- 6" Rung Spacing - 4" Depth</b>						
	6" Wide		17.00	21.25	25.50	C
	9" Wide		18.00	22.50	27.00	C
	12" Wide		19.00	23.75	28.50	C
	18" Wide		20.00	25.00	30.00	C
	24" Wide		22.00	27.50	33.00	C
	30" Wide		24.00	30.00	36.00	C
	36" Wide		26.00	32.50	39.00	C
<b>Fiberglass Cable Tray- 9" Rung Spacing - 4" Depth</b>						
	6" Wide		16.25	20.31	24.38	C
	9" Wide		17.00	21.25	25.50	C
	12" Wide		17.90	22.38	26.85	C
	18" Wide		18.70	23.38	28.05	C
	24" Wide		20.00	25.00	30.00	C
	30" Wide		21.60	27.00	32.40	C
	36" Wide		23.20	29.00	34.80	C
<b>Fiberglass Cable Tray- 12" Rung Spacing - 4" Depth</b>						
	6" Wide		15.50	19.38	23.25	C
	9" Wide		16.00	20.00	24.00	C
	12" Wide		16.80	21.00	25.20	C
	18" Wide		17.40	21.75	26.10	C
	24" Wide		18.00	22.50	27.00	C
	30" Wide		19.20	24.00	28.80	C
	36" Wide		20.40	25.50	30.60	C
<b>Fiberglass Cable Tray- 18" Rung Spacing - 4" Depth</b>						
	6" Wide		15.00	18.75	22.50	C
	9" Wide		15.60	19.50	23.40	C
	12" Wide		16.40	20.50	24.60	C
	18" Wide		16.80	21.00	25.20	C
	24" Wide		17.50	21.88	26.25	C
	30" Wide		18.60	23.25	27.90	C
	36" Wide		19.20	24.00	28.80	C
<b>Fiberglass - 45 Degree Elbow - 4" Depth</b>						
	6" Wide		2.10	2.63	3.15	E
	9" Wide		2.30	2.88	3.45	E
	12" Wide		2.60	3.25	3.90	E
	18" Wide		2.90	3.63	4.35	E
	24" Wide		3.20	4.00	4.80	E
	30" Wide		3.70	4.63	5.55	E
	36" Wide		4.20	5.25	6.30	E
<b>Fiberglass - 90 Degree Elbow - 4" Depth</b>						
	6" Wide		3.10	3.88	4.65	E
	9" Wide		3.45	4.31	5.18	E
	12" Wide		3.80	4.75	5.70	E
	18" Wide		4.20	5.25	6.30	E
	24" Wide		4.80	6.00	7.20	E
	30" Wide		5.50	6.88	8.25	E
	36" Wide		6.20	7.75	9.30	E
<b>Fiberglass - Tee - 4" Depth</b>						
	6" Wide		5.50	6.88	8.25	E
	9" Wide		5.90	7.38	8.85	E
	12" Wide		6.20	7.75	9.30	E
	18" Wide		6.90	8.63	10.35	E
	24" Wide		7.60	9.50	11.40	E
	30" Wide		8.30	10.38	12.45	E
	36" Wide		9.00	11.25	13.50	E
<b>Fiberglass - Cross - 4" Depth</b>						
	6" Wide		7.30	9.13	10.95	E
	9" Wide		7.60	9.50	11.40	E
	12" Wide		8.30	10.38	12.45	E
	18" Wide		9.00	11.25	13.50	E
	24" Wide		9.70	12.13	14.55	E
	30" Wide		10.40	13.00	15.60	E
	36" Wide		11.00	13.75	16.50	E

Section 2 - Conduit, Raceways, Fittings & Related Items

2





Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Fiberglass - Reducer - 4" Depth</b>						
 6" Wide		2.10	2.63	3.15		E
9" Wide		2.30	2.88	3.45		E
12" Wide		2.60	3.25	3.90		E
18" Wide		2.90	3.63	4.35		E
24" Wide		3.20	4.00	4.80		E
30" Wide		3.70	4.63	5.55		E
36" Wide		4.10	5.13	6.15		E
<b>Fiberglass - Vertical 45 Degree Elbow - 4" Depth</b>						
 6" Wide		2.40	3.00	3.60		E
9" Wide		2.60	3.25	3.90		E
12" Wide		3.00	3.75	4.50		E
18" Wide		3.30	4.13	4.95		E
24" Wide		3.70	4.63	5.55		E
30" Wide		4.30	5.38	6.45		E
36" Wide		4.70	5.88	7.05		E
<b>Fiberglass - Vertical 90 Degree Elbow - 4" Depth</b>						
 6" Wide		3.70	4.63	5.55		E
9" Wide		4.20	5.25	6.30		E
12" Wide		4.60	5.75	6.90		E
18" Wide		5.00	6.25	7.50		E
24" Wide		5.75	7.19	8.63		E
30" Wide		6.70	8.38	10.05		E
36" Wide		7.50	9.38	11.25		E
<b>Fiberglass - Vertical Tee - 4" Depth</b>						
6" Wide		6.90	8.63	10.35		E
9" Wide		7.40	9.25	11.10		E
12" Wide		7.80	9.75	11.70		E
18" Wide		8.60	10.75	12.90		E
24" Wide		9.50	11.88	14.25		E
30" Wide		10.40	13.00	15.60		E
36" Wide		11.20	14.00	16.80		E

Section 2 - Conduit, Raceways, Fittings & Related Items


Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Fiberglass Tray 6" Depth</b>						
<b>Fiberglass Cable Tray - 6" Rung Spacing - 6" Depth</b>						
		22.00	27.50	33.00		C
		23.00	28.75	34.50		C
		24.00	30.00	36.00		C
		25.00	31.25	37.50		C
		27.00	33.75	40.50		C
		29.00	36.25	43.50		C
		31.00	38.75	46.50		C
<b>Fiberglass Cable Tray - 9" Rung Spacing - 6" Depth</b>						
		21.25	26.56	31.88		C
		22.00	27.50	33.00		C
		22.80	28.50	34.20		C
		23.60	29.50	35.40		C
		24.90	31.13	37.35		C
		26.50	33.13	39.75		C
		28.10	35.13	42.15		C
<b>Fiberglass Cable Tray - 12" Rung Spacing - 6" Depth</b>						
		20.50	25.63	30.75		C
		21.00	26.25	31.50		C
		21.60	27.00	32.40		C
		22.20	27.75	33.30		C
		22.80	28.50	34.20		C
		24.00	30.00	36.00		C
		25.20	31.50	37.80		C
<b>Fiberglass Cable Tray - 18" Rung Spacing - 6" Depth</b>						
		19.80	24.75	29.70		C
		20.40	25.50	30.60		C
		21.00	26.25	31.50		C
		21.50	26.88	32.25		C
		22.00	27.50	33.00		C
		23.40	29.25	35.10		C
		24.00	30.00	36.00		C
<b>Fiberglass - 45 Degree Elbow - 6" Depth</b>						
		2.40	3.00	3.60		E
		2.70	3.38	4.05		E
		3.00	3.75	4.50		E
		3.30	4.13	4.95		E
		3.70	4.63	5.55		E
		4.30	5.38	6.45		E
		4.80	6.00	7.20		E
<b>Fiberglass - 90 Degree Elbow - 6" Depth</b>						
		3.60	4.50	5.40		E
		4.00	5.00	6.00		E
		4.40	5.50	6.60		E
		4.80	6.00	7.20		E
		5.50	6.88	8.25		E
		6.30	7.88	9.45		E
		7.20	9.00	10.80		E
<b>Fiberglass - Tee - 6" Depth</b>						
		6.30	7.88	9.45		E
		6.70	8.38	10.05		E
		7.10	8.88	10.65		E
		7.90	9.88	11.85		E
		8.70	10.88	13.05		E
		9.50	11.88	14.25		E
		10.40	13.00	15.60		E
<b>Fiberglass - Cross - 6" Depth</b>						
		8.40	10.50	12.60		E
		8.80	11.00	13.20		E
		9.50	11.88	14.25		E
		10.40	13.00	15.60		E
		11.20	14.00	16.80		E
		12.00	15.00	18.00		E
		12.70	15.88	19.05		E

Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Fiberglass - Reducer - 6" Depth</b>						
 6" Wide		2.40	3.00	3.60		E
9" Wide		2.60	3.25	3.90		E
12" Wide		3.00	3.75	4.50		E
18" Wide		3.40	4.25	5.10		E
24" Wide		3.70	4.63	5.55		E
30" Wide		4.30	5.38	6.45		E
36" Wide		4.70	5.88	7.05		E
<b>Fiberglass - Vertical 45 Degree Elbow - 6" Depth</b>						
 6" Wide		2.80	3.50	4.20		E
9" Wide		3.00	3.75	4.50		E
12" Wide		3.50	4.38	5.25		E
18" Wide		3.80	4.75	5.70		E
24" Wide		4.30	5.38	6.45		E
30" Wide		5.00	6.25	7.50		E
36" Wide		5.40	6.75	8.10		E
<b>Fiberglass - Vertical 90 Degree Elbow - 6" Depth</b>						
 6" Wide		4.30	5.38	6.45		E
9" Wide		4.80	6.00	7.20		E
12" Wide		5.30	6.63	7.95		E
18" Wide		5.80	7.25	8.70		E
24" Wide		6.60	8.25	9.90		E
30" Wide		7.70	9.63	11.55		E
36" Wide		8.60	10.75	12.90		E
<b>Fiberglass - Vertical Tee - 6" Depth</b>						
 6" Wide		7.90	9.88	11.85		E
9" Wide		8.50	10.63	12.75		E
12" Wide		9.00	11.25	13.50		E
18" Wide		9.90	12.38	14.85		E
24" Wide		10.90	13.63	16.35		E
30" Wide		12.00	15.00	18.00		E
36" Wide		12.90	16.13	19.35		E






## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Fiberglass Cable Tray Fittings &amp; Accessories</b>						
 <b>Combination Hold-Down Clamp and Expansion Guide</b>						
Hold Down Clamp Pair		0.8	1.00	1.20		E
<b>Fiberglass Cable Tray - Solid Covers</b>						
6" Wide		4.00	5.00	6.00		C
9" Wide		4.50	5.63	6.75		C
12" Wide		5.50	6.88	8.25		C
18" Wide		7.00	8.75	10.50		C
24" Wide		8.50	10.63	12.75		C
30" Wide		10.50	13.13	15.75		C
36" Wide		12.50	15.63	18.75		C
<b>Fiberglass Cable Tray - Solid Covers Clamps (Per Pair)</b>						
6" Wide		0.50	0.63	0.75		E
9" Wide		0.55	0.69	0.83		E
12" Wide		0.60	0.75	0.90		E
18" Wide		0.65	0.81	0.98		E
24" Wide		0.70	0.88	1.05		E
30" Wide		0.75	0.94	1.13		E
36" Wide		0.80	1.00	1.20		E
<b>Fiberglass - 45 Degree Elbow - Solid Covers</b>						
6" Wide		0.25	0.31	0.38		E
9" Wide		0.30	0.38	0.45		E
12" Wide		0.35	0.44	0.53		E
18" Wide		0.40	0.50	0.60		E
24" Wide		0.50	0.63	0.75		E
30" Wide		0.60	0.75	0.90		E
36" Wide		0.70	0.88	1.05		E
<b>Fiberglass - 90 Degree Elbow - Solid Covers</b>						
6" Wide		0.25	0.31	0.38		E
9" Wide		0.30	0.38	0.45		E
12" Wide		0.35	0.44	0.53		E
18" Wide		0.40	0.50	0.60		E
24" Wide		0.50	0.63	0.75		E
30" Wide		0.60	0.75	0.90		E
36" Wide		0.70	0.88	1.05		E
<b>Fiberglass - Tee - Solid Covers</b>						
6" Wide		0.35	0.44	0.53		E
9" Wide		0.40	0.50	0.60		E
12" Wide		0.45	0.56	0.68		E
18" Wide		0.50	0.63	0.75		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.70	0.88	1.05		E
36" Wide		0.80	1.00	1.20		E
<b>Fiberglass - Cross - Solid Covers</b>						
6" Wide		0.45	0.56	0.68		E
9" Wide		0.50	0.63	0.75		E
12" Wide		0.55	0.69	0.83		E
18" Wide		0.60	0.75	0.90		E
24" Wide		0.70	0.88	1.05		E
30" Wide		0.80	1.00	1.20		E
36" Wide		0.90	1.13	1.35		E
<b>Fiberglass - Reducer - Solid Covers</b>						
6" Wide		0.25	0.31	0.38		E
9" Wide		0.30	0.38	0.45		E
12" Wide		0.35	0.44	0.53		E
18" Wide		0.40	0.50	0.60		E
24" Wide		0.50	0.63	0.75		E
30" Wide		0.60	0.75	0.90		E
36" Wide		0.70	0.88	1.05		E
<b>Fiberglass - Vertical 45 Degree Elbow - Solid Covers</b>						
6" Wide		0.35	0.44	0.53		E
9" Wide		0.40	0.50	0.60		E
12" Wide		0.45	0.56	0.68		E
18" Wide		0.50	0.63	0.75		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.70	0.88	1.05		E
36" Wide		0.80	1.00	1.20		E










## Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Fiberglass - Vertical 90 Degree Elbow - Solid Covers</b>						
6" Wide		0.35	0.44	0.53		E
9" Wide		0.40	0.50	0.60		E
12" Wide		0.45	0.56	0.68		E
18" Wide		0.50	0.63	0.75		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.70	0.88	1.05		E
36" Wide		0.80	1.00	1.20		E
<b>Fiberglass - Vertical Tee - Solid Covers</b>						
6" Wide		0.45	0.56	0.68		E
9" Wide		0.50	0.63	0.75		E
12" Wide		0.55	0.69	0.83		E
18" Wide		0.60	0.75	0.90		E
24" Wide		0.70	0.88	1.05		E
30" Wide		0.80	1.00	1.20		E
36" Wide		0.90	1.13	1.35		E
<b>Fiberglass - End Plates</b>						
6" Wide		0.40	0.50	0.60		E
9" Wide		0.45	0.56	0.68		E
12" Wide		0.50	0.63	0.75		E
18" Wide		0.55	0.69	0.83		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.65	0.81	0.98		E
36" Wide		0.70	0.88	1.05		E
<b>Fiberglass - Ladder Drop-Outs</b>						
6" Wide		0.40	0.50	0.60		E
9" Wide		0.45	0.56	0.68		E
12" Wide		0.50	0.63	0.75		E
18" Wide		0.55	0.69	0.83		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.65	0.81	0.98		E
36" Wide		0.70	0.88	1.05		E
<b>Fiberglass - Splice Plates Pair</b>						
6" Wide		0.80	1.00	1.20		E
9" Wide		0.85	1.06	1.28		E
12" Wide		0.90	1.13	1.35		E
18" Wide		0.95	1.19	1.43		E
24" Wide		1.00	1.25	1.50		E
30" Wide		1.10	1.38	1.65		E
36" Wide		1.20	1.50	1.80		E
<b>Fiberglass Cable Tray Barrier Strips</b>						
3" Depth		6.00	7.50	9.00		C
4" Depth		8.00	10.00	12.00		C
6" Depth		10.00	12.50	15.00		C
<b>Fiberglass Cable Tray Fitting Barrier Strips</b>						
3" Depth		0.60	0.75	0.90		E
4" Depth		0.65	0.81	0.98		E
6" Depth		0.70	0.88	1.05		E
<b>Fiberglass Conduit to Cable Tray Adapters</b>						
1/2" Conduit		0.50	0.63	0.75		E
3/4" Conduit		0.55	0.69	0.83		E
1" Conduit		0.60	0.75	0.90		E
1 1/4" Conduit		0.65	0.81	0.98		E
1 1/2" Conduit		0.70	0.88	1.05		E
2" Conduit		0.75	0.94	1.13		E
2 1/2" Conduit		0.80	1.00	1.20		E
3" Conduit		0.90	1.13	1.35		E
3 1/2" Conduit		1.00	1.25	1.50		E
4" Conduit		1.20	1.50	1.80		E




Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Solid/Ventilated Steel Tray 3" Depth</b>						
<b>Solid/Ventilated Steel - Cable Tray - 3" Depth</b>						
						
6" Wide		15.00	18.75	22.50		C
9" Wide		16.00	20.00	24.00		C
12" Wide		18.00	22.50	27.00		C
18" Wide		21.00	26.25	31.50		C
24" Wide		26.00	32.50	39.00		C
30" Wide		31.00	38.75	46.50		C
36" Wide		36.00	45.00	54.00		C
<b>Solid/Ventilated Steel - 45 Degree Elbow - 3" Depth</b>						
						
6" Wide		1.80	2.25	2.70		E
9" Wide		2.00	2.50	3.00		E
12" Wide		2.25	2.81	3.38		E
18" Wide		2.50	3.13	3.75		E
24" Wide		3.00	3.75	4.50		E
30" Wide		3.50	4.38	5.25		E
36" Wide		4.00	5.00	6.00		E
<b>Solid/Ventilated Steel - 90 Degree Elbow - 3" Depth</b>						
						
6" Wide		2.70	3.38	4.05		E
9" Wide		3.00	3.75	4.50		E
12" Wide		3.30	4.13	4.95		E
18" Wide		3.75	4.69	5.63		E
24" Wide		4.50	5.63	6.75		E
30" Wide		5.35	6.69	8.03		E
36" Wide		6.75	8.44	10.13		E
<b>Solid/Ventilated Steel - Tee - 3" Depth</b>						
						
6" Wide		4.80	6.00	7.20		E
9" Wide		5.10	6.38	7.65		E
12" Wide		5.40	6.75	8.10		E
18" Wide		7.00	8.75	10.50		E
24" Wide		8.00	10.00	12.00		E
30" Wide		10.00	12.50	15.00		E
36" Wide		12.00	15.00	18.00		E
<b>Solid/Ventilated Steel - Cross - 3" Depth</b>						
						
6" Wide		6.30	7.88	9.45		E
9" Wide		6.60	8.25	9.90		E
12" Wide		7.20	9.00	10.80		E
18" Wide		8.00	10.00	12.00		E
24" Wide		9.00	11.25	13.50		E
30" Wide		11.00	13.75	16.50		E
36" Wide		13.00	16.25	19.50		E
<b>Solid/Ventilated Steel - Reducer - 3" Depth</b>						
						
6" Wide		1.80	2.25	2.70		E
9" Wide		2.00	2.50	3.00		E
12" Wide		2.25	2.81	3.38		E
18" Wide		2.50	3.13	3.75		E
24" Wide		3.00	3.75	4.50		E
30" Wide		3.50	4.38	5.25		E
36" Wide		4.10	5.13	6.15		E
<b>Solid/Ventilated Steel - Vertical 45 Degree Elbow - 3" Depth</b>						
						
6" Wide		2.10	2.63	3.15		E
9" Wide		2.30	2.88	3.45		E
12" Wide		2.60	3.25	3.90		E
18" Wide		3.00	3.75	4.50		E
24" Wide		3.50	4.38	5.25		E
30" Wide		4.00	5.00	6.00		E
36" Wide		4.60	5.75	6.90		E
<b>Solid/Ventilated Steel - Vertical 90 Degree Elbow - 3" Depth</b>						
						
6" Wide		3.25	4.06	4.88		E
9" Wide		3.60	4.50	5.40		E
12" Wide		4.00	5.00	6.00		E
18" Wide		4.50	5.63	6.75		E
24" Wide		5.20	6.50	7.80		E
30" Wide		6.20	7.75	9.30		E
36" Wide		7.80	9.75	11.70		E
<b>Solid/Ventilated Steel - Vertical Tee - 3" Depth</b>						
						
6" Wide		6.00	7.50	9.00		E
9" Wide		6.40	8.00	9.60		E
12" Wide		6.75	8.44	10.13		E
18" Wide		8.00	10.00	12.00		E
24" Wide		9.20	11.50	13.80		E
30" Wide		11.50	14.38	17.25		E
36" Wide		13.50	16.88	20.25		E










Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Solid/Ventilated Steel Tray 4" Depth</b>						
<b>Solid/Ventilated Steel- Cable Tray - 4" Depth</b>						
 6" Wide		18.00	22.50	27.00		C
9" Wide		19.00	23.75	28.50		C
12" Wide		22.00	27.50	33.00		C
18" Wide		25.00	31.25	37.50		C
24" Wide		31.00	38.75	46.50		C
30" Wide		37.00	46.25	55.50		C
36" Wide		43.00	53.75	64.50		C
<b>Solid/Ventilated Steel - 45 Degree Elbow - 4" Depth</b>						
6" Wide		2.10	2.63	3.15		E
9" Wide		2.30	2.88	3.45		E
12" Wide		2.60	3.25	3.90		E
18" Wide		2.90	3.63	4.35		E
24" Wide		3.50	4.38	5.25		E
30" Wide		4.00	5.00	6.00		E
36" Wide		4.60	5.75	6.90		E
<b>Solid/Ventilated Steel - 90 Degree Elbow - 4" Depth</b>						
6" Wide		3.10	3.88	4.65		E
9" Wide		3.50	4.38	5.25		E
12" Wide		3.80	4.75	5.70		E
18" Wide		4.30	5.38	6.45		E
24" Wide		5.20	6.50	7.80		E
30" Wide		6.20	7.75	9.30		E
36" Wide		7.80	9.75	11.70		E
<b>Solid/Ventilated Steel - Tee - 4" Depth</b>						
6" Wide		5.50	6.88	8.25		E
9" Wide		5.90	7.38	8.85		E
12" Wide		6.20	7.75	9.30		E
18" Wide		8.00	10.00	12.00		E
24" Wide		9.20	11.50	13.80		E
30" Wide		11.50	14.38	17.25		E
36" Wide		13.80	17.25	20.70		E
<b>Solid/Ventilated Steel - Cross - 4" Depth</b>						
6" Wide		7.20	9.00	10.80		E
9" Wide		7.60	9.50	11.40		E
12" Wide		8.30	10.38	12.45		E
18" Wide		9.20	11.50	13.80		E
24" Wide		10.40	13.00	15.60		E
30" Wide		12.70	15.88	19.05		E
36" Wide		15.00	18.75	22.50		E
<b>Solid/Ventilated Steel - Reducer - 4" Depth</b>						
6" Wide		2.10	2.63	3.15		E
9" Wide		2.30	2.88	3.45		E
12" Wide		2.60	3.25	3.90		E
18" Wide		2.90	3.63	4.35		E
24" Wide		3.50	4.38	5.25		E
30" Wide		4.00	5.00	6.00		E
36" Wide		4.60	5.75	6.90		E
<b>Solid/Ventilated Steel - Vertical 45 Degree Elbow - 4" Depth</b>						
6" Wide		2.40	3.00	3.60		E
9" Wide		2.60	3.25	3.90		E
12" Wide		3.00	3.75	4.50		E
18" Wide		3.50	4.38	5.25		E
24" Wide		4.00	5.00	6.00		E
30" Wide		4.60	5.75	6.90		E
36" Wide		5.30	6.63	7.95		E
<b>Solid/Ventilated Steel - Vertical 90 Degree Elbow - 4" Depth</b>						
6" Wide		3.70	4.63	5.55		E
9" Wide		4.10	5.13	6.15		E
12" Wide		4.60	5.75	6.90		E
18" Wide		5.20	6.50	7.80		E
24" Wide		6.00	7.50	9.00		E
30" Wide		7.10	8.88	10.65		E
36" Wide		9.00	11.25	13.50		E
<b>Solid/Ventilated Steel - Vertical Tee - 4" Depth</b>						
6" Wide		6.90	8.63	10.35		E
9" Wide		7.40	9.25	11.10		E
12" Wide		7.80	9.75	11.70		E
18" Wide		9.20	11.50	13.80		E
24" Wide		10.60	13.25	15.90		E
30" Wide		13.20	16.50	19.80		E
36" Wide		15.50	19.38	23.25		E




## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Solid/Ventilated Steel Tray 6" Depth</b>						
<b>Solid/Ventilated Steel - Cable Tray - 6" Depth</b>						
	6" Wide					C
	9" Wide	23.00	28.75	34.50		C
	12" Wide	25.00	31.25	37.50		C
	18" Wide	29.00	36.25	43.50		C
	24" Wide	33.00	41.25	49.50		C
	30" Wide	40.00	50.00	60.00		C
	36" Wide	48.00	60.00	72.00		C
		56.00	70.00	84.00		C
<b>Solid/Ventilated Steel - 45 Degree Elbow - 6" Depth</b>						
	6" Wide	2.40	3.00	3.60		E
	9" Wide	2.60	3.25	3.90		E
	12" Wide	3.00	3.75	4.50		E
	18" Wide	3.30	4.13	4.95		E
	24" Wide	4.00	5.00	6.00		E
	30" Wide	4.60	5.75	6.90		E
	36" Wide	5.30	6.63	7.95		E
<b>Solid/Ventilated Steel - 90 Degree Elbow - 6" Depth</b>						
	6" Wide	3.60	4.50	5.40		E
	9" Wide	4.00	5.00	6.00		E
	12" Wide	4.40	5.50	6.60		E
	18" Wide	4.90	6.13	7.35		E
	24" Wide	6.00	7.50	9.00		E
	30" Wide	7.10	8.88	10.65		E
	36" Wide	9.00	11.25	13.50		E
<b>Solid/Ventilated Steel - Tee - 6" Depth</b>						
	6" Wide	6.30	7.88	9.45		E
	9" Wide	6.80	8.50	10.20		E
	12" Wide	7.10	8.88	10.65		E
	18" Wide	9.20	11.50	13.80		E
	24" Wide	10.60	13.25	15.90		E
	30" Wide	13.20	16.50	19.80		E
	36" Wide	15.90	19.88	23.85		E
<b>Solid/Ventilated Steel - Cross - 6" Depth</b>						
	6" Wide	8.30	10.38	12.45		E
	9" Wide	8.70	10.88	13.05		E
	12" Wide	9.50	11.88	14.25		E
	18" Wide	10.60	13.25	15.90		E
	24" Wide	12.00	15.00	18.00		E
	30" Wide	14.60	18.25	21.90		E
	36" Wide	17.30	21.63	25.95		E
<b>Solid/Ventilated Steel - Reducer - 6" Depth</b>						
	6" Wide	2.40	3.00	3.60		E
	9" Wide	2.60	3.25	3.90		E
	12" Wide	3.00	3.75	4.50		E
	18" Wide	3.30	4.13	4.95		E
	24" Wide	4.00	5.00	6.00		E
	30" Wide	4.60	5.75	6.90		E
	36" Wide	5.30	6.63	7.95		E
<b>Solid/Ventilated Steel - Vertical 45 Degree Elbow - 6" Depth</b>						
	6" Wide	2.80	3.50	4.20		E
	9" Wide	3.00	3.75	4.50		E
	12" Wide	3.50	4.38	5.25		E
	18" Wide	4.00	5.00	6.00		E
	24" Wide	4.60	5.75	6.90		E
	30" Wide	5.30	6.63	7.95		E
	36" Wide	6.10	7.63	9.15		E
<b>Solid/Ventilated Steel - Vertical 90 Degree Elbow - 6" Depth</b>						
	6" Wide	4.30	5.38	6.45		E
	9" Wide	4.70	5.88	7.05		E
	12" Wide	5.30	6.63	7.95		E
	18" Wide	6.00	7.50	9.00		E
	24" Wide	6.90	8.63	10.35		E
	30" Wide	8.20	10.25	12.30		E
	36" Wide	10.40	13.00	15.60		E
<b>Solid/Ventilated Steel - Vertical Tee - 6" Depth</b>						
	6" Wide	7.90	9.88	11.85		E
	9" Wide	8.50	10.63	12.75		E
	12" Wide	9.00	11.25	13.50		E
	18" Wide	10.60	13.25	15.90		E
	24" Wide	12.20	15.25	18.30		E
	30" Wide	15.20	19.00	22.80		E
	36" Wide	17.80	22.25	26.70		E

## Section 2 - Conduit, Raceways, Fittings & Related Items

2










Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Solid/Ventilated Steel Cable Tray Fittings &amp; Accessories</b>						
 <b>Seismic Hold-Down Clamp and Expansion Guide</b>						
Hold Down Clamp Pair		1.00	1.25	1.50		E
<b>Solid/Ventilated Steel Cable Tray - Solid Covers</b>						
6" Wide		3.75	4.69	5.63		C
9" Wide		4.25	5.31	6.38		C
12" Wide		5.25	6.56	7.88		C
18" Wide		6.75	8.44	10.13		C
24" Wide		8.25	10.31	12.38		C
30" Wide		10.25	12.81	15.38		C
36" Wide		12.25	15.31	18.38		C
<b>Solid/Ventilated Steel Cable Tray - Solid Cver Clamps (Per Pair)</b>						
6" Wide		0.50	0.63	0.75		E
9" Wide		0.55	0.69	0.83		E
12" Wide		0.60	0.75	0.90		E
18" Wide		0.65	0.81	0.98		E
24" Wide		0.70	0.88	1.05		E
30" Wide		0.75	0.94	1.13		E
36" Wide		0.80	1.00	1.20		E
<b>Solid/Ventilated Steel - 45 Degree Elbow - Solid Covers</b>						
6" Wide		0.25	0.31	0.38		E
9" Wide		0.30	0.38	0.45		E
12" Wide		0.35	0.44	0.53		E
18" Wide		0.40	0.50	0.60		E
24" Wide		0.50	0.63	0.75		E
30" Wide		0.60	0.75	0.90		E
36" Wide		0.70	0.88	1.05		E
<b>Solid/Ventilated Steel - 90 Degree Elbow - Solid Covers</b>						
6" Wide		0.25	0.31	0.38		E
9" Wide		0.30	0.38	0.45		E
12" Wide		0.35	0.44	0.53		E
18" Wide		0.40	0.50	0.60		E
24" Wide		0.50	0.63	0.75		E
30" Wide		0.60	0.75	0.90		E
36" Wide		0.70	0.88	1.05		E
<b>Solid/Ventilated Steel - Tee - Solid Covers</b>						
6" Wide		0.35	0.44	0.53		E
9" Wide		0.40	0.50	0.60		E
12" Wide		0.45	0.56	0.68		E
18" Wide		0.50	0.63	0.75		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.70	0.88	1.05		E
36" Wide		0.80	1.00	1.20		E
<b>Solid/Ventilated Steel - Cross - Solid Covers</b>						
6" Wide		0.45	0.56	0.68		E
9" Wide		0.50	0.63	0.75		E
12" Wide		0.55	0.69	0.83		E
18" Wide		0.60	0.75	0.90		E
24" Wide		0.70	0.88	1.05		E
30" Wide		0.80	1.00	1.20		E
36" Wide		0.90	1.13	1.35		E
<b>Solid/Ventilated Steel - Reducer - Solid Covers</b>						
6" Wide		0.25	0.31	0.38		E
9" Wide		0.30	0.38	0.45		E
12" Wide		0.35	0.44	0.53		E
18" Wide		0.40	0.50	0.60		E
24" Wide		0.50	0.63	0.75		E
30" Wide		0.60	0.75	0.90		E
36" Wide		0.70	0.88	1.05		E
<b>Solid/Ventilated Steel - Vertical 45 Degree Elbow - Solid Covers</b>						
6" Wide		0.35	0.44	0.53		E
9" Wide		0.40	0.50	0.60		E
12" Wide		0.45	0.56	0.68		E
18" Wide		0.50	0.63	0.75		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.70	0.88	1.05		E
36" Wide		0.80	1.00	1.20		E
<b>Solid/Ventilated Steel - Vertical 90 Degree Elbow - Solid Covers</b>						
6" Wide		0.35	0.44	0.53		E
9" Wide		0.40	0.50	0.60		E
12" Wide		0.45	0.56	0.68		E
18" Wide		0.50	0.63	0.75		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.70	0.88	1.05		E
36" Wide		0.80	1.00	1.20		E

## Section 2 - Conduit, Raceways, Fittings & Related Items


Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Solid/Ventilated Steel - Vertical Tee - Solid Covers</b>						
6" Wide		0.45	0.56	0.68		E
9" Wide		0.50	0.63	0.75		E
12" Wide		0.55	0.69	0.83		E
18" Wide		0.60	0.75	0.90		E
24" Wide		0.70	0.88	1.05		E
30" Wide		0.80	1.00	1.20		E
36" Wide		0.90	1.13	1.35		E
<b>Solid/Ventilated Steel - Enclosure Connectors</b>						
6" Wide		2.00	2.50	3.00		E
9" Wide		2.25	2.81	3.38		E
12" Wide		2.60	3.25	3.90		E
18" Wide		3.00	3.75	4.50		E
24" Wide		3.50	4.38	5.25		E
30" Wide		4.25	5.31	6.38		E
36" Wide		5.00	6.25	7.50		E
<b>Solid/Ventilated Steel - End Plates</b>						
6" Wide		0.40	0.50	0.60		E
9" Wide		0.45	0.56	0.68		E
12" Wide		0.50	0.63	0.75		E
18" Wide		0.55	0.69	0.83		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.65	0.81	0.98		E
36" Wide		0.70	0.88	1.05		E
<b>Solid/Ventilated Steel - Ladder Drop-Outs</b>						
6" Wide		0.40	0.50	0.60		E
9" Wide		0.45	0.56	0.68		E
12" Wide		0.50	0.63	0.75		E
18" Wide		0.55	0.69	0.83		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.65	0.81	0.98		E
36" Wide		0.70	0.88	1.05		E
<b>Solid/Ventilated Steel - Splice Plates Pair</b>						
6" Wide		0.80	1.00	1.20		E
9" Wide		0.85	1.06	1.28		E
12" Wide		0.90	1.13	1.35		E
18" Wide		0.95	1.19	1.43		E
24" Wide		1.00	1.25	1.50		E
30" Wide		1.10	1.38	1.65		E
36" Wide		1.20	1.50	1.80		E
<b>Solid/Ventilated Steel Cable Tray Barrier Strips</b>						
3" Depth		6.00	7.50	9.00		C
4" Depth		8.00	10.00	12.00		C
6" Depth		10.00	12.50	15.00		C
<b>Solid/Ventilated Steel Cable Tray Fitting Barrier Strips</b>						
3" Depth		0.60	0.75	0.90		E
4" Depth		0.65	0.81	0.98		E
6" Depth		0.70	0.88	1.05		E
<b>Solid/Ventilated Steel Conduit to Cable Tray Adapters</b>						
1/2" Conduit		0.50	0.63	0.75		E
3/4" Conduit		0.55	0.69	0.83		E
1" Conduit		0.60	0.75	0.90		E
1 1/4" Conduit		0.65	0.81	0.98		E
1 1/2" Conduit		0.70	0.88	1.05		E
2" Conduit		0.75	0.94	1.13		E
2 1/2" Conduit		0.80	1.00	1.20		E
3" Conduit		0.90	1.13	1.35		E
3 1/2" Conduit		1.00	1.25	1.50		E
4" Conduit		1.20	1.50	1.80		E
<b>Bonding Jumpers</b>						
#1/0 Copper X 15" Long		0.60	0.75	0.90		E
#4/0 Copper X 15" Long		0.80	1.00	1.20		E
#250 Copper X 15" Long		1.00	1.25	1.50		E

Section 2 - Conduit, Raceways, Fittings & Related Items

2










Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Solid/Ventilated Aluminum Tray 3" Depth</b>						
<b>Solid/Ventilated Aluminum - Cable Tray - 3" Depth</b>						
						
6" Wide		11.30	14.13	16.95		C
9" Wide		12.00	15.00	18.00		C
12" Wide		13.50	16.88	20.25		C
18" Wide		15.80	19.75	23.70		C
24" Wide		19.50	24.38	29.25		C
30" Wide		23.30	29.13	34.95		C
36" Wide		27.00	33.75	40.50		C
<b>Solid/Ventilated Aluminum - 45 Degree Elbow - 3" Depth</b>						
						
6" Wide		1.40	1.75	2.10		E
9" Wide		1.50	1.88	2.25		E
12" Wide		1.70	2.13	2.55		E
18" Wide		1.90	2.38	2.85		E
24" Wide		2.30	2.88	3.45		E
30" Wide		2.60	3.25	3.90		E
36" Wide		3.00	3.75	4.50		E
<b>Solid/Ventilated Aluminum - 90 Degree Elbow - 3" Depth</b>						
						
6" Wide		2.00	2.50	3.00		E
9" Wide		2.30	2.88	3.45		E
12" Wide		2.50	3.13	3.75		E
18" Wide		2.80	3.50	4.20		E
24" Wide		3.40	4.25	5.10		E
30" Wide		4.00	5.00	6.00		E
36" Wide		5.00	6.25	7.50		E
<b>Solid/Ventilated Aluminum - Tee - 3" Depth</b>						
						
6" Wide		3.60	4.50	5.40		E
9" Wide		3.80	4.75	5.70		E
12" Wide		4.00	5.00	6.00		E
18" Wide		5.30	6.63	7.95		E
24" Wide		6.00	7.50	9.00		E
30" Wide		7.50	9.38	11.25		E
36" Wide		9.00	11.25	13.50		E
<b>Solid/Ventilated Aluminum - Cross - 3" Depth</b>						
						
6" Wide		4.70	5.88	7.05		E
9" Wide		5.00	6.25	7.50		E
12" Wide		5.40	6.75	8.10		E
18" Wide		6.00	7.50	9.00		E
24" Wide		6.80	8.50	10.20		E
30" Wide		8.30	10.38	12.45		E
36" Wide		9.80	12.25	14.70		E
<b>Solid/Ventilated Aluminum - Reducer - 3" Depth</b>						
						
6" Wide		1.40	1.75	2.10		E
9" Wide		1.50	1.88	2.25		E
12" Wide		1.70	2.13	2.55		E
18" Wide		1.90	2.38	2.85		E
24" Wide		2.30	2.88	3.45		E
30" Wide		2.60	3.25	3.90		E
36" Wide		3.00	3.75	4.50		E
<b>Solid/Ventilated Aluminum - Vertical 45 Degree Elbow - 3" Depth</b>						
						
6" Wide		1.60	2.00	2.40		E
9" Wide		1.70	2.13	2.55		E
12" Wide		2.00	2.50	3.00		E
18" Wide		2.30	2.88	3.45		E
24" Wide		2.60	3.25	3.90		E
30" Wide		3.00	3.75	4.50		E
36" Wide		3.50	4.38	5.25		E
<b>Solid/Ventilated Aluminum - Vertical 90 Degree Elbow - 3" Depth</b>						
						
6" Wide		2.40	3.00	3.60		E
9" Wide		2.70	3.38	4.05		E
12" Wide		3.00	3.75	4.50		E
18" Wide		3.40	4.25	5.10		E
24" Wide		3.90	4.88	5.85		E
30" Wide		4.50	5.63	6.75		E
36" Wide		5.90	7.38	8.85		E
<b>Solid/Ventilated Aluminum - Vertical Tee - 3" Depth</b>						
						
6" Wide		4.50	5.63	6.75		E
9" Wide		4.80	6.00	7.20		E
12" Wide		5.00	6.25	7.50		E
18" Wide		6.00	7.50	9.00		E
24" Wide		6.90	8.63	10.35		E
30" Wide		8.60	10.75	12.90		E
36" Wide		10.00	12.50	15.00		E

## Section 2 - Conduit, Raceways, Fittings & Related Items


Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Solid/Ventilated Aluminum Tray 4" Depth</b>						
<b>Solid/Ventilated Aluminum - Cable Tray - 4" Depth</b>						
 6" Wide		13.50	16.88	20.25		C
9" Wide		14.30	17.88	21.45		C
12" Wide		16.50	20.63	24.75		C
18" Wide		18.80	23.50	28.20		C
24" Wide		23.30	29.13	34.95		C
30" Wide		27.80	34.75	41.70		C
36" Wide		32.30	40.38	48.45		C
<b>Solid/Ventilated Aluminum - 45 Degree Elbow - 4" Depth</b>						
6" Wide		1.60	2.00	2.40		E
9" Wide		1.70	2.13	2.55		E
12" Wide		2.00	2.50	3.00		E
18" Wide		2.20	2.75	3.30		E
24" Wide		2.60	3.25	3.90		E
30" Wide		3.00	3.75	4.50		E
36" Wide		3.50	4.38	5.25		E
<b>Solid/Ventilated Aluminum - 90 Degree Elbow - 4" Depth</b>						
6" Wide		2.30	2.88	3.45		E
9" Wide		2.60	3.25	3.90		E
12" Wide		2.90	3.63	4.35		E
18" Wide		3.20	4.00	4.80		E
24" Wide		3.90	4.88	5.85		E
30" Wide		4.70	5.88	7.05		E
36" Wide		5.90	7.38	8.85		E
<b>Solid/Ventilated Aluminum - Tee - 4" Depth</b>						
6" Wide		4.00	5.00	6.00		E
9" Wide		4.40	5.50	6.60		E
12" Wide		4.60	5.75	6.90		E
18" Wide		6.00	7.50	9.00		E
24" Wide		6.90	8.63	10.35		E
30" Wide		8.60	10.75	12.90		E
36" Wide		10.40	13.00	15.60		E
<b>Solid/Ventilated Aluminum - Cross - 4" Depth</b>						
6" Wide		5.40	6.75	8.10		E
9" Wide		5.70	7.13	8.55		E
12" Wide		6.20	7.75	9.30		E
18" Wide		6.90	8.63	10.35		E
24" Wide		7.80	9.75	11.70		E
30" Wide		9.50	11.88	14.25		E
36" Wide		11.30	14.13	16.95		E
<b>Solid/Ventilated Aluminum - Reducer - 4" Depth</b>						
6" Wide		1.60	2.00	2.40		E
9" Wide		1.70	2.13	2.55		E
12" Wide		2.00	2.50	3.00		E
18" Wide		2.20	2.75	3.30		E
24" Wide		2.60	3.25	3.90		E
30" Wide		3.00	3.75	4.50		E
36" Wide		3.50	4.38	5.25		E
<b>Solid/Ventilated Aluminum - Vertical 45 Degree Elbow - 4" Depth</b>						
6" Wide		1.80	2.25	2.70		E
9" Wide		2.00	2.50	3.00		E
12" Wide		2.30	2.88	3.45		E
18" Wide		2.60	3.25	3.90		E
24" Wide		3.00	3.75	4.50		E
30" Wide		3.50	4.38	5.25		E
36" Wide		4.00	5.00	6.00		E
<b>Solid/Ventilated Aluminum - Vertical 90 Degree Elbow - 4" Depth</b>						
6" Wide		2.80	3.50	4.20		E
9" Wide		3.00	3.75	4.50		E
12" Wide		3.50	4.38	5.25		E
18" Wide		3.90	4.88	5.85		E
24" Wide		4.50	5.63	6.75		E
30" Wide		5.30	6.63	7.95		E
36" Wide		6.80	8.50	10.20		E
<b>Solid/Ventilated Aluminum - Vertical Tee - 4" Depth</b>						
6" Wide		5.20	6.50	7.80		E
9" Wide		5.60	7.00	8.40		E
12" Wide		5.80	7.25	8.70		E
18" Wide		6.90	8.63	10.35		E
24" Wide		8.00	10.00	12.00		E
30" Wide		9.90	12.38	14.85		E
36" Wide		11.60	14.50	17.40		E

Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Solid/Ventilated Aluminum Tray 6" Depth</b>						
<b>Solid/Ventilated Aluminum - Cable Tray - 6" Depth</b>						
						
6" Wide		17.30	21.63	25.95		C
9" Wide		18.80	23.50	28.20		C
12" Wide		21.80	27.25	32.70		C
18" Wide		24.80	31.00	37.20		C
24" Wide		30.00	37.50	45.00		C
30" Wide		36.00	45.00	54.00		C
36" Wide		42.00	52.50	63.00		C
<b>Solid/Ventilated Aluminum - 45 Degree Elbow - 6" Depth</b>						
						
6" Wide		1.80	2.25	2.70		E
9" Wide		2.00	2.50	3.00		E
12" Wide		2.30	2.88	3.45		E
18" Wide		2.50	3.13	3.75		E
24" Wide		3.00	3.75	4.50		E
30" Wide		3.50	4.38	5.25		E
36" Wide		4.00	5.00	6.00		E
<b>Solid/Ventilated Aluminum - 90 Degree Elbow - 6" Depth</b>						
						
6" Wide		2.70	3.38	4.05		E
9" Wide		3.00	3.75	4.50		E
12" Wide		3.30	4.13	4.95		E
18" Wide		3.70	4.63	5.55		E
24" Wide		4.50	5.63	6.75		E
30" Wide		5.30	6.63	7.95		E
36" Wide		6.80	8.50	10.20		E
<b>Solid/Ventilated Aluminum - Tee - 6" Depth</b>						
						
6" Wide		4.70	5.88	7.05		E
9" Wide		5.10	6.38	7.65		E
12" Wide		5.30	6.63	7.95		E
18" Wide		6.90	8.63	10.35		E
24" Wide		8.00	10.00	12.00		E
30" Wide		9.90	12.38	14.85		E
36" Wide		12.00	15.00	18.00		E
<b>Solid/Ventilated Aluminum - Cross - 6" Depth</b>						
						
6" Wide		6.20	7.75	9.30		E
9" Wide		6.50	8.13	9.75		E
12" Wide		7.20	9.00	10.80		E
18" Wide		8.00	10.00	12.00		E
24" Wide		9.00	11.25	13.50		E
30" Wide		11.00	13.75	16.50		E
36" Wide		13.00	16.25	19.50		E
<b>Solid/Ventilated Aluminum - Reducer - 6" Depth</b>						
						
6" Wide		1.80	2.25	2.70		E
9" Wide		2.00	2.50	3.00		E
12" Wide		2.30	2.88	3.45		E
18" Wide		2.50	3.13	3.75		E
24" Wide		3.00	3.75	4.50		E
30" Wide		3.50	4.38	5.25		E
36" Wide		4.00	5.00	6.00		E
<b>Solid/Ventilated Aluminum - Vertical 45 Degree Elbow - 6" Depth</b>						
						
6" Wide		2.10	2.63	3.15		E
9" Wide		2.30	2.88	3.45		E
12" Wide		2.60	3.25	3.90		E
18" Wide		3.00	3.75	4.50		E
24" Wide		3.50	4.38	5.25		E
30" Wide		4.00	5.00	6.00		E
36" Wide		4.60	5.75	6.90		E
<b>Solid/Ventilated Aluminum - Vertical 90 Degree Elbow - 6" Depth</b>						
						
6" Wide		3.20	4.00	4.80		E
9" Wide		3.50	4.38	5.25		E
12" Wide		4.00	5.00	6.00		E
18" Wide		4.50	5.63	6.75		E
24" Wide		5.20	6.50	7.80		E
30" Wide		6.20	7.75	9.30		E
36" Wide		7.80	9.75	11.70		E
<b>Solid/Ventilated Aluminum - Vertical Tee - 6" Depth</b>						
						
6" Wide		5.90	7.38	8.85		E
9" Wide		6.40	8.00	9.60		E
12" Wide		6.80	8.50	10.20		E
18" Wide		8.00	10.00	12.00		E
24" Wide		9.20	11.50	13.80		E
30" Wide		11.40	14.25	17.10		E
36" Wide		13.40	16.75	20.10		E








## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Solid/Ventilated Aluminum Cable Tray Fittings &amp; Accessories</b>						
 <b>Seismic Hold-Down Clamp and Expansion Guide</b>						
Hold Down Clamp Pair		1.00	1.25	1.50		E
<b>Solid/Ventilated Aluminum Cable Tray - Solid Covers</b>						
6" Wide		3.50	4.38	5.25		C
9" Wide		4.00	5.00	6.00		C
12" Wide		5.00	6.25	7.50		C
18" Wide		6.50	8.13	9.75		C
24" Wide		8.00	10.00	12.00		C
30" Wide		10.00	12.50	15.00		C
36" Wide		12.00	15.00	18.00		C
<b>Solid/Ventilated Aluminum Cable Tray - Solid Cover Clamps (Per Pair)</b>						
6" Wide		0.50	0.63	0.75		E
9" Wide		0.55	0.69	0.83		E
12" Wide		0.60	0.75	0.90		E
18" Wide		0.65	0.81	0.98		E
24" Wide		0.70	0.88	1.05		E
30" Wide		0.75	0.94	1.13		E
36" Wide		0.80	1.00	1.20		E
<b>Solid/Ventilated Aluminum - 45 Degree Elbow - Solid Covers</b>						
6" Wide		0.25	0.31	0.38		E
9" Wide		0.30	0.38	0.45		E
12" Wide		0.35	0.44	0.53		E
18" Wide		0.40	0.50	0.60		E
24" Wide		0.50	0.63	0.75		E
30" Wide		0.60	0.75	0.90		E
36" Wide		0.70	0.88	1.05		E
<b>Solid/Ventilated Aluminum - 90 Degree Elbow - Solid Covers</b>						
6" Wide		0.25	0.31	0.38		E
9" Wide		0.30	0.38	0.45		E
12" Wide		0.35	0.44	0.53		E
18" Wide		0.40	0.50	0.60		E
24" Wide		0.50	0.63	0.75		E
30" Wide		0.60	0.75	0.90		E
36" Wide		0.70	0.88	1.05		E
<b>Solid/Ventilated Aluminum - Tee - Solid Covers</b>						
6" Wide		0.35	0.44	0.53		E
9" Wide		0.40	0.50	0.60		E
12" Wide		0.45	0.56	0.68		E
18" Wide		0.50	0.63	0.75		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.70	0.88	1.05		E
36" Wide		0.80	1.00	1.20		E
<b>Solid/Ventilated Aluminum - Cross - Solid Covers</b>						
6" Wide		0.45	0.56	0.68		E
9" Wide		0.50	0.63	0.75		E
12" Wide		0.55	0.69	0.83		E
18" Wide		0.60	0.75	0.90		E
24" Wide		0.70	0.88	1.05		E
30" Wide		0.80	1.00	1.20		E
36" Wide		0.90	1.13	1.35		E
<b>Solid/Ventilated Aluminum - Reducer - Solid Covers</b>						
6" Wide		0.25	0.31	0.38		E
9" Wide		0.30	0.38	0.45		E
12" Wide		0.35	0.44	0.53		E
18" Wide		0.40	0.50	0.60		E
24" Wide		0.50	0.63	0.75		E
30" Wide		0.60	0.75	0.90		E
36" Wide		0.70	0.88	1.05		E
<b>Solid/Ventilated Aluminum - Vertical 45 Degree Elbow - Solid Covers</b>						
6" Wide		0.35	0.44	0.53		E
9" Wide		0.40	0.50	0.60		E
12" Wide		0.45	0.56	0.68		E
18" Wide		0.50	0.63	0.75		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.70	0.88	1.05		E
36" Wide		0.80	1.00	1.20		E
<b>Solid/Ventilated Aluminum - Vertical 90 Degree Elbow - Solid Covers</b>						
6" Wide		0.35	0.44	0.53		E
9" Wide		0.40	0.50	0.60		E
12" Wide		0.45	0.56	0.68		E
18" Wide		0.50	0.63	0.75		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.70	0.88	1.05		E
36" Wide		0.80	1.00	1.20		E

## Section 2 - Conduit, Raceways, Fittings & Related Items


2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Solid/Ventilated Aluminum - Vertical Tee- Solid Covers</b>						
6" Wide		0.45	0.56	0.68		E
9" Wide		0.50	0.63	0.75		E
12" Wide		0.55	0.69	0.83		E
18" Wide		0.60	0.75	0.90		E
24" Wide		0.70	0.88	1.05		E
30" Wide		0.80	1.00	1.20		E
36" Wide		0.90	1.13	1.35		E
<b>Solid/Ventilated Aluminum - Enclosure Connectors</b>						
6" Wide		2.00	2.50	3.00		E
9" Wide		2.25	2.81	3.38		E
12" Wide		2.60	3.25	3.90		E
18" Wide		3.00	3.75	4.50		E
24" Wide		3.50	4.38	5.25		E
30" Wide		4.25	5.31	6.38		E
36" Wide		5.00	6.25	7.50		E
<b>Solid/Ventilated Aluminum - End Plates</b>						
6" Wide		0.40	0.50	0.60		E
9" Wide		0.45	0.56	0.68		E
12" Wide		0.50	0.63	0.75		E
18" Wide		0.55	0.69	0.83		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.65	0.81	0.98		E
36" Wide		0.70	0.88	1.05		E
<b>Solid/Ventilated Aluminum - Ladder Drop - Outs</b>						
6" Wide		0.40	0.50	0.60		E
9" Wide		0.45	0.56	0.68		E
12" Wide		0.50	0.63	0.75		E
18" Wide		0.55	0.69	0.83		E
24" Wide		0.60	0.75	0.90		E
30" Wide		0.65	0.81	0.98		E
36" Wide		0.70	0.88	1.05		E
<b>Solid/Ventilated Aluminum - Splice Plates Pair</b>						
6" Wide		0.80	1.00	1.20		E
9" Wide		0.85	1.06	1.28		E
12" Wide		0.90	1.13	1.35		E
18" Wide		0.95	1.19	1.43		E
24" Wide		1.00	1.25	1.50		E
30" Wide		1.10	1.38	1.65		E
36" Wide		1.20	1.50	1.80		E
<b>Solid/Ventilated Aluminum Cable Tray Barrier Strips</b>						
3" Depth		6.00	7.50	9.00		C
4" Depth		8.00	10.00	12.00		C
6" Depth		10.00	12.50	15.00		C
<b>Solid/Ventilated Aluminum Cable Tray Fitting Barrier Strips</b>						
3" Depth		0.60	0.75	0.90		E
4" Depth		0.65	0.81	0.98		E
6" Depth		0.70	0.88	1.05		E
<b>Solid/Ventilated Aluminum Conduit to Cable Tray Adapters</b>						
1/2" Conduit		0.50	0.63	0.75		E
3/4" Conduit		0.55	0.69	0.83		E
1" Conduit		0.60	0.75	0.90		E
1 1/4" Conduit		0.65	0.81	0.98		E
1 1/2" Conduit		0.70	0.88	1.05		E
2" Conduit		0.75	0.94	1.13		E
2 1/2" Conduit		0.80	1.00	1.20		E
3" Conduit		0.90	1.13	1.35		E
3 1/2" Conduit		1.00	1.25	1.50		E
4" Conduit		1.20	1.50	1.80		E
<b>Bonding Jumpers</b>						
#1/0 Copper X 15" Long		0.60	0.75	0.90		E
#4/0 Copper X 15" Long		0.80	1.00	1.20		E
#250 Copper X 15" Long		1.00	1.25	1.50		E














## Section 2 - Conduit, Raceways, Fittings & Related Items


Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Cable Tray Insulator Blocks</b>						
 6" Long		0.50	0.62	0.75		E
9" Long		0.55	0.68	0.82		E
12" Long		0.60	0.75	0.90		E
18" Long		0.70	0.87	1.05		E
24" Long		0.80	1.00	1.20		E
30" Long		0.90	1.12	1.35		E
36" Long		1.00	1.25	1.50		E
<b>Cable Clamps</b>						
Porcelain Cable Clamps		0.50	0.62	0.75		E
Wood Cable Clamps		0.40	0.50	0.60		E
<b>Cable Tray Lay-in Ground Clamp</b>						
#6 - 4/0		0.15	0.20	0.25		E
<b>Cable Rollers For Tray Setup</b>						
6" W		0.60	0.75	1.10		E
9" W		0.65	0.80	0.90		E
12" W		0.70	0.85	1.00		E
18" W		0.75	0.90	1.10		E
24" W		0.85	1.00	1.25		E
30" W		0.95	1.20	1.40		E
<b>Cable Pulleys/Bull Wheels-Setup</b>						
Single Bullwheel		0.90	1.10	1.35		E
Triple Bullwheel		1.20	1.50	1.80		E
Cable Tray Warning Label		0.10	0.12	0.15		E
<b>Channel Cable Tray</b>						
4" Width		10.00	12.00	14.00		C
6" Width		12.00	15.00	18.00		C
4" 90 Degree Horiz. Bend		0.50	0.60	0.75		E
6" 90 Degree Horiz. Bend		0.60	0.70	0.85		E
Channel Single Support Bracket		0.35	0.45	0.55		E
<b>Basket Type Wire Tray-Steel</b>						
4" Width		7.00	9.00	11.00		C
6" Width		8.00	10.00	12.00		C
12" Width		10.00	12.50	15.00		C
18" Width		12.00	15.00	18.00		C
24" Width		14.00	17.50	21.00		C
Basket Tray Hanger - Generic		0.30	0.40	0.50		E
Basket Tray Field Fabricated		0.00	0.00	0.00		
Transition Elbow or Tee		1.00	1.15	1.25		E
<b>Center-R-Rail Spline Cable Tray- Aluminum</b>						
6" Width		10.00	12.50	15.00		C
9" Width		10.00	12.50	15.00		C
12" Width		12.00	15.00	18.00		C
18" Width		12.00	15.00	18.00		C
24" Width		14.00	17.50	20.00		C
<b>Fittings</b>						
Offset Couplings		0.15	0.20	0.25		E
Universal Multidirectional Ftgs		0.50	0.65	0.85		E
Spline Tray Hanger (less rod)	X	0.30	0.40	0.50		E
Basket Tray Conduit Adaptor		0.20	0.30	0.40		E
<b>Cable Tray Fire Barrier</b>						
12" Width		4.00	6.00	8.00		E
24" Width		5.00	7.00	9.00		E
36" Width		6.00	8.00	10.00		E

Section 2 - Conduit, Raceways, Fittings & Related Items

2





























Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Fasteners / Hangers / Supports</b>						
<b>Toggle Bolts</b>						
 1/4"		12.00	15.00	18.00		C
3/8"		13.00	16.20	19.50		C
1/2"		15.00	18.70	22.50		C
5/8"		17.00	21.20	25.00		C
3/4"		20.00	25.00	30.00		C
7/8"		24.00	30.00	36.00		C
<b>Drop-in Anchors</b>						
 1/4"		16.00	20.00	24.00		C
3/8"		18.00	22.50	27.00		C
1/2"		20.00	25.00	30.00		C
5/8"		23.00	28.70	34.50		C
3/4"		26.00	32.50	39.00		C
7/8"		30.00	37.50	45.00		C
<b>Expansion Shields</b>						
1/4"		18.00	22.50	27.00		C
3/8"		20.00	25.00	30.00		C
1/2"		22.00	27.50	33.00		C
5/8"		25.00	31.20	37.50		C
3/4"		28.00	35.00	42.00		C
7/8"		32.00	40.00	48.00		C
<b>Self Drill Anchors</b>						
 1/4"		20.00	25.00	30.00		C
3/8"		22.00	27.50	33.00		C
1/2"		24.00	30.00	36.00		C
5/8"		27.00	33.70	40.00		C
3/4"		30.00	37.50	45.00		C
7/8"		35.00	43.70	52.00		C
<b>Concrete Anchor Bolts</b>						
 1/4"		16.00	20.00	24.00		C
3/8"		18.00	22.50	27.00		C
1/2"		20.00	25.00	30.00		C
5/8"		23.00	28.70	34.50		C
3/4"		26.00	32.50	39.00		C
1"		30.00	37.50	45.00		C
<b>Hollow Wall Anchors</b>						
 3/16"		10.00	12.50	15.00		C
1/4"		12.00	15.00	18.00		C
5/16"		14.00	17.50	21.00		C
<b>Fiber &amp; Plastic Anchors</b>						
 #8		14.00	17.50	21.00		C
#10		15.00	18.70	22.50		C
#12		16.00	20.00	24.00		C
#14		18.00	22.50	27.00		C
#16		21.00	26.20	31.50		C
#20		24.00	30.00	36.00		C
<b>Powder Activated Fasteners - All Types</b>						
 Powder Activated Fasteners-All Types		8.00	10.00	12.00		C
<b>Hammer Drive Anchors</b>						
 1/4"		16.00	20.00	24.00		C
3/8"		18.00	22.50	27.00		C
1/2"		20.00	25.00	30.00		C
5/8"		23.00	28.70	34.50		C
<b>Anchor Bolts Set in Concrete</b>						
 1/2" x 4"		25.00	31.25	37.50		C
5/8" x 6"		30.00	37.50	45.00		C
3/4" x 8"		35.00	43.75	52.50		C
1" x 10"		40.00	50.00	60.00		C
1 1/4" x 12"		45.00	56.25	67.50		C

## Section 2 - Conduit, Raceways, Fittings & Related Items


Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Concrete Channel Inserts</b>						
 1 Ft Long		30.00	37.50	45.00		C
2 Ft Long		40.00	50.00	60.00		C
4 Ft Long		50.00	62.00	75.00		C
6 Ft Long		60.00	75.00	90.00		C
8 Ft Long		75.00	93.00	110.00		C
10 Ft Long		90.00	112.00	135.00		C
<b>Threaded Concrete Inserts</b>						
Threaded Concrete Inserts		30.00	37.50	45.00		C
<b>Concrete Channel End Plates</b>						
Concrete Channel End Plates		8.00	10.00	12.00		C
<b>Concrete Channel Nuts</b>						
Concrete Channel Nuts with Springs		6.00	7.50	9.00		C
Concrete Channel Nuts without Springs		7.00	8.50	10.00		C
<b>Concrete Channel Studs</b>						
Concrete Channel Studs with Springs		5.00	6.20	7.50		C
Concrete Channel Studs without Springs		6.00	7.50	9.00		C
<b>Pre-cut Strut Hanger Channels</b>						
	X					
6" Long		10.00	12.50	15.00		C
12" Long		11.00	13.70	16.50		C
18" Long		12.00	15.00	18.00		C
24" Long		14.00	17.50	21.00		C
36" Long		16.00	20.00	24.00		C
48" Long		18.00	22.50	27.00		C
<b>Field Cut Strut Hanger Channels</b>						
	X					
6" Long		14.00	17.50	21.00		C
12" Long		15.00	18.70	22.50		C
18" Long		16.00	20.00	24.00		C
24" Long		18.00	22.50	27.00		C
36" Long		21.00	26.20	31.50		C
48" Long		24.00	30.00	36.00		C
<b>Pre-cut Hanger Rods</b>						
6" long		8.00	10.00	12.00		C
12" Long		9.00	11.20	13.50		C
18" Long		10.00	12.50	15.00		C
24" Long		11.00	13.70	16.50		C
36" Long		13.00	16.20	19.50		C
48" Long		15.00	18.70	22.50		C
<b>Field-cut All-thread Hanger Rods</b>						
6" Long		10.00	12.50	15.00		C
12" Long		11.00	13.70	16.50		C
18" Long		12.00	15.00	18.00		C
24" Long		14.00	17.50	21.00		C
36" Long		16.00	20.00	24.00		C
48" Long		18.00	22.50	27.00		C
<b>Hanger Channel Conduit Clamps</b>						
Up to 1" Dia		3.00	3.75	4.50		C
Up to 2" Dia		4.00	5.00	6.00		C
Up to 3" Dia		5.00	6.25	7.50		C
Up to 4" Dia		6.00	7.50	9.00		C
Up to 6" Dia		8.00	10.00	12.00		C
<b>One Hole Conduit Straps</b>						
Up to 1"		4.00	5.00	6.00		C
Up to 2"		4.25	5.30	6.35		C
Up to 3"		4.50	5.60	6.75		C
Up to 4"		5.00	6.25	7.50		C
Up to 6"		6.00	7.50	9.00		C
<b>Two Hole Conduit Straps</b>						
Up to 1"		4.50	5.60	6.75		C
Up to 2"		5.00	6.25	7.50		C
Up to 3"		5.50	6.85	8.25		C
Up to 4"		6.25	7.80	9.35		C
Up to 6"		7.00	8.75	10.50		C

## Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Conduit Ring Hangers</b>						
 Up to 1"		25.00	31.20	37.50		C
Up to 2"		27.50	34.30	41.20		C
Up to 3"		30.00	37.50	45.00		C
Up to 4"		35.00	43.70	52.50		C
Up to 6"		40.00	50.00	60.00		C
<b>Adjustable Ring Hangers</b>						
 Up to 1"		22.50	28.10	33.70		C
Up to 2"		25.00	31.20	37.50		C
Up to 3"		27.50	34.30	41.20		C
Up to 4"		30.00	37.50	45.00		C
Up to 6"		35.00	43.70	52.50		C
<b>Conduit Clamps</b>						
 Up to 1"		30.00	37.50	45.00		C
Up to 2"		35.00	43.70	52.50		C
Up to 3"		40.00	50.00	60.00		C
Up to 4"		45.00	56.20	67.50		C
Up to 6"		50.00	62.50	75.00		C
<b>Minerallic Straps</b>						
 Up to 1"		12.50	15.63	19.53		C
Up to 2"		13.75	17.19	21.48		C
Up to 3"		15.00	18.75	23.44		C
Up to 4"		17.50	21.88	27.34		C
Up to 6"		20.00	25.00	31.25		C
<b>Clevis Ring Hangers</b>						
 Up to 1"		25.00	31.25	37.50		C
Up to 2"		27.50	34.40	41.25		C
Up to 3"		30.00	37.50	45.00		C
Up to 4"		35.00	41.00	52.50		C
Up to 6"		40.00	50.00	60.00		C
<b>Conduit Riser Clamps</b>						
 Up to 1"		27.50	34.30	41.20		C
Up to 2"		30.00	37.50	45.00		C
Up to 3"		35.00	43.70	52.50		C
Up to 4"		40.00	50.00	60.00		C
Up to 6"		45.00	56.20	67.50		C
<b>U-Bolts</b>						
 Up to 1"		25.00	31.20	37.50		C
Up to 2"		27.50	34.30	41.20		C
Up to 3"		30.00	37.50	45.00		C
Up to 4"		35.00	43.70	52.50		C
Up to 6"		40.00	50.00	60.00		C
<b>Conduit and Box Supports</b>						
 Flange Mount Conduit and Cable Clip 3/8"		4.00	5.00	6.00		C
 Flange Mount Conduit and Cable Clip 1/2"		5.00	6.25	7.50		C
 Flange Mount Conduit and Cable Clip 1"		6.00	7.50	9.00		C
 Flange Mount Conduit and Cable Clip 1 1/4"		7.00	8.75	10.50		C
 Flange Mount Conduit and Cable Clip 1 1/2"		8.00	10.00	12.00		C
 Flange Mount Conduit and Cable Clip 2"		9.00	11.25	13.50		C
 Conduit Hangers 1/2"		5.00	6.25	7.50		C
 Conduit Hangers 3/4"		6.00	7.50	9.00		C
 Conduit Hangers 1"		7.00	8.75	10.50		C
 Conduit Hangers 1 1/4"		8.00	10.00	12.00		C
 Multi-Function Clip		9.00	11.25	13.50		C
 Combination Box/Conduit Hangers 1/2"		6.00	7.50	9.00		C
 Combination Box/Conduit Hangers 3/4"		7.00	8.75	10.50		C
 Hammer-on Flange Clip 1/8" - 1/4"		5.00	6.25	7.50		C
 Hammer-on Flange Clip 5/16" - 1/2"		6.00	7.50	9.00		C
 Hammer-on Flange Clip 9/16" - 3/4"		7.00	8.75	10.50		C
 Box Mounting Bracket		6.00	7.50	9.00		C
 Screw Gun Box Bracket		6.00	7.50	9.00		C
 Anti-Rattle Support		4.50	5.63	6.75		C
 Snap-On Fixture Box Hanger		9.50	11.88	14.25		C
 Stud Grommet for conduit, MC or NM		0.10	0.12	0.15		E

## Section 2 - Conduit, Raceways, Fittings & Related Items

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>Beam Clamps</b>						
Beam Clamps for Threaded Rods up to 1/2"		30.00	37.50	45.00		C
Adjustable Beam Clamps-Thd Rods up to 1/2"		40.00	50.00	60.00		C
<b>Trapeze Hangers without Beam Clamps or Inserts</b>						
6" x 6"		30.00	37.50	45.00		C
6" X 12"		31.00	38.70	46.50		C
12" x 12"		32.00	40.00	48.00		C
12" x 24"		34.00	42.50	51.00		C
18" x 18"		36.00	45.00	54.00		C
18" X 36"		38.00	47.50	57.00		C
24" x 24"		40.00	50.00	60.00		C
24" x 36"		43.00	53.70	64.50		C
24" X 48"		46.00	57.50	69.00		C
36" x 36"		49.00	61.20	73.50		C
36" x 60"		56.00	70.00	84.00		C
48" x 48"		60.00	75.00	90.00		C
48" x 60"		65.00	81.00	98.00		C
<b>Drill Holes in Steel (up to 1/4" Thick)</b>						
1/4" dia		16.00	20.00	24.00		C
3/8" Dia		17.00	21.20	25.50		C
1/2" Dia		18.00	22.50	27.00		C
5/8" Dia		20.00	25.00	30.00		C
3/4" Dia		23.00	28.70	34.50		C
7/8" Dia		26.00	32.50	39.00		C
1" Dia		30.00	37.50	45.00		C
<b>Drill Holes in Wood Stud</b>						
1/2"	X					
1/2"	X	0.07	0.10	0.15		E
3/4"	X	0.10	0.14	0.20		E
1"	X	0.15	0.18	0.25		E
1 1/4"	X	0.25	0.32	0.40		E
1 1/2"	X	0.30	0.45	0.55		E
2"	X	0.35	0.55	0.65		E

### Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Misc Bolts, Washers, Nuts &amp; Screws</b>						
<b>Bolt, Washer, and Nut</b>						
1/2 X 3/16 Flat Washer		0.70	0.88	1.09		C
9/16 X 1/4 Flat Washer		0.70	0.88	1.09		C
31/31 X 3/8 Flat Washer		0.70	0.88	1.09		C
1 1/4 X 1/4 Fender Washer		0.70	0.88	1.09		C
1 1/2 X 1/4 Fender Washer		0.70	0.88	1.09		C
1 1/2 X 3/8 Fender Washer		0.70	0.88	1.09		C
1 1/2 X 1/2 Fender Washer		0.70	0.88	1.09		C
3/16 Lock Washer		0.70	0.88	1.09		C
1/4 Lock Washer		0.70	0.88	1.09		C
3/8 Lock Washer		0.70	0.88	1.09		C
1/2 Lock Washer		0.70	0.88	1.09		C
3/8 Belleville Washer		0.70	0.88	1.09		C
1/2 Belleville Washer		0.70	0.88	1.09		C
6/32 X 1/2 RHMS		2.75	3.44	4.30		C
6/32 X 3/4 RHMS		2.75	3.44	4.30		C
6/32 X 1 RHMS		2.75	3.44	4.30		C
6/32 X 1 1/4 RHMS		2.80	3.50	4.38		C
6/32 X 1 1/2 RHMS		2.80	3.50	4.38		C
6/32 X 2 RHMS		2.80	3.50	4.38		C
8/32 X 1/2 RHMS		2.75	3.44	4.30		C
8/32 X 3/4 RHMS		2.75	3.44	4.30		C
8/32 X 1 RHMS		2.75	3.44	4.30		C
8/32 X 1 1/4 RHMS		2.80	3.50	4.38		C
8/32 X 1 1/2 RHMS		2.80	3.50	4.38		C
8/32 X 2 RHMS		2.80	3.50	4.38		C
10/32 X 1/2 RHMS		2.75	3.44	4.30		C
10/32 X 3/4 RHMS		2.75	3.44	4.30		C
10/32 X 1 RHMS		2.75	3.44	4.30		C
10/32 X 1 1/4 RHMS		2.80	3.50	4.38		C
10/32 X 1 1/2 RHMS		2.80	3.50	4.38		C
10/32 X 2 RHMS		2.80	3.50	4.38		C
10/24 X 1/2 RHMS		2.75	3.44	4.30		C
10/24 X 3/4 RHMS		2.75	3.44	4.30		C
10/24 X 1 RHMS		2.75	3.44	4.30		C
10/24 X 1 1/4 RHMS		2.80	3.50	4.38		C
10/24 X 1 1/2 RHMS		2.80	3.50	4.38		C
10/24 X 2 RHMS		2.80	3.50	4.38		C
1/4-20 X 1/2 RHMS		2.75	3.44	4.30		C
1/4-20 X 3/4 RHMS		2.75	3.44	4.30		C
1/4-20 X 1 RHMS		2.75	3.44	4.30		C
1/4-20 X 1 1/4 RHMS		2.80	3.50	4.38		C
1/4-20 X 1 1/2 RHMS		2.80	3.50	4.38		C
1/4-20 X 2 RHMS		2.80	3.50	4.38		C
3/8-16 1/2 RHMS		2.80	3.50	4.38		C
3/8-16 3/4 RHMS		2.80	3.50	4.38		C
3/8-16 1 RHMS		2.80	3.50	4.38		C
3/8-16 1 1/4 RHMS		2.85	3.56	4.45		C
3/8-16 1 1/2 RHMS		2.85	3.56	4.45		C
3/8-16 2 RHMS		2.85	3.56	4.45		C
1/2-13 1/2 RHMS		2.80	3.50	4.38		C
1/2-13 3/4 RHMS		2.80	3.50	4.38		C
1/2-13 1 RHMS		2.80	3.50	4.38		C
1/2-13 1 1/4 RHMS		2.85	3.56	4.45		C
1/2-13 1 1/2 RHMS		2.85	3.56	4.45		C
1/2-13 2 RHMS		2.85	3.56	4.45		C
6/32 Hex Nut		2.60	3.25	4.06		C
8/32 Hex Nut		2.60	3.25	4.06		C
10/32 Hex Nut		2.60	3.25	4.06		C
10/24 Hex Nut		2.60	3.25	4.06		C
1/4-20 Hex Nut		2.60	3.25	4.06		C
3/8-16 Hex Nut		2.80	3.50	4.38		C
1/2-13 Hex Nut		2.80	3.50	4.38		C



Section 2 - Conduit, Raceways, Fittings & Related Items

2

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Hole Drilling and Coring</b>						
<b>Roto-Hammer Concrete</b>						
3/4" x 8"		0.50	0.75	1.00		E
1" x 8"		0.60	0.90	1.30		E
1 1/4" x 8"		1.00	1.50	2.00		E
<b>Core-Drill Concrete With Lay-out</b>						
3/4" x 8"		1.00	1.25	1.75		E
1" x 8"	X	1.00	1.25	1.75		E
1 1/4" x 8"		1.00	1.30	1.75		E
1 1/2" x 8"		1.10	1.35	1.85		E
2" x 8"		1.15	1.50	1.90		E
2 1/2" x 8"		1.50	1.75	2.00		E
3" x 8"		1.75	2.00	2.50		E
4" x 8"		2.00	2.50	3.00		E
5" x 8"		2.50	3.00	3.50		E
6" x 8"		3.00	3.50	4.00		E
<b>Firestop Material</b>						
<b>Fire Stop Pillows</b>						
Pillow Installation		10.00	12.00	15.00		C
<b>Fire Proof Wall Penetrations</b>						
FP-Wall Seal 1/2"		0.85	0.95	1.15		E
FP-Wall Seal 3/4"		0.95	1.15	1.35		E
FP-Wall Seal 1"		1.10	1.20	1.40		E
FP-Wall Seal 1 1/4"		1.50	1.60	1.80		E
FP-Wall Seal 1 1/2"		1.50	1.85	2.05		E
FP-Wall Seal 2"		2.00	2.10	2.30		E
FP-Wall Seal 2 1/2"		2.50	2.60	2.80		E
FP-Wall Seal 3"		3.00	3.10	3.30		E
FP-Wall Seal 3 1/2"		3.40	3.50	3.70		E
FP-Wall Seal 4"		3.75	3.85	4.05		E
FP-Wall Seal 5"		4.00	4.10	4.30		E
FP-Wall Seal 6"		4.50	4.60	4.80		E
Prepare Opening		1.00	2.00	3.00		E
Install Device		0.50	0.65	0.75		E
Fit To Conduit		0.75	0.85	0.95		E
Finish Seal		1.00	2.00	3.00		E
<b>Multi Cable/Tray Firestop</b>						
<b>Multi-cable and cable tray firestop penetration.</b>						
<b>Wall opening is not included in labor units.</b>						
<b>Fire pads are installed after cable installation.</b>						
Installation Labor		2.50	2.70	2.90		E
Fire Pad Installation		1.00	1.20	1.40		E
<b>Speed Sleeve</b>						
<b>Wall penetrations not included in labor units.</b>						
<b>Low voltage cable application.</b>						
<b>Wall and floor applications.</b>						
<b>Seal sleeve before installing flange.</b>						
<b>Seal occurs by rotating the sleeve clockwise.</b>						
<b>Speed sleeve can be re-opened for additional cable and re-sealed.</b>						
2" Sleeve		1.00	1.20	1.40		E
4" Sleeve		1.50	1.70	1.90		E
<b>Firestop Collar</b>						
<b>Wall penetrations not included in labor units.</b>						
<b>Adjustable position tabs for fastening.</b>						
<b>Fastening hooks used to fasten collar to wall.</b>						
1 1/2" Collar		1.00	1.20	1.40		E
2" Collar		1.15	1.17	1.19		E
3" Collar		1.30	1.50	1.70		E
4" Collar		1.50	1.70	1.90		E
6" Collar		1.90	2.10	2.30		E
<b>Floor Firestop</b>						
<b>Floor penetration not included in labor units.</b>						
<b>Mount on metal decks.</b>						
<b>Moisture and smoke seal</b>						
2" Cast-In-Device		1.00	1.20	1.40		E
3" Cast-In-Device		1.15	1.17	1.19		E
4" Cast-In-Device		1.25	1.27	1.29		E
6" Cast-In-Device		1.50	1.70	1.90		E



# SECTION 3

## WIRE, CABLE, LUGS, TERMINATIONS, BUSWAY AND BUS DUCT

### General Information

This section includes labor units for building wire, power cable plenum cable, control cable, tray cable, undercarpet cable, lugs, stress relief cones, pot heads, cable terminators, busway and bus duct.

### Scope of These Labor Units

The Introduction section includes details on the scope of labor units across the manual. Some items included are:

- Material unloading, jobsite storage and delivery to the installation area
- Drawing and specification study
- Layout, measuring and marking the installation location
- Tool acquisition and return to storage
- Set-up and removing jacks, sheaves and cable pullers
- Pulling cable
- Testing circuits for continuity only
- Clean-up of electrical contractor furnished excess materials
- Normal non-productive labor

### Work Operations Not Included In These Labor Units

- Field supervision
- Conductor terminations are not included in the wire pulling labor units
- Lugs, splices, cable terminators labor must be estimated separately
- Cable labor units do not include fasteners or supports
- Busway and bus duct labor units do not include fasteners or supports
- All testing except circuit continuity

### Labor Adjustments for Non-Typical Conditions

See the Introduction section for details.

### Application Instructions

- Labor units for conduit termination material include installing the locknuts and bushings as well
- All conductor termination labor in this manual is included with the wiring device, fixture, motor, panelboard, safety switch, etc. labor units unless noted otherwise.
- Labor units in this section should not be reduced for paralleled conductor installation situations unless the quantity of parallel conduits with paralleled conductors is unusually large. Even then, each installation condition should be evaluated critically before factoring the labor units.
- Wire and cable installed in cable tray generally require larger than normal labor units because the pulling equipment (including the sheaves) set-up time and the pulling equipment removal time are usually included in the conductor pulling labor units.
- Some electrical safety codes may require cables to be tied or laced within the cable tray enclosure. An additional allowance for installation labor must be made to meet such requirements.
- Bus duct labor unit tables in this section are for copper bus duct.
  - For aluminum bus duct labor units, deduct approximately 15% from the labor units in these tables due to the lighter weight of the material.
  - Labor unit tables are based on 3 Phase 3 Pole duct and fittings.
    - For 3 Phase 4 Pole (1/2 Neutral) bus duct installations add 15% to these duct and fitting labor units.
    - For 3 Phase 4 Pole (Full Neutral) bus duct installations add 20%.



## Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct Table of Contents

600 Volt Bldg Wire-1/C-Copper Type THHN & THWN	3-7
600 Volt Bldg Wire-1/C-Copper Type RHW-Use	3-7
600 Volt High Temp Wire-1/C-Copper Type XHHW	3-7
<b>New Installations</b>	3-8
<b>Retrofit Installations</b>	3-9
600 Volt Fixture Wire-1/C-Copper Type TF, TFF, TFN, & TFFN	3-10
600 Volt High Temp Wire-1/C Copper-Type XHHW	3-10
600 Volt Power Cable-3/C-Copper Cross Linked Poly Ins PVC Jack w/o Gnd	3-10
600 Volt Power Cable-4/C-Copper Cross Linked Poly Ins PVC Jacketed w Gnd	3-10
600 Volt Power Cable-Type USE RHW Insulation Copper	3-10
600 Volt Power Cable-Multi Conductor Stranded Copper - XLP Insulated	3-11
Thermostat Wire-Copper	3-11
Fire Alarm Wire-Solid-Copper	3-11
5 KV Power Cable-Unshielded-1/C Copper - XLP Insulated - PVC Jacketed	3-11
5 KV Power Cable-Shielded-1/C Copper - XLP Insulated - PVC Jacketed	3-12
5 KV Power Cable-3/C-w/o Ground Shielded Copper - XLP - PVC Jacketed	3-12
5 KV Power Cable-3/C-with Ground Shielded - Copper - XLP - PVC Jacketed	3-12
15 KV Power Cable-1/C Shielded - Copper - XLP - PVC Jacketed	3-12
15 KV Power Cable-3/C-w/o ground Shielded - Copper - XLP PVC Jacketed	3-13
600 Volt MC Cable with Alum. or Steel Armor - Copper	3-13
600 Volt MC Cable - Homerun Cables - Copper	3-13
600 Volt AC Cable with Alum. or Steel Armor - Copper	3-13
Fire Alarm/Control MC Cable with Alum. or Steel Armor - Copper	3-14
Solid TFFN Conductors	3-14
Solid THHN Conductors	3-14
Labor Units - 3 Conductor - Aluminum MC Cable with Alum. or Steel Armor	3-14
Labor Units - 4 Conductor - Aluminum MC Cable with Alum. or Steel Armor	3-14
MC Connector for Copper MC - General Duty	3-15
MC Connector for Aluminum MC - General Duty	3-15
Straps for MC Cable	3-15
600 Volt Non-Metallic Sheathed Cable Copper - Type NM and UF w/o Ground	3-15
600 Volt Non-Metallic Sheathed Cable Copper - Type NM and UF with Ground	3-16
600 Volt Mineral Insulated Cable Type MI Non-Heating	3-16
600 Volt Mineral Insulated Cable Terminators	3-16
300 Volt Solid Connector Plenum Cable	3-17
600 Volt Stranded Copper Control Cable	3-17
<b>Wire Connectors (Wire Nuts)</b>	3-18
Crimp Terminations - Spade Type	3-18
Crimp Terminations - Ring Type	3-18
Wire Identification	3-18
Terminal Blocks - Excludes Terminations	3-18
600 Volt Type FCC Flat Under Carpet Wiring Junction Box	3-18
Install Round To Flat Cable - Transition Block - In Junction Box	3-18
Flat Undercarpet - Tee-Tap / X Tap / Change of direction	3-18
Floor Mount Power Pedestal -Single or Double Duplex - Mount Pedestal and Terminate	3-18
Undercarpet Telephone and Data Flat Cable - Junction Box	3-18
Install Flat To Round Cable Transition Block in Junction Box - All Types	3-18
Install Telephone an Data	3-19
Floor Mount Telephone or Data	3-19
Install Floor Pedestal - Install Flat Cable to Modular Ass.	3-19
Cord Bodies	3-19
Kellems Grips up to 1"	3-19
600 Volt Type TC Copper Tray Cable THHN	3-19

## Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct Table of Contents

600 Volt Type S-SJ-SO Flexible Cord	3-19
600 Volt Interlocked Armor Cable 3/C Copper	3-20
600 Volt Interlocked Armored Cable 3/C Aluminum	3-20
5 KV Interlocked Armored Cable 3/C Copper	3-20
5 KV Interlocked Armored Cable 3/C Aluminum	3-20
15 KV Interlocked Armored Cable - 3/C Shielded - Copper Conductors	3-21
15 KV Interlocked Armored Cable - 3/C Shielded - Aluminum Conductors	3-21
300 Volt Service Entrance Cable - Type SEU 3/C Copper Conductors	3-21
300 Volt Service Entrance Cable - Type SEU 3/C Aluminum Conductors	3-21
600 Volt Service Entrance Cable - Type SER 3/C Copper Conductors	3-21
600 Volt Service Entrance Cable - Type SER 3/C Aluminum Conductors	3-21
600 Volt Service Entrance Cable - Type SER 4/C Copper Conductors	3-22
Compression Terminal Lugs-One Hole	3-22
Compression Terminal Lugs-Two Hole	3-22
Compression Terminal Lugs-Four Hole	3-22
Compression Splice Connectors	3-22
Mechanical Terminal Lugs-One Hole	3-23
Mechanical Terminal Lugs-Two Hole	3-23
Mechanical Terminal Lugs-Four Hole	3-23
Mechanical Terminal Lugs-Two Cable	3-23
Split Bolt Connectors-Tape Wrapped	3-23
Compression Tails - Copper to Aluminum	3-24
Metallic Sheathed Cable Box Connectors	3-24
Non-Metallic Sheathed Cable Box Connectors	3-24
2/C Armored Sheathed - Cable Terminators With Sealing Bushing	3-24
3/C Armored Sheathed - Cable Terminators With Sealing Bushing	3-24
4/C Armored Sheathed - Cable Terminators With Sealing Bushing	3-24
2/C Jacketed Cable to Conduit Terminators With Sealing Bushings	3-24
3/C Jacketed Cable to Conduit Terminators With Sealing Bushings	3-25
4/C Jacketed Cable to Conduit Terminators With Sealing Bushings	3-25
2/C Jacketed Cable to Conduit Terminators - Compound Filled	3-25
3/C Jacketed Cable to Conduit Terminators - Compound Filled	3-25
4/C Jacketed Cable to Conduit Terminators - Compound Filled	3-25
2/C Wire Armored Cable Terminators - Compound Filled	3-25
3/C Wire Armored Cable Terminators - Compound Filled	3-25
4/C Wire Armored Cable Terminators - Compound Filled	3-26
2/C Sheathed Armored Cable Terminators - Compound Filled	3-26
3/C Sheathed Armored Cable Terminators - Compound Filled	3-26
4/C Sheathed Armored Cable Terminators - Compound Filled	3-26
2/C Armored Cable Terminators - Weatherproof - Gland Type	3-26
3/C Armored Cable Terminators - Weatherproof - Gland Type	3-26
4/C Armored Cable Terminators - Weatherproof - Gland Type	3-26
2/C Armored Cable to Conduit Terminators - Compound Filled	3-27
3/C Armored Cable to Conduit Terminators - Compound Filled	3-27
4/C Armored Cable to Conduit Terminators - Compound Filled	3-27
5 KV Porcelain Terminators	3-27
15 KV Porcelain Terminators	3-27
25 KV Porcelain Terminators	3-27
1/C Hand Wrapped Stress Relief Cones 5KV	3-27
1/C Hand Wrapped Stress Relief Cones 15KV	3-28
1/C Hand Wrapped Stress Relief Cones 25KV	3-28
3/C Hand Wrapped Stress Relief Cones 5 KV	3-28
3/C Hand Wrapped Stress Relief Cones 15KV	3-28
3/C Hand Wrapped Stress Relief Cones 25 KV	3-28
Heat Shrink Cable Termination with 5 KV Stress Cone and Compression Lug	3-28
Heat Shrink Cable Termination with 15KV Stress Cone and Compression Lug	3-28
Heat Shrink Cable Termination with 25 KV Stress Cone and Compression Lug	3-29

## Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct Table of Contents




Cold Shrink Cable Termination with 5 KV Stress Cone and Compression Lug	3-29
Cold Shrink Cable Termination with 15 KV Stress Cone and Compression Lug	3-29
Cold Shrink Cable Termination with 25 KV Stress Cone and Compression Lug	3-29
5KV Single Conductor Potheads	3-29
15 KV Single Conductor Potheads	3-29
25 KV Single Conductor Potheads	3-30
5KV Two Conductor Potheads	3-30
15KV Two Conductor Potheads	3-30
25KV Two Conductor Potheads	3-30
5KV Three Conductor Potheads	3-30
15KV Three Conductor Potheads	3-30
25KV Three Conductor Potheads	3-31
15KV Loadbreak Cable Elbows	3-31
25KV Loadbreak Cable Elbows	3-31
600 Volt Tape Wrapped Cable Splices 1/C	3-31
600 Volt Tape Wrapped Cable Splices 2/C	3-31
600 Volt Tape Wrapped Cable Splices 3/C	3-31
1/C Shielded Cables Splices-5KV Cold Shrink	3-32
1/C Shielded Cable Splices-15KV Cold Shrink	3-32
1/C Shielded Cable Splices-25KV Cold Shrink	3-32
3/C Cable Splices-5KV Cold Shrink	3-32
3/C Cable Splices-15KV Cold Shrink	3-32
3/C Cable Splices-25KV Cold Shrink	3-33
1/C Heat Shrink & Premolded Shielded Cable Splices - 5KV	3-33
1/C Heat Shrink & Premolded Shielded Cable Splices - 15KV	3-33
1/C Heat Shrink & Premolded Shielded Cable Splices - 25KV	3-33
3/C Heat Shrink Cable Splices - 5KV	3-33
3/C Heat Shrink Cable Splices - 15KV	3-34
3/C Heat Shrink Cable Splices - 25KV	3-34
3/C Interlocked Armored Cable Splices-5KV	3-34
3/C Interlocked Armored Cable Splices 15KV	3-34
3/C Interlocked Armored Cable Splices 25KV	3-34
3/C I.A.C. Splices-5KV-Compound Filled	3-35
3/C I.A.C. Splices-15KV-Compound Filled	3-35
Fire Proof Tape	3-35
2 Pole Ltg & Motor Busway up to 240 Volt	3-35
3 Pole Ltg & Motor Busway up to 480 Volt	3-35
Trolley Busway	3-35
Trolley Busway Feed Boxes	3-36
Trolley Busway Curve Sections	3-36
Trolley Busway Track Switches	3-36
2-Pole Trolleys	3-36
3-Pole Trolleys	3-36
Three Pole Heavy Duty Trolley Busway	3-36
Busway End Power Feeds	3-36
Busway Center Power Feeds	3-36
One Pole Crane Hoist & Monorail Busway	3-36
Busway Expansion Joints	3-37
3 Phase 3P Copper Bus Duct Plug-In Type	3-37
3 Phase 3P Copper Bus Duct-Elbows	3-37
3 Phase 3P Copper Bus Duct-Tees	3-37
3 Phase 3P Copper Bus Duct-Crosses	3-37
3 Phase 3P Copper Bus Duct-Offset Fittings	3-37
3 Phase 3P Copper Bus Duct-End Closures	3-38
3 Phase 3P Copper Bus Duct-Unfused Reducers	3-38
3 Phase 3P Copper Bus Duct-Offset Elbows	3-38
3 Phase 3P Copper Bus Duct-Expansion Fittings	3-38

(Updated)

## Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct Table of Contents

3	3 Phase 3P Copper Bus Duct-Panelboard Fittings	3-38
	3 Phase 3P Copper Bus Duct-Cable Tap Boxes	3-38
	3 Phase 3P Copper Bus Duct-Transformer Fittings	3-39
	Bus Duct-2P2W Nonfusible Switches	3-39
	Bus Duct-2P3W Nonfusible Switches	3-39
	Bus Duct-3P3W Nonfusible Switches	3-39
	Bus Duct-3P4W Nonfusible Switches	3-39
	Bus Duct-2P2W Fusible Switches	3-39
	Bus Duct-2P3W Fusible Switches	3-39
	Bus Duct-3P3W Fusible Switches	3-40
	Bus Duct 3P4W Fusible Switches	3-40
	Bus Duct-2P2W Molded Case Circuit Breakers	3-40
	Bus Duct-2P3W Molded Case Circuit Breakers	3-40
	Bus Duct-3P3W Molded Case Circuit Breakers	3-40
	3 Phase 3P Copper Bus Duct-Feeder Type	3-40
	3 Phase 3P Feeder Bus Duct-Elbows	3-40
	3 Phase 3P Feeder Bus Duct-Tee Fittings	3-41
	3 Phase 3P Feeder Bus Duct-Cross Fittings	3-41
	3 Phase 3P Feeder Bus Duct-Offset Fittings	3-41
	3 Phase 3P Feeder Bus Duct-Unfused Reducers	3-41
	3 Phase 3P Feeder Bus Duct-Offset Elbows	3-41
	3 Phase 3P Feeder Bus Duct-Expansion Fittings	3-41
	3 Phase 3P Feeder Bus Duct-Panelboard Fittings	3-42
	3 Phase 3P Feeder Bus Duct-End Closures	3-42
	3 Phase 3P Feeder Bus Duct-Cable Tap Boxes	3-42
	3 Phase 3P Feeder Bus Duct-Transformer Fittings	3-42
	Three Phase 3P Feeder Bus Duct - Service Heads	3-42
	3 Phase 3P Bus Duct-Wall & Floor Flanges	3-42
	3 Phase 3P Bus Duct-Fire & Weather Stops	3-43
	Floor Springload Factory Hanger	3-43
	Teck Cable 5Kv 3c	3-43
	Teck Cable 1Kv 3C	3-43
	Teck Cable 1Kv 4C	3-43
	Teck Cable 1Kv 1C	3-44
	Teck Cable 600v mh/1000 FT	3-44
	Teck Cable 600v 12AWG	3-44
	Teck Cable 14AWG	3-45
	Teck Cable 16AWG	3-45
	Teck Cable 18AWG	3-46
	Teck Cable 20AWG	3-46
	Teck Connectors	3-47

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>600 Volt Bldg Wire-1/C-Copper Type THHN &amp; THWN</b>						
#14		5.00	6.20	7.50		M
#12		6.00	7.50	9.00		M
#10		7.00	8.75	10.50		M
#8		9.00	11.25	13.50		M
#6		11.00	13.75	16.50		M
#4		13.00	16.25	19.50		M
#3		15.00	18.75	22.50		M
#2		17.00	21.25	25.50		M
#1		19.00	23.75	28.50		M
1/0		22.00	27.50	33.00		M
2/0		24.00	30.00	36.00		M
3/0		26.00	32.50	39.00		M
4/0		29.00	36.20	43.50		M
250 kcmil		32.00	40.00	48.00		M
300 kcmil		35.00	44.00	52.00		M
350 kcmil		38.00	48.00	57.00		M
400 kcmil		41.00	51.00	62.00		M
500 kcmil		44.00	55.00	66.00		M
600 kcmil		48.00	60.00	72.00		M
750 kcmil		54.00	67.00	81.00		M
1000 kcmil		62.00	77.00	93.00		M
<i>Note: 1/0 - 4/0 Reduce labor 10% for Aluminum</i>						
<i>Note: 250 - 1000 Reduce labor 15% for Aluminum</i>						
<i>Note: Reduce Labor Units 10% When Using Factory Lubricated Wire</i>						
 <b>600 Volt Bldg Wire-1/C-Copper Type RHW-Use</b>						
#14		6.00	7.50	9.00		M
#12		7.00	8.70	10.50		M
#10		8.00	10.00	12.00		M
#8		10.00	12.50	15.00		M
#6		12.00	15.00	18.00		M
#4		15.00	18.70	22.50		M
#3		17.00	21.20	25.50		M
#2		19.00	23.70	28.50		M
#1		21.00	26.20	31.50		M
1/0		24.00	30.00	36.00		M
2/0		27.00	33.70	40.50		M
3/0		30.00	37.50	45.00		M
4/0		33.00	41.20	49.50		M
250 kcmil		36.00	45.00	54.00		M
300 kcmil		39.00	48.00	58.00		M
350 kcmil		42.00	53.00	63.00		M
400 kcmil		45.00	56.00	67.00		M
500 kcmil		48.00	60.00	72.00		M
600 kcmil		52.00	65.00	78.00		M
750 kcmil		58.00	72.00	87.00		M
1000 kcmil		68.00	85.00	102.00		M
<i>Note: 1/0 - 4/0 Reduce labor 10% for Aluminum</i>						
<i>Note: 250 - 1000 Reduce labor 15% for Aluminum</i>						
 <b>600 Volt High Temp Wire-1/C-Copper Type XHHW</b>						
#14		6.00	7.50	9.00		M
#12		7.00	8.70	10.50		M
#10		8.50	10.60	12.70		M
#8		11.00	13.70	16.50		M
#6		13.00	16.20	19.50		M
#4		15.00	18.70	22.50		M
#3		17.00	21.20	25.50		M
#2		19.00	23.70	28.50		M
#1		21.00	26.20	31.50		M
1/0		24.00	30.00	36.00		M
2/0		27.00	33.70	40.50		M
3/0		30.00	37.50	45.00		M
4/0		33.00	41.20	49.50		M
250 kcmil		36.00	45.00	54.00		M
300 kcmil		39.00	48.00	58.00		M
350 kcmil		42.00	53.00	63.00		M
400 kcmil		45.00	56.00	67.00		M
500 kcmil		48.00	60.00	72.00		M
600 kcmil		52.00	65.00	78.00		M
750 kcmil		58.00	72.00	87.00		M
1000 kcmil		68.00	85.00	102.00		M
<i>Note: 1/0 - 4/0 Reduce labor 10% for Aluminum</i>						
<i>Note: 250 - 1000 Reduce labor 15% for Aluminum</i>						
<i>Note: Reduce Labor Units 10% When Using Factory Lubricated Wire</i>						













Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>600 Volt Fixture Wire-1/C-Copper Type TF, TFF, TFN, &amp; TFFN</b>						
#18		4.00	5.00	6.00		M
#16		5.00	6.25	7.50		M
#14		6.00	7.50	9.00		M
 <b>600 Volt High Temp Wire-1/C Copper-Type XHHW</b>						
#14		6.00	7.50	9.00		M
#12		7.00	8.75	10.50		M
#10		8.00	10.00	12.00		M
#8		10.00	12.50	15.00		M
#6		12.00	15.00	18.75		M
 <b>600 Volt Power Cable-3/C- Copper Cross Linked Poly Ins PVC Jack w/o Gnd</b>						
#12		10.00	12.50	15.00		M
#10		13.00	16.20	19.50		M
#8		16.00	20.00	24.00		M
#6		20.00	25.00	30.00		M
#4		24.00	30.00	36.00		M
#2		28.00	35.00	42.00		M
#1		32.00	40.00	48.00		M
1/0		36.00	45.00	54.00		M
2/0		40.00	50.00	60.00		M
3/0		45.00	56.00	67.00		M
4/0		50.00	62.00	75.00		M
250 kcmil		55.00	68.00	82.00		M
300 kcmil		60.00	75.00	90.00		M
350 kcmil		65.00	81.00	97.00		M
400 kcmil		70.00	87.00	105.00		M
500 kcmil		75.00	93.00	112.00		M
600 kcmil		80.00	100.00	120.00		M
750 kcmil		90.00	112.00	135.00		M
1000 kcmil		100.00	125.00	150.00		M
 <b>600 Volt Power Cable-4/C- Copper Cross Linked Poly Ins PVC Jacketed w Gnd</b>						
#12		12.00	15.00	18.00		M
#10		15.00	18.70	22.50		M
#8		18.00	22.50	27.00		M
#6		22.00	27.50	33.00		M
#4		26.00	32.50	39.00		M
#3		30.00	37.50	50.00		M
#2		35.00	44.00	52.00		M
#1		40.00	50.00	60.00		M
1/0		45.00	56.00	67.00		M
2/0		50.00	62.00	75.00		M
3/0		55.00	68.70	82.00		M
4/0		60.00	75.00	90.00		M
250 kcmil		65.00	81.00	97.00		M
300 kcmil		70.00	87.00	105.00		M
350 kcmil		75.00	93.00	112.00		M
400 kcmil		80.00	100.00	120.00		M
500 kcmil		90.00	112.00	135.00		M
600 kcmil		100.00	125.00	150.00		M
750 kcmil		110.00	137.00	165.00		M
1000 kcmil		120.00	150.00	180.00		M
 <b>600 Volt Power Cable-Type USE RHW Insulation Copper</b>						
2/C #12		14.00	17.50	21.00		M
2/C #10		18.00	22.50	27.00		M
2/C #8		24.00	30.00	36.00		M
3/C #12		17.00	21.20	25.50		M
3/C #10		22.00	27.50	33.00		M
3/C #8		30.00	37.50	45.00		M
4/C #12		20.00	25.00	30.00		M
4/C #10		28.00	35.00	42.00		M
4/C #8		40.00	50.00	60.00		M

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>600 Volt Power Cable-</b>						
<b>Multi Conductor Stranded Copper - XLP Insulated</b>						
 #16 2/C		10.00	12.50	15.00		M
#16 3/C		12.00	15.00	18.00		M
#16 4/C		14.00	17.50	21.00		M
#16 6/C		17.00	21.20	25.50		M
#16 8/C		20.00	25.00	30.00		M
#14 2/C		12.00	15.00	18.00		M
#14 3/c		14.00	17.50	21.00		M
#14 4/C		17.00	21.20	25.50		M
#14 6/C		22.00	27.50	33.00		M
#14 8/C		27.00	33.30	40.50		M
#12 2/C		14.00	17.50	21.00		M
#12 3/C		17.00	21.20	25.50		M
#12 4/C		20.00	25.00	30.00		M
#12 6/C		27.00	33.20	40.50		M
#12 8/C		34.00	42.50	51.00		M
#10 2/c		18.00	22.50	27.00		M
#10 3/C		22.00	27.50	33.00		M
#10 4/C		28.00	35.00	42.00		M
#10 6/C		36.00	45.00	54.00		M
#10 8/C		46.00	57.50	69.00		M
#8 2/C		24.00	30.00	36.00		M
#8 3/C		32.00	40.00	48.00		M
#8 4/C		40.00	50.00	60.00		M
#8 6/C		50.00	62.00	75.00		M
#8 8/C		60.00	75.00	90.00		M
<b>Thermostat Wire-Copper</b>						
#18 2/C		7.00	8.70	10.50		M
#18 3/C		8.00	10.00	12.00		M
#18 4/C		9.00	11.20	13.50		M
#18 6/C		10.00	12.50	15.00		M
#18 6/C		12.00	15.00	18.00		M
<b>Fire Alarm Wire-Solid-Copper</b>						
#22 2/C		10.00	12.50	15.00		M
#22 3/C		12.00	15.00	18.00		M
#22 4/C		14.00	17.50	21.00		M
#22 7/C		16.00	20.00	24.00		M
#22 9/C		18.00	22.50	27.00		M
#22 12/C		20.00	25.00	30.00		M
#18 2/C		12.00	15.00	18.00		M
#18 3/C		14.00	17.50	21.00		M
#18 4/C		16.00	20.00	24.00		M
#18 7/C		18.00	22.50	27.00		M
#18 9/C		20.00	25.00	30.00		M
#18 12/C		22.00	27.50	33.00		M
#16 2/C		16.00	20.00	24.00		M
#16 3/C		18.00	22.50	27.00		M
#16 4/C		20.00	25.00	30.00		M
#14 2/C		20.00	25.00	30.00		M
#14 3/C		22.00	27.50	33.00		M
#14 4/C		24.00	30.00	36.00		M
<b>5 KV Power Cable-Unshielded-</b>						
<b>1/C Copper - XLP Insulated - PVC Jacketed</b>						
#10		9.00	11.25	13.50		M
#8		11.00	13.75	16.50		M
#6		13.00	16.25	19.50		M
#4		15.00	18.75	22.50		M
#3		17.00	21.25	25.50		M
#2		19.00	23.75	28.50		M
#1		21.00	26.25	31.50		M
1/0		23.00	28.75	34.50		M
2/0		25.00	31.25	37.50		M
3/0		28.00	35.00	42.00		M
4/0		31.00	38.75	46.50		M
250 kcmil		34.00	42.50	51.00		M
300 kcmil		37.00	46.25	55.50		M
350 kcmil		40.00	50.00	60.00		M
400 kcmil		44.00	55.00	66.00		M
500 kcmil		50.00	62.50	75.00		M
600 kcmil		56.00	70.00	84.00		M
750 kcmil		60.00	75.00	90.00		M
1000 kcmil		70.00	87.50	105.00		M

3




Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>5 KV Power Cable-Shielded-</b>						
<b>1/C Copper - XLP Insulated - PVC Jacketed</b>						
#10		10.00	12.50	15.00		M
#8		12.00	15.00	18.00		M
#6		14.00	17.50	21.00		M
#4		16.00	20.00	24.00		M
#3		18.00	22.50	27.00		M
#2		20.00	25.00	30.00		M
#1		22.00	27.50	33.00		M
1/0		24.00	30.00	36.00		M
2/0		27.00	33.75	40.50		M
3/0		30.00	37.50	45.00		M
4/0		33.00	41.25	49.50		M
250 kcmil		36.00	45.00	54.00		M
300 kcmil		40.00	50.00	60.00		M
350 kcmil		44.00	55.00	66.00		M
400 kcmil		48.00	60.00	72.00		M
500 kcmil		52.00	65.00	78.00		M
600 kcmil		60.00	75.00	90.00		M
750 kcmil		66.00	82.50	99.00		M
1000 kcmil		74.00	92.50	111.00		M
<b>5 KV Power Cable-3/C-</b>						
<b>w/o Ground Shielded Copper - XLP - PVC Jacketed</b>						
#8		25.00	31.20	37.50		M
#6		30.00	37.50	45.00		M
#4		35.00	43.70	52.50		M
#2		40.00	50.00	60.00		M
#1		45.00	56.00	67.00		M
1/0		50.00	62.00	75.00		M
2/0		55.00	68.00	82.00		M
3/0		60.00	75.00	90.00		M
4/0		65.00	81.00	97.00		M
250 kcmil		70.00	87.00	105.00		M
300 kcmil		75.00	93.00	112.00		M
350 kcmil		80.00	100.00	120.00		M
400 kcmil		85.00	106.00	127.00		M
500 kcmil		90.00	112.00	135.00		M
600 kcmil		100.00	125.00	150.00		M
750 kcmil		110.00	137.00	165.00		M
<b>5 KV Power Cable-3/C-</b>						
<b>with Ground Shielded - Copper - XLP - PVC Jacketed</b>						
#8		30.00	37.50	45.00		M
#6		35.00	43.70	52.50		M
#4		40.00	50.00	60.00		M
#2		45.00	56.00	67.00		M
#1		50.00	62.00	75.00		M
1/0		55.00	68.00	82.00		M
2/0		60.00	75.00	90.00		M
3/0		65.00	81.00	97.00		M
4/0		70.00	87.00	105.00		M
250 kcmil		75.00	93.00	112.00		M
300 kcmil		80.00	100.00	120.00		M
350 kcmil		85.00	106.00	127.00		M
400 kcmil		90.00	112.00	135.00		M
500 kcmil		100.00	125.00	150.00		M
600 kcmil		110.00	137.00	165.00		M
750 kcmil		120.00	150.00	180.00		M
1000 kcmil		135.00	165.00	200.00		M
<b>15 KV Power Cable-1/C Shielded -</b>						
<b>Copper - XLP - PVC Jacketed</b>						
#6		20.00	25.00	30.00		M
#4		22.00	27.50	33.00		M
#2		26.00	32.50	39.00		M
#1		28.00	35.00	42.00		M
1/0		30.00	37.50	45.00		M
2/0		32.00	40.00	48.00		M
3/0		35.00	43.75	52.50		M
4/0		38.00	47.50	57.00		M
250 kcmil		41.00	51.25	61.50		M
300 kcmil		44.00	55.00	66.00		M
350 kcmil		48.00	60.00	72.00		M
400 kcmil		52.00	65.00	78.00		M
500 kcmil		58.00	72.50	87.00		M
600 kcmil		64.00	80.00	96.00		M
750 kcmil		70.00	87.50	105.00		M
1000 kcmil		80.00	100.00	120.00		M

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct




Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>15 KV Power Cable-3/C-</b>						
<b>w/o ground Shielded - Copper - XLP PVC Jacketed</b>						
#6		40.00	50.00	60.00		M
#4		45.00	56.00	67.00		M
#2		50.00	62.00	75.00		M
#1		55.00	68.00	82.00		M
1/0		60.00	75.00	90.00		M
2/0		65.00	81.00	97.00		M
3/0		70.00	87.00	105.00		M
4/0		75.00	93.00	112.00		M
250 kcmil		80.00	100.00	120.00		M
300 kcmil		85.00	106.00	127.00		M
350 kcmil		90.00	112.00	135.00		M
400 kcmil		100.00	125.00	150.00		M
500 kcmil		110.00	137.00	165.00		M
600 kcmil		120.00	150.00	180.00		M
750 kcmil		135.00	165.00	200.00		M
1000 kcmil		150.00	185.00	225.00		M
<b>600 Volt MC Cable with Alum. or Steel Armor - Copper</b>						
<b>Cable available in 120/208V and 277/480V Colors</b>						
#14-2-G Solid		25.00	31.25	39.06		M
#14-3-G Solid		27.00	33.75	42.19		M
#14-4-G Solid		29.00	36.25	45.31		M
#12-2-G Solid		26.00	32.50	40.63		M
#12-3-G Solid		28.00	35.00	43.75		M
#12-4-G Solid		30.00	37.50	46.88		M
#10-2-G Solid		29.00	36.25	45.31		M
#10-3-G Solid		32.00	40.00	50.00		M
#10-4-G Solid		35.00	43.75	54.69		M
#14-2-G Stranded		25.00	31.25	39.06		M
#14-3-G Stranded		27.00	33.75	42.19		M
#14-4-G Stranded		29.00	36.25	45.31		M
#12-2-G Stranded		26.00	32.50	40.63		M
#12-3-G Stranded		28.00	35.00	43.75		M
#12-4-G Stranded		30.00	37.50	46.88		M
#10-2-G Stranded		28.50	35.63	44.53		M
#10-3-G Stranded		31.50	39.38	49.22		M
#10-4-G Stranded		34.50	43.13	53.91		M
#8-2-10 GRD Stranded		33.00	41.25	51.56		M
#8-3-10 GRD Stranded		36.00	45.00	56.25		M
#8-4-10 GRD Stranded		41.00	51.25	64.06		M
#6-2-8 GRD Stranded		37.00	46.25	57.81		M
#6-3-8 GRD Stranded		41.00	51.25	64.06		M
#6-4-8 GRD Stranded		45.00	56.25	70.31		M
#4-2-8 GRD Stranded		41.00	51.25	64.06		M
#4-3-8 GRD Stranded		45.00	56.25	70.31		M
#4-4-8 GRD Stranded		49.00	61.25	76.56		M
#3-2-6 GRD Stranded		44.00	55.00	68.75		M
#3-3-6 GRD Stranded		48.00	60.00	75.00		M
#3-4-6 GRD Stranded		52.00	65.00	81.25		M
#2-3-6 GRD Stranded		48.00	60.00	75.00		M
#2-4-6 GRD Stranded		52.00	65.00	81.25		M
#1-3-6 GRD Stranded		56.00	70.00	87.50		M
<b>600 Volt MC Cable - Homerun Cables - Copper</b>						
#12-6-G Solid		36.00	45.00	56.25		M
#12-8-G Solid		40.00	50.00	62.50		M
#12-12-G Solid		48.00	60.00	75.00		M
#12-16-G Solid		56.00	70.00	87.50		M
#10-6-G Solid		41.00	51.25	64.06		M
#10-8-G Solid		47.00	58.75	73.44		M
#10-12-G Solid		56.00	70.00	87.50		M
#10-16-G Solid		68.00	85.00	106.25		M
#12-6-G Stranded		36.00	45.00	56.25		M
#12-8-G Stranded		40.00	50.00	62.50		M
#12-12-G Stranded		48.00	60.00	75.00		M
#12-16-G Stranded		56.00	70.00	87.50		M
#10-6-G Stranded		40.00	50.00	62.50		M
#10-8-G Stranded		46.00	57.50	71.88		M
#10-12-G Stranded		55.00	68.75	85.94		M
#10-16-G Stranded		67.00	83.75	104.69		M
<b>600 Volt AC Cable with Alum. or Steel Armor - Copper</b>						
<b>AC Cable has #16 aluminum bonding inside metal armor</b>						
<b>Metal armor provides equipment ground</b>						
<b>Health Care Facilities Cable (HCF)</b>						
<b>Cable includes the #16 bonding strip plus a full size grounding conductor</b>						
<b>Combination provides redundant ground or isolated ground</b>						
<b>Cables available in 120/208V and 277/480V colors</b>						
#12-2-G Solid		26.50	33.13	41.41		M
#12-3-G Solid		28.50	35.63	44.53		M
#12-4-G Solid		30.50	38.13	47.66		M
#10-2-G Solid		29.50	36.88	46.09		M
#10-3-G Solid		32.50	40.63	50.78		M
#10-4-G Solid		35.50	44.38	55.47		M
#12-2-G Stranded		26.50	33.13	41.41		M
#12-3-G Stranded		28.50	35.63	44.53		M
#12-4-G Stranded		30.50	38.13	47.66		M
#10-2-G Stranded		29.00	36.25	45.31		M
#10-3-G Stranded		32.00	40.00	50.00		M
#10-4-G Stranded		35.00	43.75	54.69		M



Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct


3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Fire Alarm/Control MC Cable with Alum. or Steel Armor - Copper</b>						
<b>Solid TFFN Conductors</b>						
#18-2 Blk, Wh		20.00	25.00	31.25		M
#18-4 Blk, Wh, Red, Bl		24.00	30.00	37.50		M
#18-6 Blk, Wh, Red, Bl, Yel, Or		28.00	35.00	43.75		M
#18-8 Blk, Wh, Red, Bl, Yel, Or, Br, Pur		32.00	40.00	50.00		M
#16-2 Blk, Wh		22.00	27.50	34.38		M
#16-4 Blk, Wh, Red, Bl		25.00	31.25	39.06		M
#16-6 Blk, Wh, Red, Bl, Yel, Or		28.00	35.00	43.75		M
#16-8 Blk, Wh, Red, Bl, Yel, Or, Br, Pur		32.00	40.00	50.00		M
<b>Solid THHN Conductors</b>						
#14-2 Blk, Wh		25.00	31.25	39.06		M
#14-4 Blk, Wh, Red, Bl		29.00	36.25	45.31		M
#14-6 Blk, Wh, Red, Bl, Yel, Or		33.00	41.25	51.56		M
#14-8 Blk, Wh, Red, Bl, Yel, Or Br, Pur		37.00	46.25	57.81		M
#12-2 Blk, Wh		26.00	32.50	40.63		M
#12-4 Blk, Wh, Red, Bl		30.00	37.50	46.88		M
<b>Solid Twisted Shielded Pairs</b>						
#18-2 Blk, Wh		20.00	25.00	31.25		M
#18-2 Blk, Wh 14-2 Blk, Wh		28.00	35.00	43.75		M
#16-2 Blk, Wh		22.00	27.50	34.38		M
#16-4 Blk, Wh & Red, Bl		25.00	31.25	39.06		M
#16-2 Blk, Wh 12-2 Blk, Red		30.00	37.50	46.88		M
#14-2 Blk, Wh		25.00	31.25	39.06		M
#14-4 Blk, Red & Bl, Wh		29.00	36.25	45.31		M
<b>Labor Units - 3 Conductor - Aluminum</b>						
<b>MC Cable with Alum. or Steel Armor</b>						
<b>Cables available in 120/208V and 277/480V colors</b>						
#8-8-8-8		31.00	38.75	48.44		M
#6-6-6-6		35.00	43.75	54.69		M
#4-4-4-6		39.00	48.75	60.94		M
#2-2-2-6		47.00	58.75	73.44		M
#1-1-1-4		51.00	63.75	79.69		M
#1/0-1/0-1/0-4		56.00	70.00	87.50		M
#2/0-2/0-2/0-4		61.00	76.25	95.31		M
#3/0-3/0-3/0-4		66.00	82.50	103.13		M
#4/0-4/0-4/0-2		71.00	88.75	110.94		M
#250-250-250-2		76.00	95.00	118.75		M
#300-300-300-2		81.00	101.25	126.56		M
#350-350-350-2		91.00	113.75	142.19		M
#400-400-400-1		96.00	120.00	150.00		M
#500-500-500-1		101.00	126.25	157.81		M
#600-600-600-1		111.00	138.75	173.44		M
#700-700-700-1/0		116.00	145.00	181.25		M
#750-750-750-1/0		121.00	151.25	189.06		M
<b>Labor Units - 4 Conductor - Aluminum</b>						
<b>MC Cable with Alum. or Steel Armor</b>						
<b>Cables available in 120/208V and 277/480V colors</b>						
#8-8-8-8-8		36.00	45.00	56.25		M
#6-6-6-6-6		40.00	50.00	62.50		M
#4-4-4-4-6		43.00	53.75	67.19		M
#2-2-2-2-6		52.00	65.00	81.25		M
#1-1-1-1-4		56.00	70.00	87.50		M
#1/0-1/0-1/0-1/0-4		61.00	76.25	95.31		M
#2/0-2/0-2/0-2/0-4		66.00	82.50	103.13		M
#3/0-3/0-3/0-3/0-4		71.00	88.75	110.94		M
#4/0-4/0-4/0-4/0-2		76.00	95.00	118.75		M
#250-250-250-250-1		81.00	101.25	126.56		M
#300-300-300-300-1		86.00	107.50	134.38		M
#350-350-350-350-1/0		96.00	120.00	150.00		M
#400-400-400-400-1/0		99.00	123.75	154.69		M
#500-500-500-500-2/0		106.00	132.50	165.63		M
#500-500-500-500-250		111.00	138.75	173.44		M
#600-600-600-600-2/0		116.00	145.00	181.25		M
#600-600-600-600-400		121.00	151.25	189.06		M
#700-700-700-700-2/0		126.00	157.50	196.88		M
#750-750-750-750-3/0		136.00	170.00	212.50		M
#750-750-750-750-750		146.00	182.50	228.13		M



Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct




Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>MC Connector for Copper MC - General Duty</b>						
1/2" MC Conn = 14-2, 12-2, 10-2, 14-3, 12-3, 10-3, 14-4, 12-4, 10-4 (All cables have a grd cond)						
3/4" MC Conn = 8-3, 8-4 (Cables have a #10 grd)						
1" MC Conn = 6-3, 4-3, 2-3, 6-7, 4-4 (#6, 4 cables have a #8 grd, #2 cable has a #6 grd)						
1 1/4" MC Conn = 1-3, 1/0-3, 2/0-3, 3/0-3, 2-4, 1-4, 1/0-4 (#1, 2, 1, 1/0, 2/0 cables have a #6 grd, #3/0 cable has a #4 grd)						
1 1/2" MC Conn = 4/0-3, 2/0-4, 3/0-4, 4/0-4 (#2 cable has a #6 grd, #3/0, 4/0 cables have a #4 grd)						
2" MC Conn = 250-3, 350-3, 250-4, 350-4 (#250 cables have a #4 grd, #350 cables have #3 grd)						
2 1/2" MC Conn = 500-3, 750-3, 500-4, 600-4 (#500, 600 cables have a #2 grd, #750 cable has a #4/0 grd)						
3" MC Conn = #750-4 (#750 cable has a #1/0 grd)						
<b>MC Connector for Aluminum MC - General Duty</b>						
1" MC Conn = 6-3, 4-3, 2-3, 6-4, 4-4, 2-4 (#6, 4 cables have a #6 grd, #2 cables has a #4 grd)						
1 1/4" MC Conn = 1-3, 1/0-3, 2/0-3, 3/0-3, 1-4, 1/0-4 (#1, 1/0, 2/0 cables have a #4 grd)						
1 1/2" MC Conn = 4/0-3, 250-3, 2/0-4, 3/0-4, 4/0-4 (#2/0, 3/0 cables have a #4 grd, #4/0, 250 cables have a #2 grd)						
2" MC Conn = 300-3, 350-3, 400-3, 250-4, 300-4, 350-4 (#250, 300, 400 cables have a #1 grd, #350-4 cable has a #1/0 grd)						
2 1/2" MC Conn = 500-3, 600-3, 750-3, 400-4, 500-4, 600-4 (#500-3=#1 grd, #600-3; 750-3=#1/0 grd; 400-4, 500-4, 600-4=#3/0 grd)						
3" MC Conn K= 750-3, 900-3 (#750-4 has #3/0 grd. #900 has a #250 grd)						
1/2" MC Connector		0.12	0.15	0.19		E
3/4" MC Connector		0.14	0.18	0.22		E
1" MC Connector		0.16	0.20	0.25		E
1 1/4" MC Connector		0.18	0.23	0.28		E
1 1/2" MC Connector		0.25	0.31	0.39		E
2" MC Connector		0.30	0.38	0.47		E
2 1/2" MC Connector		0.35	0.44	0.55		E
3" MC Connector		0.45	0.56	0.70		E
<b>Straps for MC Cable</b>						
3/4" and larger straps are EMT 1-hole straps						
3/8" = 14-2, 12-2						
3/8" = 14-3, 12-3						
1/2" = 12-4, 10-2, 10-3						
3/4" = 8-3, 8-4						
1" = 6-3, 4-3, 2-3, 6-4, 4-4						
1 1/4" = 1-3, 1/0-3, 2/0-3, 3/0-3, 2-4, 1-4, 1/0-4						
1 1/2" = 4/0-3, 2/0-4, 3/0-4, 4/0-4						
2" = 250-3, 350-3, 250-4, 350-4						
2 1/2" = 500-3, 750-3, 500-4, 600-4						
3" = #750-4						
14-2, 12-2 One Hole Strap		0.03	0.04	0.05		E
14-3, 12-3 One Hole Strap		0.03	0.04	0.05		E
3/8" One Hole Strap		0.03	0.04	0.05		E
3/4" One Hole Strap		0.04	0.05	0.06		E
1" One Hole Strap		0.04	0.05	0.06		E
1 1/4" One Hole Strap		0.05	0.06	0.08		E
1 1/2" One Hole Strap		0.06	0.08	0.09		E
2" One Hole Strap		0.10	0.13	0.16		E
2 1/2" One Hole Strap		0.11	0.14	0.17		E
3" One Hole Strap		0.12	0.15	0.19		E
<b>600 Volt Non-Metallic Sheathed Cable Copper -</b>						
<b>Type NM and UF w/o Ground</b>						
1/C #12		25.00	31.20	37.50		M
1/C #10		30.00	37.50	45.00		M
1/C #8		35.00	43.70	52.50		M
1/C #6		40.00	50.00	60.00		M
2/C #14		30.00	37.50	45.00		M
2/C #12		35.00	43.70	52.70		M
2/C #10		40.00	50.00	60.00		M
2/C #8		45.00	56.20	67.50		M
2/C #6		55.00	68.70	82.50		M
3/C #14		40.00	50.00	60.00		M
3/C #12		45.00	56.20	67.50		M
3/C #10		50.00	62.50	75.00		M
3/C #8		60.00	75.00	90.00		M
3/C #6		70.00	87.00	105.00		M
<i>Deduct 10% for U.F. Cable Installed in a trench.</i>						



Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>600 Volt Non-Metallic Sheathed Cable Copper - Type NM and UF with Ground</b>						
2/C #14		30.00	37.50	45.00		M
2/C #12		35.00	43.75	52.50		M
2/C #10		40.00	50.00	60.00		M
2/C #8		45.00	56.25	67.50		M
2/C #6		50.00	62.50	75.00		M
3/C #14		35.00	43.75	52.50		M
3/C #12		40.00	50.00	60.00		M
3/C #10		45.00	56.25	67.50		M
3/C #8		50.00	62.50	75.00		M
3/C #6		60.00	75.00	90.00		M
3/C #4		70.00	81.00	98.00		M
3/C #2		80.00	92.00	105.00		M
4/C #14		35.00	44.00	53.00		M
4/C #12		40.00	50.00	60.00		M
4/C #10		45.00	56.00	68.00		M
<i>Deduct 10% for U.F. Cable Installed in a trench.</i>						
<b>600 Volt Mineral Insulated Cable Type MI Non-Heating</b>						
#16 1/C		35.00	43.75	52.50		M
#16 2/C		40.00	50.00	60.00		M
#16 3/C		45.00	56.25	67.50		M
#16 4/C		50.00	62.50	75.00		M
#16 7/C		55.00	68.75	82.50		M
#14 1/C		40.00	50.00	60.00		M
#14 2/C		45.00	56.25	67.50		M
#14 3/C		50.00	62.50	75.00		M
#14 4/C		55.00	68.75	82.50		M
#14 7/C		60.00	75.00	90.00		M
#12 1/C		45.00	56.25	67.50		M
#12 2/C		50.00	62.50	75.00		M
#12 3/C		55.00	68.75	82.50		M
#12 4/C		60.00	75.00	90.00		M
#12 7/C		65.00	81.25	97.50		M
#10 1/C		50.00	62.50	75.00		M
#10 2/C		60.00	75.00	90.00		M
#10 3/C		70.00	87.50	105.00		M
#10 4/C		80.00	100.00	120.00		M
#10 7/C		90.00	112.50	135.00		M
#8 1/C		60.00	75.00	90.00		M
#8 2/C		70.00	87.50	105.00		M
#8 3/C		80.00	100.00	120.00		M
#8 4/C		90.00	112.50	135.00		M
#6 1/C		70.00	87.50	105.00		M
#6 2/C		80.00	100.00	120.00		M
#6 3/C		90.00	112.50	135.00		M
#6 4/C		100.00	125.00	150.00		M
#4 1/C		80.00	100.00	120.00		M
#4 2/C		90.00	112.50	135.00		M
#4 3/C		100.00	125.00	150.00		M
#4 4/C		110.00	137.50	165.00		M
#3 1/C		80.00	100.00	120.00		M
#2 1/C		85.00	106.25	127.50		M
#1 1/C		90.00	112.50	135.00		M
1/0 1/C		95.00	118.75	142.50		M
2/0 1/C		100.00	125.00	150.00		M
3/0 1/C		105.00	131.25	157.50		M
4/0 1/C		110.00	137.50	165.00		M
<b>600 Volt Mineral Insulated Cable Terminators</b>						
#12 1/C		0.40	0.50	0.60		E
#12 2/C		0.50	0.60	0.75		E
#12 3/C		0.60	0.75	0.90		E
#12 4/C		0.70	0.90	1.05		E
#12 7/C		0.80	1.00	1.20		E
#10 1/C		0.50	0.60	0.75		E
#10 2/C		0.60	0.75	0.90		E
#10 3/C		0.70	0.90	1.05		E
#10 4/C		0.80	1.00	1.20		E
#10 7/C		0.90	1.10	1.35		E
#8 1/C		0.60	0.75	0.90		E
#8 2/C		0.70	0.90	1.05		E
#8 3/C		0.80	1.00	1.20		E
#8 4/C		0.90	1.10	1.35		E
#6 1/C		0.70	0.90	1.05		E
#6 2/C		0.80	1.00	1.20		E
#6 3/C		0.90	1.10	1.35		E
#6 4/C		1.00	1.25	1.50		E
#4 1/C		0.80	1.00	1.20		E
#4 2/C		0.90	1.10	1.35		E
#4 3/C		1.00	1.25	1.50		E
#4 4/C		1.10	1.40	1.65		E
#3 1/C		0.90	1.10	1.35		E
#2 1/C		1.00	1.25	1.50		E
#1 1/C		1.10	1.40	1.65		E
1/0 1/C		1.25	1.60	1.90		E
2/0 1/C		1.40	1.75	2.10		E
3/0 1/C		1.60	2.00	2.40		E
4/0 1/C		1.80	2.25	2.70		E







Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>300 Volt Solid Connector Plenum Cable</b>						
#22 1-Pair		10.00	12.50	15.00		M
#22 2-Pair		11.00	13.70	16.50		M
#22 3-Pair		12.00	15.00	18.00		M
#22 4-Pair		13.00	16.20	19.50		M
#22 5-Pair		14.00	17.50	21.00		M
#22 6-Pair		16.00	20.00	24.00		M
#22 10-Pair		19.00	23.70	28.50		M
#22-15-Pair		22.00	27.50	33.00		M
#22 20-Pair		26.00	32.50	39.00		M
#22 25-Pair		30.00	37.50	45.00		M
#20 1-Pair		11.00	13.70	16.50		M
#20 2-Pair		12.00	15.00	18.00		M
#20 3-Pair		14.00	17.50	21.00		M
#20 4-Pair		16.00	20.00	24.00		M
#20 5-Pair		18.00	22.50	27.00		M
#20 6-Pair		20.00	25.00	30.00		M
#20 10-Pair		24.00	30.00	36.00		M
#20 15-Pair		28.00	35.00	42.00		M
#18 1-Pair		12.00	15.00	18.00		M
#18 2-Pair		14.00	17.50	21.00		M
#18 3-Pair		17.00	21.20	25.50		M
#18 4-Pair		20.00	25.00	30.00		M
#18 5-Pair		23.00	28.70	34.50		M
#18 6-Pair		26.00	32.50	39.00		M
#18 10-Pair		30.00	37.50	45.00		M
#16 1-Pair		14.00	17.50	21.00		M
#16 2-Pair		17.00	21.20	25.50		M
#16 3-Pair		20.00	25.00	30.00		M
#16 4-Pair		23.00	28.70	34.50		M
#16 5-Pair		26.00	32.50	39.00		M
#16 6-Pair		29.00	36.20	43.50		M
#16 10-Pair		34.00	42.50	51.00		M
<b>600 Volt Stranded Copper Control Cable</b>						
#16 5/C		16.00	20.00	24.00		M
#16 6/C		17.00	21.20	25.50		M
#16 8/C		18.00	22.50	27.00		M
#16 10/C		19.00	23.70	28.50		M
#16 12/C		21.00	26.20	31.50		M
#16 16/C		24.00	30.00	36.00		M
#16 20/C		27.00	33.70	40.50		M
#14 2/C		14.00	17.50	21.00		M
#14 3/C		15.00	18.70	22.50		M
#14 4/C		16.00	20.00	24.00		M
#14 6/C		18.00	22.50	27.00		M
#14 8/C		20.00	25.00	30.00		M
#14 10/C		23.00	28.70	34.50		M
#14 14/C		26.00	32.50	39.00		M
#14 18/C		29.00	36.20	43.50		M
#14 24/C		33.00	41.20	49.50		M
#12 2/C		15.00	18.70	22.50		M
#12 3/C		16.00	20.00	24.00		M
#12 4/C		18.00	22.50	27.00		M
#12 6/C		21.00	26.20	31.50		M
#12 8/C		24.00	30.00	36.00		M
#12 10/C		27.00	33.70	40.50		M
#12 14/C		31.00	38.70	46.50		M
#12 18/C		35.00	43.70	52.50		M
#12 24/C		40.00	50.00	60.00		M

3

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct




3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Wire Connectors (Wire Nuts)</b>						
 Orange Wire Connector		0.04	0.06	0.08		E
 Yellow Wire Connector		0.05	0.07	0.09		E
Red Wire Connector		0.06	0.08	0.10		E
Gray Wire Connector		0.07	0.09	0.11		E
Blue Wire Connector		0.08	0.10	0.12		E
<b>Crimp Terminations - Spade Type</b>						
#22 to #18		0.08	0.10	0.12		E
#16 TO #14		0.10	0.13	0.15		E
#12 TO #10		0.12	0.15	0.18		E
<b>Crimp Terminations - Ring Type</b>						
#22 to # 18		0.10	0.13	0.15		E
#16 to #14		0.12	0.15	0.18		E
#12 to #10		0.14	0.17	0.21		E
<b>Wire Identification</b>						
Brady Marker - Per Digit		0.02	0.03	0.04		E
Clear Wrap Tape		0.02	0.03	0.04		E
Machine Coded Sleeve		0.05	0.08	0.10		E
Phase Tape - Per Phase		0.02	0.03	0.04		E
Feeder Designation Tag		0.10	0.15	0.20		E
<b>Terminal Blocks - Excludes Terminations</b>						
Mounting Channel - Per Foot		0.10	0.12	0.15		E
End Plate		0.03	0.04	0.05		E
Terminal Block		0.02	0.03	0.04		E
Plastic Wire Trough		0.10	0.12	0.15		LF
Cover		0.02	0.03	0.04		E
<b>600 Volt Type FCC Flat Under Carpet Wiring</b>						
<b>Junction Box</b>						
New Construction		0.25	0.31	0.38		E
Utilize Existing Box		0.20	0.25	0.30		E
Retro-Fit Existing Construction		0.50	0.63	0.75		E
<b>Install Round To Flat Cable</b>						
<b>Transition Block</b>						
<b>In Junction Box</b>		0.50	0.63	0.75		E
3 Conductor # 10 Cable		7.50	9.38	11.25		C
5 Conductor # 10 Cable		7.50	9.38	11.25		C
<i>Includes: Clean Concrete Floor</i>						
<i>Moisture Barrier Tape</i>						
<i>Power cable</i>						
<i>Hold-down Tape</i>						
<b>Flat Undercarpet</b>						
<b>Tee-Tap / X Tap / Change of direction</b>						
3 Conductor # 10 Cable		0.25	0.31	0.38		E
5 Conductor # 10 Cable		0.50	0.63	0.75		E
<i>One Splice Per Conductor</i>						
<i>Requires Special Crimp Tool</i>						
<i>Insulator Kit For Ea Crimp Splice</i>						
<b>Floor Mount Power Pedestal</b>						
<b>Single or Double Duplex</b>						
<b>Mount Pedestal and Terminate</b>						
3 Conductor # 10 Cable		0.50	0.63	0.75		E
5 Conductor # 10 Cable		0.50	0.63	0.75		E
Remove and Replace Carpet Tile		3.30	4.13	4.95		C
<b>Undercarpet Telephone and Data Flat Cable</b>						
<b>Junction Box</b>						
New Construction		0.25	0.31	0.38		E
Utilize Existing Box		0.20	0.25	0.30		E
Retro-Fit Existing Box		0.50	0.63	0.75		E
<b>Install Flat To Round</b>						
<b>Cable Transition Block in</b>						
<b>Junction Box - All Types</b>						
Single Conductor		0.25	0.31	0.38		E
Multi-Conductor		0.40	0.50	0.60		E

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Install Telephone an Data</b>						
Flat Cable - All Types		7.50	9.38	11.25		C
<i>Includes: Clean Concrete Floor Moisture Barrier Tele/Data Cable Hold-Down Tape</i>						
<b>Floor Mount Telephone or Data</b>						
Pedestal		0.50	0.63	0.75		E
<b>Install Floor Pedestal</b>						
<b>Install Flat Cable to Modular Ass.</b>						
Single Conductor		0.25	0.31	0.38		E
Mult-Conductor		0.40	0.50	0.60		E
Remove and Replace Carpet Tile		3.30	4.13	4.95		C
<i>Note: Does not include testing of tele/data cable</i>						
<b>Cord Bodies</b>						
15 - 20 Amp		0.50	0.63	0.75		E
30 Amp		0.60	0.75	0.90		E
50 Amp		0.75	0.94	1.13		E
<b>Kellems Grips up to 1"</b>						
Threaded		0.25	0.31	0.38		E
With Yoke		0.15	0.19	0.23		E
<b>600 Volt Type TC Copper Tray Cable THHN</b>						
2/C #12		16.00	20.00	24.00		M
2/C #10		18.00	22.50	27.00		M
2/C #8		20.00	25.00	30.00		M
2/C #6		23.00	28.70	34.50		M
2/C #4		28.00	35.00	42.00		M
2/C #2		34.00	42.50	51.00		M
3/C #12		18.00	22.50	27.00		M
3/C # 10		20.00	25.00	30.00		M
3/C #8		22.00	27.50	33.00		M
3/C #6		26.00	32.50	39.00		M
3/C #4		32.00	40.00	48.00		M
3/C #2		38.00	47.50	57.00		M
3/C #1		44.00	55.00	66.00		M
3/C 1/0		52.00	65.00	78.00		M
3/C 2/0		60.00	75.00	90.00		M
3/C 3/0		70.00	87.00	105.00		M
3/C 4/0		80.00	100.00	120.00		M
4/C #12		20.00	25.00	30.00		M
4/C #10		22.00	27.50	33.00		M
4/C #8		25.00	31.20	37.50		M
4/C #6		30.00	37.50	45.00		M
4/C #4		40.00	50.00	60.00		M
4/C #2		50.00	62.00	75.00		M
4/C #1		60.00	75.00	90.00		M
4/C 1/0		70.00	87.00	105.00		M
4/C 2/0		80.00	100.00	120.00		M
4/C 3/0		90.00	112.00	135.00		M
4/C 4/0		100.00	125.00	150.00		M
<b>600 Volt Type S-SJ-SO Flexible Cord</b>						
#18 2/C		23.00	28.75	34.50		M
#18 3/C		25.00	31.25	37.50		M
#18 4/C		27.00	33.75	40.50		M
#16 2/C		23.00	28.75	34.50		M
#16 3/C		25.00	31.25	37.50		M
#16 4/C		27.00	33.75	40.50		M
#14 2/C		30.00	37.50	45.00		M
#14 3/C		32.00	40.00	48.00		M
#14 4/C		34.00	42.50	51.00		M
#12 2/C		32.00	40.00	48.00		M
#12 3/C		34.00	42.50	51.00		M
#12 4/C		36.00	45.00	54.00		M
#10 2/C		35.00	43.75	52.50		M
#10 3/C		37.00	46.25	55.50		M
#10 4/C		39.00	48.75	58.50		M
#8 2/C		38.00	47.50	57.00		M
#8 3/C		40.00	50.00	60.00		M
#8 4/C		42.00	52.50	63.00		M



Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3



Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>600 Volt Interlocked Armor Cable 3/C Copper</b>						
#12		28.00	35.00	42.00		M
#10		31.00	38.70	46.50		M
#8		34.00	42.50	51.00		M
#6		38.00	47.50	57.00		M
#4		42.00	52.00	63.00		M
#3		46.00	57.50	69.00		M
#2		50.00	62.50	75.00		M
#1		55.00	68.70	82.00		M
1/0		60.00	75.00	90.00		M
2/0		65.00	81.00	97.00		M
3/0		70.00	87.00	105.00		M
4/0		75.00	93.00	112.00		M
250 kcmil		80.00	100.00	120.00		M
300 MC		90.00	112.00	135.00		M
350 kcmil		100.00	125.00	150.00		M
500 kcmil		110.00	137.00	165.00		M
600 kcmil		120.00	150.00	180.00		M
750 kcmil		130.00	162.00	195.00		M
1000 kcmil		150.00	187.00	225.00		M
<b>600 Volt Interlocked Armored Cable 3/C Aluminum</b>						
#12		24.00	30.00	36.00		M
#10		27.00	33.70	40.50		M
#8		30.00	37.50	45.00		M
#6		34.00	42.50	51.00		M
#4		38.00	47.50	57.00		M
#3		42.00	52.00	63.00		M
#2		46.00	57.50	69.00		M
#1		50.00	62.50	75.00		M
1/0		55.00	68.70	82.00		M
2/0		60.00	75.00	90.00		M
3/0		65.00	81.00	97.00		M
4/0		70.00	87.00	105.00		M
250 kcmil		75.00	93.00	112.00		M
300 kcmil		80.00	100.00	120.00		M
350 kcmil		90.00	112.00	135.00		M
500 kcmil		100.00	125.00	150.00		M
600 kcmil		110.00	137.00	165.00		M
750 kcmil		120.00	150.00	180.00		M
1000 kcmil		140.00	175.00	210.00		M
<b>5 KV Interlocked Armored Cable 3/C Copper</b>						
#12		32.00	40.00	48.00		M
#10		35.00	43.70	52.50		M
#8		38.00	47.50	57.00		M
#6		42.00	52.50	63.00		M
#4		46.00	57.50	69.00		M
#3		50.00	62.50	75.00		M
#2		55.00	68.70	82.00		M
#1		60.00	75.00	90.00		M
1/0		65.00	81.00	97.00		M
2/0		70.00	87.00	105.00		M
3/0		75.00	93.00	112.00		M
4/0		80.00	100.00	120.00		M
250 kcmil		90.00	112.00	135.00		M
300 kcmil		100.00	125.00	150.00		M
350 kcmil		110.00	137.00	165.00		M
500 kcmil		120.00	150.00	180.00		M
600 kcmil		130.00	162.00	195.00		M
750 kcmil		140.00	175.00	210.00		M
1000 kcmil		160.00	200.00	240.00		M
<b>5 KV Interlocked Armored Cable 3/C Aluminum</b>						
#12		30.00	37.50	45.00		M
#10		32.00	40.00	48.00		M
#8		34.00	42.50	51.00		M
#6		36.00	45.00	54.00		M
#4		38.00	47.50	57.00		M
#3		41.00	51.20	61.50		M
#2		45.00	56.20	67.50		M
#1		50.00	62.50	75.00		M
1/0		55.00	68.70	82.50		M
2/0		60.00	75.00	90.00		M
3/0		65.00	81.00	97.00		M
4/0		70.00	87.00	105.00		M
250 kcmil		80.00	100.00	120.00		M
300 kcmil		90.00	112.00	135.00		M
350 kcmil		100.00	125.00	150.00		M
500 kcmil		110.00	137.00	165.00		M
600 kcmil		120.00	150.00	180.00		M
750 kcmil		130.00	162.00	195.00		M
1000 kcmil		150.00	187.00	225.00		M

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>15 KV Interlocked Armored Cable</b>						
<b>3/C Shielded - Copper Conductors</b>						
#8		40.00	50.00	60.00		M
#6		45.00	56.20	67.50		M
#4		50.00	62.50	75.00		M
#3		55.00	68.70	82.50		M
#2		60.00	75.00	90.00		M
#1		65.00	81.00	97.00		M
1/0		70.00	87.00	105.00		M
2/0		75.00	93.00	112.00		M
3/0		80.00	100.00	120.00		M
4/0		90.00	112.00	135.00		M
250 kcmil		100.00	125.00	150.00		M
300 kcmil		110.00	137.00	165.00		M
350 kcmil		120.00	150.00	180.00		M
500 kcmil		130.00	162.00	195.00		M
600 kcmil		140.00	175.00	210.00		M
750 kcmil		155.00	193.00	232.00		M
1000 kcmil		170.00	212.00	255.00		M
<b>15 KV Interlocked Armored Cable</b>						
<b>3/C Shielded - Aluminum Conductors</b>						
#8		35.00	43.70	52.50		M
#6		40.00	50.00	60.00		M
#4		45.00	56.20	67.50		M
#3		50.00	62.50	75.00		M
#2		55.00	68.70	82.50		M
#1		60.00	75.00	90.00		M
1/0		65.00	81.00	97.00		M
2/0		70.00	87.00	105.00		M
3/0		75.00	93.00	112.00		M
4/0		80.00	100.00	120.00		M
250 kcmil		90.00	112.00	135.00		M
300 kcmil		100.00	125.00	150.00		M
350 kcmil		110.00	137.00	165.00		M
500 kcmil		120.00	150.00	180.00		M
600 kcmil		120.00	150.00	180.00		M
750 kcmil		145.00	181.00	217.00		M
1000 kcmil		160.00	200.00	240.00		M
<b>300 Volt Service Entrance Cable</b>						
<b>Type SEU 3/C Copper Conductors</b>						
#8		36.00	45.00	54.00		M
#6		42.00	52.50	63.00		M
#4		48.00	60.00	72.00		M
#3		56.00	70.00	84.00		M
#2		64.00	80.00	96.00		M
#1		72.00	90.00	108.00		M
1/0		82.00	102.50	123.00		M
2/0		94.00	117.50	141.00		M
3/0		106.00	132.50	159.00		M
4/0		125.00	156.25	187.50		M
<b>300 Volt Service Entrance Cable</b>						
<b>Type SEU 3/C Aluminum Conductors</b>						
#8		33.00	41.25	49.50		M
#6		39.00	48.75	58.50		M
#4		45.00	56.25	67.50		M
#3		53.00	66.25	79.50		M
#2		61.00	76.25	91.50		M
#1		69.00	86.25	103.50		M
1/0		79.00	98.75	118.50		M
2/0		90.00	112.50	135.00		M
3/0		100.00	125.00	150.00		M
4/0		110.00	137.50	165.00		M
<b>600 Volt Service Entrance Cable</b>						
<b>Type SER 3/C Copper Conductors</b>						
#8		40.00	50.00	60.00		M
#6		46.00	57.50	69.00		M
#4		52.00	65.00	78.00		M
#3		60.00	75.00	90.00		M
#2		68.00	85.00	102.00		M
#1		76.00	95.00	114.00		M
1/0		86.00	107.50	129.00		M
2/0		98.00	122.50	147.00		M
3/0		110.00	137.50	165.00		M
4/0		130.00	162.50	195.00		M
<b>600 Volt Service Entrance Cable</b>						
<b>Type SER 3/C Aluminum Conductors</b>						
#8		36.00	45.00	54.00		M
#6		42.00	52.50	63.00		M
#4		48.00	60.00	72.00		M
#3		56.00	70.00	84.00		M
#2		64.00	80.00	96.00		M
#1		72.00	90.00	108.00		M
1/0		82.00	102.50	123.00		M
2/0		92.00	115.00	138.00		M
3/0		104.00	130.00	156.00		M
4/0		124.00	155.00	186.00		M

3

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>600 Volt Service Entrance Cable</b>						
<b>Type SER 4/C Copper Conductors</b>						
#8		50.00	62.50	75.00		M
#6		56.00	70.00	84.00		M
#4		62.00	77.50	93.00		M
#3		70.00	87.50	105.00		M
#2		78.00	97.50	117.00		M
#1		86.00	107.50	129.00		M
1/0		96.00	120.00	144.00		M
2/0		108.00	135.00	162.00		M
3/0		124.00	155.00	186.00		M
4/0		140.00	175.00	210.00		M
<b>Compression Terminal Lugs-One Hole</b>						
Up to #8		0.30	0.38	0.45		E
#6		0.35	0.44	0.53		E
#4		0.40	0.50	0.60		E
#3		0.45	0.56	0.68		E
#2		0.50	0.63	0.75		E
#1		0.55	0.69	0.83		E
1/0		0.60	0.75	0.90		E
2/0		0.65	0.80	0.98		E
3/0		0.70	0.87	1.05		E
4/0		0.75	0.90	1.13		E
250 kcmil		0.80	1.00	1.20		E
350 kcmil		0.90	1.20	1.35		E
500 kcmil		1.00	1.25	1.50		E
750 kcmil		1.25	1.60	1.88		E
1000 kcmil		1.50	1.88	2.25		E
<b>Compression Terminal Lugs-Two Hole</b>						
Up to #8		0.40	0.50	0.60		E
#6		0.45	0.56	0.68		E
#4		0.50	0.63	0.75		E
#3		0.55	0.69	0.83		E
#2		0.60	0.75	0.90		E
#1		0.65	0.80	0.98		E
1/0		0.70	0.87	1.05		E
2/0		0.75	0.90	1.13		E
3/0		0.80	1.00	1.20		E
4/0		0.85	1.10	1.28		E
250 kcmil		0.90	1.20	1.35		E
350 kcmil		1.00	1.25	1.50		E
500 kcmil		1.10	1.40	1.65		E
750 kcmil		1.35	1.70	2.00		E
1000 kcmil		1.60	2.00	2.40		E
<b>Compression Terminal Lugs-Four Hole</b>						
Up to #2		0.72	0.90	1.08		E
#1		0.78	0.98	1.17		E
1/0		0.84	1.05	1.26		E
2/0		0.90	1.10	1.35		E
3/0		0.95	1.20	1.43		E
4/0		1.00	1.30	1.50		E
250 kcmil		1.10	1.30	1.65		E
350 kcmil		1.20	1.50	1.80		E
500 kcmil		1.35	1.70	2.03		E
750 kcmil		1.65	2.06	2.48		E
1000 kcmil		1.95	2.44	2.90		E
<b>Compression Splice Connectors</b>						
Up to #8		0.40	0.50	0.60		E
#6		0.45	0.56	0.67		E
#4		0.50	0.62	0.75		E
#3		0.55	0.68	0.82		E
#2		0.60	0.75	0.90		E
#1		0.70	0.87	1.05		E
1/0		0.80	1.00	1.20		E
2/0		0.90	1.12	1.35		E
3/0		1.05	1.30	1.55		E
4/0		1.25	1.55	1.85		E
250 kcmil		1.50	1.85	2.25		E
350 kcmil		1.75	2.15	2.60		E
500 kcmil		2.00	2.50	3.00		E
750 kcmil		2.25	2.80	3.35		E
1000 kcmil		2.50	3.10	3.75		E

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Mechanical Terminal Lugs-One Hole</b>						
Up to #8		0.30	0.38	0.45		E
#6		0.35	0.44	0.53		E
#4		0.40	0.50	0.60		E
#3		0.45	0.56	0.68		E
#2		0.50	0.63	0.75		E
#1		0.55	0.69	0.83		E
1/0		0.60	0.75	0.90		E
2/0		0.65	0.81	0.98		E
3/0		0.70	0.88	1.05		E
4/0		0.75	0.94	1.13		E
250 kcmil		0.80	1.00	1.20		E
350 kcmil		0.90	1.13	1.35		E
500 kcmil		1.00	1.25	1.50		E
750 kcmil		1.25	1.56	1.88		E
1000 kcmil		1.50	1.88	2.25		E
<b>Mechanical Terminal Lugs-Two Hole</b>						
Up to #8		0.40	0.50	0.60		E
#6		0.45	0.56	0.68		E
#4		0.50	0.63	0.75		E
#3		0.55	0.69	0.83		E
#2		0.60	0.75	0.90		E
#1		0.65	0.81	0.98		E
1/0		0.70	0.88	1.05		E
2/0		0.75	0.94	1.13		E
3/0		0.80	1.00	1.20		E
4/0		0.85	1.06	1.30		E
250 kcmil		0.90	1.13	1.35		E
350 kcmil		1.00	1.25	1.50		E
500 kcmil		1.10	1.38	1.65		E
750 kcmil		1.35	1.69	2.03		E
1000 kcmil		1.60	2.00	2.40		E
<b>Mechanical Terminal Lugs-Four Hole</b>						
Up to #2		0.72	0.90	1.08		E
#1		0.78	0.98	1.17		E
1/0		0.84	1.05	1.26		E
2/0		0.90	1.10	1.35		E
3/0		0.95	1.20	1.43		E
4/0		1.00	1.25	1.50		E
250 kcmil		1.10	1.38	1.65		E
350 kcmil		1.20	1.50	1.80		E
500 kcmil		1.35	1.69	2.03		E
750 kcmil		1.65	2.06	2.48		E
1000 kcmil		1.95	2.44	3.35		E
<b>Mechanical Terminal Lugs-Two Cable</b>						
Up to #8		0.80	1.00	1.20		E
#6		0.90	1.12	1.35		E
#4		1.00	1.25	1.50		E
#3		1.15	1.43	1.70		E
#2		1.30	1.65	2.00		E
#1		1.50	1.85	2.25		E
1/0		1.75	2.15	2.60		E
2/0		2.00	2.50	3.00		E
3/0		2.30	2.85	3.50		E
4/0		2.60	3.25	4.00		E
250 kcmil		3.00	3.75	4.50		E
350 kcmil		3.50	4.35	5.25		E
500 kcmil		4.00	5.00	6.00		E
750 kcmil		4.50	5.60	6.75		E
1000 kcmil		5.00	6.25	7.50		E
<b>Split Bolt Connectors-Tape Wrapped</b>						
Up to #8		0.50	0.62	0.75		E
#6		0.55	0.68	0.82		E
#4		0.60	0.75	0.90		E
#3		0.70	0.87	1.05		E
#2		0.85	1.05	1.25		E
#1		1.00	1.25	1.50		E
1/0		1.20	1.50	1.80		E
2/0		1.40	1.75	2.10		E
3/0		1.60	2.00	2.40		E
4/0		1.80	2.25	2.70		E
250 kcmil		2.00	2.50	3.00		E
350 kcmil		2.25	2.80	3.35		E
500 kcmil		2.50	3.10	3.75		E
750 kcmil		2.75	3.40	4.10		E
1000 kcmil		3.00	3.75	4.50		E








Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Compression Tails - Copper to Aluminum</b>						
Up to #8		0.25	0.31	0.37		E
#6		0.30	0.37	0.45		E
#4		0.35	0.43	0.52		E
#3		0.40	0.50	0.60		E
#2		0.45	0.56	0.67		E
#1		0.50	0.62	0.75		E
1/0		0.60	0.75	0.90		E
2/0		0.70	0.87	1.05		E
3/0		0.80	1.00	1.20		E
4/0		0.90	1.12	1.35		E
250 kcmil		1.10	1.37	1.65		E
350 kcmil		1.30	1.62	1.95		E
500 kcmil		1.50	1.85	2.25		E
750 kcmil		1.75	2.15	2.60		E
1000 kcmil		2.00	2.50	3.00		E
<b>Metallic Sheathed Cable Box Connectors</b>						
1/2"		0.18	0.22	0.27		E
3/4"		0.19	0.23	0.28		E
1"		0.20	0.25	0.30		E
1 1/4"		0.22	0.27	0.33		E
1 1/2"		0.25	0.31	0.37		E
<b>Non-Metallic Sheathed Cable Box Connectors</b>						
3/8"		0.10	0.12	0.15		E
1/2"		0.11	0.13	0.16		E
5/8"		0.12	0.15	0.18		E
3/4"		0.13	0.17	0.20		E
7/8"		0.15	0.19	0.22		E
1"		0.17	0.21	0.25		E
1 1/4"		0.20	0.25	0.30		E
1 1/2"		0.24	0.30	0.36		E
<b>2/C Armored Sheathed Cable Terminators With Sealing Bushing</b>						
Up to #4		1.00	1.25	1.50		E
#3		1.10	1.37	1.65		E
#2		1.20	1.50	1.80		E
#1		1.30	1.68	2.00		E
1/0		1.50	1.87	2.25		E
2/0		1.75	2.18	2.60		E
3/0		2.00	2.50	3.00		E
4/0		2.25	2.80	3.35		E
250 kcmil		2.50	3.10	3.75		E
350 kcmil		2.75	3.40	4.10		E
500 kcmil		3.00	3.75	4.50		E
<b>3/C Armored Sheathed Cable Terminators With Sealing Bushings</b>						
Up to #3		1.00	1.25	1.50		E
#2		1.25	1.55	1.85		E
#1		1.50	1.85	2.25		E
1/0		1.75	2.15	2.60		E
2/0		2.00	2.50	3.00		E
3/0		2.25	2.80	3.35		E
4/0		2.50	3.10	3.75		E
250 kcmil		2.75	3.40	4.10		E
350 kcmil		3.00	3.75	4.50		E
500 kcmil		3.50	4.35	5.25		E
750 kcmil		4.00	5.00	6.00		E
1000 kcmil		4.50	5.60	6.75		E
<b>4/C Armored Sheathed Cable Terminators with Sealing Bushings</b>						
Up to #3		1.25	1.55	1.85		E
#2		1.50	1.85	2.25		E
#1		1.75	2.15	2.60		E
1/0		2.00	2.50	3.00		E
2/0		2.25	2.80	3.35		E
3/0		2.50	3.10	3.75		E
4/0		2.75	3.40	4.10		E
250 kcmil		3.00	3.75	4.50		E
350 kcmil		3.50	4.35	5.25		E
500 kcmil		4.00	5.00	6.00		E
750 kcmil		4.50	5.60	6.75		E
1000 kcmil		5.00	6.25	7.50		E
<b>2/C Jacketed Cable to Conduit Terminators With Sealing Bushings</b>						
Up to 1 1/2" Conduit		1.00	1.25	1.50		E
2" Conduit		1.25	1.55	1.85		E
2 1/2" Conduit		1.50	1.85	2.25		E
3" Conduit		1.75	2.15	2.60		E
3 1/2" Conduit		2.00	2.50	3.00		E
4" Conduit		2.25	2.80	3.35		E
5" Conduit		2.50	3.10	3.75		E
6" Conduit		3.00	3.75	4.50		E



Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
						
<b>3/C Jacketed Cable to Conduit Terminators With Sealing Bushings</b>						
Up to 1 1/2" Conduit		1.25	1.55	1.85		E
2" Conduit		1.50	1.85	2.25		E
2 1/2" Conduit		1.75	2.15	2.60		E
3" Conduit		2.00	2.50	3.00		E
3 1/2" Conduit		2.25	2.80	3.35		E
4" Conduit		2.50	3.10	3.75		E
5" Conduit		3.00	3.75	4.50		E
6" Conduit		3.50	4.35	5.25		E
						
<b>4/C Jacketed Cable to Conduit Terminators with Sealing Bushings</b>						
Up to 1 1/2" Conduit		1.50	1.85	2.25		E
2" Conduit		1.75	2.15	2.60		E
2 1/2" Conduit		2.00	2.50	3.00		E
3" Conduit		2.25	2.80	3.35		E
3 1/2" Conduit		2.50	3.10	3.75		E
4" Conduit		3.00	3.75	4.50		E
5" Conduit		3.50	4.35	5.25		E
6" Conduit		4.00	5.00	6.00		E
						
<b>2/C Jacketed Cable to Conduit Terminators - Compound Filled</b>						
Up to 1 1/2" Conduit		1.50	1.55	2.25		E
2" Conduit		1.75	2.15	2.60		E
2 1/2" Conduit		2.00	2.50	3.00		E
3" Conduit		2.25	2.80	3.35		E
3 1/2" Conduit		2.50	3.10	3.75		E
4" Conduit		3.00	3.75	4.50		E
5" Conduit		3.75	4.65	5.60		E
6" Conduit		4.50	5.60	6.75		E
						
<b>3/C Jacketed Cable to Conduit Terminators - Compound Filled</b>						
Up to 1 1/2" Conduit		1.75	2.15	2.60		E
2" Conduit		2.00	2.50	3.00		E
2 1/2" Conduit		2.25	2.80	3.35		E
3" Conduit		2.50	3.10	3.75		E
3 1/2" Conduit		3.00	3.75	4.50		E
4" Conduit		3.50	4.35	5.25		E
5" Conduit		4.25	5.30	6.35		E
6" Conduit		5.00	6.25	7.50		E
						
<b>4/C Jacketed Cable to Conduit Terminators - Compound Filled</b>						
Up to 1 1/2" Conduit		2.00	2.50	3.00		E
2" Conduit		2.25	2.80	3.35		E
2 1/2" Conduit		2.50	3.10	3.75		E
3" Conduit		3.00	3.75	4.50		E
3 1/2" Conduit		3.50	4.35	5.25		E
4" Conduit		4.00	5.00	6.00		E
5" Conduit		4.75	5.90	7.10		E
6" Conduit		5.50	6.85	8.25		E
						
<b>2/C Wire Armored Cable Terminators - Compound Filled</b>						
Up to #1		2.00	2.50	3.00		E
1/0		2.25	2.80	3.35		E
2/0		2.50	3.10	3.75		E
3/0		2.75	3.40	4.10		E
4/0		3.00	3.75	4.50		E
250 kcmil		3.50	4.35	5.25		E
350 kcmil		4.00	5.00	6.00		E
500 kcmil		4.50	5.60	6.75		E
750 kcmil		5.00	6.25	7.50		E
						
<b>3/C Wire Armored Cable Terminators - Compound Filled</b>						
Up to #1		2.25	2.80	3.35		E
1/0		2.50	3.10	3.75		E
2/0		2.75	3.40	4.10		E
3/0		3.00	3.75	4.50		E
4/0		3.25	4.05	4.90		E
250 kcmil		3.75	4.65	5.60		E
350 kcmil		4.25	5.30	6.35		E
500 kcmil		5.00	6.25	7.50		E
750 kcmil		6.00	7.50	9.00		E

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>4/C Wire Armored Cable Terminators - Compound Filled</b>						
Up to #1		2.50	3.10	3.75		E
1/0		2.75	3.40	4.10		E
2/0		3.00	3.75	4.50		E
3/0		3.25	4.05	4.90		E
4/0		3.50	4.35	5.25		E
250 kcmil		4.00	5.00	6.00		E
350 kcmil		4.50	5.60	6.75		E
500 kcmil		5.50	6.85	8.25		E
750 kcmil		6.50	8.10	9.75		E
<b>2/C Sheathed Armored Cable Terminators - Compound Filled</b>						
Up to #1		4.00	5.00	6.00		E
1/0		4.50	5.60	6.75		E
2/0		5.00	6.25	7.50		E
3/0		5.50	6.85	8.25		E
4/0		6.00	7.50	9.00		E
250 kcmil		6.50	8.10	9.75		E
350 kcmil		7.00	8.75	10.50		E
500 kcmil		7.50	9.35	11.25		E
750 kcmil		8.00	10.00	12.00		E
<b>3/C Sheathed Armored Cable Terminators - Compound Filled</b>						
Up to #1		4.50	5.60	6.75		E
1/0		5.00	6.25	7.50		E
2/0		5.50	6.85	8.25		E
3/0		6.00	7.50	9.00		E
4/0		6.50	8.10	9.75		E
250 kcmil		7.00	8.75	10.50		E
350 kcmil		7.50	9.35	11.25		E
500 kcmil		8.00	10.00	12.00		E
750 kcmil		8.50	10.60	12.75		E
<b>4/C Sheathed Armored Cable Terminators - Compound Filled</b>						
Up to #1		5.00	6.25	7.50		E
1/0		5.50	6.85	8.25		E
2/0		6.00	7.50	9.00		E
3/0		6.50	8.10	9.75		E
4/0		7.00	8.75	10.50		E
250 kcmil		7.50	9.35	11.25		E
350 kcmil		8.00	10.00	12.00		E
500 kcmil		8.50	10.60	12.75		E
750 kcmil		9.00	11.25	13.50		E
<b>2/C Armored Cable Terminators - Weatherproof - Gland Type</b>						
Up to #1		2.00	2.50	3.00		E
1/0		2.25	2.80	3.35		E
2/0		2.50	3.10	3.75		E
3/0		2.75	3.40	4.10		E
4/0		3.00	3.75	4.50		E
250 kcmil		3.50	4.35	5.25		E
350 kcmil		4.00	5.00	6.00		E
500 kcmil		4.50	5.60	6.75		E
750 kcmil		5.00	6.25	7.50		E
<b>3/C Armored Cable Terminators - Weatherproof - Gland Type</b>						
Up to #1		2.25	2.80	3.35		E
1/0		2.50	3.10	3.75		E
2/0		2.75	3.40	4.10		E
3/0		3.00	3.75	4.50		E
4/0		3.25	4.05	4.90		E
250 kcmil		3.75	4.65	5.60		E
350 kcmil		4.25	5.30	6.35		E
500 kcmil		4.75	5.90	7.10		E
750 kcmil		5.25	6.55	7.85		E
<b>4/C Armored Cable Terminators - Weatherproof - Gland Type</b>						
Up to #1		2.50	3.10	3.75		E
1/0		2.75	3.40	4.10		E
2/0		3.00	3.75	4.50		E
3/0		3.25	4.05	4.90		E
4/0		3.50	4.35	5.25		E
250 kcmil		4.00	5.00	6.00		E
350 kcmil		4.50	5.60	6.75		E
500 kcmil		5.00	6.25	7.50		E
750 kcmil		5.50	6.85	8.25		E

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>2/C Armored Cable to</b>						
<b>Conduit Terminators - Compound Filled</b>						
Up to #1		5.00	6.25	7.50		E
1/0		5.50	6.85	8.25		E
2/0		6.00	7.50	9.00		E
3/0		6.50	8.10	9.75		E
4/0		7.00	8.75	10.50		E
250 kcmil		7.50	9.35	11.25		E
350 kcmil		8.00	10.00	12.00		E
500 kcmil		8.50	10.60	12.75		E
750 kcmil		9.00	11.25	13.50		E
<b>3/C Armored Cable to</b>						
<b>Conduit Terminators - Compound Filled</b>						
Up to #1		5.50	6.85	8.25		E
1/0		6.00	7.50	9.00		E
2/0		6.50	8.10	9.75		E
3/0		7.00	8.75	10.50		E
4/0		7.50	9.35	11.25		E
250 kcmil		8.00	10.00	12.00		E
350 kcmil		8.50	10.60	12.75		E
500 kcmil		9.00	11.25	13.50		E
750 kcmil		9.50	11.85	14.25		E
<b>4/C Armored Cable to</b>						
<b>Conduit Terminators - Compound Filled</b>						
Up to #1		6.00	7.50	9.00		E
1/0		6.50	8.10	9.75		E
2/0		7.00	8.75	10.50		E
3/0		7.50	9.35	11.25		E
4/0		8.00	10.00	12.00		E
250 kcmil		8.50	10.60	12.75		E
350 kcmil		9.00	11.25	13.50		E
500 kcmil		9.50	11.85	14.25		E
750 kcmil		10.00	12.50	15.00		E
<b>5 KV Porcelain Terminators</b>						
Up to #2		3.00	3.75	4.50		E
#1		3.20	4.00	4.80		E
1/0		3.40	4.25	5.10		E
2/0		3.60	4.50	5.40		E
3/0		3.80	4.75	5.70		E
4/0		4.00	5.00	6.00		E
250 kcmil		4.30	5.35	6.45		E
350 kcmil		4.60	5.75	6.90		E
500 kcmil		5.00	6.25	7.50		E
750 kcmil		5.50	6.85	8.25		E
1000 kcmil		6.00	7.50	9.00		E
<b>15 KV Porcelain Terminators</b>						
Up to #2		4.00	5.00	6.00		E
#1		4.25	5.30	6.35		E
1/0		4.50	5.60	6.75		E
2/0		4.80	6.00	7.20		E
3/0		5.20	6.50	7.80		E
4/0		5.60	7.00	8.40		E
250 kcmil		6.00	7.50	9.00		E
350 kcmil		6.50	8.10	9.75		E
500 kcmil		7.00	8.75	10.50		E
750 kcmil		7.50	9.35	11.25		E
1000 kcmil		8.00	10.00	12.00		E
<b>25 KV Porcelain Terminators</b>						
Up to #2		5.00	6.25	7.50		E
#1		5.30	6.60	7.90		E
1/0		5.60	7.00	8.40		E
2/0		6.00	7.50	9.00		E
3/0		6.50	8.10	9.75		E
4/0		7.00	8.75	10.50		E
250 kcmil		7.50	9.35	11.25		E
350 kcmil		8.00	10.00	12.00		E
500 kcmil		8.50	10.60	12.75		E
750 kcmil		9.25	11.60	13.90		E
1000 kcmil		10.00	12.50	15.00		E
<b>1/C Hand Wrapped Stress Relief Cones 5KV</b>						
Up to 1/0		2.00	2.50	3.00		E
2/0		2.25	2.80	3.35		E
3/0		2.50	3.10	3.75		E
4/0		2.75	3.40	4.10		E
250 kcmil		3.00	3.75	4.50		E
350 kcmil		3.25	4.05	4.85		E
500 kcmil		3.40	4.35	5.25		E
750 kcmil		3.75	4.65	5.60		E
1000 kcmil		4.00	5.00	6.00		E

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>1/C Hand Wrapped Stress Relief Cones 15KV</b>						
Up to 1/0		2.50	3.10	3.75		E
2/0		2.75	3.40	4.10		E
3/0		3.00	3.75	4.50		E
4/0		3.25	4.05	4.85		E
250 kcmil		3.50	4.35	5.25		E
350 kcmil		3.75	4.65	5.60		E
500 kcmil		4.00	5.00	6.00		E
750 kcmil		4.50	5.60	6.75		E
1000 kcmil		5.00	6.25	7.50		E
 <b>1/C Hand Wrapped Stress Relief Cones 25KV</b>						
Up to 1/0		3.00	3.75	4.50		E
2/0		3.25	4.05	4.85		E
3/0		3.50	4.35	5.25		E
4/0		3.75	4.65	5.60		E
250 kcmil		4.00	5.00	6.00		E
350 kcmil		4.50	5.60	6.75		E
500 kcmil		5.00	6.25	7.50		E
750 kcmil		5.50	6.85	8.25		E
1000 kcmil		6.00	7.50	9.00		E
 <b>3/C Hand Wrapped Stress Relief Cones 5 KV</b>						
Up to 1/0		4.00	5.00	6.00		E
2/0		4.50	5.60	6.75		E
3/0		5.00	6.25	7.50		E
4/0		5.50	6.85	8.25		E
250 kcmil		6.00	7.50	9.00		E
350 kcmil		6.50	8.10	9.75		E
500 kcmil		7.00	8.75	10.50		E
750 kcmil		7.50	9.35	11.25		E
1000 kcmil		8.00	10.00	12.00		E
 <b>3/C Hand Wrapped Stress Relief Cones 15KV</b>						
Up to 1/0		5.00	6.25	7.50		E
2/0		5.50	6.85	8.25		E
3/0		6.00	7.50	9.00		E
4/0		6.50	8.10	9.75		E
250 kcmil		7.00	8.75	10.50		E
350 kcmil		7.50	9.35	11.25		E
500 kcmil		8.00	10.00	12.00		E
750 kcmil		9.00	11.25	13.50		E
1000 kcmil		10.00	12.50	15.00		E
 <b>3/C Hand Wrapped Stress Relief Cones 25 KV</b>						
Up to 1/0		6.00	7.50	9.00		E
2/0		6.50	8.10	9.75		E
3/0		7.00	8.75	10.50		E
4/0		7.50	9.35	11.25		E
250 kcmil		8.00	10.00	12.00		E
350 kcmil		9.00	11.25	13.50		E
500 kcmil		10.00	12.50	15.00		E
750 kcmil		11.00	13.75	16.50		E
1000 kcmil		12.00	15.00	18.00		E
 <b>Heat Shrink Cable Termination with 5 KV Stress Cone and Compression Lug</b>						
Up to #2		2.50	3.10	3.75		E
#1		2.75	3.40	4.10		E
1/0		3.00	3.75	4.50		E
2/0		3.25	4.05	4.85		E
3/0		3.50	4.35	5.25		E
4/0		3.75	4.65	5.60		E
250 kcmil		4.00	5.00	6.00		E
350 kcmil		4.50	5.60	6.75		E
500 kcmil		5.00	6.25	7.50		E
750 kcmil		5.50	6.85	8.25		E
1000 kcmil		6.00	7.50	9.00		E
 <b>Heat Shrink Cable Termination with 15KV Stress Cone and Compression Lug</b>						
Up to #2		3.00	3.75	4.50		E
#1		3.25	4.05	4.85		E
1/0		3.50	4.35	5.25		E
2/0		3.50	4.65	5.60		E
3/0		4.00	5.00	6.00		E
4/0		4.50	5.60	6.75		E
250 kcmil		5.00	6.25	7.50		E
350 kcmil		5.50	6.85	7.50		E
500 kcmil		6.00	7.50	9.00		E
750 kcmil		6.50	8.10	9.75		E
1000 kcmil		7.00	8.75	10.50		E

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Heat Shrink Cable Termination with</b>						
<b>25 KV Stress Cone and Compression Lug</b>						
Up to #2		3.50	4.35	5.25		E
#1		3.75	4.65	5.60		E
1/0		4.00	5.00	6.00		E
2/0		4.25	5.30	6.35		E
3/0		4.50	5.60	6.75		E
4/0		5.00	6.25	7.50		E
250 kcmil		5.50	6.85	8.25		E
350 kcmil		6.00	7.50	9.00		E
500 kcmil		6.50	8.10	9.75		E
750 kcmil		7.00	8.75	10.50		E
1000 kcmil		8.00	10.00	12.00		E
<b>Cold Shrink Cable Termination with</b>						
<b>5 KV Stress Cone and Compression Lug</b>						
Up to #2		1.80	2.25	2.70		E
#1		2.00	2.50	3.00		E
1/0		2.25	2.81	3.38		E
2/0		2.40	3.00	3.60		E
3/0		2.60	3.25	3.90		E
4/0		2.80	3.50	4.20		E
250 kcmil		3.00	3.75	4.50		E
350 kcmil		3.40	4.25	5.10		E
500 kcmil		3.75	4.69	5.63		E
750 kcmil		4.10	5.13	6.15		E
1000 kcmil		4.50	5.63	6.75		E
<b>Cold Shrink Cable Termination with</b>						
<b>15 KV Stress Cone and Compression Lug</b>						
Up to #2		2.25	2.81	3.38		E
#1		2.40	3.00	3.60		E
1/0		2.60	3.25	3.90		E
2/0		2.60	3.25	3.90		E
3/0		3.00	3.75	4.50		E
4/0		3.40	4.25	5.10		E
250 kcmil		3.75	4.69	5.63		E
350 kcmil		4.10	5.13	6.15		E
500 kcmil		4.50	5.63	6.75		E
750 kcmil		4.80	6.00	7.20		E
1000 kcmil		5.25	6.56	7.88		E
<b>Cold Shrink Cable Termination with</b>						
<b>25 KV Stress Cone and Compression Lug</b>						
Up to #2		2.60	3.25	3.90		E
#1		2.80	3.50	4.20		E
1/0		3.00	3.75	4.50		E
2/0		3.20	4.00	4.80		E
3/0		3.40	4.25	5.10		E
4/0		3.75	4.69	5.63		E
250 kcmil		4.10	5.13	6.15		E
350 kcmil		4.50	5.63	6.75		E
500 kcmil		4.80	6.00	7.20		E
750 kcmil		5.25	6.56	7.88		E
1000 kcmil		6.00	7.50	9.00		E
<b>5KV Single Conductor Potheads</b>						
Up to #2		5.00	6.25	7.50		E
#1		5.30	6.60	7.95		E
1/0		5.60	7.00	8.40		E
2/0		6.00	7.50	9.00		E
3/0		6.50	8.10	9.75		E
4/0		7.00	8.75	10.50		E
250 kcmil		7.50	9.35	11.25		E
350 kcmil		8.00	10.00	12.00		E
500 kcmil		8.50	10.60	12.75		E
750 kcmil		9.00	11.25	13.50		E
1000 kcmil		10.00	12.50	15.00		E
<b>15 KV Single Conductor Potheads</b>						
Up to #2		6.00	7.50	9.00		E
#1		6.30	7.85	9.50		E
1/0		6.60	8.25	10.00		E
2/0		7.00	8.75	10.50		E
3/0		7.50	9.35	11.25		E
4/0		8.00	10.00	12.00		E
250 kcmil		8.50	10.60	12.75		E
350 kcmil		9.00	11.25	13.50		E
500 kcmil		10.00	12.50	15.00		E
750 kcmil		11.00	13.25	16.50		E
1000 kcmil		12.00	15.00	18.00		E

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>25 KV Single Conductor Potheads</b>						
Up to #2		8.00	10.00	12.00		E
#1		8.50	10.60	12.75		E
1/0		9.00	11.25	13.50		E
2/0		9.50	11.85	14.25		E
3/0		10.00	12.50	15.00		E
4/0		11.00	13.75	16.50		E
250 kcmil		12.00	15.00	18.00		E
350 kcmil		13.00	16.25	19.50		E
500 kcmil		14.00	17.50	21.00		E
750 kcmil		15.00	18.75	22.50		E
1000 kcmil		16.00	20.00	24.00		E
<b>5KV Two Conductor Potheads</b>						
Up to #2		8.00	10.00	12.00		E
#1		8.50	10.60	12.75		E
1/0		9.00	11.25	13.50		E
2/0		9.50	11.85	14.25		E
3/0		10.00	12.50	15.00		E
4/0		11.00	13.75	16.50		E
250 kcmil		12.00	15.00	18.00		E
350 kcmil		13.00	16.25	19.50		E
500 kcmil		14.00	17.50	21.00		E
750 kcmil		15.00	18.75	22.50		E
1000 kcmil		16.00	20.00	24.00		E
<b>15KV Two Conductor Potheads</b>						
Up to #2		10.00	12.50	15.00		E
#1		11.00	13.75	16.50		E
1/0		12.00	15.00	18.00		E
2/0		13.00	16.25	19.50		E
3/0		14.00	17.50	21.00		E
4/0		15.00	18.75	22.50		E
250 kcmil		16.00	20.00	24.00		E
350 kcmil		17.00	21.25	25.50		E
500 kcmil		18.00	22.50	27.00		E
750 kcmil		19.00	23.75	28.50		E
1000 kcmil		20.00	25.00	30.00		E
<b>25KV Two Conductor Potheads</b>						
Up to #2		12.00	15.00	18.00		E
#1		13.00	16.25	19.50		E
1/0		14.00	17.50	21.00		E
2/0		15.00	18.75	22.50		E
3/0		16.00	20.00	24.00		E
4/0		17.00	21.25	25.50		E
250 kcmil		18.00	22.50	27.00		E
350 kcmil		19.00	23.75	28.50		E
500 kcmil		20.00	25.00	30.00		E
750 kcmil		22.00	27.50	33.00		E
1000 kcmil		24.00	30.00	36.00		E
<b>5KV Three Conductor Potheads</b>						
Up to #2		10.00	12.50	15.00		E
#1		11.00	13.75	16.50		E
1/0		12.00	15.00	18.00		E
2/0		13.00	16.25	19.50		E
3/0		14.00	17.50	21.00		E
4/0		15.00	18.75	22.50		E
250 kcmil		16.00	20.00	24.00		E
350 kcmil		17.00	21.25	25.50		E
500 kcmil		18.00	22.50	27.00		E
750 kcmil		19.00	23.75	28.50		E
1000 kcmil		20.00	25.00	30.00		E
<b>15KV Three Conductor Potheads</b>						
Up to #2		12.00	15.00	18.00		E
#1		13.00	16.25	19.50		E
1/0		14.00	17.50	21.00		E
2/0		15.00	18.75	22.50		E
3/0		16.00	20.00	24.00		E
4/0		17.00	21.25	25.50		E
250 kcmil		18.00	22.50	27.00		E
350 kcmil		19.00	23.75	28.50		E
500 kcmil		20.00	25.00	30.00		E
750 kcmil		22.00	27.50	33.00		E
1000 kcmil		24.00	30.00	36.00		E

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>25KV Three Conductor Potheads</b>						
Up to #2		16.00	20.00	24.00		E
#1		17.00	21.25	25.50		E
1/0		18.00	22.50	26.00		E
2/0		19.00	23.75	28.50		E
3/0		20.00	25.00	30.00		E
4/0		22.00	27.50	33.00		E
250 kcmil		24.00	30.00	36.00		E
350 kcmil		26.00	32.50	39.00		E
500 kcmil		28.00	35.00	42.00		E
750 kcmil		30.00	37.50	45.00		E
1000 kcmil		32.00	40.00	48.00		E
<b>15KV Loadbreak Cable Elbows</b>						
Up to #2		3.00	3.75	4.50		E
#1		3.20	4.00	4.80		E
1/0		3.40	4.25	5.10		E
2/0		3.60	4.50	5.60		E
3/0		3.75	4.70	5.60		E
4/0		4.00	5.00	6.00		E
250 kcmil		4.20	5.25	6.30		E
350 kcmil		4.50	5.60	6.75		E
500 kcmil		4.90	6.10	7.35		E
750 kcmil		5.25	6.60	7.90		E
1000 kcmil		6.00	7.50	9.00		E
Ground Strap for Load Break Included		0.00	0.00	0.00		
<b>25KV Loadbreak Cable Elbows</b>						
Up to #2		3.75	4.70	5.60		E
#1		4.00	5.00	6.00		E
1/0		4.20	5.25	6.30		E
2/0		4.30	5.40	6.45		E
3/0		4.50	5.60	6.75		E
4/0		4.90	6.10	7.35		E
250 kcmil		5.25	6.60	7.90		E
350 kcmil		5.60	7.00	8.40		E
500 kcmil		6.00	7.50	9.00		E
750 kcmil		6.75	8.40	10.00		E
1000 kcmil		7.50	9.40	11.25		E
Ground Strap for Load Break Included		0.00	0.00	0.00		
<b>600 Volt Tape Wrapped Cable Splices 1/C</b>						
Up to #6		2.10	2.60	3.15		E
#4		2.10	2.60	3.15		E
#3		2.10	2.60	3.15		E
#2		2.10	2.60	3.15		E
#1		2.40	3.00	3.60		E
1/0		2.50	3.10	3.75		E
2/0		2.80	3.50	4.20		E
3/0		3.00	3.75	4.50		E
4/0		3.00	3.75	4.50		E
250 kcmil		3.50	4.40	5.25		E
350 kcmil		3.60	4.50	5.40		E
500 kcmil		4.00	5.00	6.00		E
750 kcmil		4.50	5.60	6.75		E
1000 kcmil		5.00	6.25	7.50		E
<b>600 Volt Tape Wrapped Cable Splices 2/C</b>						
Up to #6		4.00	5.00	6.00		E
#4		4.10	5.10	6.15		E
#3		4.20	5.25	6.30		E
#2		4.35	5.40	6.50		E
#1		4.50	5.60	6.75		E
1/0		4.75	5.90	7.10		E
2/0		5.00	6.25	7.50		E
3/0		5.30	6.60	7.90		E
4/0		5.60	7.00	8.40		E
250 kcmil		6.00	7.50	9.00		E
350 kcmil		6.50	8.10	9.75		E
500 kcmil		7.00	8.75	10.50		E
750 kcmil		7.50	9.35	11.25		E
1000 kcmil		8.00	10.00	12.00		E
<b>600 Volt Tape Wrapped Cable Splices 3/C</b>						
Up to #6		5.00	6.25	7.50		E
#4		5.10	6.35	7.65		E
#3		5.20	6.50	7.80		E
#2		5.40	6.75	8.10		E
#1		5.60	7.00	8.40		E
1/0		5.90	7.35	8.85		E
2/0		6.20	7.75	9.30		E
3/0		6.50	8.30	9.75		E
4/0		7.00	8.75	10.50		E
250 kcmil		7.50	9.35	11.25		E
350 kcmil		8.00	10.00	12.00		E
500 kcmil		8.50	10.60	12.75		E
750 kcmil		9.00	11.25	13.50		E
1000 kcmil		10.00	12.50	15.00		E

3

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>1/C Shielded Cables Splices-5KV Cold Shrink</b>						
Up to #6		4.00	5.00	6.00		E
#4		4.10	5.10	6.15		E
#3		4.20	5.25	6.30		E
#2		4.35	5.40	6.50		E
#1		4.50	5.60	6.75		E
1/0		4.75	5.90	7.10		E
2/0		5.00	6.25	7.50		E
3/0		5.30	6.60	7.90		E
4/0		5.60	7.00	8.40		E
250 kcmil		6.00	7.50	9.00		E
350 kcmil		6.50	8.10	9.75		E
500 kcmil		7.00	8.75	10.50		E
750 kcmil		7.50	9.35	11.25		E
1000 kcmil		8.00	10.00	12.00		E
<b>1/C Shielded Cable Splices-15KV Cold Shrink</b>						
Up to #6		5.00	6.25	7.50		E
#4		5.10	6.35	7.65		E
#3		5.20	6.50	7.80		E
#2		5.40	6.75	8.10		E
#1		5.60	7.00	8.40		E
1/0		5.90	7.35	8.85		E
2/0		6.20	7.75	9.30		E
3/0		6.50	8.30	9.75		E
4/0		7.00	8.75	10.50		E
250 kcmil		7.50	9.35	11.25		E
350 kcmil		8.00	10.00	12.00		E
500 kcmil		8.50	10.60	12.75		E
750 kcmil		9.00	11.25	13.50		E
1000 kcmil		10.00	12.50	15.00		E
<b>1/C Shielded Cable Splices-25KV Cold Shrink</b>						
Up to #6		6.00	7.50	9.00		E
#4		6.10	7.60	9.15		E
#3		6.20	7.75	9.30		E
#2		6.35	7.90	9.50		E
#1		6.50	8.10	9.75		E
1/0		7.00	8.75	10.50		E
2/0		7.50	9.35	11.25		E
3/0		8.00	10.00	12.00		E
4/0		8.50	10.60	12.75		E
250 kcmil		9.00	11.25	13.50		E
350 kcmil		9.50	11.85	14.25		E
500 kcmil		10.00	12.50	15.00		E
750 kcmil		11.00	13.75	16.50		E
1000 kcmil		12.00	15.00	18.00		E
<b>3/C Cable Splices-5KV Cold Shrink</b>						
Up to #6		8.00	10.00	12.00		E
#4		8.20	10.25	12.30		E
#3		8.40	10.50	12.60		E
#2		8.70	10.85	13.00		E
#1		9.00	11.25	13.50		E
1/0		9.30	11.60	14.00		E
2/0		9.60	12.00	14.50		E
3/0		10.00	12.50	15.00		E
4/0		11.00	13.75	16.50		E
250 kcmil		12.00	15.00	18.00		E
350 kcmil		13.00	16.25	19.50		E
500 kcmil		14.00	17.50	21.00		E
750 kcmil		15.00	18.75	22.50		E
1000 kcmil		16.00	20.00	24.00		E
<b>3/C Cable Splices-15KV Cold Shrink</b>						
Up to #6		10.00	12.50	15.00		E
#4		10.25	12.80	15.35		E
#3		10.50	13.10	15.75		E
#2		10.75	13.40	16.10		E
#1		11.00	13.75	16.50		E
1/0		11.50	14.35	17.25		E
2/0		12.00	15.00	18.00		E
3/0		13.00	16.25	19.50		E
4/0		14.00	17.50	21.00		E
250 kcmil		15.00	18.75	22.50		E
350 kcmil		16.00	20.00	24.00		E
500 kcmil		17.00	21.25	25.50		E
750 kcmil		18.00	22.50	27.00		E
1000 kcmil		20.00	25.00	30.00		E



Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>3/C Cable Splices-25KV Cold Shrink</b>						
Up to #6		12.00	15.00	18.00		E
#4		12.50	15.60	18.75		E
#3		13.00	16.25	19.50		E
#2		13.50	16.85	20.25		E
#1		14.00	17.50	21.00		E
1/0		14.50	18.10	21.75		E
2/0		15.00	18.75	22.50		E
3/0		16.00	20.00	24.00		E
4/0		17.00	21.25	25.50		E
250 kcmil		18.00	22.50	27.00		E
350 kcmil		19.00	23.75	28.50		E
500 kcmil		20.00	25.00	30.00		E
750 kcmil		22.00	27.50	33.00		E
1000 kcmil		24.00	30.00	36.00		E
<b>1/C Heat Shrink &amp; Premolded Shielded Cable Splices - 5KV</b>						
Up to #6		5.00	6.25	7.50		E
#4		5.10	6.40	7.70		E
#3		5.20	6.50	7.80		E
#2		5.35	6.70	8.00		E
#1		5.50	6.90	8.25		E
1/0		6.00	7.50	9.00		E
2/0		6.25	7.80	9.40		E
3/0		6.60	8.25	9.90		E
4/0		7.00	8.75	10.50		E
250 kcmil		7.50	9.40	11.25		E
350 kcmil		8.10	10.00	12.15		E
500 kcmil		8.70	10.90	13.00		E
750 kcmil		9.30	11.60	14.00		E
1000 kcmil		10.00	12.50	15.00		E
<b>1/C Heat Shrink &amp; Premolded Shielded Cable Splices - 15KV</b>						
Up to #6		6.25	7.80	9.40		E
#4		6.40	8.00	9.60		E
#3		6.50	8.20	9.75		E
#2		6.75	8.40	10.00		E
#1		7.00	8.75	10.50		E
1/0		7.40	9.25	11.00		E
2/0		7.75	9.70	11.60		E
3/0		8.10	10.00	12.00		E
4/0		8.75	10.90	13.00		E
250 kcmil		9.40	11.75	14.00		E
350 kcmil		10.00	12.50	15.00		E
500 kcmil		10.60	13.25	15.90		E
750 kcmil		11.25	14.00	16.90		E
1000 kcmil		12.50	15.60	18.80		E
<b>1/C Heat Shrink &amp; Premolded Shielded Cable Splices - 25KV</b>						
Up to #6		7.50	9.40	11.25		E
#4		7.60	9.50	11.40		E
#3		7.75	9.70	11.60		E
#2		7.90	9.90	11.85		E
#1		8.12	10.00	12.20		E
1/0		8.75	10.90	13.00		E
2/0		9.37	11.70	14.00		E
3/0		10.00	12.50	15.00		E
4/0		10.60	13.25	15.90		E
250 kcmil		11.25	14.00	16.90		E
350 kcmil		11.90	14.90	17.90		E
500 kcmil		12.50	15.60	18.75		E
750 kcmil		13.75	17.00	20.60		E
1000 kcmil		15.00	18.75	22.50		E
<b>3/C Heat Shrink Cable Splices - 5KV</b>						
Up to #6		10.00	12.50	15.00		E
#4		10.30	12.90	15.45		E
#3		10.50	13.00	15.75		E
#2		10.90	13.60	16.35		E
#1		11.25	14.00	16.90		E
1/0		11.70	14.60	17.60		E
2/0		12.00	15.00	18.00		E
3/0		12.50	15.60	18.75		E
4/0		12.75	15.90	19.00		E
250 kcmil		15.00	18.75	22.50		E
350 kcmil		16.25	20.30	24.00		E
500 kcmil		17.50	21.90	26.00		E
750 kcmil		18.75	23.40	28.00		E
1000 kcmil		20.00	25.00	30.00		E

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct







3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>3/C Heat Shrink Cable Splices - 15KV</b>						
Up to #6	X	12.50	15.60	18.75		E
#4		12.80	16.00	19.20		E
#3		13.10	16.40	19.70		E
#2		13.40	16.75	20.00		E
#1		13.75	17.00	20.60		E
1/0		14.40	18.00	21.60		E
2/0		15.00	18.75	22.50		E
3/0		16.25	20.00	24.40		E
4/0		17.50	21.90	26.25		E
250 kcmil		18.75	23.40	28.00		E
350 kcmil		20.00	25.00	30.00		E
500 kcmil		21.25	26.60	31.90		E
750 kcmil		22.50	28.00	33.75		E
1000 kcmil		25.00	31.25	37.50		E
<b>3/C Heat Shrink Cable Splices - 25KV</b>						
Up to #6		15.00	18.75	22.50		E
#4		15.60	19.50	23.40		E
#3		16.25	20.30	24.40		E
#2		16.90	21.00	25.40		E
#1		17.50	21.90	26.25		E
1/0		18.10	22.60	27.00		E
2/0		18.75	23.40	28.00		E
3/0		20.00	25.00	30.00		E
4/0		21.25	26.60	31.90		E
250 kcmil		22.50	28.00	33.75		E
350 kcmil		23.75	29.70	35.60		E
500 kcmil		25.00	31.25	37.50		E
750 kcmil		27.50	34.40	41.25		E
1000 kcmil		30.00	37.50	45.00		E
<b>3/C Interlocked Armored Cable Splices-5KV</b>						
Up to #6		10.00	12.50	15.00		E
#4		10.25	12.80	15.35		E
#3		10.50	13.10	15.75		E
#2		10.75	13.40	16.10		E
#1		11.00	13.75	16.50		E
1/0		11.50	14.35	17.25		E
2/0		12.00	15.00	18.00		E
3/0		13.00	16.25	19.50		E
4/0		14.00	17.50	21.00		E
250 kcmil		15.00	18.75	22.50		E
350 kcmil		16.00	20.00	24.00		E
500 kcmil		17.00	21.25	25.50		E
750 kcmil		18.00	22.50	27.00		E
1000 kcmil		20.00	25.00	30.00		E
<b>3/C Interlocked Armored Cable Splices 15KV</b>						
Up to #6		12.00	15.00	18.00		E
#4		12.50	15.60	18.75		E
#3		13.00	16.25	20.25		E
#2		13.50	16.85	20.25		E
#1		14.00	17.50	21.00		E
1/0		14.50	18.10	21.75		E
2/0		15.00	18.75	22.50		E
3/0		16.00	20.00	24.00		E
4/0		17.00	21.25	25.50		E
250 kcmil		18.00	22.50	27.00		E
350 kcmil		19.00	23.75	28.50		E
500 kcmil		20.00	25.00	30.00		E
750 kcmil		22.00	27.50	33.00		E
1000 kcmil		24.00	30.00	36.00		E
<b>3/C Interlocked Armored Cable Splices 25KV</b>						
Up to #6		14.00	17.50	21.00		E
#4		14.50	18.10	21.75		E
#3		15.00	18.75	22.50		E
#2		15.50	19.35	23.25		E
#1		16.00	20.00	24.00		E
1/0		16.50	20.60	24.75		E
2/0		17.00	21.25	25.50		E
3/0		18.00	22.50	27.00		E
4/0		19.00	23.75	28.50		E
250 kcmil		20.00	25.00	30.00		E
350 kcmil		22.00	27.50	33.00		E
500 kcmil		24.00	30.00	36.00		E
750 kcmil		26.00	32.50	39.00		E
1000 kcmil		28.00	35.00	42.00		E
































































Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>3/C I.A.C. Splices-5KV-Compound Filled</b>						
Up to #6		11.00	13.75	16.50		E
#4		11.50	14.35	17.25		E
#3		12.00	15.00	18.00		E
#2		12.50	15.60	18.75		E
#1		13.00	16.25	19.50		E
1/0		13.50	16.85	20.25		E
2/0		14.00	17.50	21.00		E
3/0		15.00	18.75	22.50		E
4/0		16.00	20.00	24.00		E
250 kcmil		17.00	21.25	25.50		E
350 kcmil		18.00	22.50	27.00		E
500 kcmil		19.00	23.75	28.50		E
750 kcmil		20.00	25.00	30.00		E
1000 kcmil		22.00	27.50	33.00		E
<b>3/C I.A.C. Splices-15KV-Compound Filled</b>						
Up to #6		13.00	16.25	19.50		E
#4		13.50	16.85	20.25		E
#3		14.00	17.50	21.00		E
#2		14.50	18.10	21.75		E
#1		15.00	18.75	22.50		E
1/0		15.50	19.35	23.25		E
2/0		16.00	20.00	24.00		E
3/0		17.00	21.25	25.50		E
4/0		18.00	22.50	27.00		E
250 kcmil		19.00	23.75	28.00		E
350 kcmil		20.00	25.00	30.00		E
500 kcmil		22.00	27.50	33.00		E
750 kcmil		24.00	30.00	36.00		E
1000 kcmil		26.00	32.50	39.00		E
<b>Fire Proof Tape</b>						
1 1/2" X 20' Tape		0.50	0.63	0.75		E
3" X 20' Tape		0.50	0.63	0.75		E
<b>2 Pole Ltg &amp; Motor Busway up to 240 Volt</b>						
30 Amp Busway		8.00	10.00	12.00		C
60 Amp Busway		9.00	11.25	13.50		C
100 Amp Busway		10.00	12.50	15.00		C
225 Amp Busway		12.00	15.00	18.00		C
30 Amp 90 Degree Elbow		0.40	0.50	0.60		E
60 Amp 90 Degree Elbow		0.45	0.56	0.68		E
100 Amp 90 Degree Elbow		0.55	0.69	0.83		E
225 Amp 90 Degree Elbow		0.65	0.81	0.98		E
30 Amp End Feed Boxes		0.40	0.50	0.60		E
60 Amp End Feed Boxes		0.50	0.63	0.75		E
100 Amp End Feed Boxes		0.65	0.81	0.98		E
225 Amp End Feed Boxes		0.75	0.94	1.13		E
30 Amp Center Feed Boxes		0.50	0.63	0.75		E
60 Amp Center Feed Boxes		0.60	0.75	0.90		E
100 Amp Center Feed Boxes		0.75	0.94	1.13		E
225 Amp Center Feed Boxes		0.85	1.06	1.28		E
Plugin Device to 30 Amp		0.25	0.31	0.38		E
Plugin Device to 100 Amp		0.40	0.50	0.60		E
Plugin Device to 225 Amp		0.50	0.63	0.75		E
2 Pole End Cap		0.05	0.06	0.08		E
<b>3 Pole Ltg &amp; Motor Busway up to 480 Volt</b>						
30 Amp Busway		8.00	10.00	12.00		C
60 Amp Busway		9.00	11.25	13.50		C
100 Amp Busway		10.00	12.50	15.00		C
225 Amp Busway		12.00	15.00	18.00		C
30 Amp 90 Degree Elbow		0.40	0.50	0.60		E
60 Amp 90 Degree Elbow		0.45	0.56	0.68		E
100 Amp 90 Degree Elbow		0.55	0.69	0.83		E
225 Amp 90 Degree Elbow		0.65	0.81	0.98		E
30 Amp End Feed Boxes		0.40	0.50	0.60		E
60 Amp End Feed Boxes		0.50	0.63	0.75		E
100 Amp End Feed Boxes		0.65	0.81	0.98		E
225 Amp End Feed Boxes		0.75	0.94	1.13		E
30 Amp Center Feed Boxes		0.50	0.63	0.75		E
60 Amp Center Feed Boxes		0.60	0.75	0.90		E
100 Amp Center Feed Boxes		0.75	0.94	1.13		E
225 Amp Center Feed Boxes		0.85	1.06	1.28		E
Plugin Device to 30 Amp		0.25	0.31	0.38		E
Plugin Device to 100 Amp		0.40	0.50	0.60		E
Plugin Device to 225 Amp		0.50	0.63	0.75		E
3 Pole End Cap		0.05	0.06	0.08		E
<b>Trolley Busway</b>						
2-Pole - 100 Ampere		8.00	10.00	12.00		C
3-Pole - 100 Ampere		10.00	12.50	15.00		C
4-Pole - 100 Ampere		12.00	15.00	18.00		C
5-Pole - 100 Ampere		14.00	17.50	21.00		C
10 Ft Section without Bus Bars		1.00	1.25	1.50		E
Trolley Busway Couplings		0.50	0.60	0.75		E
Trolley Busway End Caps		0.10	0.12	0.15		E

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
	<b>Trolley Busway Feed Boxes</b>					
#10 Wire		0.70	0.85	1.00		E
#8 Wire		0.75	0.90	1.10		E
#6 wire		0.80	1.00	1.20		E
#4 Wire		0.90	1.10	1.35		E
#2 Wire		1.00	1.25	1.50		E
	<b>Trolley Busway Curve Sections</b>					
2-Pole		0.40	0.50	0.60		E
3-Pole		0.45	0.55	0.70		E
4-Pole		0.50	0.60	0.80		E
5-Pole		0.60	0.75	0.90		E
	<b>Trolley Busway Track Switches</b>					
2-Pole		0.50	0.60	0.75		E
3-Pole		0.55	0.65	0.80		E
4-Pole		0.60	0.75	0.90		E
5-Pole		0.70	0.85	1.00		E
	<b>2-Pole Trolleys</b>					
15 Amp		0.40	0.50	0.60		E
20 Amp		0.45	0.55	0.65		E
30 Amp		0.50	0.60	0.75		E
40 Amp		0.60	0.75	0.85		E
60 Amp		0.70	0.85	1.00		E
100 Amp		0.90	1.10	1.35		E
	<b>3-Pole Trolleys</b>					
15 Amp		0.45	0.55	0.65		E
20 Amp		0.50	0.60	0.75		E
30 Amp		0.60	0.70	0.85		E
40 Amp		0.70	0.85	1.00		E
60 Amp		0.80	1.00	1.20		E
100 Amp		1.00	1.25	1.50		E
4-Pole 15 amp Trolleys		0.50	0.60	0.75		E
5-Pole 15 Amp Trolleys		0.60	0.70	0.85		E
2-Pole 15 Amp Receptacles		0.20	0.25	0.30		E
2-Pole 30 Amp Receptacles		0.30	0.35	0.45		E
3-Pole 15 Amp Receptacles		0.25	0.30	0.35		E
3-Pole 30 Amp Receptacles		0.35	0.40	0.50		E
2-Pole Fusible Jacks		0.35	0.40	0.50		E
3-pole Fusible Jacks		0.40	0.50	0.60		E
6 Ft Cord & 20 Amp Wiring devices		0.50	0.60	0.75		E
6 Ft Cord & 30 Amp Wiring Devices		0.60	0.75	0.90		E
6 Ft Cord & 50 Amp Wiring Devices		0.75	0.90	1.10		E
6 Ft Cord & 60 Amp Wiring Devices		0.90	1.10	1.35		E
	<b>Three Pole Heavy Duty Trolley Busway</b>					
250 Amp Busway		14.00	17.50	21.00		C
350 Amp Busway		16.00	20.00	24.00		C
450 Amp Busway		18.00	22.00	27.00		C
Busway Couplings		1.00	1.25	1.50		E
	<b>Busway End Power Feeds</b>					
250 Amp		0.90	1.10	1.35		E
350 Amp		1.00	1.25	1.50		E
450 Amp		1.10	1.40	1.65		E
	<b>Busway Center Power Feeds</b>					
250 Amp		1.40	1.75	2.10		E
350 Amp		1.50	1.85	2.25		E
450 Amp		1.60	2.00	2.40		E
Busway End Caps		0.20	0.25	0.30		E
Collector Arms		2.00	2.50	3.00		E
Heavy Duty Trolleys		1.00	1.25	1.50		E
Busway Hangers		0.10	0.12	0.15		E
	<b>One Pole Crane Hoist &amp; Monorail Busway</b>					
90 Amp Aluminum Busway		4.00	5.00	6.00		C
350 Amp Aluminum Busway		5.00	6.20	7.50		C
350 Amp Bronze or Copper Busway		6.00	7.50	9.00		C
450 Amp Bronze or Copper Busway		7.00	8.70	10.50		C
550 Amp Bronze or Copper Busway		8.00	10.00	12.00		C
Busway Splice Joints		0.20	0.25	0.30		E
90 Amp Feeder Lugs		0.60	0.75	0.90		E
350 Amp Feeder Lugs		0.80	1.00	1.20		E
450 Amp Feeder Lugs		0.90	1.10	1.35		E
550 Amp Feeder Lugs		1.00	1.25	1.50		E

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct







Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Busway Expansion Joints</b>						
 90 Amp Aluminum		0.40	0.50	0.60		E
 350 Amp Aluminum		0.50	0.60	0.75		E
 350 Amp Bronze or Copper		0.60	0.75	0.90		E
 450 Amp Bronze or Copper		0.70	0.85	1.00		E
 550 Amp Bronze or Copper		0.80	1.00	1.20		E
 Fiberglass Anchors		0.10	0.12	0.15		E
 150 Amp Collector Arm		0.90	1.10	1.35		E
 200 Amp Collector Arm		1.00	1.25	1.50		E
 250 Amp Collector Arm		1.10	1.40	1.65		E
 Busway Mounting Brackets		0.50	0.60	0.75		E
<b>3 Phase 3P Copper Bus Duct Plug-In Type</b>						
 225 Amp		35.00	44.00	52.00		C
 400 Amp		40.00	50.00	60.00		C
 600 Amp		45.00	56.00	67.00		C
 800 Amp		50.00	62.00	75.00		C
 1000 Amp		55.00	68.00	82.00		C
 1200 Amp		60.00	75.00	90.00		C
 1350 Amp		65.00	81.00	97.00		C
 1600 Amp		75.00	93.00	112.00		C
 2000 Amp		85.00	106.00	127.00		C
 2500 Amp		100.00	125.00	150.00		C
 3000 Amp		115.00	143.00	172.00		C
 4000 Amp		140.00	175.00	210.00		C
<b>3 Phase 3P Copper Bus Duct-Elbows</b>						
 225 Amp		3.50	4.40	5.20		E
 400 Amp		4.00	5.00	6.00		E
 600 Amp		4.50	5.60	6.70		E
 800 Amp		5.00	6.20	7.50		E
 1000 Amp		5.50	6.80	8.20		E
 1200 Amp		6.00	7.50	9.00		E
 1350 Amp		6.50	8.10	9.70		E
 1600 Amp		7.50	9.30	11.20		E
 2000 Amp		8.50	10.60	12.70		E
 3000 Amp		12.00	15.00	18.00		E
 4000 Amp		14.00	17.50	21.00		E
<b>3 Phase 3P Copper Bus Duct-Tees</b>						
 225 Amp		4.00	5.00	6.00		E
 400 Amp		4.50	5.60	6.70		E
 600 Amp		5.00	6.20	7.50		E
 800 Amp		5.50	6.80	8.20		E
 1000 Amp		6.00	7.50	9.00		E
 1200 Amp		7.00	8.70	10.50		E
 1350 Amp		8.00	10.00	12.00		E
 1600 Amp		9.00	11.20	13.50		E
 2000 Amp		10.00	12.50	15.00		E
 2500 Amp		11.00	13.70	16.50		E
 3000 Amp		13.00	16.50	20.00		E
 4000 Amp		16.00	20.00	24.00		E
<b>3 Phase 3P Copper Bus Duct-Crosses</b>						
 225 Amp		5.00	6.20	7.50		E
 400 Amp		5.50	6.80	8.20		E
 600 Amp		6.00	7.50	9.00		E
 800 Amp		6.50	8.10	9.70		E
 1000 Amp		7.00	8.70	10.50		E
 1200 Amp		8.00	10.00	12.00		E
 1350 Amp		9.00	11.20	13.50		E
 1600 Amp		10.00	12.50	15.00		E
 2000 Amp		12.00	15.00	18.00		E
 2500 Amp		14.00	17.50	21.00		E
 3000 Amp		16.00	20.00	24.00		E
4000 Amp		20.00	25.00	30.00		E
<b>3 Phase 3P Copper Bus Duct-Offset Fittings</b>						
 225 Amp		3.50	4.40	5.20		E
 400 Amp		4.00	5.00	6.00		E
 600 Amp		4.50	5.60	6.70		E
 800 Amp		5.00	6.20	7.50		E
 1000 Amp		5.50	6.80	8.20		E
 1200 Amp		6.00	7.50	9.00		E
 1350 Amp		6.50	8.10	9.70		E
1600 Amp		7.00	8.70	10.50		E
2000 Amp		8.00	10.00	12.00		E
2500 Amp		9.00	11.20	13.50		E
3000 Amp		10.00	12.50	15.00		E
4000 Amp		12.00	15.00	18.00		E

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>3 Phase 3P Copper Bus Duct-End Closures</b>						
225 Amp		0.30	0.37	0.45		E
400 Amp		0.35	0.43	0.52		E
600 Amp		0.40	0.50	0.60		E
800 Amp		0.45	0.56	0.67		E
1000 Amp		0.50	0.62	0.75		E
1200 Amp		0.55	0.68	0.82		E
1350 Amp		0.60	0.75	0.90		E
1600 Amp		0.65	0.81	0.97		E
2000 Amp		0.70	0.87	1.05		E
2500 Amp		0.80	1.00	1.20		E
3000 Amp		0.90	1.12	1.35		E
4000 Amp		1.00	1.25	1.50		E
<b>3 Phase 3P Copper Bus Duct-Unfused Reducers</b>						
225 Amp		3.00	3.70	4.50		E
400 Amp		3.50	4.30	5.20		E
600 Amp		4.00	5.00	6.00		E
800 Amp		4.50	5.60	6.70		E
1000 Amp		5.00	6.20	7.50		E
1200 Amp		5.50	6.80	8.20		E
1350 Amp		6.00	7.50	9.00		E
1600 Amp		6.50	8.10	9.70		E
2000 Amp		7.00	8.70	10.50		E
2500 Amp		8.00	10.00	12.00		E
3000 Amp		9.00	11.20	13.50		E
4000 Amp		11.00	13.70	16.50		E
<b>3 Phase 3P Copper Bus Duct-Offset Elbows</b>						
225 Amp		4.00	5.00	6.00		E
400 Amp		4.50	5.60	6.70		E
600 Amp		5.00	6.20	7.50		E
800 Amp		5.50	6.80	8.20		E
1000 Amp		6.00	7.50	9.00		E
1200 Amp		7.00	8.70	10.50		E
1350 Amp		8.00	10.00	12.00		E
1600 Amp		9.00	11.20	13.50		E
2000 Amp		10.00	12.50	15.00		E
2500 Amp		12.00	15.00	18.00		E
3000 Amp		14.00	17.50	21.00		E
4000 Amp		16.00	20.00	24.00		E
<b>3 Phase 3P Copper Bus Duct-Expansion Fittings</b>						
225 Amp		4.00	5.00	6.00		E
400 Amp		4.50	5.60	6.70		E
600 Amp		5.00	6.20	7.50		E
800 Amp		5.50	6.80	8.20		E
1000 Amp		6.00	7.50	9.00		E
1200 Amp		7.00	8.70	10.50		E
1350 Amp		8.00	10.00	12.00		E
1600 Amp		9.00	11.20	13.50		E
2000 Amp		10.00	12.50	15.00		E
2500 Amp		12.00	15.00	18.00		E
3000 Amp		14.00	17.50	21.00		E
4000 Amp		16.00	20.00	24.00		E
<b>3 Phase 3P Copper Bus Duct-Panelboard Fittings</b>						
225 Amp		2.00	2.50	3.00		E
400 Amp		2.20	2.70	3.30		E
600 Amp		2.40	3.00	3.60		E
800 Amp		2.70	3.30	4.00		E
1000 Amp		3.00	3.70	4.50		E
1200 Amp		3.50	4.40	5.20		E
1600 Amp		4.50	5.60	6.70		E
2000 Amp		5.00	6.20	7.50		E
2500 Amp		6.00	7.50	9.00		E
3000 Amp		7.00	8.70	10.50		E
4000 Amp		8.00	10.00	12.00		E
<b>3 Phase 3P Copper Bus Duct-Cable Tap Boxes</b>						
225 Amp		5.00	6.20	7.50		E
400 Amp		5.50	6.80	8.20		E
600 Amp		6.00	7.50	9.00		E
800 Amp		6.50	8.10	9.70		E
1000 Amp		7.00	8.70	10.50		E
1200 Amp		8.00	10.00	12.00		E
1350 Amp		9.00	11.20	13.50		E
1600 Amp		10.00	12.50	15.00		E
2000 Amp		12.00	15.00	18.00		E
2500 Amp		14.00	17.50	21.00		E
3000 Amp		16.00	20.00	24.00		E
4000 Amp		20.00	25.00	30.00		E

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>3 Phase 3P Copper Bus Duct-Transformer Fittings</b>						
 225 Amp		4.00	5.00	6.00		E
400 Amp		4.50	5.60	6.70		E
600 Amp		5.00	6.20	7.50		E
800 Amp		5.50	6.80	8.20		E
1000 Amp		6.00	7.50	9.00		E
1200 Amp		7.00	8.70	10.50		E
1350 Amp		8.00	10.00	12.00		E
1600 Amp		9.00	11.20	13.50		E
2000 Amp		10.00	12.50	15.00		E
2500 Amp		12.00	15.00	18.00		E
3000 Amp		14.00	17.50	21.00		E
4000 Amp		16.00	20.00	24.00		E
<b>Bus Duct-2P2W Nonfusible Switches</b>						
 30 Amp		1.20	1.50	1.80		E
60 Amp		1.50	1.80	2.20		E
100 Amp		2.00	2.50	3.00		E
200 Amp		3.50	4.40	5.20		E
400 Amp		7.50	9.50	11.50		E
600 Amp		12.00	15.00	18.00		E
800 Amp		16.00	20.00	24.00		E
1000 Amp		21.00	26.00	32.00		E
1200 Amp		26.00	33.00	40.00		E
<b>Bus Duct-2P3W Nonfusible Switches</b>						
 30 Amp		1.30	1.60	1.90		E
60 Amp		1.60	2.00	2.40		E
100 Amp		2.20	2.70	3.30		E
200 Amp		4.00	6.00	8.00		E
400 Amp		8.00	10.00	12.00		E
600 Amp		13.00	16.00	19.00		E
800 Amp		18.00	22.00	27.00		E
1000 Amp		23.00	28.00	34.00		E
1200 Amp		28.00	35.00	42.00		E
<b>Bus Duct-3P3W Nonfusible Switches</b>						
 30 Amp		1.40	1.70	2.10		E
60 Amp		1.70	2.10	2.50		E
100 Amp		2.30	2.80	3.40		E
200 Amp		5.00	6.20	7.50		E
400 Amp		9.00	11.20	13.50		E
600 Amp		14.00	17.50	21.00		E
800 Amp		20.00	25.00	30.00		E
1000 Amp		25.00	31.00	37.00		E
1200 Amp		31.00	38.00	46.00		E
<b>Bus Duct-3P4W Nonfusible Switches</b>						
 30 Amp		1.60	2.00	2.40		E
60 Amp		2.00	2.50	3.00		E
100 Amp		3.00	3.70	4.50		E
200 Amp		6.00	7.50	9.00		E
400 Amp		10.00	12.50	15.00		E
600 Amp		16.00	20.00	24.00		E
800 Amp		23.00	28.00	34.00		E
1000 Amp		28.00	35.00	42.00		E
1200 Amp		34.00	42.00	51.00		E
<b>Bus Duct-2P2W Fusible Switches</b>						
 30 Amp		1.30	1.60	1.90		E
60 Amp		1.60	2.00	2.40		E
100 Amp		2.20	2.70	3.30		E
200 Amp		4.00	6.00	8.00		E
400 Amp		8.00	10.00	12.00		E
600 Amp		13.00	16.00	19.00		E
800 Amp		18.00	22.00	27.00		E
1000 Amp		23.00	28.00	34.00		E
1200 Amp		28.00	35.00	42.00		E
<b>Bus Duct-2P3W Fusible Switches</b>						
 30 Amp		1.40	1.70	2.10		E
60 Amp		1.70	2.10	2.50		E
100 Amp		2.30	2.80	3.40		E
200 Amp		5.00	6.20	7.50		E
400 Amp		9.00	11.20	13.50		E
600 Amp		14.00	17.50	21.00		E
800 Amp		20.00	25.00	30.00		E
1000 Amp		25.00	31.00	37.00		E
1200 Amp		31.00	38.00	46.00		E







Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Bus Duct-3P3W Fusible Switches</b>						
30 Amp		1.60	2.00	2.40		E
60 Amp		2.00	2.50	3.00		E
100 Amp		3.00	3.70	4.50		E
200 Amp		6.00	7.50	9.00		E
400 Amp		10.00	12.50	15.00		E
600 Amp		16.00	20.00	24.00		E
800 Amp		23.00	28.00	34.00		E
1000 Amp		28.00	35.00	42.00		E
1200 Amp		34.00	42.00	50.00		E
<b>Bus Duct 3P4W Fusible Switches</b>						
30 Amp		1.80	2.20	2.70		E
60 Amp		2.20	2.70	3.30		E
100 Amp		3.40	4.20	5.10		E
200 Amp		6.50	8.10	9.70		E
400 Amp		11.00	13.70	16.50		E
600 Amp		17.00	21.00	25.00		E
800 Amp		24.00	30.00	36.00		E
1000 Amp		30.00	37.00	45.00		E
1200 Amp		36.00	45.00	54.00		E
<b>Bus Duct-2P2W Molded Case Circuit Breakers</b>						
Up to 30 Amp		1.55	1.85	2.25		E
Up to 60 Amp		2.35	2.85	3.45		E
Up to 100 Amp		4.50	4.85	5.85		E
Up to 200 Amp		7.00	8.40	10.10		E
Up to 400 Amp		12.50	15.00	18.00		E
Up to 600 Amp		18.00	22.50	27.00		E
Up to 800 Amp		23.00	28.70	34.00		E
Up to 1200 Amp		30.00	36.00	43.20		E
Up to 1600 Amp		35.00	42.00	50.40		E
Up to 2000 Amp		45.00	54.00	64.00		E
<b>Bus Duct-2P3W Molded Case Circuit Breakers</b>						
Up to 30 Amp		1.50	1.85	2.25		E
Up to 60 Amp		2.35	2.85	3.45		E
Up to 100 Amp		4.05	4.85	5.85		E
Up to 200 Amp		7.00	8.40	10.10		E
Up to 400 Amp		12.50	15.00	18.00		E
Up to 600 Amp		18.00	22.50	27.00		E
Up to 800 Amp		23.00	28.70	34.00		E
Up to 1200 Amp		30.00	36.00	43.70		E
Up to 1600 Amp		35.00	42.00	50.40		E
Up to 2000 Amp		45.00	54.00	64.00		E
<b>Bus Duct-3P3W Molded Case Circuit Breakers</b>						
Up to 30 Amp		1.55	1.85	2.25		E
Up to 60 Amp		2.35	2.85	3.45		E
Up to 100 Amp		4.05	4.85	5.85		E
Up to 200 Amp		7.00	8.40	10.10		E
Up to 400 Amp		12.50	15.00	18.00		E
Up to 600 Amp		18.00	22.50	27.00		E
Up to 800 Amp		23.00	28.70	34.00		E
Up to 1200 Amp		30.00	36.00	43.20		E
Up to 1600 Amp		35.00	42.00	50.40		E
Up to 2000 Amp		45.00	54.00	64.00		E
<b>3 Phase 3P Copper Bus Duct-Feeder Type</b>						
600 Amp		45.00	56.00	67.00		C
800 Amp		50.00	62.00	75.00		C
1000 Amp		55.00	68.00	82.00		C
1200 Amp		60.00	75.00	90.00		C
1350 Amp		65.00	81.00	97.00		C
1600 Amp		75.00	93.00	112.00		C
2000 Amp		85.00	106.00	127.00		C
2500 Amp		100.00	125.00	150.00		C
3000 Amp		115.00	143.00	172.00		C
4000 Amp		140.00	175.00	210.00		C
5000 Amp		160.00	200.00	240.00		C
<b>3 Phase 3P Feeder Bus Duct-Elbows</b>						
600 Amp		4.50	5.60	6.70		E
800 Amp		5.00	6.20	7.50		E
1000 Amp		5.50	6.80	8.20		E
1200 Amp		6.00	7.50	9.00		E
1350 Amp		6.50	8.10	9.70		E
1600 Amp		7.50	9.30	11.20		E
2000 Amp		8.50	10.60	12.70		E
2500 Amp		10.00	13.00	15.00		E
3000 Amp		12.00	15.00	18.00		E
4000 Amp		14.00	17.50	21.00		E
5000 Amp		16.00	20.00	24.00		E



Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>3 Phase 3P Feeder Bus Duct-Tee Fittings</b>						
 600 Amp		5.00	6.20	7.50		E
800 Amp		5.50	6.80	8.20		E
1000 Amp		6.00	7.50	9.00		E
1200 Amp		7.00	8.70	10.50		E
1350 Amp		8.00	10.00	12.00		E
1600 Amp		9.00	11.20	13.50		E
2000 Amp		10.00	12.50	15.00		E
2500 Amp		11.00	13.70	16.50		E
3000 Amp		13.00	16.50	20.00		E
4000 Amp		16.00	20.00	24.00		E
5000 Amp		18.00	22.50	27.00		E
<b>3 Phase 3P Feeder Bus Duct-Cross Fittings</b>						
 600 Amp		6.00	7.50	9.00		E
800 Amp		6.50	8.10	9.70		E
1000 Amp		7.00	8.70	10.50		E
1200 Amp		8.00	10.00	12.00		E
1350 Amp		9.00	11.20	13.50		E
1600 Amp		10.00	12.50	15.00		E
2000 Amp		12.00	15.00	18.00		E
2500 Amp		14.00	17.50	21.00		E
3000 Amp		16.00	20.00	24.00		E
4000 Amp		20.00	25.00	30.00		E
5000 Amp		24.00	30.00	36.00		E
<b>3 Phase 3P Feeder Bus Duct-Offset Fittings</b>						
 600 Amp		4.50	5.60	6.70		E
800 Amp		5.00	6.20	7.50		E
1000 Amp		5.50	6.80	8.20		E
1200 Amp		6.00	7.50	9.00		E
1350 Amp		6.50	8.10	9.70		E
1600 Amp		7.00	8.70	10.50		E
2000 Amp		8.00	10.00	12.00		E
2500 Amp		9.00	11.20	13.50		E
3000 Amp		10.00	12.50	15.00		E
4000 Amp		12.00	15.00	18.00		E
5000 Amp		16.00	20.00	24.00		E
<b>3 Phase 3P Feeder Bus Duct-Unfused Reducers</b>						
 600 Amp		4.00	5.00	6.00		E
800 Amp		4.50	5.60	6.70		E
1000 Amp		5.00	6.20	7.50		E
1200 Amp		5.50	6.80	8.20		E
1350 Amp		6.00	7.50	9.00		E
1600 Amp		6.50	8.10	9.70		E
2000 Amp		7.00	8.70	10.50		E
2500 Amp		8.00	10.00	12.00		E
3000 Amp		9.00	11.20	13.50		E
4000 Amp		11.00	13.70	16.50		E
5000 Amp		13.00	16.25	19.50		E
<b>3 Phase 3P Feeder Bus Duct-Offset Elbows</b>						
 600 Amp		5.00	6.20	7.50		E
800 Amp		5.50	6.80	8.20		E
1000 Amp		6.00	7.50	9.00		E
1200 Amp		7.00	8.70	10.50		E
1350 Amp		8.00	10.00	12.00		E
1600 Amp		9.00	11.20	13.50		E
2000 Amp		10.00	12.50	15.00		E
2500 Amp		12.00	15.00	18.00		E
3000 Amp		14.00	17.50	21.00		E
4000 Amp		16.00	20.00	24.00		E
5000 Amp		18.00	22.50	27.00		E
<b>3 Phase 3P Feeder Bus Duct-Expansion Fittings</b>						
 600 Amp		5.00	6.20	7.50		E
800 Amp		5.50	6.80	8.20		E
1000 Amp		6.00	7.50	9.00		E
1200 Amp		7.00	8.70	10.50		E
1350 Amp		8.00	10.00	12.00		E
1600 Amp		9.00	11.20	13.50		E
2000 Amp		10.00	12.50	15.00		E
2500 Amp		12.00	15.00	18.00		E
3000 Amp		14.00	17.50	21.00		E
4000 Amp		17.00	21.00	25.00		E
5000 Amp		20.00	25.00	30.00		E

3


Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>3 Phase 3P Feeder Bus Duct-Panelboard Fittings</b>						
600 Amp		2.40	3.00	3.60		E
800 Amp		2.70	3.40	4.00		E
1000 Amp		3.00	3.75	4.50		E
1200 Amp		3.50	4.40	5.25		E
1350 Amp		4.00	5.00	6.00		E
1600 Amp		4.50	5.60	6.75		E
2000 Amp		5.00	6.20	7.50		E
2500 Amp		6.00	7.50	9.00		E
3000 Amp		7.00	8.70	10.50		E
4000 Amp		8.00	10.00	12.00		E
5000 Amp		9.00	11.25	13.50		E
<b>3 Phase 3P Feeder Bus Duct-End Closures</b>						
600 Amp		0.40	0.50	0.60		E
800 Amp		0.45	0.56	0.67		E
1000 Amp		0.50	0.62	0.75		E
1200 Amp		0.55	0.68	0.82		E
1350 Amp		0.60	0.75	0.90		E
1600 Amp		0.65	0.82	1.00		E
2000 Amp		0.70	0.90	1.10		E
3000 Amp		0.80	1.00	1.20		E
4000 Amp		0.90	1.12	1.35		E
5000 Amp		1.00	1.25	1.50		E
<b>3 Phase 3P Feeder Bus Duct-Cable Tap Boxes</b>						
600 Amp		6.00	7.50	9.00		E
800 Amp		6.50	8.10	9.70		E
1000 Amp		7.00	8.70	10.50		E
1200 Amp		8.00	10.00	12.00		E
1350 Amp		9.00	11.20	13.50		E
1600 Amp		10.00	12.50	15.00		E
2000 Amp		12.00	15.00	18.00		E
2500 Amp		14.00	17.50	21.00		E
3000 Amp		16.00	20.00	24.00		E
4000 Amp		20.00	25.00	30.00		E
5000 Amp		24.00	30.00	36.00		E
<b>3 Phase 3P Feeder Bus Duct-Transformer Fittings</b>						
600 Amp		5.00	6.20	7.50		E
800 Amp		5.50	6.80	8.20		E
1000 Amp		6.00	7.50	9.00		E
1200 Amp		7.00	8.70	10.50		E
1350 Amp		8.00	10.00	12.00		E
1600 Amp		9.00	11.20	13.50		E
2000 Amp		10.00	12.50	15.00		E
2500 Amp		12.00	15.00	18.00		E
3000 Amp		14.00	17.50	21.00		E
4000 Amp		16.00	20.00	24.00		E
5000 Amp		18.00	22.50	27.00		E
<b>Three Phase 3P Feeder Bus Duct - Service Heads</b>						
600 Amp		6.00	7.50	9.00		E
800 Amp		7.00	8.70	10.50		E
1000 Amp		8.00	10.00	12.00		E
1200 Amp		9.00	11.20	13.50		E
1350 Amp		10.00	12.50	15.00		E
1600 Amp		12.00	15.00	18.00		E
2000 Amp		14.00	17.50	21.00		E
2500 Amp		16.00	20.00	24.00		E
3000 Amp		18.00	22.50	27.00		E
4000 Amp		20.00	25.00	30.00		E
5000 Amp		24.00	30.00	36.00		E
<b>3 Phase 3P Bus Duct-Wall &amp; Floor Flanges</b>						
600 Amp		2.00	2.50	3.00		E
800 Amp		2.30	2.80	3.40		E
1000 Amp		2.60	3.20	3.90		E
1200 Amp		3.00	3.70	4.50		E
1350 Amp		3.50	4.30	5.20		E
1600 Amp		4.00	5.00	6.00		E
2000 Amp		4.50	5.60	6.70		E
2500 Amp		5.00	6.20	7.50		E
3000 Amp		6.00	7.50	9.00		E
4000 Amp		7.00	8.70	10.50		E
5000 Amp		8.00	10.00	12.00		E

Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>3 Phase 3P Bus Duct-Fire &amp; Weather Stops</b>						
600 Amp		3.00	3.70	4.50		E
800 Amp		3.50	4.30	5.20		E
1000 Amp		4.00	5.00	6.00		E
1200 Amp		4.50	5.60	6.70		E
1350 Amp		5.00	6.20	7.50		E
1600 Amp		6.00	7.50	9.00		E
2000 Amp		7.00	8.70	10.50		E
2500 Amp		8.00	10.00	12.00		E
3000 Amp		9.00	11.20	13.50		E
4000 Amp		10.00	12.50	15.00		E
5000 Amp		12.00	15.00	18.00		E
<i>Does not include Fire Stop Material.</i>						
<b>Floor Springload Factory Hanger</b>						
600 Amp		3.00	3.70	4.50		E
800 Amp		3.50	4.30	5.20		E
1000 Amp		4.00	5.00	6.00		E
1200 Amp		4.50	5.60	6.70		E
1350 Amp		5.00	6.20	7.50		E
1600 Amp		6.00	7.50	9.00		E
2000 Amp		7.00	8.70	10.50		E
2500 Amp		8.00	10.00	12.00		E
3000 Amp		9.00	11.20	13.50		E
4000 Amp		10.00	12.50	15.00		E
5000 Amp		12.00	15.00	18.00		E
<b>Teck Cable 5Kv 3c</b>						
8		46.60	59.20	71.80		M
6		50.40	64.00	77.60		M
4		52.90	67.20	81.50		M
3		55.40	70.40	85.40		M
2		59.20	75.20	91.20		M
1		63.00	80.00	97.00		M
1/0		68.00	86.40	104.80		M
2/0		73.10	92.80	112.50		M
3/0		76.90	97.60	118.30		M
4/0		81.90	104.00	126.10		M
250		86.90	110.40	133.90		M
300		93.20	118.40	143.60		M
350		100.80	128.00	155.20		M
500		113.40	144.00	174.60		M
600		118.40	150.40	182.40		M
750		126.00	160.00	194.00		M
1000		138.60	176.00	213.40		M
<b>Teck Cable 1Kv 3C</b>						
12		30.20	38.40	46.60		M
10		35.30	44.80	54.30		M
8		40.30	51.20	62.10		M
6		45.40	57.60	69.80		M
4		49.10	62.40	75.70		M
3		52.90	67.20	81.50		M
2		55.40	70.40	85.40		M
1		60.50	76.80	93.10		M
1/0		65.50	83.20	100.90		M
2/0		70.60	89.60	108.60		M
3/0		74.30	94.40	114.50		M
4/0		78.10	99.20	120.30		M
250		84.40	107.20	130.00		M
300		90.70	115.20	139.70		M
350		98.30	124.80	151.30		M
500		107.10	136.00	164.90		M
600		118.40	150.40	182.40		M
750		126.00	160.00	194.00		M
1000		138.60	176.00	213.40		M
<b>Teck Cable 1Kv 4C</b>						
12		32.80	41.60	50.40		M
10		37.80	48.00	58.20		M
8		42.80	54.40	66.00		M
6		47.90	60.80	73.70		M
4		52.90	67.20	81.50		M
3		58.00	73.60	89.20		M
2		65.50	83.20	100.90		M
1		70.60	89.60	108.60		M
1/0		75.60	96.00	116.40		M
2/0		80.60	102.40	124.20		M
3/0		85.70	108.80	131.90		M
4/0		90.70	115.20	139.70		M
250		95.80	121.60	147.40		M
300		102.10	129.60	157.10		M
350		108.40	137.60	166.80		M
500		118.40	150.40	182.40		M
600		123.50	156.80	190.10		M
750		131.00	166.40	201.80		M
1000		163.80	208.00	252.20		M



Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3



Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Teck Cable 1Kv 1C</b>						
6		31.50	40.00	48.50		M
4		34.00	43.20	52.40		M
3		36.50	46.40	56.30		M
2		39.10	49.60	60.10		M
1		41.60	52.80	64.00		M
1/0		44.10	56.00	67.90		M
2/0		47.90	60.80	73.70		M
3/0		51.70	65.60	79.50		M
4/0		55.40	70.40	85.40		M
250		59.20	75.20	91.20		M
300		63.00	80.00	97.00		M
350		68.00	86.40	104.80		M
500		73.10	92.80	112.50		M
600		75.60	96.00	116.40		M
750		81.90	104.00	126.10		M
1000		90.70	115.20	139.70		M
<b>Teck Cable 600v mh/1000 FT</b>						
10 / 2		30.20	38.40	46.60		M
10 / 3		32.80	41.60	50.40		M
10 / 4		35.30	44.80	54.30		M
10 / 5		37.80	48.00	58.20		M
10 / 6		40.30	51.20	62.10		M
10 / 7		42.80	54.40	66.00		M
10 / 8		45.40	57.60	69.80		M
10 / 9		46.60	59.20	71.80		M
10 / 10		47.90	60.80	73.70		M
10 / 11		49.10	62.40	75.70		M
10 / 12		50.40	64.00	77.60		M
10 / 13		51.70	65.60	79.50		M
10 / 14		52.90	67.20	81.50		M
10 / 15		54.20	68.80	83.40		M
10 / 16		55.40	70.40	85.40		M
10 / 17		56.70	72.00	87.30		M
10 / 18		58.00	73.60	89.20		M
10 / 19		59.20	75.20	91.20		M
10 / 20		60.50	76.80	93.10		M
10 / 25		63.00	80.00	97.00		M
10 / 30		68.00	86.40	104.80		M
10 / 40		73.10	92.80	112.50		M
10 / 50		75.60	96.00	116.40		M
<b>Teck Cable 600v 12AWG</b>						
12 / 2		23.90	30.40	36.90		M
12 / 3		25.20	32.00	38.80		M
12 / 4		27.70	35.20	42.70		M
12 / 5		31.50	40.00	48.50		M
12 / 6		34.00	43.20	52.40		M
12 / 7		36.50	46.40	56.30		M
12 / 8		39.10	49.60	60.10		M
12 / 9		41.60	52.80	64.00		M
12 / 10		42.80	54.40	66.00		M
12 / 11		45.40	57.60	69.80		M
12 / 12		46.60	59.20	71.80		M
12 / 13		47.90	60.80	73.70		M
12 / 14		49.10	62.40	75.70		M
12 / 15		50.40	64.00	77.60		M
12 / 16		51.70	65.60	79.50		M
12 / 17		52.90	67.20	81.50		M
12 / 18		54.20	68.80	83.40		M
12 / 19		55.40	70.40	85.40		M
12 / 20		56.70	72.00	87.30		M
12 / 25		58.00	73.60	89.20		M
12 / 30		60.50	76.80	93.10		M
12 / 40		63.00	80.00	97.00		M
12 / 50		68.00	86.40	104.80		M
12 / 60		70.60	89.60	108.60		M
12 / 70		73.10	92.80	112.50		M
12 / 80		75.60	96.00	116.40		M
12 / 90		83.20	105.60	128.00		M
12 / 100		85.70	108.80	131.90		M



Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

3



Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Teck Cable 18AWG</b>						
1pr 18		20.00	25.30	30.70		M
1tr 18		21.10	26.80	32.40		M
2pr 18		22.20	28.20	34.10		M
3pr 18		26.60	33.80	41.00		M
2tr 18		26.60	33.80	41.00		M
4pr 18		29.90	38.00	46.10		M
3tr 18		31.00	39.40	47.80		M
5pr 18		33.30	42.20	51.20		M
4tr 18		35.50	45.10	54.60		M
6pr 18		35.50	45.10	54.60		M
7pr 18		37.70	47.90	58.00		M
5tr 18		38.80	49.30	59.80		M
8pr 18		39.90	50.70	61.50		M
9pr 18		42.10	53.50	64.90		M
10pr 18		44.40	56.30	68.30		M
11pr 18		44.80	56.90	69.00		M
12pr 18		45.20	57.40	69.70		M
14pr 18		46.10	58.60	71.00		M
15pr 18		46.60	59.10	71.70		M
16pr 18		47.00	59.70	72.40		M
18pr 18		47.90	60.80	73.80		M
20pr 18		48.80	62.00	75.10		M
22pr 18		50.60	64.20	77.80		M
24pr 18		52.30	66.50	80.60		M
25pr 18		53.20	67.60	81.90		M
26pr 18		54.10	68.70	83.30		M
28pr 18		55.90	71.00	86.00		M
30pr 18		57.70	73.20	88.80		M
32pr 18		58.50	74.30	90.10		M
35pr 18		59.90	76.00	92.20		M
36pr 18		60.30	76.60	92.90		M
40pr 18		62.10	78.80	95.60		M
42pr 18		63.00	80.00	97.00		M
45pr 18		64.30	81.70	99.00		M
48pr 18		65.60	83.40	101.10		M
50pr 18		66.50	84.50	102.40		M
<b>Teck Cable 20AWG</b>						
1pr 20		18.60	23.60	28.60		M
1tr 20		19.60	24.90	30.20		M
2pr 20		20.70	26.20	31.80		M
3pr 20		24.80	31.50	38.20		M
2tr 20		24.80	31.50	38.20		M
4pr 20		27.90	35.40	43.00		M
3tr 20		28.90	36.70	44.50		M
5pr 20		31.00	39.40	47.70		M
4tr 20		33.10	42.00	50.90		M
6pr 20		33.10	42.00	50.90		M
7pr 20		35.10	44.60	54.10		M
5tr 20		36.20	45.90	55.70		M
8pr 20		37.20	47.20	57.30		M
9pr 20		39.30	49.90	60.50		M
10pr 20		41.30	52.50	63.60		M
11pr 20		41.70	53.00	64.30		M
12pr 20		42.20	53.50	64.90		M
14pr 20		43.00	54.60	66.20		M
15pr 20		43.40	55.10	66.80		M
16pr 20		43.80	55.60	67.40		M
18pr 20		44.60	56.70	68.70		M
20pr 20		45.50	57.70	70.00		M
22pr 20		47.10	59.80	72.50		M
24pr 20		48.80	61.90	75.10		M
25pr 20		49.60	63.00	76.40		M
26pr 20		50.40	64.00	77.60		M
28pr 20		52.10	66.10	80.20		M
30pr 20		53.70	68.20	82.70		M
32pr 20		54.60	69.30	84.00		M
35pr 20		55.80	70.80	85.90		M
36pr 20		56.20	71.40	86.50		M
40pr 20		57.90	73.50	89.10		M
42pr 20		58.70	74.50	90.40		M
45pr 20		59.90	76.10	92.30		M
48pr 20		61.20	77.70	94.20		M
50pr 20		62.00	78.70	95.40		M

### Section 3 - Wire, Cable, Lugs, Terminations, Busway & Bus Duct

Description		Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Teck Connectors</b>							
Throat	Cable						
1/2"	14 / 2		0.34	0.43	0.52		E
1/2"	14 / 3 , 4		0.34	0.43	0.52		E
1/2"	14 / 5 , 6		0.34	0.43	0.52		E
1/2"	12 / 2 , 3 , 4		0.34	0.43	0.52		E
1/2"	12 / 5 , 6		0.34	0.43	0.52		E
1/2"	10 / 2		0.34	0.43	0.52		E
1/2"	10 / 3 , 4 , 5		0.34	0.43	0.52		E
3/4"	10 / 6		0.50	0.63	0.75		E
1/2"	1C 6		0.31	0.39	0.47		E
1/2"	1C 4 , 2		0.31	0.39	0.47		E
3/4"	1C 1 - 2/0		0.50	0.63	0.75		E
3/4"	1C 3/0		0.50	0.63	0.75		E
1"	1C 250, 350		0.75	0.94	1.13		E
1 1/4"	1C 350, 400		1.06	1.33	1.59		E
1 1/4"	1C 500		1.06	1.33	1.59		E
1 1/4"	1C 600		1.06	1.33	1.59		E
1 1/2"	1C 750		1.44	1.80	2.16		E
1 1/2"	1C 1000		1.44	1.80	2.16		E
1/2"	2C 14, 12		0.31	0.39	0.47		E
1/2"	2C 10, 8		0.31	0.39	0.47		E
3/4"	2C 6		0.50	0.63	0.75		E
3/4"	2C 4		0.50	0.63	0.75		E
1"	2C 2		0.75	0.94	1.13		E
1 1/4"	2C 1		1.06	1.33	1.59		E
1 1/4"	2C 1/0, 2/0		1.06	1.33	1.59		E
1 1/4"	2C 3/0		1.06	1.33	1.59		E
1 1/2"	2C 4/0		1.44	1.80	2.16		E
2"	2C 250		1.88	2.34	2.81		E
2"	2C 300 - 400		1.88	2.34	2.81		E
1/2"	3C 14		0.31	0.39	0.47		E
1/2"	3C 12, 10		0.31	0.39	0.47		E
3/4"	3C 8		0.50	0.63	0.75		E
3/4"	3C 6		0.50	0.63	0.75		E
1"	3C 4, 2		0.75	0.94	1.13		E
1 1/4"	3C 1, 1/0		1.06	1.33	1.59		E
1 1/4"	3C 2/0		1.06	1.33	1.59		E
1 1/2"	3C 3/0		1.44	1.80	2.16		E
1 1/2"	3C 4/0		1.44	1.80	2.16		E
2"	3C 250, 300		1.88	2.34	2.81		E
2"	3C 350, 400		1.88	2.34	2.81		E
2 1/2"	3C 500		2.38	2.97	3.56		E
3"	3C 750		2.81	3.52	4.22		E
1/2"	4C 14, 12		0.34	0.43	0.52		E
3/4"	4C 10, 8		0.50	0.63	0.75		E
1"	4C 4		0.75	0.94	1.13		E
1 1/4"	4C 2		1.06	1.33	1.59		E
1 1/4"	4C 1		1.06	1.33	1.59		E
1 1/2"	4C 1/0, 2/0		1.44	1.80	2.16		E
2"	4C 3/0		1.88	2.34	2.81		E
2"	4C 4/0, 350		1.88	2.34	2.81		E
2 1/2"	4C 500		2.38	2.97	3.56		E
3"	4C 750		2.81	3.52	4.22		E
Note: Throat sizes vary with cable and connector manufacturers.							







# SECTION 4

## SWITCHBOARDS, MCC'S, PANELBOARDS AND POWER EQUIPMENT

### General Information

Several pages in this section contain labor units for handling electrical equipment and exclude the labor for conductor terminations. The labor for conductor terminations must be added separately for these items. When labor units in this section do include the conductor terminations, the labor units are based on the minimum sizes of copper conductors allowed by the National Electrical Code.

4

### Scope of These Labor Units

The Introduction section includes details on the scope of labor units across the manual. Some items included are:

- Labor units are intended for new construction, de-energized in compliance with NFPA 70E
- Safety measures indicated in NFPA 70E will need to be factored by contractor's resources
- Drawing and specification study
- Layout, measuring and marking installation location
- Material unloading, storage and delivery to the installation area
- Tool acquisition and return to storage
- Uncrating and shipping support removal
- Inspection for shipping damage
- Rigging for lifting and hoisting
- Moving, handling, placing in position, bolting sections/bussing together and factory harness wiring for fans, heaters and controls.
- Removal of trash

### Work Operations Not Included In These Labor Units

- Field supervision
- Raceway terminations
- Grounding systems
- Bonding systems
- Welding
- Painting
- Coordination studies, including fuse and circuit breaker sizing and settings, arc hazard analysis and fault current analysis
- Testing or commissioning of any type
- Terminations unless stated
- Grouting or anchoring
- Cutting holes or openings in walls, floors, cabinets, or panels
- Heavy equipment (crane) operators' time
- High Altitude Electromagnetic Pulse HEMP or Electro Magnetic Pulse EMP Shielding

### Labor Adjustments for Non-Typical Conditions

See the Introduction section for details.

### Application Instructions

- Labor units for switchboards and MCC's are based on NEMA Class 2 equipment, which includes the electrical interlocking, interwiring between units and the control circuitry.
  - When NEMA Class 1 equipment is used, the electrical contractor must include a substantial amount of additional labor for the interlocking, interwiring and control circuitry.

- For switchboard mounted “draw-out” type circuit breakers the labor units shown must be doubled.
- When lugs, stress cones, pre-molded termination insulation or hand wrapped termination insulation are required on equipment conductor terminations, an additional labor allowance must be added for these items.
- Labor units for panelboard empty enclosure mounting include the labor for installing the empty enclosure, interior components, circuit breakers, trim and the preparation of the directory, but exclude all conductor terminations.
- Labor units for installing limit switches do not include the labor for the FS box, flexible conduit and flexible fittings that are usually required.

## Section 4 - Switchboards, MCC's, Panelboards & Power Equipment Table of Contents

Switchboard Section Handling Labor Only	4-7
Switchboard/Gear Sections	4-7
Switchboard Heater	(Updated) 4-8
Switchboard 600 Volt Feed Conductor Terminations	4-8
Switchboard Grounding Conductor Terminations	4-8
Switchboard 2 Pole Copper Cond. Term. On Circuit Breakers & Switches	(Updated) 4-9
Switchboard 3 Pole Copper Cond. Term. On Circuit Breakers & Switches	(Updated) 4-9
Switchboard Bus Bar Splice Connections - 3 Phase 4 Wire W/ Copper Ground	4-9
Steel Channels Embedded in Concrete	4-9
Custom Made Steel Pull Boxes	4-9
Fuse Installation in Fused Switch in Safety Switches and MCC's Cartridge Fuse (250V - 600V)	4-10
Bolt-On Fuse 600 Volt	4-10
Panelboard Empty Enclosure, Surface Mounted - 100 Amp Rating	4-10
Panelboard Empty Enclosure, Surface Mounted - 125 Amp Rating	4-10
Panelboard Empty Enclosure, Surface Mounted - 150 Amp Rating	4-10
Panelboard Empty Enclosure, Surface Mounted - 225 Amp Rating	4-10
Panelboard Empty Enclosure, Surface Mounted - 400 Amp Rating	4-10
Panelboard Empty Enclosure, Surface Mounted - 600 Amp Rating	4-10
Panelboard Empty Enclosure, Surface Mounted - 800 Amp Rating	4-11
Panelboard Empty Enclosure, Surface Mounted - 1200 Amp Rating	4-11
Panelboard Empty Enclosure, Recessed Mounting - 100 Amp Rating	4-11
Panelboard Empty Enclosure, Recessed Mounting - 125 Amp Rating	4-11
Panelboard Empty Enclosure, Recessed Mounting - 150 Amp Rating	4-11
Panelboard Empty Enclosure, Recessed Mounting - 225 Amp Rating	4-11
Panelboard Empty Enclosure, Recessed Mounting - 400 Amp Rating	4-11
Panelboard Empty Enclosure, Recessed Mounting - 600 Amp Rating	4-12
Panelboard Empty Enclosure, Recessed Mounting - 800 Amp Rating	4-12
Panelboard Empty Enclosure, Recessed Mounting - 1200 Amp Rating	4-12
Panelboard 600 Volt Feed Conductor Terminations	4-12
Panelboard Grounding Conductor Terminations	4-12
Panelboard Terminations: Single Pole Circuit Breaker	(Updated) 4-13
Panelboard Terminations: Two Pole Circuit Breaker	(Updated) 4-13
Panelboard Terminations: Three Pole Circuit Breaker	(Updated) 4-13
Motor Control Centers: Receiving, Handling and Set In Place	4-13
MCC: Anchoring to Concrete Pad	4-14
MCC: Multiple Section Bolting Connections	4-14
MCC: Multiple Section Bus Bar Connections - Per Bus Bar	4-14
Motor Starters Mounted in MCC's - Single Speed Non-Reversing 2-Pole	4-14
Motor Starters Mounted in MCC's - Single Speed Non-Reversing 3-Pole	4-14
Motor Starters Mounted in MCC's - Single Speed Non-Reversing 4-Pole	4-14
Motor Starters Mounted in MCC's - Single Speed Reversing 2-Pole	4-14
Motor Starters Mounted in MCC's - Single Speed Reversing 3-Pole	4-14
Motor Starters Mounted in MCC's - Single Speed Reversing 4-Pole	4-14
Motor Starters Mounted in MCC's - Multi - Speed Non-Reversing 2-Pole	4-14
Motor Starters Mounted in MCC's - Multi - Speed Non-Reversing 3-Pole	4-15
Motor Starters Mounted in MCC's - Multi - Speed Non-Reversing 4-Pole	4-15
Motor Starters Mounted in MCC's - Multi - Multi Speed Reversing 2-Pole	4-15
Motor Starters Mounted in MCC's - Multi - Multi Speed Reversing 3-Pole	4-15
Motor Starters Mounted in MCC's - Multi - Multi Speed Reversing 4-Pole	4-15
Factory Mounted Disconnect/Circuit Breaker - Termination Labor Only	4-15
Factory Mounted Variable Frequency Drive - Termination Labor Only	4-15
Control Transformer Termination - Factory Mounted in MCC's	4-15
MCC Control Relay Termination - Factory Mounted in MCC's	4-15
Auxiliary Contacts NO/NC	4-15
Control Wire Terminations	4-16
Control Switch Factory Mounted	4-16
Factory Mounted Push Button Stations	4-16

## Section 4 - Switchboards, MCC's, Panelboards & Power Equipment Table of Contents

Field Mounted in MCC's - Single Speed Non-Reversing 2-Pole	4-16
Field Mounted in MCC's - Single Speed Non-Reversing 3-Pole	4-16
Field Mounted in MCC's - Single Speed Non-Reversing 4-Pole	4-16
Field Mounted in MCC's - Single Speed Reversing 2-Pole	4-16
Field Mounted in MCC's - Single Speed Reversing 3-Pole	4-16
Field Mounted in MCC's - Single Speed Reversing 4-Pole	4-16
Field Mounted in MCC's - Variable Speed Non-Reversing 2-Pole	4-17
Field Mounted in MCC's - Variable Speed Non-Reversing 3-Pole	4-17
Field Mounted in MCC's - Variable Speed Non-Reversing 4-Pole	4-17
Field Mounted in MCC's - Variable Speed Reversing 2-Pole	4-17
Field Mounted in MCC's - Variable Speed Reversing 3-Pole	4-17
Field Mounted in MCC's - Variable Speed Reversing 4-Pole	4-17
Drive Units - 200 - 550 Volt DC	4-17
Drive Units - Variable Frequency A.C.	4-18
Field Mounted Disconnect/Circuit Breaker - Includes Termination Labor	4-18
Field Mounted Variable Frequency Drive - Includes Termination Labor	4-18
Field Mounted in MCC's - Auxiliary Contacts NO/NC	4-18
Field Mounted Control Switch	4-18
Field Mounted in MCC's MCC Control Transformers	4-18
Field Mounted in MCC's MCC Control Relays	4-18
Field Mounted Push Button Switches	4-18
Integrated Power Centers	4-19
Fuse Installation in Fused Switch in Safety Switches and MCC's - Cartridge Fuse (250 V or 600V)	4-19
Bolt-On Fuse 600V	4-19
Free Standing Bolted Press. Switches - Installation & 2P3W Conductor Term.	4-19
Free Standing Bolted Press. Switches - Installation & 3P4W Conductor Term.	4-19
Disconnect Safety Switches - Nonfused 2-Pole	4-20
Disconnect Safety Switches - Nonfused 3-Pole	4-20
Disconnect Safety Switches - Nonfused 4-Pole	4-20
Disconnect Safety Switches - Fused 2-Pole	4-20
Disconnect Safety Switches - Fused 3-Pole	4-20
Disconnect Safety Switches - Fused 4-Pole	4-20
Enclosed Circuit Breakers, Wall Mounted - 2-Pole (or 1-Pole and Neutral)	4-21
Enclosed Circuit Breakers, Wall Mounted - 3-Pole (or 2-Pole and Neutral)	4-21
Enclosed Circuit Breakers, Wall Mounted - 4-Pole (or 3-Pole and Neutral)	4-21
Enclosed Magnetic Motor Starter, Wall Mounted, Non-Reversing 2-Pole	4-21
Enclosed Magnetic Motor Starter, Wall Mounted, Non-Reversing 3-Pole	4-22
Enclosed Magnetic Motor Starter, Wall Mounted, Non-Reversing 4-Pole	4-22
Enclosed Magnetic Motor Starter, Wall Mounted, Reversing 2-Pole	4-22
Enclosed Magnetic Motor Starter, Wall Mounted, Reversing 3-Pole	4-22
Enclosed Magnetic Motor Starter, Wall Mounted, Reversing 4-Pole	4-22
Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Non-Reversing 2-Pole	4-22
Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Non-Reversing 3-Pole	4-23
Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Non-Reversing 4-Pole	4-23
Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Reversing 2-Pole	4-23
Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Reversing 3-Pole	4-23
Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Reversing 4-Pole	4-23
Push Button Station NEMA-1 Enclosure, Factory Assembled	4-23
Push Button Station NEMA-3 Enclosure, Factory Assembled	4-23
Limit Switch	4-24
Manual Motor Starter 115/230 Volt AC - NEMA-1 Enclosure Toggle Switch	4-24
Enclosed Lighting & Heating Contactors - NEMA 1 Enclosure up to 600 Volt AC	4-24
Enclosed 600 Volt Overload Relays - NEMA 1 Enclosure 600 Volt	4-24
Fuse Installation in Fused Switch in Safety Switches and MCC's - Cartridge Fuse (250 V or 600V)	4-24
Bolt-On Fuse 600V	4-24
Meter Center NEMA 1 & 3R (Typ) Enclosure - 3 Wire Solid Neutral MLO or Tap Box Module	4-25
Meter Center NEMA 1 & 3R (Typ) Enclosure - 3 Wire Solid Neutral Main Circuit Breaker or Fused Switch	4-25

## Section 4 - Switchboards, MCC's, Panelboards & Power Equipment Table of Contents

Meter Center NEMA 1 & 3R (Typ) Enclosure - 4 Wire Solid Neutral MLO or Tap Box Module	4-25
Meter Center NEMA 1 & 3R (Typ) Enclosure - 4 Wire Solid Neutral Main Circuit Breaker or Fused Switch	4-25
Meter Center NEMA 1 & 3R Single Phase - 125 Amp Meter Socket Modules	4-25
Meter Center NEMA 1 & 3R Single Phase - 200 Amp Meter Socket Modules	4-25
Meter Center NEMA 1 & 3R Three Phase - 125 Amp Meter Socket Modules	4-25
Meter Center NEMA 1 & 3R Three Phase - 200 Amp Meter Socket Modules	4-26
240/120 Volt Meter Socket	4-26
PT/CT Components	4-26
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 208 to 240 Volt Full Voltage Starting	4-25
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 208 to 240 Volt Part Winding Starting	4-26
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 208 to 240 Wye Delta Starting	4-26
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 208 to 240 Volt Reduced Voltage Starting	4-26
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 380 to 600 Volt Full Voltage Starting	4-27
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 380 to 600 Volt Part Winding Starting	4-27
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 380 to 600 Volt Wye Delta Starting	4-27
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 380 to 600 Volt Reduced Voltage Starting	4-27
Transformers Outdoor Type Up to 15 KV Primary	4-28
Transformers Indoor Type Up to 15 KV Primary	4-28
Transformers Indoor Type Up to 600 V Primary	4-28
Transformers Single Phase Floor Mounted Up to 600 V Primary	4-29
Transformers Three Phase Floor Mounted Up to 600 V Primary	4-29
Transformers Single Phase Wall Mounted Up to 600 V Primary	4-29
Transformers Three Phase Wall Mounted Up to 600 V Primary	4-29
Transformer Lightning Arrestors	4-30
Flexible Steel Conduit 30" to 60" Long	4-30
Liquid-Tight Steel Conduit 30" to 60" Long	4-30
Flexible Braid Connectors	4-30
208 & 240 Volt 3 Phase Power Capacitors	4-30
480 & 600 Volt 3 Phase Power Capacitors	4-31
Manual Transfer Switch: Enclosed - 600 Volt 2 Pole Double Throw Wall Mounted	4-31
Manual Transfer Switch: Enclosed - 600 Volt 3 Pole Double Throw Wall Mounted	4-31
Manual Transfer Switch: Enclosed - 600 Volt 4 Pole Double Throw Wall Mounted	4-32
Automatic Transfer Switch: Enclosed - 600 Volt 2 Pole Double Throw Wall Mounted	4-32
Automatic Transfer Switch: Enclosed - 600 Volt 3 Pole Double Throw Wall Mounted	4-32
Automatic Transfer Switch: Enclosed - 600 Volt 4 Pole Double Throw Wall Mounted	4-32
Automatic Transfer & Bypass Isolation Switches: Drawout Type 3 Pole 600 Volt	4-33
Automatic Transfer & Bypass Isolation Switches: Drawout Type 4 Pole 600 Volt	4-33
Generator Sets	4-34
Emergency Generator & 2-Source Auto Transfer Switch in Single Enclosure - 208 Volt Service	4-34
Emergency Generator & 2-Source Auto Transfer Switch in Single Enclosure - 220 Volt Service	4-34
Emergency Generator & 2-Source Auto Transfer Switch in Single Enclosure - 480 Volt Service	4-34
Emergency Generator & 2-Source Auto Transfer Switch in Single Enclosure - 600 Volt Service	4-34
Emergency Generator & 3-Source Auto Transfer Switch in Two Enclosures - 208 Volt Service	4-35
Emergency Generator & 3-Source Auto Transfer Switch in Two Enclosures - 220 Volt Service	4-35
Emergency Generator & 3-Source Auto Transfer Switch in Two Enclosures - 480 Volt Service	4-35
Emergency Generator & 3-Source Auto Transfer Switch in Two Enclosures - 600 Volt Service	4-35
Emergency Generator & 3-Source Auto Transfer Switch in Four Enclosures - 208 Volt Service	4-35
Emergency Generator & 3-Source Auto Transfer Switch in Four Enclosures - 220 Volt Service	4-35
Emergency Generator & 3-Source Auto Transfer Switch in Four Enclosures - 480 Volt Service	4-36
Emergency Generator & 3-Source Auto Transfer Switch in Four Enclosures - 600 Volt Service	4-36
Emergency Generator Fused 2-Pole Switch Distribution Section in Single Enclosure	4-36
Emergency Generator Fused 3-Pole Switch Distribution Section in Single Enclosure	4-36
Emergency Generator Fused 4-Pole Switch Distribution Section in Single Enclosure	4-36
Emergency Generator Selective Load Transfer Switches in Single Enclosure	4-37
Emergency Generator Master Control - Single Enclosure	4-37
Generator w/o Fuel Tank Up to 60KW	4-37
Generator w/o Fuel Tank - Over 60KW	4-38

## Section 4 - Switchboards, MCC's, Panelboards & Power Equipment Table of Contents

Generator Accessories	4-38
Controls	4-38
Water Radiator	4-38
Miscellaneous	4-38
TVSS Self Contained Unit - Lug Type	4-39
TVSS Includes Nipples/Knock Outs/Mounting Brackets/Terminations	4-39
TVSS - Serviceable Unit - Lug Type	4-39
TVSS - Serviceable Unit - Disconnect Type	4-39
EPO Emergency Power Off Systems	4-39
Uninterruptible Power Supply Up to 600 Volt Self Contained	4-39
UPS Systems - Single Phase 120V	4-39
UPS Systems - Three Phase 208V - System Control Cabinet w/o Internal Batteries	4-39
UPS Systems - Three Phase 120/208V with Internal batteries	4-39
UPS Systems - Three Phase System Control Cabinets - 208V or 480V	4-39
UPS Systems - Three Phase Maintenance Bypass Cabinet (MBC)	4-39
UPS Systems - Three Phase Sealed Battery Cabinets on a maximum battery time of 30 minutes	4-40
UPS Systems - Three Phase Single Module Systems	4-40
UPS Systems - Control Cabinet	4-40
Battery Spacesaver System	4-40
Accessories	4-40
UPS Systems - Battery Racks	4-40
UPS Systems - Wet-Cell Battery	4-40
UPS Systems - Battery Disconnect Switch	4-40
UPS Systems - Battery Charging Unit - Rack Mounted	4-40
UPS Systems - Spill Containment System	4-40
UPS Systems - Battery Cycle Monitor	4-40
UPS Systems - Battery Monitoring System	4-41
UPS Systems - Remote Status Panel	4-41
UPS Systems - Static Transfer Switches	4-41
UPS Systems - Power Distribution Units - PDU's 208/480V Input	4-41
UPS Systems - Remote Distribution Cabinets - RDC's / RPP's	4-41
UPS Systems - Static Transfer Switch & PDU Combined	4-41
Emergency Power Off System	4-41
UPS Systems - Hydrogen Detection System	4-41
Generators - Permanent Outdoor Loadbank Units - Installed on Grade Level	4-41
Generators - Portable Loadbank Units - Installed on Grade Level	4-41

**(Updated)**

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Switchboard Section Handling Labor Only</b>						
200 Lbs		8.00	10.00	12.00		E
300 Lbs		9.00	11.25	13.50		E
400 Lbs		10.00	12.50	15.00		E
500 Lbs		11.00	13.75	16.50		E
600 Lbs		12.00	15.00	18.00		E
700 Lbs		13.00	16.25	19.50		E
800 Lbs		14.00	17.50	21.00		E
900 Lbs		15.00	18.75	22.50		E
1000 Lbs		16.00	20.00	24.00		E
1200 Lbs		18.00	22.50	27.00		E
1400 Lbs		20.00	25.00	30.00		E
1600 Lbs		22.00	27.50	33.00		E
1800 Lbs		24.00	30.00	36.00		E
2000 Lbs		26.00	32.50	39.00		E
2500 Lbs		29.00	36.25	43.50		E
3000 Lbs		32.00	40.00	48.00		E
3500 Lbs		36.00	45.00	54.00		E
4000 Lbs		40.00	50.00	60.00		E
5000 Lbs		46.00	57.50	69.00		E
6000 Lbs		52.00	65.00	78.00		E
7000 Lbs		58.00	72.50	87.00		E
8000 Lbs		64.00	80.00	96.00		E
9000 Lbs		72.00	90.00	108.00		E
10000 Lbs		80.00	100.00	120.00		E
<b>Switchboard/Gear Sections</b>						
200A 1-Section Distrib Swbd		8.00	10.00	12.00		E
200A 2-Section Distrib Swbd		14.40	18.00	21.60		E
400A 1-Section Distrib Swbd		10.00	12.50	15.00		E
400A 2-Section Distrib Swbd		18.00	22.50	27.00		E
400A 3-Section Distrib Swbd		27.00	33.75	40.50		E
600A 1-Section Distrib Swbd		12.00	15.00	18.00		E
600A 2-Section Distrib Swbd		21.60	27.00	32.40		E
600A 3-Section Distrib Swbd		32.40	40.50	48.60		E
800A 1-Section Distrib Swbd		14.00	17.50	21.00		E
800A 2-Section Distrib Swbd		25.20	31.50	37.80		E
800A 3-Section Distrib Swbd		37.80	47.25	56.70		E
1200A 1-Section Distrib Swbd		18.00	22.50	27.00		E
1200A 2-Section Distrib Swbd		32.40	40.50	48.60		E
1200A 3-Section Distrib Swbd		48.60	60.75	72.90		E
1200A 4-Section Distrib Swbd		64.80	81.00	97.20		E
1600A 1-Section Distrib Swbd		22.00	27.50	33.00		E
1600A 2-Section Distrib Swbd		39.60	49.50	59.40		E
1600A 3-Section Distrib Swbd		59.40	74.25	89.10		E
1600A 4-Section Distrib Swbd		79.20	99.00	118.80		E
1600A 5-Section Distrib Swbd		99.00	123.75	148.50		E
2000A 1-Section Distrib Swbd		26.00	32.50	39.00		E
2000A 2-Section Distrib Swbd		46.80	58.50	70.20		E
2000A 3-Section Distrib Swbd		70.20	87.75	105.30		E
2000A 4-Section Distrib Swbd		93.60	117.00	140.40		E
2000A 5-Section Distrib Swbd		117.00	146.25	175.50		E
2000A 6-Section Distrib Swbd		140.40	175.50	210.60		E
2500A 1-Section Distrib Swbd		30.00	37.50	45.00		E
2500A 2-Section Distrib Swbd		54.00	67.50	81.00		E
2500A 3-Section Distrib Swbd		81.00	101.25	121.50		E
2500A 4-Section Distrib Swbd		108.00	135.00	162.00		E
2500A 5-Section Distrib Swbd		135.00	168.75	202.50		E
2500A 6-Section Distrib Swbd		162.00	202.50	243.00		E
2500A 7-Section Distrib Swbd		189.00	236.25	283.50		E
2500A 8-Section Distrib Swbd		216.00	270.00	324.00		E
3000A 1-Section Distrib Swbd		34.00	42.50	51.00		E
3000A 2-Section Distrib Swbd		61.20	76.50	91.80		E
3000A 3-Section Distrib Swbd		91.80	114.75	137.70		E
3000A 4-Section Distrib Swbd		122.40	153.00	183.60		E
3000A 5-Section Distrib Swbd		153.00	191.25	229.50		E
3000A 6-Section Distrib Swbd		183.60	229.50	275.40		E
3000A 7-Section Distrib Swbd		214.20	267.75	321.30		E
3000A 8-Section Distrib Swbd		244.80	306.00	367.20		E
3000A 9-Section Distrib Swbd		275.40	344.25	413.10		E

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment






4











Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
3000A 10-Section Distrib Swbd		306.00	382.50	459.00		E
4000A 1-Section Distrib Swbd		40.00	50.00	60.00		E
4000A 2-Section Distrib Swbd		72.00	90.00	108.00		E
4000A 3-Section Distrib Swbd		108.00	135.00	162.00		E
4000A 4-Section Distrib Swbd		144.00	180.00	216.00		E
4000A 5-Section Distrib Swbd		180.00	225.00	270.00		E
4000A 6-Section Distrib Swbd		216.00	270.00	324.00		E
4000A 7-Section Distrib Swbd		252.00	315.00	378.00		E
4000A 8-Section Distrib Swbd		288.00	360.00	432.00		E
4000A 9-Section Distrib Swbd		324.00	405.00	486.00		E
4000A 10-Section Distrib Swbd		360.00	450.00	540.00		E
5000A 1-Section Distrib Swbd		48.00	60.00	72.00		E
5000A 2-Section Distrib Swbd		86.40	108.00	129.60		E
5000A 3-Section Distrib Swbd		129.60	162.00	194.40		E
5000A 4-Section Distrib Swbd		172.80	216.00	259.20		E
5000A 5-Section Distrib Swbd		216.00	270.00	324.00		E
5000A 6-Section Distrib Swbd		259.20	324.00	388.80		E
5000A 7-Section Distrib Swbd		302.40	378.00	453.60		E
5000A 8-Section Distrib Swbd		345.60	432.00	518.40		E
5000A 9-Section Distrib Swbd		388.80	486.00	583.20		E
5000A 10-Section Distrib Swbd		432.00	540.00	648.00		E
<b>Switchboard Heater</b>	<b>X</b>					
Switchboard heater	<b>X</b>					
120V or 250V	<b>X</b>	0.50	0.75	1.00		E
<b>Switchboard 600 Volt Feed Conductor Terminations</b>						
#12		0.15	0.19	0.23		E
#10		0.16	0.20	0.24		E
#8		0.18	0.23	0.27		E
#6		0.20	0.25	0.30		E
#4		0.22	0.27	0.33		E
#3		0.24	0.30	0.36		E
#2		0.27	0.33	0.40		E
#1		0.30	0.37	0.45		E
1/0		0.33	0.41	0.50		E
2/0		0.36	0.45	0.55		E
3/0		0.40	0.50	0.60		E
4/0		0.45	0.56	0.67		E
250 kcmil		0.50	0.62	0.75		E
300 kcmil		0.55	0.68	0.82		E
350 kcmil		0.60	0.75	0.90		E
400 kcmil		0.65	0.81	0.97		E
500 kcmil		0.70	0.87	1.05		E
600 kcmil		0.80	1.00	1.20		E
750 kcmil		0.90	1.12	1.35		E
1000 kcmil		1.00	1.25	1.50		E
<b>Switchboard Grounding Conductor Terminations</b>						
#12		0.15	0.19	0.23		E
#10		0.16	0.20	0.24		E
#8		0.18	0.23	0.27		E
#6		0.20	0.25	0.30		E
#4		0.22	0.28	0.33		E
#3		0.24	0.30	0.36		E
#2		0.27	0.34	0.41		E
#1		0.30	0.38	0.45		E
1/0		0.33	0.41	0.50		E
2/0		0.36	0.45	0.54		E
3/0		0.40	0.50	0.60		E
4/0		0.45	0.56	0.68		E
250 kcmil		0.50	0.63	0.75		E
300 kcmil		0.53	0.66	0.80		E
350 kcmil		0.55	0.69	0.83		E
400 kcmil		0.60	0.75	0.90		E
500 kcmil		0.70	0.88	1.05		E



Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>Switchboard 2 Pole Copper Cond. Term. On Circuit Breakers &amp; Switches (Includes labor for terminating neutrals)</b>						
20 Amp #12		0.50	0.63	0.75		E
30 Amp #10		0.55	0.69	0.83		E
60 Amp #8		0.60	0.75	0.90		E
80 Amp #6		0.70	0.88	1.05		E
100 Amp #4		0.80	1.00	1.20		E
125 Amp #2		1.00	1.25	1.50		E
150 Amp #1		1.10	1.38	1.65		E
175 Amp 1/0		1.20	1.50	1.80		E
200 Amp 2/0		1.40	1.75	2.10		E
225 Amp 3/0		1.60	2.00	2.40		E
250 Amp 4/0		1.80	2.25	2.70		E
300 Amp 250 kcmil		2.00	2.50	3.00		E
350 Amp 350 kcmil		2.50	3.13	3.75		E
400 Amp 500 kcmil		3.00	3.75	4.50		E
600 Amp 750 kcmil		4.00	5.00	6.00		E
800 Amp 1000 kcmil		5.25	6.56	7.88		E
1000 Amp		7.25	9.06	10.88		E
1200 Amp		8.25	10.31	12.38		E
Add For Shunt Trip	X	1.00	1.25	1.50		E
 <b>Switchboard 3 Pole Copper Cond. Term. On Circuit Breakers &amp; Switches (Includes labor for terminating neutrals)</b>						
20 Amp #12		0.70	0.88	1.05		E
30 Amp #10		0.80	1.00	1.20		E
60 Amp #8		0.90	1.13	1.35		E
80 Amp #6		1.00	1.25	1.50		E
100 Amp #4		1.20	1.50	1.80		E
125 Amp #2		1.50	1.88	2.25		E
150 Amp #1		1.65	2.06	2.48		E
175 Amp 1/0		1.80	2.25	2.70		E
200 Amp 2/0		2.10	2.63	3.15		E
225 Amp 3/0		2.40	3.00	3.60		E
250 Amp 4/0		2.70	3.38	4.05		E
300 Amp 250 kcmil		3.00	3.75	4.50		E
350 Amp 350 kcmil		4.00	5.00	6.00		E
400 Amp 500 kcmil		5.00	6.25	7.50		E
600 Amp 750 kcmil		6.00	7.50	9.00		E
800 Amp 1000 kcmil		7.25	9.06	10.88		E
1000 Amp		9.25	11.56	13.88		E
1200 Amp		10.25	12.81	15.38		E
Add for Shunt Trip	X	1.00	1.25	1.50		E
 <b>Switchboard Bus Bar Splice Connections</b>						
<b>3 Phase 4 Wire W/ Copper Ground</b>						
400 Amp		4.00	5.00	6.00		E
800 Amp		6.00	7.50	9.00		E
1000 Amp		8.00	10.00	12.00		E
1200 Amp		10.00	12.50	15.00		E
2000 Amp		12.00	15.00	18.00		E
 <b>Steel Channels Embedded in Concrete</b>						
4 Ft Long		1.00	1.25	1.50		E
6 Ft Long		1.25	1.56	1.88		E
8 Ft Long		1.50	1.88	2.25		E
10 Ft Long		1.75	2.19	2.63		E
12 Ft Long		2.00	2.50	3.00		E
 <b>Custom Made Steel Pull Boxes</b>						
<b>Bolted To Switchboards or Motor Control Center</b>						
<b>"Top Hat" or "Pull Section"</b>						
12" x 24" x 72" 140 lb		8.00	10.00	12.00		E
12" x 24" x 96" 170 lb		10.00	12.50	15.00		E
12" x 24" x 120" 200 lb		12.00	15.00	18.00		E
12" X 24" X 144" 230 LB		14.00	17.50	21.00		E
12" x 36" x 72" 170 lb		10.00	12.50	15.00		E
12" x 36" x 96" 205 lb		12.00	15.00	18.00		E
12" x 36" x 120" 240 lb		14.00	17.50	21.00		E
12" x 36" x 144" 275 lb		16.00	20.00	24.00		E
12" x 48" x 72" 200 lb		12.00	15.00	18.00		E
12" x 48" x 96" 240 lb		14.00	17.50	21.00		E
12" x 48" x 120" 280 lb		16.00	20.00	24.00		E
12" x 48" x 144" 320 lb		18.00	22.50	27.00		E
18" x 36" x 72" 230 lb		14.00	17.50	21.00		E
18" x 36" x 96" 280 lb		16.00	20.00	24.00		E
18" x 36" x 120" 330 lb		19.00	23.75	28.50		E
18" x 36" x 144" 380 lb		22.00	27.50	33.00		E
24" x 24" 72" 260 lb		16.00	20.00	24.00		E
24" x 24" x 96" 300 lb		18.00	22.50	27.00		E
24" x 24" x 120" 350 lb		21.00	26.25	31.50		E
24" x 24" x 144" 400 lb		24.00	30.00	36.00		E
24" x 36" 72" 460 lb		26.00	32.50	39.00		E
24" x 36" x 96" 540 lb		30.00	37.50	45.00		E
24" x 36" x 120" 620 lb		35.00	43.75	52.50		E
24" x 36" x 144" 700 lb		40.00	50.00	60.00		E

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment






Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>Fuse Installation in Fused Switch in Safety Switches and MCC's Cartridge Fuse (250V - 600V)</b>						
1 Amp to 100 Amp		0.04	0.05	0.06		E
110 Amp to 200 Amp		0.10	0.13	0.15		E
210 Amp to 400 Amp		0.17	0.21	0.26		E
410 Amp to 600 Amp		0.20	0.25	0.30		E
 <b>Bolt-On Fuse 600 Volt</b>						
600 Amp to 1800 Amp		0.30	0.38	0.45		E
2000 Amp to 6000 Amp		0.50	0.63	0.75		E
Fuse Reducer		0.15	0.19	0.23		E
Fuse Cabinet		1.00	1.25	1.50		E
 <b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Surface Mounted - 100 Amp Rating</b>						
16 Circuit		2.00	2.50	3.00		E
20 Circuit		2.20	2.75	3.30		E
24 Circuit		2.40	3.00	3.60		E
28 Circuit		2.60	3.25	3.90		E
32 Circuit		2.80	3.50	4.20		E
36 Circuit		3.00	3.75	4.50		E
 <b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Surface Mounted - 125 Amp Rating</b>						
16 Circuit		2.20	2.75	3.30		E
20 Circuit		2.40	3.00	3.60		E
24 Circuit		2.60	3.25	3.90		E
28 Circuit		2.80	3.50	4.20		E
32 Circuit		3.00	3.75	4.50		E
36 Circuit		3.20	4.00	4.80		E
 <b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Surface Mounted - 150 Amp Rating</b>						
16 Circuit		2.40	3.00	3.60		E
20 Circuit		2.60	3.25	3.90		E
24 Circuit		2.80	3.50	4.20		E
28 Circuit		3.00	3.75	4.50		E
32 Circuit		3.20	4.00	4.80		E
36 Circuit		3.40	4.25	5.10		E
42 Circuit		3.60	4.40	5.30		E
 <b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Surface Mounted - 225 Amp Rating</b>						
16 Circuit		2.80	3.50	4.20		E
20 Circuit		3.00	3.75	4.50		E
24 Circuit		3.20	4.00	4.80		E
28 Circuit		3.40	4.25	5.10		E
32 Circuit		3.60	4.50	5.40		E
36 Circuit		3.80	4.75	5.70		E
42 Circuit		4.00	5.00	6.00		E
 <b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Surface Mounted - 400 Amp Rating</b>						
16 Circuit		3.20	4.00	4.80		E
20 Circuit		3.60	4.50	5.40		E
24 Circuit		4.00	5.00	6.00		E
28 Circuit		4.40	5.50	6.60		E
32 Circuit		4.80	6.00	7.20		E
36 Circuit		5.20	6.50	7.80		E
42 Circuit		5.60	7.00	8.40		E
 <b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Surface Mounted - 600 Amp Rating</b>						
16 Circuit		4.00	5.00	6.00		E
20 Circuit		4.50	5.63	6.75		E
24 Circuit		5.00	6.25	7.50		E
28 Circuit		5.50	6.88	8.25		E
32 Circuit		6.00	7.50	9.00		E
36 Circuit		6.50	8.13	9.75		E
42 Circuit		7.00	8.75	10.50		E

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment





Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
	<b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Surface Mounted - 800 Amp Rating</b>					
	16 Circuit		6.00	7.50	9.00	E
	20 Circuit		7.00	8.75	10.50	E
	24 Circuit		8.00	10.00	12.00	E
	28 Circuit		9.00	11.25	13.50	E
	32 Circuit		10.00	12.50	15.00	E
	36 Circuit		11.00	13.75	16.50	E
	42 Circuit		12.00	15.00	18.00	E
	<b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Surface Mounted - 1200 Amp Rating</b>					
	16 Circuit		8.00	10.00	12.00	E
	20 Circuit		9.00	11.25	13.50	E
	24 Circuit		10.00	12.50	15.00	E
	28 Circuit		11.00	13.75	16.50	E
	32 Circuit		12.00	15.00	18.00	E
	36 Circuit		13.00	16.25	19.50	E
	42 Circuit		14.00	17.50	21.00	E
	<b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Recessed Mounting - 100 Amp Rating</b>					
	16 Circuit		3.00	3.75	4.50	E
	20 Circuit		3.20	4.00	4.80	E
	24 Circuit		3.40	4.25	5.10	E
	28 Circuit		3.60	4.50	5.40	E
	32 Circuit		3.80	4.75	5.70	E
	36 Circuit		4.00	5.00	6.00	E
	<b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Recessed Mounting - 125 Amp Rating</b>					
	16 Circuit		3.20	4.00	4.80	E
	20 Circuit		3.40	4.25	5.10	E
	24 Circuit		3.60	4.50	5.40	E
	28 Circuit		3.80	4.75	5.70	E
	32 Circuit		4.00	5.00	6.00	E
	36 Circuit		4.20	5.25	6.30	E
	<b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Recessed Mounting - 150 Amp Rating</b>					
	16 Circuit		3.60	4.50	5.40	E
	20 Circuit		3.80	4.75	5.70	E
	24 Circuit		4.00	5.00	6.00	E
	28 Circuit		4.20	5.25	6.30	E
	32 Circuit		4.40	5.50	6.60	E
	36 Circuit		4.60	5.75	6.90	E
	42 Circuit		4.80	5.90	7.20	E
	<b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Recessed Mounting - 225 Amp Rating</b>					
	16 Circuit		4.00	5.00	6.00	E
	20 Circuit		4.20	5.25	6.30	E
	24 Circuit		4.40	5.50	6.60	E
	28 Circuit		4.60	5.75	6.90	E
	32 Circuit		4.80	6.00	7.20	E
	36 Circuit		5.00	6.25	7.50	E
	42 Circuit		5.20	6.50	7.80	E
	<b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Recessed Mounting - 400 Amp Rating</b>					
	16 Circuit		5.00	6.25	7.50	E
	20 Circuit		5.40	6.75	8.10	E
	24 Circuit		5.80	7.25	8.70	E
	28 Circuit		6.20	7.75	9.30	E
	32 Circuit		6.60	8.25	9.90	E
	36 Circuit		7.00	8.75	10.50	E
	42 Circuit		7.50	9.20	11.70	E

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

4

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Recessed Mounting - 600 Amp Rating</b>						
16 Circuit		6.00	7.50	9.00		E
20 Circuit		6.50	8.13	9.75		E
24 Circuit		7.00	8.75	10.50		E
28 Circuit		7.50	9.38	11.25		E
32 Circuit		8.00	10.00	12.00		E
36 Circuit		8.50	10.63	12.75		E
42 Circuit		9.00	11.25	13.50		E
 <b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Recessed Mounting - 800 Amp Rating</b>						
16 Circuit		8.00	10.00	12.00		E
20 Circuit		9.00	11.25	13.50		E
24 Circuit		10.00	12.50	15.00		E
28 Circuit		11.00	13.75	16.50		E
32 Circuit		12.00	15.00	18.00		E
36 Circuit		13.00	16.25	19.50		E
42 Circuit		14.00	17.50	21.00		E
 <b>Panelboard Empty Enclosure, Interior and Cover Mounting Labor - Recessed Mounting - 1200 Amp Rating</b>						
16 Circuit		10.00	12.50	15.00		E
20 Circuit		11.00	13.75	16.50		E
24 Circuit		12.00	15.00	18.00		E
28 Circuit		13.00	16.25	19.50		E
32 Circuit		14.00	17.50	21.00		E
36 Circuit		15.00	18.75	22.50		E
42 Circuit		16.00	20.00	24.00		E
 <b>Panelboard 600 Volt Feed Conductor Terminations</b>						
#12		0.16	0.20	0.24		E
#10		0.18	0.23	0.27		E
#8		0.20	0.25	0.30		E
#6		0.22	0.28	0.33		E
#4		0.25	0.31	0.38		E
#3		0.28	0.35	0.42		E
#2		0.30	0.38	0.45		E
#1		0.33	0.41	0.50		E
1/0		0.36	0.45	0.54		E
2/0		0.40	0.50	0.60		E
3/0		0.45	0.56	0.68		E
4/0		0.50	0.63	0.75		E
250 kcmil		0.55	0.69	0.83		E
300 kcmil		0.60	0.75	0.90		E
350 kcmil		0.65	0.81	0.98		E
400 kcmil		0.70	0.88	1.05		E
500 kcmil		0.75	0.94	1.13		E
600 kcmil		0.80	1.00	1.20		E
750 kcmil		0.85	1.06	1.28		E
800 kcmil		0.90	1.13	1.35		E
1000 kcmil		1.00	1.25	1.50		E
 <b>Panelboard Grounding Conductor Terminations</b>						
#12		0.16	0.20	0.24		E
#10		0.18	0.23	0.27		E
#8		0.20	0.25	0.30		E
#6		0.22	0.28	0.33		E
#4		0.25	0.31	0.38		E
#3		0.28	0.35	0.42		E
#2		0.30	0.38	0.45		E
#1		0.33	0.41	0.50		E
1/0		0.36	0.45	0.54		E
2/0		0.40	0.50	0.60		E
3/0		0.45	0.56	0.68		E
4/0		0.50	0.63	0.75		E
250 kcmil		0.55	0.69	0.83		E
300 kcmil		0.60	0.75	0.90		E
350 kcmil		0.70	0.88	1.05		E
400 kcmil		0.80	1.00	1.20		E
500 kcmil		1.00	1.25	1.50		E

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
						
<b>Panelboard Terminations: Single Pole Circuit Breaker</b>						
<b>Copper Conductor Termination Including Neutral</b>						
15 Amp		0.32	0.40	0.48		E
20 Amp		0.34	0.43	0.51		E
30 Amp		0.38	0.48	0.57		E
50 Amp		0.42	0.53	0.63		E
60 Amp		0.47	0.59	0.71		E
70 Amp		0.53	0.66	0.80		E
90 Amp		0.58	0.73	0.87		E
100 Amp		0.61	0.76	0.92		E
125 Amp		0.69	0.86	1.04		E
150 Amp		0.80	1.00	1.20		E
175 Amp		0.90	1.13	1.35		E
200 Amp		1.00	1.25	1.50		E
225 Amp		1.10	1.38	1.65		E
250 Amp		1.20	1.50	1.80		E
300 Amp		1.35	1.69	2.03		E
Add for Special Purpose Breakers (Arc-Fault, GFI, Shunt Trip)	X	0.15	0.25	0.35		E
						
<b>Panelboard Terminations: Two Pole Circuit Breaker</b>						
<b>Copper Conductor Termination Including Neutral</b>						
15 Amp		0.48	0.60	0.72		E
20 Amp		0.52	0.65	0.78		E
30 Amp		0.58	0.73	0.87		E
50 Amp		0.64	0.80	0.96		E
60 Amp		0.72	0.90	1.08		E
70 Amp		0.81	1.01	1.22		E
90 Amp		0.88	1.10	1.32		E
100 Amp		0.94	1.18	1.41		E
125 Amp		1.05	1.31	1.58		E
150 Amp		1.20	1.50	1.80		E
175 Amp		1.35	1.69	2.03		E
200 Amp		1.50	1.88	2.25		E
225 Amp		1.65	2.06	2.48		E
250 Amp		1.85	2.31	2.78		E
300 Amp		2.05	2.56	3.08		E
400 Amp		2.25	2.81	3.38		E
600 Amp		2.50	3.13	3.75		E
800 Amp		2.75	3.44	4.13		E
Add for Special Purpose Breakers (Arc-Fault, GFI, Shunt Trip)	X	0.15	0.25	0.35		E
						
<b>Panelboard Terminations: Three Pole Circuit Breaker</b>						
<b>Copper Conductor Termination Including Neutral</b>						
15 Amp		0.66	0.83	0.99		E
20 Amp		0.71	0.89	1.07		E
30 Amp		0.78	0.98	1.17		E
40 Amp	X	0.82	1.00	1.22		E
50 Amp		0.85	1.06	1.28		E
60 Amp		0.92	1.15	1.38		E
70 Amp		1.05	1.31	1.58		E
90 Amp		1.18	1.48	1.77		E
100 Amp		1.28	1.60	1.92		E
125 Amp		1.43	1.79	2.15		E
150 Amp		1.60	2.00	2.40		E
175 Amp		1.80	2.25	2.70		E
200 Amp		2.00	2.50	3.00		E
225 Amp		2.25	2.81	3.38		E
250 Amp		2.50	3.13	3.75		E
300 Amp		2.75	3.44	4.13		E
400 Amp		3.00	3.75	4.50		E
600 Amp		3.25	4.06	4.88		E
800 Amp		3.50	4.38	5.25		E
Add for Special Purpose Breakers (Arc-Fault, GFI, Shunt Trip)	X	0.15	0.25	0.35		E
						
<b>Motor Control Centers: Receiving, Handling and Set In Place</b>						
1 Section		6.00	7.50	9.00		E
2 Sections		12.00	15.00	18.00		E
3 Sections		18.00	22.50	27.00		E
<i>Note: Labor Units Do Not Include:</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
<i>Note: For MCC's with More Than 3 Sections,</i>						
<i>Add Appropriate Section Labor To the 3 Section Total</i>						
<i>Additional Items To Consider:</i>						
1) Re-Torque Lugs/Inspection						
2) Rigging Equipment						
3) Provisions For Concrete Pad						
4) Commissioning and Testing						

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

4

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>MCC: Anchoring to Concrete Pad</b>						
1 Section		1.25	1.56	1.88		E
2 Sections		2.50	3.13	3.75		E
3 Sections		3.75	4.69	5.63		E
<i>Note: For MCC's with More Than 3 Sections, Add Appropriate Section Labor To the 3 Section Total</i>						
<i>Note: Add Local Seismic Zone Anchoring Requirements</i>						
<b>MCC: Multiple Section Bolting Connections</b>						
Per Splice Point		1.50	1.88	2.25		E
<b>MCC: Multiple Section Bus Bar Connections - Per Bus Bar</b>						
200 A		0.50	0.63	0.75		E
400 A		0.50	0.63	0.75		E
600 A		0.75	0.94	1.13		E
800 A		0.75	0.94	1.13		E
1200 A		1.50	1.88	2.25		E
<b>Motor Starters Mounted in MCC's</b>						
<b>Single Speed Non-Reversing 2-Pole</b>						
NEMA 00		0.90	1.13	1.35		E
NEMA 0		1.00	1.25	1.50		E
NEMA 1		1.10	1.38	1.65		E
NEMA 2		1.35	1.69	2.03		E
<b>Motor Starters Mounted in MCC's</b>						
<b>Single Speed Non-Reversing 3-Pole</b>						
NEMA 00		1.00	1.25	1.50		E
NEMA 0		1.10	1.38	1.65		E
NEMA 1		1.20	1.50	1.80		E
NEMA 2		1.50	1.88	2.25		E
NEMA 3		2.00	2.50	3.00		E
NEMA 4		3.00	3.75	4.50		E
NEMA 5		4.00	5.00	6.00		E
NEMA 6		6.00	7.50	9.00		E
<b>Motor Starters Mounted in MCC's</b>						
<b>Single Speed Non-Reversing 4-Pole</b>						
NEMA 00		1.10	1.38	1.65		E
NEMA 0		1.20	1.50	1.80		E
NEMA 1		1.30	1.63	1.95		E
NEMA 2		1.70	2.13	2.55		E
NEMA 3		2.20	2.75	3.30		E
<b>Motor Starters Mounted in MCC's</b>						
<b>Single Speed Reversing 2-Pole</b>						
NEMA 00		1.00	1.25	1.50		E
NEMA 0		1.10	1.38	1.65		E
NEMA 1		1.20	1.50	1.80		E
NEMA 2		1.45	1.81	2.18		E
<i>Note: Reversing Motors are Assumed To Be Factory Wired</i>						
<b>Motor Starters Mounted in MCC's</b>						
<b>Single Speed Reversing 3-Pole</b>						
NEMA 00		1.10	1.38	1.65		E
NEMA 0		1.20	1.50	1.80		E
NEMA 1		1.30	1.63	1.95		E
NEMA 2		1.60	2.00	2.40		E
NEMA 3		2.10	2.63	3.15		E
NEMA 4		3.10	3.88	4.65		E
NEMA 5		4.10	5.13	6.15		E
NEMA 6		6.10	7.63	9.15		E
<i>Note: Reversing Motors are Assumed To Be Factory Wired</i>						
<b>Motor Starters Mounted in MCC's</b>						
<b>Single Speed Reversing 4-Pole</b>						
NEMA 00		1.20	1.50	1.80		E
NEMA 0		1.30	1.63	1.95		E
NEMA 1		1.40	1.75	2.10		E
NEMA 2		1.80	2.25	2.70		E
NEMA 3		2.30	2.88	3.45		E
<i>Note: Reversing Motors are Assumed To Be Factory Wired</i>						
<b>Motor Starters Mounted in MCC's</b>						
<b>Multi - Speed Non-Reversing 2-Pole</b>						
NEMA 00		1.80	2.25	2.70		E
NEMA 0		2.00	2.50	3.00		E
NEMA 1		2.25	2.81	3.38		E
NEMA 2		2.75	3.44	4.13		E

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <p><b>Motor Starters Mounted in MCC's</b> <b>Multi - Speed Non-Reversing 3-Pole</b></p>	NEMA 00		2.00	2.50	3.00	E
	NEMA 0		2.20	2.75	3.30	E
	NEMA 1		2.40	3.00	3.60	E
	NEMA 2		3.00	3.75	4.50	E
	NEMA 3		4.00	5.00	6.00	E
	NEMA 4		5.00	6.25	7.50	E
	NEMA 5		6.00	7.50	9.00	E
	NEMA 6		8.00	10.00	12.00	E
 <p><b>Motor Starters Mounted in MCC's</b> <b>Multi - Speed Non-Reversing 4-Pole</b></p>	NEMA 00		2.20	2.75	3.30	E
	NEMA 0		2.40	3.00	3.60	E
	NEMA 1		2.60	3.25	3.90	E
	NEMA 2		3.30	4.13	4.95	E
	NEMA 3		4.40	5.50	6.60	E
 <p><b>Motor Starters Mounted in MCC's</b> <b>Multi - Multi Speed Reversing 2-Pole</b></p> <p><i>Note: Reversing Motors are Assumed To Be Factory Wired</i></p>	NEMA 00		2.80	3.50	4.20	E
	NEMA 0		3.00	3.75	4.50	E
	NEMA 1		3.40	4.25	5.10	E
	NEMA 2		4.00	5.00	6.00	E
 <p><b>Motor Starters Mounted in MCC's</b> <b>Multi - Multi Speed Reversing 3-Pole</b></p> <p><i>Note: Reversing Motors are Assumed To Be Factory Wired</i></p>	NEMA 00		3.00	3.75	4.50	E
	NEMA 0		3.20	4.00	4.80	E
	NEMA 1		3.60	4.50	5.40	E
	NEMA 2		4.40	5.50	6.60	E
	NEMA 3		5.00	6.25	7.50	E
	NEMA 4		6.00	7.50	9.00	E
	NEMA 5		8.00	10.00	12.00	E
	NEMA 6		10.00	12.50	15.00	E
 <p><b>Motor Starters Mounted in MCC's</b> <b>Multi - Multi Speed Reversing 4-Pole</b></p> <p><i>Note: Reversing Motors are Assumed To Be Factory Wired</i></p>	NEMA 00		3.40	4.25	5.10	E
	NEMA 0		3.60	4.50	5.40	E
	NEMA 1		4.00	5.00	6.00	E
	NEMA 2		5.00	6.25	7.50	E
	NEMA 3		6.00	7.50	9.00	E
 <p><b>Factory Mounted Disconnect/Circuit Breaker - Termination Labor Only</b></p>	30 A		1.75	2.19	2.63	E
	60 A		1.90	2.38	2.85	E
	100 A		2.25	2.81	3.38	E
	200 A		2.75	3.44	4.13	E
	400 A		3.50	4.38	5.25	E
	600 A		4.00	5.00	6.00	E
	800 A		5.00	6.25	7.50	E
 <p><b>Factory Mounted Variable Frequency Drive - Termination Labor Only</b></p>	5 HP		1.00	1.25	1.50	E
	7.5 HP		1.25	1.56	1.88	E
	10 HP		1.50	1.88	2.25	E
	15 HP		2.00	2.50	3.00	E
	20 HP		2.50	3.13	3.75	E
	25 HP		3.00	3.75	4.50	E
 <p><b>Control Transformer Termination - Factory Mounted in MCC's</b></p>	Size 1		0.80	1.00	1.20	E
	Size 2		0.90	1.13	1.35	E
	Size 3		1.00	1.25	1.50	E
	Size 4		1.15	1.44	1.73	E
	Size 5		1.30	1.63	1.95	E
 <p><b>MCC Control Relay Termination - Factory Mounted in MCC's</b></p>	MCC 4-Pole Control relay		1.60	2.00	2.40	E
	MCC 8-Pole Control Relay		2.00	2.50	3.00	E
 <p><b>Auxiliary Contacts NO/NC</b></p>	Auxiliary Contacts NO/NC		0.50	0.63	0.75	E

## Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Control Wire Terminations</b>						
#14 AWG Control Wire Terminations		0.20	0.25	0.30		E
<b>Control Switch Factory Mounted</b>						
Control Switch - 2 Position		0.50	0.63	0.75		E
Control Switch-3 position		0.60	0.75	0.90		E
Control Switch-4 position		0.70	0.88	1.05		E
<b>Factory Mounted Push Button Stations</b>						
1 Button		0.40	0.50	0.60		E
2 Button		0.50	0.63	0.75		E
3 Button		0.60	0.75	0.90		E
4 Button		0.70	0.88	1.05		E
<b>Field Mounted in MCC's -</b>						
<b>Single Speed Non-Reversing 2-Pole</b>						
NEMA 00		1.80	2.25	2.70		E
NEMA 0		2.00	2.50	3.00		E
NEMA 1		2.20	2.75	3.30		E
NEMA 2		2.70	3.38	4.05		E
<i>Note: Installing a brand or type of starting equipment in a different brand or type of Motor Control Center could void the U.L. Label of the MCC</i>						
<b>Field Mounted in MCC's -</b>						
<b>Single Speed Non-Reversing 3-Pole</b>						
NEMA 00		2.00	2.50	3.00		E
NEMA 0		2.20	2.75	3.30		E
NEMA 1		2.40	3.00	3.60		E
NEMA 2		3.00	3.75	4.50		E
NEMA 3		4.00	5.00	6.00		E
NEMA 4		6.00	7.50	9.00		E
NEMA 5		8.00	10.00	12.00		E
NEMA 6		12.00	15.00	18.00		E
<i>Note: Installing a brand or type of starting equipment in a different brand or type of Motor Control Center could void the U.L. Label of the MCC</i>						
<b>Field Mounted in MCC's -</b>						
<b>Single Speed Non-Reversing 4-Pole</b>						
NEMA 00		2.20	2.75	3.30		E
NEMA 0		2.40	3.00	3.60		E
NEMA 1		2.60	3.25	3.90		E
NEMA 2		3.40	4.25	5.10		E
NEMA 3		4.40	5.50	6.60		E
<i>Note: Installing a brand or type of starting equipment in a different brand or type of Motor Control Center could void the U.L. Label of the MCC</i>						
<b>Field Mounted in MCC's - Single Speed Reversing 2-Pole</b>						
NEMA 00		2.00	2.50	3.00		E
NEMA 0		2.20	2.75	3.30		E
NEMA 1		2.40	3.00	3.60		E
NEMA 2		2.90	3.63	4.35		E
<i>Note: Installing a brand or type of starting equipment in a different brand or type of Motor Control Center could void the U.L. Label of the MCC</i>						
<b>Field Mounted in MCC's - Single Speed Reversing 3-Pole</b>						
NEMA 00		2.20	2.75	3.30		E
NEMA 0		2.40	3.00	3.60		E
NEMA 1		2.60	3.25	3.90		E
NEMA 2		3.20	4.00	4.80		E
NEMA 3		4.20	5.25	6.30		E
NEMA 4		6.20	7.75	9.30		E
NEMA 5		9.20	11.50	13.80		E
NEMA 6		12.20	15.25	18.30		E
<i>Note: Installing a brand or type of starting equipment in a different brand or type of Motor Control Center could void the U.L. Label of the MCC</i>						
<b>Field Mounted in MCC's - Single Speed Reversing 4-Pole</b>						
NEMA 00		2.40	3.00	3.60		E
NEMA 0		2.60	3.25	3.90		E
NEMA 1		2.80	3.50	4.20		E
NEMA 2		3.60	4.50	5.40		E
NEMA 3		4.60	5.75	6.90		E
<i>Note: Installing a brand or type of starting equipment in a different brand or type of Motor Control Center could void the U.L. Label of the MCC</i>						
<i>Motor Control Center could void the U.L. Label of the MCC</i>						
<i>U.L. Label of the MCC</i>						



## Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
						
<b>Field Mounted in MCC's - Variable Speed Non-Reversing 2-Pole</b>						
NEMA 00		3.60	4.50	5.40		E
NEMA 0		4.00	5.00	6.00		E
NEMA 1		4.50	5.63	6.75		E
NEMA 2		5.50	6.88	8.25		E
<i>Note: Installing a brand or type of starting equipment in a different brand or type of Motor Control Center could void the U.L. Label of the MCC</i>						
						
<b>Field Mounted in MCC's - Variable Speed Non-Reversing 3-Pole</b>						
NEMA 00		4.00	5.00	6.00		E
NEMA 0		4.40	5.50	6.60		E
NEMA 1		4.80	6.00	7.20		E
NEMA 2		6.00	7.50	9.00		E
NEMA 3		8.00	10.00	12.00		E
NEMA 4		10.00	12.50	15.00		E
NEMA 5		12.00	15.00	18.00		E
NEMA 6		16.00	20.00	24.00		E
<i>Note: Installing a brand or type of starting equipment in a different brand or type of Motor Control Center could void the U.L. Label of the MCC</i>						
						
<b>Field Mounted in MCC's - Variable Speed Non-Reversing 4-Pole</b>						
NEMA 00		4.40	5.50	6.60		E
NEMA 0		4.80	6.00	7.20		E
NEMA 1		5.20	6.50	7.80		E
NEMA 2		6.60	8.25	9.90		E
NEMA 3		8.80	11.00	13.20		E
<i>Note: Installing a brand or type of starting equipment in a different brand or type of Motor Control Center could void the U.L. Label of the MCC</i>						
						
<b>Field Mounted in MCC's - Variable Speed Reversing 2-Pole</b>						
NEMA 00		5.60	7.00	8.40		E
NEMA 0		6.00	7.50	9.00		E
NEMA 1		6.80	8.50	10.20		E
NEMA 2		8.00	10.00	12.00		E
<i>Note: Installing a brand or type of starting equipment in a different brand or type of Motor Control Center could void the U.L. Label of the MCC</i>						
<i>Note: Reversing Motors are Assumed To Be Factory Wired</i>						
						
<b>Field Mounted in MCC's - Variable Speed Reversing 3-Pole</b>						
NEMA 00		6.00	7.50	9.00		E
NEMA 0		6.40	8.00	9.60		E
NEMA 1		7.20	9.00	10.80		E
NEMA 2		8.80	11.00	13.20		E
NEMA 3		10.00	12.50	15.00		E
NEMA 4		12.00	15.00	18.00		E
NEMA 5		16.00	20.00	24.00		E
NEMA 6		20.00	25.00	30.00		E
<i>Note: Installing a brand or type of starting equipment in a different brand or type of Motor Control Center could void the U.L. Label of the MCC</i>						
<i>Note: Reversing Motors are Assumed To Be Factory Wired</i>						
						
<b>Field Mounted in MCC's - Variable Speed Reversing 4-Pole</b>						
NEMA 00		6.80	8.50	10.20		E
NEMA 0		7.20	9.00	10.80		E
NEMA 1		8.00	10.00	12.00		E
NEMA 2		10.00	12.50	15.00		E
NEMA 3		12.00	15.00	18.00		E
<i>Note: Installing a brand or type of starting equipment in a different brand or type of Motor Control Center could void the U.L. Label of the MCC</i>						
<i>Note: Reversing Motors are Assumed To Be Factory Wired</i>						
						
<b>Drive Units - 200 - 550 Volt DC (Unload, Inspect, Handle, Install - Labor Only)</b>						
Up to 20 H.P.		7.00	9.00	11.00		E
25 to 50 H.P.		10.00	12.00	14.00		E
60 to 100 H.P.		13.00	16.00	19.00		E
125 to 150 H.P.		17.00	21.00	26.00		E
200 to 400 H.P.		25.00	31.00	38.00		E
500 to 600 H.P.		30.00	37.00	43.00		E

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

4

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
	<b>Drive Units - Variable Frequency A.C.</b>					
<b>(Unload, Inspect, Handle, Install - Labor Only)</b>						
Up to 20 H.P.		6.50	8.00	10.00		E
25 to 50 H.P.		9.50	12.00	14.00		E
60 to 100 H.P.		12.50	15.00	17.50		E
125 to 150 H.P.		16.50	20.50	24.50		E
200 to 400 H.P.		24.50	31.00	36.00		E
500 to 600 H.P.		30.00	36.00	42.50		E
2300 - 5000 Volt Up to 20 H.P.		16.00	18.00	20.00		E
2300 - 5000 Volt 25 to 50 H.P.		18.00	20.00	22.00		E
2300 - 5000 Volt 60 to 100 H.P.		20.00	22.00	24.00		E
2300 - 5000 Volt 125 to 150 H.P.		24.00	28.00	32.00		E
2300 - 5000 Volt 200 to 400 H.P.		27.00	33.00	39.00		E
2300 - 5000 Volt 500 to 600 H.P.		31.00	37.00	44.00		E
2300 - 5000 Volt 750 to 1000 H.P.		37.00	44.00	51.00		E
2300 - 5000 Volt 1100 to 1200 H.P.		41.00	49.00	56.00		E
	<b>Field Mounted Disconnect/Circuit Breaker</b>					
<b>Includes Termination Labor</b>						
30A		3.50	4.38	5.25		E
60A		3.75	4.69	5.63		E
100A		4.50	5.63	6.75		E
200A		5.50	6.88	8.25		E
400A		7.00	8.75	10.50		E
600A		8.00	10.00	12.00		E
800A		10.00	12.50	15.00		E
	<b>Field Mounted Variable Frequency Drive -</b>					
<b>Includes Termination labor</b>						
5 HP		2.00	2.50	3.00		E
7.5 HP		2.50	3.13	3.75		E
10 HP		3.00	3.75	4.50		E
15 HP		4.00	5.00	6.00		E
20 HP		5.00	6.25	7.50		E
25 HP		6.00	7.50	9.00		E
	<b>Field Mounted in MCC's - Auxiliary Contacts NO/NC</b>					
Auxiliary Contacts NO/NC		1.00	1.25	1.50		E
	<b>Field Mounted Control Switch</b>					
Control Switch - 2 Position		1.00	1.25	1.50		E
Control Switch - 3 Position		1.20	1.50	1.80		E
Control Switch - 4 Position		1.40	1.75	2.10		E
	<b>Field Mounted in MCC's MCC Control Transformers</b>					
NEMA Size 1		1.60	2.00	2.40		E
NEMA Size 2		1.80	2.25	2.70		E
NEMA Size 3		2.00	2.50	3.00		E
NEMA Size 4		2.30	2.88	3.45		E
NEMA Size 5		2.60	3.25	3.90		E
<i>Note: Installing a brand or type of starting equipment in a different brand or type of Motor Control Center could void the U.L. Label of the MCC</i>						
	<b>Field Mounted in MCC's MCC Control Relays</b>					
MCC 4-Pole Control Relay		3.20	4.00	4.80		E
MCC 8-Pole Control Relay		4.00	5.00	6.00		E
<i>Note: Installing a brand or type of starting equipment in a different brand or type of Motor Control Center could void the U.L. Label of the MCC</i>						
	<b>Field Mounted Push Button Switches</b>					
1 Button		0.80	1.00	1.20		E
2 Button		1.00	1.25	1.50		E
3 Button		1.20	1.50	1.80		E
4 Button		1.40	1.75	2.10		E

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment





Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit	
 <p><b>Integrated Power Centers</b> Integrated Power Centers (IPC) bundles distribution equipment into a single factory assembled and wired integrated system, eliminating the traditional method of independently mounting each component separately. The IPC allows for the integration of a variety of components including panelboards, transformers, surge suppression, lighting controls, metering, etc., pending on the project requirements. The IPC concept also save space, which is always a premium on most projects. The following are basic units consisting of 277/480V panelboards, transformers, and 120/208V panelboards. Labor includes receiving, moving to the installation location, securing in place, and termination of the line side of the IPC. Labor does not include KO's, conduit connectors or terminations, trans. grounding or wire terminations, of the load side of the panelboards.</p>							
	<b>Integrated Power Center</b> Input = 125A / 3 Ph 277/480V Transformer = 30 KVA Output = 100A / 3 Ph 120/208V Weight = 800 lbs Dimensions = 42" Wide X 91 1/2" High X 24" Deep						
	Labor		15.50	18.50	21.50		E
	<b>Integrated Power Center</b> Input = 125A / 3Ph 277/480V Transformer = 45 KVA Output = 125A / 3Ph 120/208V Weight = 900 lbs Dimensions = 42" Wide X 91 1/2" High X 24" Deep						
	Labor		16.50	19.50	22.50		E
	<b>Integrated Power Center</b> Input = 225A / 3Ph 277/480V Transformer = 75 KVA Output = 255A / 3Ph 120/208V Weight = 1,150 lbs Dimensions = 42" Wide X 91 1/2" High X 24" Deep						
	Labor		20.00	24.00	28.00		E
	<b>Integrated Power Center</b> Input = 400A / 3Ph 277/480V Transformer = 75 KVA Output =255A / 3Ph 120/208V Weight = 1,150 lbs Dimensions = 42" Wide X 91 1/2" High X 24" Deep						
	Labor		21.50	25.50	29.50		E
	<b>Integrated Power Center</b> Input = 400A / 3Ph 277/480V Transformer = 112.5 KVA Output = 400A / 3Ph 120/208V Weight = 1,385 lbs Dimensions = 42" Wide X 91 1/2" High X 24" Deep						
Labor		23.50	27.50	31.50		E	
 <p><b>Fuse Installation in Fused Switch in Safety Switches and MCC's - Cartridge Fuse (250 V or 600V)</b> 1 Amp to 100 Amp 110 Amp to 200 Amp 210 Amp to 400 Amp 410 Amp to 600 Amp</p> <p><b>Bolt-On Fuse 600V</b> 600 Amp - 1800 Amp 2000 Amp - 6000 Amp Fuse Reducers Fuse Cabinet</p>							
	1 Amp to 100 Amp		0.04	0.05	0.06		E
	110 Amp to 200 Amp		0.10	0.13	0.15		E
	210 Amp to 400 Amp		0.17	0.21	0.26		E
	410 Amp to 600 Amp		0.20	0.25	0.30		E
 <p><b>Free Standing Bolted Press. Switches - Installation &amp; 2P3W Conductor Term. (Includes labor for terminating neutrals)</b> 800 Amp 1200 Amp 1600 Amp 2000 Amp 2500 Amp 3000 Amp 4000 Amp</p>							
	800 Amp		20.00	25.00	30.00		E
	1200 Amp		24.00	30.00	36.00		E
	1600 Amp		28.00	35.00	42.00		E
	2000 Amp		32.00	40.00	48.00		E
	2500 Amp		36.00	45.00	54.00		E
	3000 Amp		40.00	50.00	60.00		E
4000 Amp		48.00	60.00	72.00		E	
 <p><b>Free Standing Bolted Press. Switches - Installation &amp; 3P4W Conductor Term. (Includes labor for terminating neutrals)</b> 800 Amp 1200 Amp 1600 Amp 2000 Amp 2500 Amp 3000 Amp 4000 Amp</p>							
	800 Amp		24.00	30.00	36.00		E
	1200 Amp		28.00	35.00	42.00		E
	1600 Amp		33.00	41.25	49.50		E
	2000 Amp		38.00	47.50	57.00		E
	2500 Amp		43.00	53.75	64.50		E
	3000 Amp		48.00	60.00	72.00		E
4000 Amp		56.00	70.00	84.00		E	

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

4

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
	<b>Disconnect Safety Switches - Nonfused 2-Pole</b>					
30 Amp		1.70	2.13	2.55		E
60 Amp		2.50	3.13	3.75		E
100 Amp		3.50	4.38	5.25		E
200 Amp		5.50	6.88	8.25		E
400 Amp		8.00	10.00	12.00		E
600 Amp		12.00	15.00	18.00		E
800 Amp		16.00	20.00	24.00		E
1200 Amp		20.00	25.00	30.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%. For Stainless Steel Enclosures add 20%</i>						
	<b>Disconnect Safety Switches - Nonfused 3-Pole</b>					
30 Amp		2.00	2.50	3.00		E
60 Amp		3.00	3.75	4.50		E
100 Amp		4.00	5.00	6.00		E
200 Amp		7.00	8.75	10.50		E
400 Amp		10.00	12.50	15.00		E
600 Amp		14.00	17.50	21.00		E
800 Amp		18.00	22.50	27.00		E
1200 Amp		22.00	27.50	33.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%. For Stainless Steel Enclosures add 20%</i>						
	<b>Disconnect Safety Switches - Nonfused 4-Pole</b>					
30 Amp		2.50	3.13	3.75		E
60 Amp		3.50	4.38	5.25		E
100 Amp		5.00	6.25	7.50		E
200 Amp		8.00	10.00	12.00		E
400 Amp		12.00	15.00	18.00		E
600 Amp		16.00	20.00	24.00		E
800 Amp		20.00	25.00	30.00		E
1200 Amp		24.00	30.00	36.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%. For Stainless Steel Enclosures add 20%</i>						
	<b>Disconnect Safety Switches - Fused 2-Pole</b>					
30 Amp		2.00	2.50	3.00		E
60 Amp		2.70	3.38	4.05		E
100 Amp		3.80	4.75	5.70		E
200 Amp		6.00	7.50	9.00		E
400 Amp		8.80	11.00	13.20		E
600 Amp		13.00	16.25	19.50		E
800 Amp		17.00	21.25	25.50		E
1200 Amp		22.00	27.50	33.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%. For Stainless Steel Enclosures add 20%</i>						
	<b>Disconnect Safety Switches - Fused 3-Pole</b>					
30 Amp		2.20	2.75	3.30		E
60 Amp		3.30	4.13	4.95		E
100 Amp		4.40	5.50	6.60		E
200 Amp		7.70	9.63	11.55		E
400 Amp		11.00	13.75	16.50		E
600 Amp		15.00	18.75	22.50		E
800 Amp		20.00	25.00	30.00		E
1200 Amp		24.00	30.00	36.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%. For Stainless Steel Enclosures add 20%</i>						
	<b>Disconnect Safety Switches - Fused 4-Pole</b>					
30 Amp		2.70	3.38	4.05		E
60 Amp		3.80	4.75	5.70		E
100 Amp		5.50	6.88	8.25		E
200 Amp		9.00	11.25	13.50		E
400 Amp		13.00	16.25	19.50		E
600 Amp		17.00	21.25	25.50		E
800 Amp		22.00	27.50	33.00		E
1200 Amp		26.00	32.50	39.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%. For Stainless Steel Enclosures add 20%</i>						








Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Enclosed Circuit Breakers, Wall Mounted</b>						
<b>2-Pole (or 1-Pole and Neutral)</b>						
 20 Amp		1.60	2.00	2.40		E
30 Amp		1.80	2.25	2.70		E
50 Amp		2.00	2.50	3.00		E
60 Amp		2.30	2.88	3.45		E
80 Amp		2.70	3.38	4.05		E
100 Amp		3.10	3.88	4.65		E
125 Amp		3.60	4.50	5.40		E
150 Amp		4.00	5.00	6.00		E
175 Amp		4.50	5.63	6.75		E
200 Amp		5.00	6.25	7.50		E
225 Amp		5.50	6.88	8.25		E
250 Amp		6.00	7.50	9.00		E
300 Amp		7.00	8.75	10.50		E
400 Amp		8.00	10.00	12.00		E
500 Amp		9.00	11.25	13.50		E
600 Amp		11.00	13.75	16.50		E
800 Amp		14.00	17.50	21.00		E
1000 Amp		18.00	22.50	27.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%. For Stainless Steel Enclosures add 20%</i>						
<b>Enclosed Circuit Breakers, Wall Mounted</b>						
<b>3-Pole (or 2-Pole and Neutral)</b>						
 20 Amp		1.80	2.25	2.70		E
30 Amp		2.00	2.50	3.00		E
50 Amp		2.30	2.88	3.45		E
60 Amp		2.70	3.38	4.05		E
80 Amp		3.10	3.88	4.65		E
100 Amp		3.60	4.50	5.40		E
125 Amp		4.00	5.00	6.00		E
150 Amp		4.50	5.63	6.75		E
175 Amp		5.00	6.25	7.50		E
200 Amp		5.50	6.88	8.25		E
225 Amp		6.00	7.50	9.00		E
250 Amp		7.00	8.75	10.50		E
300 Amp		8.00	10.00	12.00		E
400 Amp		9.00	11.25	13.50		E
500 Amp		10.00	12.50	15.00		E
600 Amp		12.00	15.00	18.00		E
800 Amp		16.00	20.00	24.00		E
1000 Amp		20.00	25.00	30.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%. For Stainless Steel Enclosures add 20%</i>						
<b>Enclosed Circuit Breakers, Wall Mounted</b>						
<b>4-Pole (or 3-Pole and Neutral)</b>						
 20 Amp		2.00	2.50	3.00		E
30 Amp		2.20	2.75	3.30		E
50 Amp		2.50	3.13	3.75		E
60 Amp		3.00	3.75	4.50		E
80 Amp		3.50	4.38	5.25		E
100 Amp		4.00	5.00	6.00		E
125 Amp		4.50	5.63	6.75		E
150 Amp		5.00	6.25	7.50		E
175 Amp		5.50	6.88	8.25		E
200 Amp		6.00	7.50	9.00		E
225 Amp		7.00	8.75	10.50		E
250 Amp		8.00	10.00	12.00		E
300 Amp		9.00	11.25	13.50		E
400 Amp		10.00	12.50	15.00		E
500 Amp		11.00	13.75	16.50		E
600 Amp		13.00	16.25	19.50		E
800 Amp		17.00	21.25	25.50		E
1000 Amp		22.00	27.50	33.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%. For Stainless Steel Enclosures add 20%</i>						
<b>Enclosed Magnetic Motor Starter,</b>						
<b>Wall Mounted, Non-Reversing 2-Pole</b>						
 NEMA 00		2.00	2.50	3.00		E
NEMA 0		2.20	2.75	3.30		E
NEMA 1		2.40	3.00	3.60		E
NEMA 2		2.70	3.38	4.05		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 4 Add 15%</i>						
<i>For NEMA 12 Add 20%</i>						

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
	<b>Enclosed Magnetic Motor Starter, Wall Mounted, Non-Reversing 3-Pole</b>					
NEMA 00		2.20	2.75	3.30		E
NEMA 0		2.40	3.00	3.60		E
NEMA 1		2.60	3.25	3.90		E
NEMA 2		3.00	3.75	4.50		E
NEMA 3		4.00	5.00	6.00		E
NEMA 4		6.00	7.50	9.00		E
NEMA 5		8.00	10.00	12.00		E
NEMA 6		12.00	15.00	18.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 4 Add 15%</i>						
<i>For NEMA 12 Add 20%</i>						
	<b>Enclosed Magnetic Motor Starter, Wall Mounted, Non-Reversing 4-Pole</b>					
NEMA 00		2.50	3.13	3.75		E
NEMA 0		3.00	3.75	4.50		E
NEMA 1		3.50	4.38	5.25		E
NEMA 2		4.00	5.00	6.00		E
NEMA 3		5.00	6.25	7.50		E
NEMA 4		7.00	8.75	10.50		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 4 Add 15%</i>						
<i>For NEMA 12 Add 20%</i>						
	<b>Enclosed Magnetic Motor Starter, Wall Mounted, Reversing 2-Pole</b>					
NEMA 00		2.40	3.00	3.60		E
NEMA 0		2.80	3.50	4.20		E
NEMA 1		3.20	4.00	4.80		E
NEMA 2		3.60	4.50	5.40		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 4 Add 15%</i>						
<i>For NEMA 12 Add 20%</i>						
	<b>Enclosed Magnetic Motor Starter, Wall Mounted, Reversing 3-Pole</b>					
NEMA 00		2.60	3.25	3.90		E
NEMA 0		3.00	3.75	4.50		E
NEMA 1		3.50	4.38	5.25		E
NEMA 2		4.00	5.00	6.00		E
NEMA 3		6.00	7.50	9.00		E
NEMA 4		9.00	11.25	13.50		E
NEMA 5		12.00	15.00	18.00		E
NEMA 6		16.00	20.00	24.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 4 Add 15%</i>						
<i>For NEMA 12 Add 20%</i>						
	<b>Enclosed Magnetic Motor Starter, Wall Mounted, Reversing 4-Pole</b>					
NEMA 00		3.00	3.75	4.50		E
NEMA 0		3.50	4.38	5.25		E
NEMA 1		4.00	5.00	6.00		E
NEMA 2		5.00	6.25	7.50		E
NEMA 3		7.00	8.75	10.50		E
NEMA 4		10.00	12.50	15.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 4 Add 15%</i>						
<i>For NEMA 12 Add 20%</i>						
	<b>Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Non-Reversing 2-Pole</b>					
NEMA 00		3.60	4.50	5.40		E
NEMA 0		4.00	5.00	6.00		E
NEMA 1		4.50	5.63	6.75		E
NEMA 1		4.50	5.63	6.75		E
NEMA 2		5.00	6.25	7.50		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 4 Add 15%</i>						
<i>For NEMA 12 Add 20%</i>						

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
						
<b>Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Non-Reversing 3-Pole</b>						
NEMA 00		4.00	5.00	6.00		E
NEMA 0		4.50	5.63	6.75		E
NEMA 1		5.00	6.25	7.50		E
NEMA 2		6.00	7.50	9.00		E
NEMA 3		8.00	10.00	12.00		E
NEMA 4		10.00	12.50	15.00		E
NEMA 5		12.00	15.00	18.00		E
NEMA 6		16.00	20.00	24.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 4 Add 15%</i>						
<i>For NEMA 12 Add 20%</i>						
						
<b>Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Non-Reversing 4-Pole</b>						
NEMA 00		5.00	6.25	7.50		E
NEMA 0		5.50	6.88	8.25		E
NEMA 1		6.00	7.50	9.00		E
NEMA 2		7.00	8.75	10.50		E
NEMA 3		9.00	11.25	13.50		E
NEMA 4		11.00	13.75	16.50		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 4 Add 15%</i>						
<i>For NEMA 12 Add 20%</i>						
						
<b>Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Reversing 2-Pole</b>						
NEMA 00		5.50	6.88	8.25		E
NEMA 0		6.00	7.50	9.00		E
NEMA 1		7.00	8.75	10.50		E
NEMA 2		8.00	10.00	12.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 4 Add 15%</i>						
<i>For NEMA 12 Add 20%</i>						
						
<b>Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Reversing 3-Pole</b>						
NEMA 00		6.00	7.50	9.00		E
NEMA 0		7.00	8.75	10.50		E
NEMA 2		9.00	11.25	13.50		E
NEMA 3		10.00	12.50	15.00		E
NEMA 4		12.00	15.00	18.00		E
NEMA 5		16.00	20.00	24.00		E
NEMA 6		20.00	25.00	30.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 4 Add 15%</i>						
<i>For NEMA 12 Add 20%</i>						
						
<b>Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Reversing 4-Pole</b>						
NEMA 00		7.00	8.75	10.50		E
NEMA 0		8.00	10.00	12.00		E
NEMA 1		9.00	11.25	13.50		E
NEMA 2		10.00	12.50	15.00		E
NEMA 3		12.00	15.00	18.00		E
NEMA 4		14.00	17.50	21.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 4 Add 15%</i>						
<i>For NEMA 12 Add 20%</i>						
						
<b>Push Button Station NEMA-1 Enclosure, Factory Assembled</b>						
1 Button		1.00	1.25	1.50		E
2 Button		1.20	1.50	1.80		E
3 Button		1.40	1.75	2.10		E
4 Button		1.60	2.00	2.40		E
						
<b>Push Button Station NEMA-3 Enclosure, Factory Assembled</b>						
1 Button		1.20	1.50	1.80		E
2 Button		1.40	1.75	2.10		E
3 Button		1.60	2.00	2.40		E
4 Button		1.80	2.25	2.70		E

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

4

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Limit Switch</b>						
 NEMA-1 Plunger Limit Switch 2 Circuit		1.00	1.25	1.50		E
NEMA-1 Plunger Limit Switch 4 Circuit		1.50	1.88	2.25		E
NEMA-3 Plunger Limit Switch 2 Circuit		1.25	1.56	1.88		E
NEMA-3 Plunger Limit Switch 4 Circuit		1.75	2.19	2.63		E
NEMA-1 Rotary Limit Switch 2 Blocks		1.50	1.88	2.25		E
NEMA-1 Rotary Limit Switch 3 Blocks		1.75	2.19	2.63		E
NEMA-1 Rotary Limit Switch 4 Blocks		2.00	2.50	3.00		E
<b>Manual Motor Starter 115/230 Volt AC</b>						
<b>NEMA-1 Enclosure Toggle Switch</b>						
1P NEMA 00		0.80	1.00	1.20		E
1P NEMA 0		0.90	1.13	1.35		E
1P NEMA 1		1.00	1.25	1.50		E
2P NEMA 00		1.10	1.38	1.65		E
2P NEMA 0		1.20	1.50	1.80		E
2P NEMA 1		1.30	1.63	1.95		E
3P NEMA 00		1.40	1.75	2.10		E
3P NEMA 0		1.50	1.88	2.25		E
3P NEMA 1		1.60	2.00	2.40		E
<b>Enclosed Lighting &amp; Heating Contactors</b>						
<b>NEMA 1 Enclosure up to 600 Volt AC</b>						
20 Amp 2 Pole		1.60	2.00	2.40		E
20 Amp 3 Pole		1.80	2.25	2.70		E
20 Amp 4 Pole		2.00	2.50	3.00		E
20 Amp 6 pole		2.40	3.00	3.60		E
20 Amp 8 Pole		2.80	3.50	4.20		E
30 Amp 2 Pole		1.80	2.25	2.70		E
30 Amp 3 Pole		2.00	2.50	3.00		E
30 Amp 4 Pole		2.20	2.75	3.30		E
30 Amp 6 Pole		2.60	3.25	3.90		E
30 Amp 8 Pole		3.00	3.75	4.50		E
60 Amp 2 Pole		2.80	3.50	4.20		E
60 Amp 3 Pole		3.20	4.00	4.80		E
60 Amp 4 Pole		3.60	4.50	5.40		E
60 Amp 8 Pole		4.00	5.00	6.00		E
100 Amp 2 Pole		3.80	4.75	5.70		E
100 Amp 3 Pole		4.20	5.25	6.30		E
100 Amp 4 Pole		4.60	5.75	6.90		E
200 Amp 2 Pole		5.00	6.25	7.50		E
200 Amp 3 Pole		5.50	6.88	8.25		E
200 Amp 4 Pole		6.00	7.50	9.00		E
300 Amp 2 Pole		7.00	8.75	10.50		E
300 Amp 3 Pole		8.00	10.00	12.00		E
400 Amp 2 Pole		9.00	11.25	13.50		E
400 Amp 3 Pole		10.00	12.50	15.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%. For Stainless Steel Enclosures add 20%</i>						
<b>Enclosed 600 Volt Overload Relays</b>						
<b>NEMA 1 Enclosure 600 Volt</b>						
15 Amp NEMA 00		2.00	2.50	3.00		E
20 Amp NEMA 00		2.25	2.81	3.38		E
25 Amp NEMA 00		2.50	3.13	3.75		E
30 Amp NEMA 00		3.00	3.75	4.50		E
40 Amp NEMA 0		3.50	4.38	5.25		E
50 Amp NEMA 1		4.00	5.00	6.00		E
60 Amp NEMA 2		5.00	6.25	7.50		E
80 Amp NEMA 3		6.00	7.50	9.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%. For Stainless Steel Enclosures add 20%</i>						
<b>Fuse Installation in Fused Switch in Safety Switches and MCC's - Cartridge Fuse (250 V or 600V)</b>						
1 Amp to 100 Amp		0.04	0.05	0.06		E
110 Amp to 200 Amp		0.10	0.13	0.15		E
210 Amp to 400 Amp		0.17	0.21	0.26		E
410 Amp to 600 Amp		0.20	0.25	0.30		E
<b>Bolt-On Fuse 600V</b>						
600 Amp - 1800 Amp		0.30	0.38	0.45		E
2000 Amp - 6000 Amp		0.50	0.63	0.75		E
Fuse Reducers		0.15	0.19	0.23		E
Fuse Cabinet		1.00	1.25	1.50		E



Section 4 - Switchboards, MCC's, Panelboards & Power Equipment





Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
						
<b>Meter Center NEMA 1 &amp; 3R (Typ) Enclosure</b>						
<b>3 Wire Solid Neutral MLO or Tap Box Module</b>						
400 Amp		16.00	20.00	24.00		E
600 Amp		18.00	22.50	27.00		E
800 Amp		21.00	26.25	31.50		E
1000 Amp		24.00	30.00	36.00		E
1200 Amp		28.00	35.00	42.00		E
1600 Amp		32.00	40.00	48.00		E
2000 Amp		36.00	45.00	54.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
						
<b>Meter Center NEMA 1 &amp; 3R (Typ) Enclosure</b>						
<b>3 Wire Solid Neutral Main Circuit Breaker or Fused Switch</b>						
400 Amp		20.00	25.00	30.00		E
600 Amp		22.00	27.50	33.00		E
800 Amp		25.00	31.25	37.50		E
1000 Amp		28.00	35.00	42.00		E
1200 Amp		32.00	40.00	48.00		E
1600 Amp		36.00	45.00	54.00		E
2000 Amp		40.00	50.00	60.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
						
<b>Meter Center NEMA 1 &amp; 3R (Typ) Enclosure</b>						
<b>4 Wire Solid Neutral MLO or Tap Box Module</b>						
400 Amp		18.00	22.50	27.00		E
600 Amp		20.00	25.00	30.00		E
800 Amp		23.00	28.75	34.50		E
1000 Amp		26.00	32.50	39.00		E
1200 Amp		30.00	37.50	45.00		E
1600 Amp		34.00	42.50	51.00		E
2000 Amp		38.00	47.50	57.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
						
<b>Meter Center NEMA 1 &amp; 3R (Typ) Enclosure</b>						
<b>4 Wire Solid Neutral Main Circuit Breaker or Fused Switch</b>						
400 Amp		22.00	27.50	33.00		E
600 Amp		24.00	30.00	36.00		E
800 Amp		28.00	35.00	42.00		E
1000 Amp		32.00	40.00	48.00		E
1200 Amp		36.00	45.00	54.00		E
1600 Amp		40.00	50.00	60.00		E
2000 Amp		44.00	55.00	66.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
						
<b>Meter Center NEMA 1 &amp; 3R Single Phase</b>						
<b>125 Amp Meter Socket Modules</b>						
2 Meters		4.00	5.00	6.00		E
3 Meters		4.60	5.75	6.90		E
4 Meters		5.20	6.50	7.80		E
5 Meters		6.00	7.50	9.00		E
6 Meters		6.80	8.50	10.20		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
						
<b>Meter Center NEMA 1 &amp; 3R Single Phase</b>						
<b>200 Amp Meter Socket Modules</b>						
2 Meters		4.40	5.50	6.60		E
3 Meters		5.00	6.25	7.50		E
4 Meters		5.60	7.00	8.40		E
5 Meters		6.40	8.00	9.60		E
6 Meters		7.25	9.06	10.88		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
						
<b>Meter Center NEMA 1 &amp; 3R Three Phase</b>						
<b>125 Amp Meter Socket Modules</b>						
2 Meters		4.80	6.00	7.20		E
3 Meters		5.20	6.50	7.80		E
4 Meters		5.80	7.25	8.70		E
5 Meters		6.60	8.25	9.90		E
6 Meters		7.75	9.69	11.63		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment


4

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
						
<b>Meter Center NEMA 1 &amp; 3R Three Phase</b>						
<b>200 Amp Meter Socket Modules</b>						
2 Meters		5.20	6.50	7.80		E
3 Meters		5.60	7.00	8.40		E
4 Meters		6.20	7.75	9.30		E
5 meters		7.00	8.75	10.50		E
6 Meters		7.95	9.94	11.93		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
						
<b>240/120 Volt Meter Socket</b>						
100 Amp 240/120 Volt Meter Socket		2.25	2.81	3.38		E
200 Amp 240/120 Volt Meter Socket		3.25	4.06	4.88		E
400 Amp 240/120 Volt Meter Socket		8.50	10.63	12.75		E
						
<b>PT/CT Components</b>						
36 x 36 PT/CT Cabinet		3.50	4.38	5.25		E
40 x 48 PT/CT Cabinet		4.00	5.00	6.00		E
Meter Socket PT/CT Rated		3.50	4.38	5.25		E
						
<b>Fire Pump Controller, Free Standing NEMA 1 Enclosure</b>						
<b>208 to 240 Volt Full Voltage Starting</b>						
25 HP - Full Voltage Starting		10.00	12.50	15.00		E
50 HP - Full Voltage Starting		12.00	15.00	18.00		E
75 HP - Full Voltage Starting		15.00	18.75	22.50		E
100 HP - Full Voltage Starting		19.00	23.75	28.50		E
150 HP - Full Voltage Starting		24.00	30.00	36.00		E
200 HP - Full Voltage Starting		30.00	37.50	45.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
						
<b>Fire Pump Controller, Free Standing NEMA 1 Enclosure</b>						
<b>208 to 240 Volt Part Winding Starting</b>						
25 HP - Part Winding Starting		12.00	15.00	18.00		E
50 HP - Part Winding Starting		15.00	18.75	22.50		E
75 HP - Part Winding Starting		18.00	22.50	27.00		E
100 HP - Part Winding Starting		23.00	28.75	34.50		E
150 HP - Part Winding Starting		29.00	36.25	43.50		E
200 HP - Part Winding Starting		36.00	45.00	54.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
						
<b>Fire Pump Controller, Free Standing NEMA 1 Enclosure</b>						
<b>208 to 240 Wye Delta Starting</b>						
25 HP - Wye Delta Starting		13.00	16.25	19.50		E
50 HP - Wye Delta Starting		16.00	20.00	24.00		E
75 HP - Wye Delta Starting		20.00	25.00	30.00		E
100 HP - Wye Delta Starting		26.00	32.50	39.00		E
150 HP - Wye Delta Starting		33.00	41.25	49.50		E
200 HP - Wye Delta Starting		40.00	50.00	60.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
						
<b>Fire Pump Controller, Free Standing NEMA 1 Enclosure</b>						
<b>208 to 240 Volt Reduced Voltage Starting</b>						
25 HP - Reduced Voltage Starting		16.00	20.00	24.00		E
50 HP - Reduced Voltage Starting		21.00	26.25	31.50		E
75 HP - Reduced Voltage Starting		26.00	32.50	39.00		E
100 HP - Reduced Voltage Starting		33.00	41.25	49.50		E
150 HP - Reduced Voltage Starting		40.00	50.00	60.00		E
200 HP - Reduced Voltage Starting		48.00	60.00	72.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
						
<b>Fire Pump Controller, Free Standing NEMA 1 Enclosure</b>						
<b>380 to 600 Volt Full Voltage Starting</b>						
25 HP - Full Voltage Starting		7.00	8.75	10.50		E
50 HP - Full Voltage Starting		9.00	11.25	13.50		E
75 HP - Full Voltage Starting		11.00	13.75	16.50		E
100 HP - Full Voltage Starting		14.00	17.50	21.00		E
150 HP - Full Voltage Starting		18.00	22.50	27.00		E
200 HP - Full Voltage Starting		22.00	27.50	33.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
						
<b>Fire Pump Controller, Free Standing NEMA 1 Enclosure</b>						
<b>380 to 600 Volt Part Winding Starting</b>						
25 HP - Part Winding Starting		9.00	11.25	13.50		E
50 HP - Part Winding Starting		11.00	13.75	16.50		E
75 HP - Part Winding Starting		14.00	17.50	21.00		E
100 HP - Part Winding Starting		18.00	22.50	27.00		E
150 HP - Part Winding Starting		22.00	27.50	33.00		E
200 HP - Part Winding Starting		27.00	33.75	40.50		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
						
<b>Fire Pump Controller, Free Standing NEMA 1 Enclosure</b>						
<b>380 to 600 Volt Wye Delta Starting</b>						
25 HP - Wye Delta Starting		10.00	12.50	15.00		E
50 HP - Wye Delta Starting		13.00	16.25	19.50		E
75 HP - Wye Delta Starting		16.00	20.00	24.00		E
100 HP - Wye Delta Starting		20.00	25.00	30.00		E
150 HP - Wye Delta Starting		25.00	31.25	37.50		E
200 HP - Wye Delta Starting		30.00	37.50	45.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
						
<b>Fire Pump Controller, Free Standing NEMA 1 Enclosure</b>						
<b>380 to 600 Volt Reduced Voltage Starting</b>						
25 HP - Reduced Voltage Starting		13.00	16.25	19.50		E
50 HP - Reduced Voltage Starting		16.00	20.00	24.00		E
75 HP - Reduced Voltage Starting		20.00	25.00	30.00		E
100 HP - Reduced Voltage Starting		26.00	32.50	39.00		E
150 HP - Reduced Voltage Starting		33.00	41.25	49.50		E
200 HP - Reduced Voltage Starting		40.00	50.00	60.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment




Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Transformers Outdoor Type Up to 15 KV Primary, Unload, Inspect and Handling Labor Only</b>						
25 KVA		6.00	7.50	9.00		E
50 KVA		7.00	8.75	10.50		E
75 KVA		8.00	10.00	12.00		E
100 KVA		9.00	11.25	13.50		E
150 KVA		10.00	12.50	15.00		E
200 KVA		11.00	13.75	16.50		E
225 KVA		12.00	15.00	18.00		E
250 KVA		13.00	16.25	19.50		E
300 KVA		14.00	17.50	21.00		E
400 KVA		15.00	18.75	22.50		E
500 KVA		16.00	20.00	24.00		E
600 KVA		18.00	22.50	27.00		E
750 KVA		20.00	25.00	30.00		E
1000 KVA		22.00	27.50	33.00		E
1500 KVA		24.00	30.00	36.00		E
2000 KVA		26.00	32.50	39.00		E
2500 KVA		29.00	36.25	43.50		E
3000 KVA		32.00	40.00	48.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>Transformers Indoor Type Up to 15 KV Primary, Unload, Inspect and Handling Labor Only</b>						
25 KVA		14.00	17.50	21.00		E
50 KVA		16.00	20.00	24.00		E
75 KVA		18.00	22.50	27.00		E
100 KVA		20.00	25.00	30.00		E
150 KVA		24.00	30.00	36.00		E
200 KVA		28.00	35.00	42.00		E
225 KVA		32.00	40.00	48.00		E
250 KVA		36.00	45.00	54.00		E
300 KVA		40.00	50.00	60.00		E
400 KVA		44.00	55.00	66.00		E
500 KVA		48.00	60.00	72.00		E
600 KVA		52.00	65.00	78.00		E
750 KVA		56.00	70.00	84.00		E
1000 KVA		60.00	75.00	90.00		E
1500 KVA		65.00	81.25	97.50		E
2000 KVA		70.00	87.50	105.00		E
2500 KVA		75.00	93.75	112.50		E
3000 KVA		80.00	100.00	120.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>Transformers Indoor Type Up to 600 V Primary, Unload, Inspect and Handling Labor Only</b>						
10 KVA		4.00	6.00	8.00		E
15 KVA		6.00	8.00	10.00		E
25 KVA		8.00	10.00	12.00		E
37.5 KVA		9.00	11.00	13.00		E
45 KVA		10.00	12.00	15.00		E
50 KVA		10.00	12.50	15.00		E
75 KVA		12.00	15.00	18.00		E
100 KVA		14.00	17.50	21.00		E
150 KVA		16.00	20.00	24.00		E
167.5 KVA		17.00	21.00	25.00		E
200 KVA		18.00	22.50	27.00		E
225 KVA		20.00	25.00	30.00		E
250 KVA		22.00	27.50	33.00		E
300 KVA		24.00	30.00	36.00		E
400 KVA		28.00	35.00	42.00		E
500 KVA		32.00	40.00	48.00		E
600 KVA		36.00	45.00	54.00		E
750 KVA		40.00	50.00	60.00		E
1000 KVA		45.00	56.25	67.50		E
1500 KVA		50.00	62.50	75.00		E
2000 KVA		55.00	68.75	82.50		E
2500 KVA		60.00	75.00	90.00		E
3000 KVA		66.00	82.50	99.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Transformers Single Phase Floor Mounted</b>						
<b>Up to 600 V Primary - Install &amp; Connect</b>						
15 KVA		8.00	10.00	12.00		E
25 KVA		9.00	11.25	13.50		E
37 1/2 KVA		10.00	12.50	15.00		E
50 KVA		11.00	13.75	16.50		E
75 KVA		12.00	15.00	18.00		E
100 KVA		14.00	17.50	21.00		E
150 KVA		16.00	20.00	24.00		E
167 KVA		18.00	22.50	27.00		E
200 KVA		20.00	25.00	30.00		E
225 KVA		22.00	27.50	33.00		E
250 KVA		24.00	30.00	36.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>Transformers Three Phase Floor Mounted</b>						
<b>Up to 600 V Primary - Install &amp; Connect</b>						
15 KVA		9.00	11.25	13.50		E
25 KVA		10.00	12.50	15.00		E
30 KVA		11.00	13.75	16.50		E
37 1/2 KVA		12.00	15.00	18.00		E
45 KVA		13.00	16.25	19.50		E
50 KVA		14.00	17.50	21.00		E
75 KVA		15.00	18.75	22.50		E
100 KVA		16.00	20.00	24.00		E
112 1/2 KVA		18.00	22.50	27.00		E
150 KVA		20.00	25.00	30.00		E
200 KVA		22.00	27.50	33.00		E
225 KVA		25.00	31.25	37.50		E
250 KVA		28.00	35.00	42.00		E
300 KVA		31.00	38.75	46.50		E
400 KVA		34.00	42.50	51.00		E
500 KVA		38.00	47.50	57.00		E
600 KVA		42.00	52.50	63.00		E
750 KVA		46.00	57.50	69.00		E
1000 KVA		50.00	62.50	75.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>Transformers Single Phase Wall Mounted</b>						
<b>Up to 600 V Primary - Install &amp; Connect</b>						
1/2 KVA		4.00	5.00	6.00		E
3/4 KVA		4.20	5.25	6.30		E
1 KVA		4.40	5.50	6.60		E
1 1/2 KVA		4.60	5.75	6.90		E
2 KVA		5.00	6.25	7.50		E
3 KVA		5.40	6.75	8.10		E
5 KVA		6.00	7.50	9.00		E
7 1/2 KVA		7.00	8.75	10.50		E
10 KVA		8.00	10.00	12.00		E
15 KVA		10.00	12.50	15.00		E
25 KVA		12.00	15.00	18.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Fabrication of Wall Bracket						
2) Vibration Isolation						
3) Seismic Bracing						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>Transformers Three Phase Wall Mounted</b>						
<b>Up to 600 V Primary - Install &amp; Connect</b>						
1 KVA		5.00	6.25	7.50		E
2 KVA		5.50	6.88	8.25		E
3 KVA		6.00	7.50	9.00		E
6 KVA		7.00	8.75	10.50		E
9 KVA		8.00	10.00	12.00		E
15 KVA		10.00	12.50	15.00		E
25 KVA		12.00	15.00	18.00		E
30 KVA		14.00	17.50	21.00		E
45 KVA		16.00	20.00	24.00		E
50 KVA		18.00	22.50	27.00		E
60 KVA		20.00	25.00	30.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Fabrication of Wall Bracket						
2) Vibration Isolation						
3) Seismic Bracing						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Transformer Lightning Arrestors - Install and Terminate</b>						
3 KV		4.00	5.00	6.00		E
6 KV		4.20	5.25	6.30		E
9 KV		4.40	5.50	6.60		E
12 KV		4.60	5.75	6.90		E
15 KV		4.80	6.00	7.20		E
20 KV		5.00	6.25	7.50		E
25 KV		5.20	6.50	7.80		E
30 KV		5.40	6.75	8.10		E
35 KV		5.60	7.00	8.40		E
40 KV		6.00	7.50	9.00		E
50 KV		6.50	8.13	9.75		E
60 KV		7.00	8.75	10.50		E
70 KV		7.50	9.38	11.25		E
80 KV		8.00	10.00	12.00		E
90 KV		8.50	10.63	12.75		E
100 KV		9.00	11.25	13.50		E
120 KV		10.00	12.50	15.00		E
140 KV		11.00	13.75	16.50		E
160 KV		12.00	15.00	18.00		E
180 KV		13.00	16.25	19.50		E
200 KV		14.00	17.50	21.00		E
250 KV		16.00	20.00	24.00		E
300 KV		18.00	22.50	27.00		E
<b>Flexible Steel Conduit 30" to 60" Long - Attached to Transformers</b>						
3/4"		1.00	1.25	1.50		E
1"		1.10	1.38	1.65		E
1 1/4"		1.20	1.50	1.80		E
1 1/2"		1.30	1.63	1.95		E
2"		1.40	1.75	2.10		E
2 1/2"		2.00	2.50	3.00		E
3"		2.25	2.81	3.38		E
3 1/2"		3.50	4.38	5.25		E
4"		3.75	4.69	5.63		E
<b>Liquid-Tight Steel Conduit 30" to 60" Long - Attached to Transformers</b>						
3/4"		1.50	1.88	2.25		E
1"		1.60	2.00	2.40		E
1 1/4"		1.70	2.13	2.55		E
1 1/2"		1.80	2.25	2.70		E
2"		1.90	2.38	2.85		E
2 1/2"		2.25	2.81	3.38		E
3"		2.50	3.13	3.75		E
3 1/2"		3.75	4.69	5.63		E
4"		4.00	5.00	6.00		E
<b>Flexible Braid Connectors</b>						
Up to 100 Amp		1.00	1.25	1.50		E
200 Amp		1.10	1.38	1.65		E
300 Amp		1.20	1.50	1.80		E
500 Amp		1.35	1.69	2.03		E
800 Amp		1.50	1.88	2.25		E
1000 Amp		1.75	2.19	2.63		E
1600 Amp		2.00	2.50	3.00		E
<b>208 &amp; 240 Volt 3 Phase Power Capacitors - Install and Terminate</b>						
2 KVAR		3.00	3.75	4.50		E
4 KVAR		3.20	4.00	4.80		E
6 KVAR		3.50	4.38	5.25		E
8 KVAR		3.70	4.63	5.55		E
10 KVAR		4.00	5.00	6.00		E
12 KVAR		4.50	5.63	6.75		E
15 KVAR		5.00	6.25	7.50		E
20 KVAR		6.00	7.50	9.00		E
25 KVAR		7.00	8.75	10.50		E
30 KVAR		8.00	10.00	12.00		E
35 KVAR		9.00	11.25	13.50		E
40 KVAR		10.00	12.50	15.00		E
50 KVAR		11.00	13.75	16.50		E
60 KVAR		12.00	15.00	18.00		E
70 KVAR		13.00	16.25	19.50		E
80 KVAR		14.00	17.50	21.00		E
90 KVAR		15.00	18.75	22.50		E
100 KVAR		16.00	20.00	24.00		E
110 KVAR		17.00	21.25	25.50		E
125 KVAR		18.00	22.50	27.00		E
150 KVAR		20.00	25.00	30.00		E



Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>480 &amp; 600 Volt 3 Phase Power Capacitors - Install and Terminate</b>						
4 KVAR		4.00	5.00	6.00		E
6 KVAR		4.50	5.63	6.75		E
8 KVAR		5.00	6.25	7.50		E
10 KVAR		5.50	6.88	8.25		E
15 KVAR		6.00	7.50	9.00		E
20 KVAR		7.00	8.75	10.50		E
25 KVAR		8.00	10.00	12.00		E
30 KVAR		9.00	11.25	13.50		E
40 KVAR		10.00	12.50	15.00		E
50 KVAR		11.00	13.75	16.50		E
60 KVAR		12.00	15.00	18.00		E
70 KVAR		14.00	17.50	21.00		E
80 KVAR		16.00	20.00	24.00		E
90 KVAR		18.00	22.50	27.00		E
100 KVAR		20.00	25.00	30.00		E
125 KVAR		22.00	27.50	33.00		E
150 KVAR		24.00	30.00	36.00		E
175 KVAR		26.00	32.50	39.00		E
200 KVAR		28.00	35.00	42.00		E
250 KVAR		32.00	40.00	48.00		E
300 KVAR		36.00	45.00	54.00		E
<b>Manual Transfer Switch: Enclosed 600 Volt 2 Pole Double Throw Wall Mounted</b>						
100 Amp		5.00	6.25	7.50		E
150 Amp		6.00	7.50	9.00		E
225 Amp		7.00	8.75	10.50		E
260 Amp		8.00	10.00	12.00		E
400 Amp		10.00	12.50	15.00		E
600 Amp		12.00	15.00	18.00		E
800 Amp		15.00	18.75	22.50		E
1000 Amp (Free Standing Only)		20.00	25.00	30.00		E
1200 Amp (Free Standing Only)		22.00	27.50	33.00		E
1600 Amp (Free Standing Only)		25.00	31.25	37.50		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>Manual Transfer Switch: Enclosed 600 Volt 3 Pole Double Throw Wall Mounted</b>						
100 Amp		6.00	7.50	9.00		E
150 Amp		7.00	8.75	10.50		E
225 Amp		8.00	10.00	12.00		E
260 Amp		9.00	11.25	13.50		E
400 Amp		11.00	13.75	16.50		E
600 Amp		13.00	16.25	19.50		E
800 Amp		16.00	20.00	24.00		E
1000 Amp (Free Standing Only)		22.00	27.50	33.00		E
1200 Amp (Free Standing Only)		24.00	30.00	36.00		E
1600 Amp (Free Standing Only)		27.00	33.75	40.50		E
3000 Amp (free standing only)		38.00	47.50	57.00		E
4000 Amp (free standing only)		46.00	57.50	69.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						



Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

4



Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Manual Transfer Switch: Enclosed</b>						
<b>600 Volt 4 Pole Double Throw Wall Mounted</b>						
100 Amp		7.00	8.75	10.50		E
150 Amp		8.00	10.00	12.00		E
225 Amp		9.00	11.25	13.50		E
260 Amp		10.00	12.50	15.00		E
400 Amp		13.00	16.25	19.50		E
600 Amp		16.00	20.00	24.00		E
800 Amp		20.00	25.00	30.00		E
1000 Amp (Free Standing Only)		26.00	32.50	39.00		E
1200 Amp (Free Standing Only)		28.00	35.00	42.00		E
1600 Amp (Free Standing Only)		32.00	40.00	48.00		E
2000 Amp (Free Standing Only)		36.00	45.00	54.00		E
3000 Amp (Free Standing Only)		44.00	55.00	66.00		E
4000 Amp (Free Standing Only)		52.00	65.00	78.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>Automatic Transfer Switch: Enclosed</b>						
<b>600 Volt 2 Pole Double Throw Wall Mounted</b>						
100 Amp		6.00	7.50	9.00		E
150 Amp		7.00	8.75	10.50		E
225 Amp		8.00	10.00	12.00		E
260 Amp		9.00	11.25	13.50		E
400 Amp		11.00	13.75	16.50		E
600 Amp		13.00	16.25	19.50		E
800 Amp		16.00	20.00	24.00		E
1000 Amp (Free Standing Only)		22.00	27.50	33.00		E
1200 Amp (Free Standing Only)		24.00	30.00	36.00		E
1600 Amp (Free Standing Only)		27.00	33.75	40.50		E
2000 Amp (Free Standing Only)		32.00	40.00	48.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>Automatic Transfer Switch: Enclosed</b>						
<b>600 Volt 3 Pole Double Throw Wall Mounted</b>						
225 Amp		9.00	11.25	13.50		E
260 Amp		10.00	12.50	15.00		E
400 Amp		12.00	15.00	18.00		E
600 Amp		15.00	18.75	22.50		E
800 Amp		18.00	22.50	27.00		E
1000 Amp (Free Standing Only)		24.00	30.00	36.00		E
1200 Amp (Free Standing Only)		26.00	32.50	39.00		E
1600 Amp (Free Standing Only)		30.00	37.50	45.00		E
2000 Amp (free standing only)		34.00	42.50	51.00		E
3000 Amp (Free Standing Only)		42.00	52.50	63.00		E
4000 Amp (Free Standing Only)		50.00	62.50	75.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>Automatic Transfer Switch: Enclosed</b>						
<b>600 Volt 4 Pole Double Throw Wall Mounted</b>						
100 Amp		8.00	10.00	12.00		E
150 Amp		9.00	11.25	13.50		E
225 Amp		10.00	12.50	15.00		E
260 Amp		12.00	15.00	18.00		E
400 Amp		14.00	17.50	21.00		E
600 Amp		18.00	22.50	27.00		E
800 Amp		22.00	27.50	33.00		E
1000 Amp (Free Standing Only)		28.00	35.00	42.00		E
1200 Amp (free standing only)		31.00	38.75	46.50		E
1600 Amp (Free Standing Only)		35.00	43.75	52.50		E
2000 Amp (Free Standing Only)		40.00	50.00	60.00		E
3000 Amp (Free Standing Only)		50.00	62.50	75.00		E
4000 Amp (Free Standing Only)		60.00	75.00	90.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						







Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Automatic Transfer &amp; Bypass Isolation Switches:</b>						
<b>Drawout Type 3 Pole 600 Volt</b>						
100 Amp 1-Enclosure		36.00	45.00	54.00		E
150 Amp 1-Enclosure		38.00	47.50	57.00		E
225 Amp 1-Enclosure		40.00	50.00	60.00		E
260 Amp 1-Enclosure		42.00	52.50	63.00		E
400 Amp 1-Enclosure		44.00	55.00	66.00		E
600 Amp 1-Enclosure		46.00	57.50	69.00		E
800 Amp 1-Enclosure		48.00	60.00	72.00		E
1000 Amp 2-Enclosures		56.00	70.00	84.00		E
1200 Amp 2-Enclosures		60.00	75.00	90.00		E
1600 Amp 2-Enclosures		64.00	80.00	96.00		E
2000 Amp 2-Enclosures		70.00	87.50	105.00		E
3000 Amp 2-Enclosures		80.00	100.00	120.00		E
4000 Amp 2-Enclosures		90.00	112.50	135.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>Automatic Transfer &amp; Bypass Isolation Switches:</b>						
<b>Drawout Type 4 Pole 600 Volt</b>						
100 Amp 1-Enclosure		38.00	47.50	57.00		E
150 Amp 1-Enclosure		40.00	50.00	60.00		E
225 Amp 1-Enclosure		42.00	52.50	63.00		E
260 Amp 1-Enclosure		44.00	55.00	66.00		E
400 Amp 1-Enclosure		46.00	57.50	69.00		E
600 Amp 1-Enclosure		48.00	60.00	72.00		E
800 Amp 1-Enclosure		50.00	62.50	75.00		E
1000 Amp 2-Enclosures		60.00	75.00	90.00		E
1200 Amp 2-Enclosures		66.00	82.50	99.00		E
1600 Amp 2-Enclosures		72.00	90.00	108.00		E
2000 Amp 2-Enclosures		80.00	100.00	120.00		E
3000 Amp 2-Enclosures		90.00	112.50	135.00		E
4000 Amp 2-Enclosures		100.00	125.00	150.00		E
<i>Note: These labor Units Apply to NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						




Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

4

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Generator Sets</b>						
<i>Items to consider when generator sets are outdoors:</i>						
1) Concrete curb or pad						
2) Structural engineering drawings						
3) Unload/Unpack Unit and Accessories						
4) Rigging and setting in place						
5) Bolt and Shim in place						
6) Remove Annunciator Panel						
7) Fuel						
8) Fuel Tank and Fuel Piping						
9) Exhaust System						
10) Load Testing						
11) Commissioning						
<i>Items to consider when generator sets are indoors:</i>						
1) Hoisting to Basement or Penthouse						
2) All above items relating to outdoor units						
3) Fuel Tank Fill, Vent and Fuel Piping						
4) Exhaust Piping to Exterior						
5) Ductwork and Dampers for Intake, Exhaust and Combustion Air						
<b>Emergency Generator &amp; 2-Source Auto Transfer Switch in Single Enclosure - 208 Volt Service</b>						
		20.00	25.00	30.00		E
		22.00	27.50	33.00		E
		24.00	30.00	36.00		E
		26.00	32.50	39.00		E
		28.00	35.00	42.00		E
		30.00	37.50	45.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>Emergency Generator &amp; 2-Source Auto Transfer Switch in Single Enclosure - 220 Volt Service</b>						
		19.00	23.75	28.50		E
		21.00	26.25	31.50		E
		23.00	28.75	34.50		E
		25.00	31.25	37.50		E
		27.00	33.75	40.50		E
		29.00	36.25	43.50		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>Emergency Generator &amp; 2-Source Auto Transfer Switch in Single Enclosure - 480 Volt Service</b>						
		18.00	22.50	27.00		E
		20.00	25.00	30.00		E
		22.00	27.50	33.00		E
		24.00	30.00	36.00		E
		26.00	32.50	39.00		E
		28.00	35.00	42.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>Emergency Generator &amp; 2-Source Auto Transfer Switch in Single Enclosure - 600 Volt Service</b>						
		17.00	21.25	25.50		E
		19.00	23.75	28.50		E
		21.00	26.25	31.50		E
		23.00	28.75	34.50		E
		25.00	31.25	37.50		E
		27.00	33.75	40.50		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
						
<b>Emergency Generator &amp; 3-Source Auto Transfer Switch in Two Enclosures - 208 Volt Service</b>						
260 Amp		32.00	40.00	48.00		E
400 Amp		34.00	42.50	51.00		E
600 Amp		36.00	45.00	54.00		E
800 Amp		39.00	48.75	58.50		E
1000 Amp		42.00	52.50	63.00		E
1200 Amp		46.00	57.50	69.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
						
<b>Emergency Generator &amp; 3-Source Auto Transfer Switch in Two Enclosures - 220 Volt Service</b>						
260 Amp		30.00	37.50	45.00		E
400 Amp		32.00	40.00	48.00		E
600 Amp		34.00	42.50	51.00		E
800 Amp		37.00	46.25	55.50		E
1000 Amp		40.00	50.00	60.00		E
1200 Amp		44.00	55.00	66.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
						
<b>Emergency Generator &amp; 3-Source Auto Transfer Switch in Two Enclosures - 480 Volt Service</b>						
260 Amp		28.00	35.00	42.00		E
400 Amp		30.00	37.50	45.00		E
600 Amp		32.00	40.00	48.00		E
800 Amp		35.00	43.75	52.50		E
1000 Amp		38.00	47.50	57.00		E
1200 Amp		42.00	52.50	63.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
						
<b>Emergency Generator &amp; 3-Source Auto Transfer Switch in Two Enclosures - 600 Volt Service</b>						
260 Amp		26.00	32.50	39.00		E
400 Amp		28.00	35.00	42.00		E
600 Amp		30.00	37.50	45.00		E
800 Amp		33.00	41.25	49.50		E
1000 Amp		36.00	45.00	54.00		E
1200 Amp		40.00	50.00	60.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
						
<b>Emergency Generator &amp; 3-Source Auto Transfer Switch in Four Enclosures - 208 Volt Service</b>						
260 Amp		60.00	75.00	90.00		E
400 Amp		65.00	81.25	97.50		E
600 Amp		70.00	87.50	105.00		E
800 Amp		76.00	95.00	114.00		E
1000 Amp		82.00	102.50	123.00		E
1200 Amp		90.00	112.50	135.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
						
<b>Emergency Generator &amp; 3-Source Auto Transfer Switch in Four Enclosures - 220 Volt Service</b>						
260 Amp		58.00	72.50	87.00		E
400 Amp		63.00	78.75	94.50		E
600 Amp		68.00	85.00	102.00		E
800 Amp		74.00	92.50	111.00		E
1000 Amp		80.00	100.00	120.00		E
1200 Amp		88.00	110.00	132.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

4

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
						
<b>Emergency Generator &amp; 3-Source Auto Transfer Switch in Four Enclosures - 480 Volt Service</b>						
260 Amp		56.00	70.00	84.00		E
400 Amp		61.00	76.25	91.50		E
600 Amp		66.00	82.50	99.00		E
800 Amp		72.00	90.00	108.00		E
1000 Amp		78.00	97.50	117.00		E
1200 Amp		86.00	107.50	129.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
						
<b>Emergency Generator &amp; 3-Source Auto Transfer Switch in Four Enclosures - 600 Volt Service</b>						
260 Amp		54.00	67.50	81.00		E
400 Amp		59.00	73.75	88.50		E
600 Amp		64.00	80.00	96.00		E
800 Amp		70.00	87.50	105.00		E
1000 Amp		76.00	95.00	114.00		E
1200 Amp		84.00	105.00	126.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
						
<b>Emergency Generator Fused 2-Pole Switch Distribution Section in Single Enclosure</b>						
200 Amp		12.00	15.00	18.00		E
260 Amp		13.00	16.25	19.50		E
400 Amp		14.00	17.50	21.00		E
600 Amp		15.00	18.75	22.50		E
800 Amp		16.00	20.00	24.00		E
1200 Amp		20.00	25.00	30.00		E
1600 Amp		22.00	27.50	33.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
						
<b>Emergency Generator Fused 3-Pole Switch Distribution Section in Single Enclosure</b>						
200 Amp		14.00	17.50	21.00		E
260 Amp		15.00	18.75	22.50		E
400 Amp		16.00	20.00	24.00		E
600 Amp		17.00	21.25	25.50		E
800 Amp		19.00	23.75	28.50		E
1000 Amp		21.00	26.25	31.50		E
1200 Amp		23.00	28.75	34.50		E
1600 Amp		25.00	31.25	37.50		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
						
<b>Emergency Generator Fused 4-Pole Switch Distribution Section in Single Enclosure</b>						
200 Amp		16.00	20.00	24.00		E
260 Amp		17.00	21.25	25.50		E
400 Amp		18.00	22.50	27.00		E
600 Amp		19.00	23.75	28.50		E
800 Amp		21.00	26.25	31.50		E
1000 Amp		23.00	28.75	34.50		E
1200 Amp		25.00	31.25	37.50		E
1600 Amp		28.00	35.00	42.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						

### Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Emergency Generator Selective Load</b>						
<b>Transfer Switches in Single Enclosure</b>						
One 70 Amp		12.00	15.00	18.00		E
Two 70 Amp		14.00	17.50	21.00		E
Three 70 Amp		16.00	20.00	24.00		E
Four 70 Amp		18.00	22.50	27.00		E
One 100 Amp		14.00	17.50	21.00		E
Two 100 Amp		16.00	20.00	24.00		E
Three 100 Amp		18.00	22.50	27.00		E
Four 100 Amp		20.00	25.00	30.00		E
One 150 Amp		22.00	27.50	33.00		E
Two 150 Amp		26.00	32.50	39.00		E
Three 150 Amp		30.00	37.50	45.00		E
One 260 Amp		38.00	47.50	57.00		E
Two 260 Amp		46.00	57.50	69.00		E
Three 260 Amp		54.00	67.50	81.00		E
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>Emergency Generator Master Control - Single Enclosure</b>						
260 Amp		30.00	37.50	45.00		E
400 Amp		34.00	42.50	51.00		E
600 Amp		38.00	47.50	57.00		E
800 Amp		42.00	52.50	63.00		E
1200 Amp		46.00	57.50	69.00		E
1600 Amp		50.00	62.50	75.00		E
<i>Note: These labor Units Apply to</i>						
<i>NEMA 1 Enclosures Only</i>						
<i>For NEMA 3R Add 10%</i>						
<i>For NEMA 12 Add 20%</i>						
<i>Note: Labor Units Do Not Include</i>						
1) Housekeeping Pad						
2) Vibration Isolator						
3) Seismic Supports						
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>Generator w/o Fuel Tank Up to 60KW</b>						
7.5 KW		10.00	12.50	15.00		E
10 KW		11.50	14.38	17.25		E
12 KW		12.50	15.63	18.75		E
15 KW		13.00	16.25	19.50		E
17.5 KW		13.00	16.25	19.50		E
30 KW		15.00	18.75	22.50		E
45 KW		15.50	19.38	23.25		E
50 KW		16.00	20.00	24.00		E
55 KW		17.00	21.25	25.50		E
60 KW		19.00	23.75	28.50		E
<i>Items to consider when generator sets are outdoors:</i>						
1) Concrete curb or pad						
2) Structural engineering drawings						
3) Unload/Unpack Unit and Accessories						
4) Rigging and setting in place						
5) Bolt and Shim in place						
6) Remove Annunciator Panel						
7) Fuel						
8) Fuel Tank and Fuel Piping						
9) Exhaust System						
10) Load Testing						
11) Commissioning						
<i>Items to consider when generator sets are indoors:</i>						
1) Hoisting to Basement or Penthouse						
2) All above items relating to outdoor units						
3) Fuel Tank Fill, Vent and Fuel Piping						
4) Exhaust Piping to Exterior						
5) Ductwork and Dampers for Intake, Exhaust and Combustion Air						

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

4

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Generator w/o Fuel Tank - Over 60KW</b>						
70 KW		21.00	26.25	31.50		E
75 KW		23.00	28.75	34.50		E
85 KW		25.00	31.25	37.50		E
90 KW		26.50	33.13	39.75		E
100 KW		27.50	34.38	41.25		E
115 KW		30.00	37.50	45.00		E
125 KW		31.00	38.75	46.50		E
150 KW		32.50	40.63	48.75		E
170 KW		33.50	41.88	50.25		E
175 KW		34.00	42.50	51.00		E
200 KW		34.50	43.13	51.75		E
230 KW		35.00	43.75	52.50		E
250 KW		36.00	45.00	54.00		E
300 KW		38.00	47.50	57.00		E
350 KW		41.50	51.88	62.25		E
400 KW		43.50	54.38	65.25		E
450 KW		45.00	56.25	67.50		E
500 KW		46.00	57.50	69.00		E
600 KW		48.00	60.00	72.00		E
750 KW		52.00	65.00	78.00		E
900 KW		60.00	75.00	90.00		E
1000 KW		68.50	85.63	102.75		E
<i>Items to consider when generator sets are outdoors:</i>						
1) Concrete curb or pad						
2) Structural engineering drawings						
3) Unload/Unpack Unit and Accessories						
4) Rigging and setting in place						
5) Bolt and Shim in place						
6) Remove Annunciator Panel						
7) Fuel						
8) Fuel Tank and Fuel Piping						
9) Exhaust System						
10) Load Testing						
11) Commissioning						
<i>Items to consider when generator sets are indoors:</i>						
1) Hoisting to Basement or Penthouse						
2) All above items relating to outdoor units						
3) Fuel Tank Fill, Vent and Fuel Piping						
4) Exhaust Piping to Exterior						
5) Ductwork and Dampers for Intake, Exhaust and Combustion Air						
<b>Generator Accessories - Install &amp; Terminate</b>						
Generator Battery Rack		1.20	1.50	1.80		E
Generator Battery Charger		1.20	1.50	1.80		E
<b>Controls</b>						
Generator Control Panel		14.40	18.00	21.60		E
Generator Remote Annunciator		1.80	2.25	2.70		E
Generator Fuel Gauge Connect		1.20	1.50	1.80		E
Remote Fuel Indicator		1.20	1.50	1.80		E
Generator Muffler		2.40	3.00	3.60		E
Generator Flexible Exhaust Pipe		0.24	0.30	0.36		E
Generator Exhaust Rain Cap		0.24	0.30	0.36		E
Insulate Exhaust		1.20	1.50	1.80		E
Muffler Hanger		1.20	1.50	1.80		E
<b>Water Radiator</b>						
Generator Remote Radiator		1.80	2.25	2.70		E
Generator Flex Radiator Adapter		0.60	0.75	0.90		E
Generator Louver/Radiator Duct		1.50	1.88	2.25		E
Generator Louver Electrical Connect		0.60	0.75	0.90		E
Generator Wall Louver Connect		0.60	0.75	0.90		E
Generator Block Heater Connect		0.15	0.19	0.23		E
<b>Miscellaneous</b>						
WP Generator Housing		7.20	9.00	10.80		E
Form Lumber for Generator Pad		3.60	4.50	5.40		E
Generator Anchor Bolts		0.06	0.08	0.09		E
Generator Vibration Isolators		2.40	3.00	3.60		E
Test Generator		1.20	1.50	1.80		E
Fuel for Testing		1.20	1.50	1.80		E
Test Fuel Piping		3.60	4.50	5.40		E
55 Gal Fuel Tank Installation		2.40	3.00	3.60		E
75 - 500 Gal Fuel Tank Installation		5.20	6.50	7.80		E
650 - 1000 Gal Fuel Tank Installation		9.60	12.00	14.40		E
1000 - 1500 Gal Fuel Tank Installation		12.00	15.00	18.00		E
1500 - 2500 Gal Fuel Tank Installation		14.40	18.00	21.60		E
3000 - 5000 Gal Fuel Tank Installation		19.20	24.00	28.80		E

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
Generator Flexible Fuel Hoses		0.30	0.38	0.45		LF
Generator Day Tank Connect		0.60	0.75	0.90		E
Generator Fuel Solenoid Connect		0.60	0.75	0.90		E
Fuel Tank Hold Down Straps		0.30	0.38	0.45		E
Fuel Tank Turnbuckle		0.30	0.38	0.45		E
Fuel Level Mechanical Indicator		1.20	1.50	1.80		E
<b>TVSS Self Contained Unit - Lug Type</b> 200KAIC - 120/208V - 277/480V		2.50	3.13	3.75		E
<b>TVSS Includes Nipples/Knock Outs/ Mounting Brackets/Terminations</b>						
Category B - 400 A & Less		3.00	3.75	4.50		E
Category C - Greater Than 400 A		6.00	7.50	9.00		E
<b>TVSS - Serviceable Unit - Lug Type</b>						
16kA - 25kA - 120/208V - 277/480V		4.00	5.00	6.00		E
32kA - 50kA - 120/208V - 277/480V		5.00	6.25	7.50		E
60kA - 75kA - 120/208V - 277/480V		7.00	8.75	10.50		E
1000kA - 120/208V - 277/480V		8.00	10.00	12.00		E
<b>TVSS - Serviceable Unit - Disconnect Type</b>						
16kA - 25kA - 120/208V - 277/480V		5.00	6.25	7.50		E
32kA - 50kA - 120/208V - 277/480V		6.00	7.50	9.00		E
60kA - 75kA - 120/208V - 277/480V		8.00	10.00	12.00		E
1000kA - 120/208V - 277/480V		9.00	11.25	13.50		E
<b>EPO Emergency Power Off Systems</b>						
Emergency Power-Off Push button		1.00	1.25	1.50		E
<b>Uninterruptible Power Supply Up to 600 Volt Self Contained</b>						
1.0 KVA		4.00	5.00	6.00		E
1.5 KVA		4.50	5.63	6.75		E
2 KVA		5.00	6.25	7.50		E
2.5 KVA		6.00	7.50	9.00		E
3.0 KVA		7.00	8.75	10.50		E
5.0 KVA		8.00	10.00	12.00		E
7.5 KVA		10.00	12.50	15.00		E
10 KVA		12.00	15.00	18.00		E
15 KVA		16.00	20.00	24.00		E
20 KVA		20.00	25.00	30.00		E
30.0 KVA		26.00	32.50	39.00		E
40.0 KVA		32.00	40.00	48.00		E
50.0 KVA		40.00	50.00	60.00		E
<b>UPS Systems - Single Phase 120V</b>						
Up to 650 VA		1.25	1.56	1.88		E
Up to 3000 VA		1.30	1.63	1.95		E
<b>UPS Systems - Three Phase 208V</b>						
<b>System Control Cabinet w/o Internal Batteries</b>						
10 - 30KVA - 120/208V - Size 24x32x64 (up to 550 lbs)		16.00	20.00	24.00		E
<b>UPS Systems - Three Phase 120/208V with Internal batteries</b>						
10 - 15KVA - Size 24x24x64 (550 lbs) 15 Min Backup		12.00	15.00	18.00		E
15 - 20KVA - Size 24x24x64 (700 lbs) 15 Min Backup		16.00	20.00	24.00		E
30 KVA - Size 24x24x64 (700 lbs) 8 Min Backup		16.00	20.00	24.00		E
<b>UPS Systems - Three Phase System Control Cabinets - 208V or 480V (excluding MBC or Battery Cabinet)</b>						
30 KVA - Size 32x32x71 (Up to 2100 lbs)*		36.00	45.00	54.00		E
40 KVA - Size 32x32x71 (Up to 2200 lbs)*		38.00	47.50	57.00		E
50 KVA - Size 32x32x71 (Up to 2200 lbs)*		38.00	47.50	57.00		E
65 KVA - Size 40x32x71 (Up to 2500 lbs)*		44.00	55.00	66.00		E
80 KVA - Size 40x32x71 (Up to 2500 lbs)*		48.00	60.00	72.00		E
100 KVA - Size 50x32x71 (Up to 3350 lbs)*		58.00	72.50	87.00		E
130 KVA - Size 50x32x71 (Up to 3350 lbs)*		60.00	75.00	90.00		E
<b>UPS Systems - Three Phase Maintenance Bypass Cabinet (MBC)</b>						
30 - 50 KVA - Size 25x32x71 (660 lbs)		16.00	20.00	24.00		E
65 - 80 KVA - Size 32x32x71 (750 lbs)		17.50	21.88	26.25		E
100 - 130 KVA - Size 32x32x71 (800 lbs)		19.00	23.75	28.50		E

Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

4

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>UPS Systems - Three Phase Sealed Battery Cabinets</b>						
on a maximum battery time of 30 minutes						
30 - 50 KVA - Size 25x32x71 (2350-3000 lbs)*		40.00	50.00	60.00		E
50 - 65 KVA - Size 25x32x71 (3000-4250 lbs)*		56.00	70.00	84.00		E
65 - 80 KVA - Size 49x32x71 (4250-5420 lbs)*		72.00	90.00	108.00		E
100 - 130 KVA - Size 49x32x71 (7800-8500 lbs)*		112.00	140.00	168.00		E
*This equipment will require special handling and/or rigging equipment.						
<b>UPS Systems - Three Phase Single Module Systems</b>						
150 KVA 208V or 480V Batt. - Size 56x33x78 (Up to 3300 lbs)*		48.00	60.00	72.00		E
225 KVA 208V or 480V Batt. - Size 56x33x78 (Up to 3800 lbs)*		56.00	70.00	84.00		E
300 KVA 208V or 480V Batt. - Size 72x35x78 (Up to 5400 lbs)*		78.00	97.50	117.00		E
400 KVA 208V or 480V Batt. - Size 72x35x78 (Up to 8400 lbs)*		120.00	150.00	180.00		E
500 KVA 480V Batt. - Size 96x39x78 (Up to 8700 lbs)*		130.00	162.50	195.00		E
750 KVA 480V Batt. - Size 120x39x78 (Up to 11800 lbs)*		176.00	220.00	264.00		E
1000 KVA 480V Batt. - Size 177x44x82 (Up to 16500 lbs)*		240.00	300.00	360.00		E
*This equipment will require special handling and/or rigging equipment.						
(1) Multi-Module Systems require additional labor based on number of modules in the line-up						
(2) System Control Cabinet labor additional						
(3) Battery Rack Assembly labor additional						
(4) Battery Installation Labor additional						
(5) Battery Disconnect Labor additional						
(6) Battery Charger System Labor additional						
(7) Battery Spill Containment Labor additional						
(8) Battery Cycle Monitor Labor additional						
(9) Battery Monitoring System Labor additional						
<b>UPS Systems - Control Cabinet</b>						
The System Control Cabinet (SCC) can be configured in many ways based on the number of modules in a system. This affects the size and weight of the unit. The estimator has to evaluate the system being installed from the information provided and determine the labor hours accordingly. (To Be Determined)						
<b>Battery Spacesaver System</b>						
Set & bolt 3-wide Base Mounting Plate		1.50	1.88	2.25		E
Set single 3-wide Battery Pallet (Weight 750lbs) including unpacking, terminal polishing and interconnecting *		5.40	6.75	8.10		E
3- Wide Pallets are stackable up to (8) high						
<b>Accessories</b>						
3-wide front protective shield		0.30	0.38	0.45		E
Top mounting plate for electronics		0.50	0.63	0.75		E
Battery Test Kit		0.75	0.94	1.13		E
Floor Loading Plate - For even weight distribution		1.00	1.25	1.50		E
*Special lifting equipment is necessary						
<b>UPS Systems - Battery Racks</b>						
Single Tier Rack - Up to 6 Batteries		3.60	4.50	5.40		E
Note: Add 20 % additional labor for Seismic braced racks						
<b>UPS Systems - Wet-Cell Battery</b>						
Wet Cell "Flooded" Battery Installation and conn <= 150Lbs		3.50	4.38	5.25		E
Wet Cell "Flooded" Battery Installation and conn <= 300Lbs		4.25	5.31	6.38		E
Wet Cell "Flooded" Battery Installation and conn <= 600Lbs		5.00	6.25	7.50		E
Wet Cell "Flooded" Battery Installation and conn <= 700Lbs		5.50	6.88	8.25		E
<b>UPS Systems - Battery Disconnect Switch</b>						
1200 A		24.00	30.00	36.00		E
1600 A		26.00	32.50	39.00		E
2000 A		28.00	35.00	42.00		E
2500 A		32.00	40.00	48.00		E
<b>UPS Systems - Battery Charging Unit - Rack Mounted</b>						
Charger - Up to 12 Batteries		4.00	5.00	6.00		E
Charger - Up to 24 Batteries		5.00	6.25	7.50		E
Charger - Up to 48 Batteries		6.00	7.50	9.00		E
Charger - Up to 120 Batteries		8.00	10.00	12.00		E
<b>UPS Systems - Spill Containment System</b>						
4" Perimeter Barrier (Floor) - up to 6 Batteries		2.50	3.13	3.75		E
<b>UPS Systems - Battery Cycle Monitor</b>						
Battery Cycle Monitor		4.00	5.00	6.00		E



Section 4 - Switchboards, MCC's, Panelboards & Power Equipment

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>UPS Systems - Battery Monitoring System</b> Battery Monitoring Panel (for up to 256 Batteries) Voltage Sensing Lead/Cell - Install and Connect Current Sensing Lead/Cell - Install and Connect		8.00 0.75 0.75	10.00 0.94 0.94	12.00 1.13 1.13		E E E
 <b>UPS Systems - Remote Status Panel</b> Remote Status Panel - Size 20"x20"x8" (48lbs)		4.00	5.00	6.00		E
 <b>UPS Systems - Static Transfer Switches</b> 100A - Size 30"x32"x77" (up to 880 lbs) 300A - Size 30"x32"x77" (up to 880 lbs) 400A - Size 38"x32"x77" (up to 1300 lbs) 600A - Size 38"x32"x77" (up to 1300 lbs) * 800A - Size 84"x32"x77" (up to 2600 lbs) * 1000A - Size 84"x32"x77" (up to 2600 lbs) <i>*This equipment will require special handling and/or rigging equipment.</i>		18.00 20.00 24.00 24.00 40.00 40.00	22.50 25.00 30.00 30.00 50.00 50.00	27.00 30.00 36.00 36.00 60.00 60.00		E E E E E E
 <b>UPS Systems - Power Distribution Units - PDU's 208/480V Input</b> 15KVA - 42 Pole - Size 30x32x68 (600lbs) 30KVA - 42 Pole - Size 42x32x68 (750lbs) 50KVA - 84 Pole - Size 44x32x68 (900lbs) 75KVA - 84 Pole - Size 44x32x68 (1100lbs) 100KVA - 84 Pole - Size 44x32x68 (1325lbs) 125KVA - 84 Pole - Size 44x32x68 (1500lbs) 150KVA - 84 Pole - Size 44x32x68 (1750lbs) <i>Branch Circuit termination labor additional Labor to assemble and install PDU Stand additional</i>		16.00 18.00 20.00 22.00 24.00 26.00 30.00	20.00 22.50 25.00 27.50 30.00 32.50 37.50	24.00 27.00 30.00 33.00 36.00 39.00 45.00		E E E E E E E
 <b>UPS Systems - Remote Distribution Cabinets - RDC's / RPP's</b> 4 Section - 168 Pole - Size 24x26x78 (750 lbs) <i>Branch Circuit termination labor additional</i>		18.00	22.50	27.00		E
 <b>UPS Systems - Static Transfer Switch &amp; PDU Combined</b> * 250KVA - Size 77x32x77 (3730 lbs) * 400KVA - Size 77x49x77 (4700 lbs) * 600KVA - Size 77x49x77 (5400 lbs) * 1200KVA - Size 97x49x77 (8400 lbs) <i>*This equipment will require special handling and/or rigging equipment.</i>		56.00 60.00 78.00 120.00	70.00 75.00 97.50 150.00	84.00 90.00 117.00 180.00		E E E E
 <b>Emergency Power Off System</b> EPO Relay Cabinet EPO Pushbutton	x x	5.00 1.40	6.25 1.88	7.50 2.25		E E
 <b>UPS Systems - Hydrogen Detection System</b> Gas Detection Controller N4X - Handles up to 4 heads Gas Detection Head N4X Remote Horn - NEMA 4X Remote Light - NEMA 4X Remote Horn - NEMA 1 Remote Light - NEMA 1		4.60 1.80 1.80 1.80 1.00 1.00	5.75 2.25 2.25 2.25 1.25 1.25	6.90 2.70 2.70 2.70 1.50 1.50		E E E E E E
 <b>Generators - Permanent Outdoor Loadbank Units - Installed on Grade Level</b> 50-150KW - Size 48x27x35 (Up to 500lbs) 200-500KW - Size 69x47x52 (Up to 900lbs) * 750-1000KW - Size 40x59x138 (Up to 2000lbs) * 1500-2000KW - Size 80x59x156 (Up to 4000 lbs) * 2500-3000KW - Size 120x59x156 (Up to 6000lbs) <i>*This equipment will require special handling and/or rigging equipment.</i>		20.00 24.00 36.00 48.00 80.00	25.00 30.00 45.00 60.00 100.00	30.00 36.00 54.00 72.00 120.00		E E E E E
 <b>Generators - Portable Loadbank Units - Installed on Grade Level</b> 100KW - Size 25x16x29 (Up to 300lbs) 200KW - Size 47x34x52 (Up to 650lbs) 400KW - Size 56x34x52 (Up to 800lbs) 500-750KW - Size 61x34x75 (Up to 1150lbs) * 1000-1250KW - Size 208x93x84 w/trailer (Up to 4000lbs) * 1500-2000KW - Size 188x93x118 w/trailer (Up to 5500lbs) * 2500-3000KW - Size 208x93x118 w/trailer (Up to 7000lbs) <i>Note: (1) Portable Loadbank removal requires additional labor (2) Cable terminations and removal requires additional labor</i>		6.00 8.00 12.00 16.00 24.00 24.00 24.00	7.50 10.00 15.00 20.00 30.00 30.00 30.00	9.00 12.00 18.00 24.00 36.00 36.00 36.00		E E E E E E E



# SECTION 5

## LIGHTING FIXTURES, POLES AND PARKING LOT LIGHTING

### General Information

This section includes labor units for the installation of incandescent fixtures, metal halide, multi-vapor HID indoor and outdoor fixtures, fluorescent fixtures, LED fixtures, exit fixtures, chandeliers, showroom, stage and auditorium fixtures, airport lighting fixtures and parking lot lighting.

### Scope of These Labor Units

The Introduction section includes details on the scope of labor units across the manual. Some items included are:

- Material unloading, jobsite storage and delivery to the installation area
- Drawing and specification study
- Layout, measuring and marking the installation location
- Tool acquisition and return to storage
- Fixture installation
- Power and grounding conductor terminations
- Original installation of lamps and fluorescent tubes
- Cover and lens installation
- Verification of fixture operation
- Removal of shipping cartons and excess contractor furnished materials
- Normal non-productive labor

5

### Work Operations Not Included In These Labor Units

- Field supervision
- Hoisting above three floors
- Conduit terminations
- Cable connections
- Installation or replacement of ballasts
- Installing mounting brackets or supports
- Assembling fixtures
- Measurement and alignment more precise than normal industry standards

### Labor Adjustments for Non-Typical Conditions

See the Introduction section for details.

### Application Instructions

- Labor units under the “Normal” column may apply to mounting heights up to ten feet above a smooth hard floor. Labor units under the “Difficult” column may apply to mounting heights up to 12 feet. Labor units under the “Very Difficult” column may apply to mounting heights up to 20 feet.
- When ceiling mounted recessed fixtures require plaster rings, a separate labor allowance must be added for those items.
- Labor units for all indoor fixture installations are based on the use of rolling scaffolds and step ladders on commercial projects. Labor units for fixture installations in warehouses, auditoriums, showrooms, etc., are based on the use of mechanical personnel lifts.
- Labor units in this section are for new work only with electrical contractor purchased fixtures. For remodeling or change order situations these labor units must be substantially increased when the type or quantity of fixtures is changed.
- Clarification on Evolving Led Technology: Due the rapidly evolving product base for LED lighting fixtures, for products not explicitly described within this manual the contractor shall use a fixture of similar design, size and function to extrapolate a labor units to be used for the installation of the fixture type.




## Section 5 - Lighting Fixtures, Poles and Parking Lot Lighting Table of Contents

Lighting Fixtures 2' x 2' Surface Mount		5-5
Lighting Fixtures 2' x 4' Surface Mount		5-5
Surface Mounted Light Fixture		5-5
Wrap Around Light Fixture	<i>(Updated)</i>	5-5
Surface Mount Vaportite - Indoor / Outdoor	<i>(Updated)</i>	5-5
Lay-in (T-Bar) Fixtures - w/ Lens		5-5
Fluorescent Lay-in Parabolic Fixtures		5-6
Fluorescent Lay-in Paracube Fixtures		5-6
Recess Mounted Gyp Bd Ceiling		5-6
Recessed Mounted Vaportite Gyp Bd Ceiling	<i>(Updated)</i>	5-6
Linear : Pendant, Stem or Aircraft Cable Mounted		5-6
Industrial - Chain Hung Suspended from Ceiling	<i>(Updated)</i>	5-7
Stem Mounted Vaportite Suspended from Ceiling	<i>(Updated)</i>	5-7
Under Counter Lights	<i>(Updated)</i>	5-7
Commercial Grade Wall or Cove Mounted	<i>(Updated)</i>	5-7
Surface Mount Strip	<i>(Updated)</i>	5-8
Weatherproof Fluorescent Fixture - Outdoor		5-8
Fixture Mounting Accessories	<i>(Updated)</i>	5-8
Lighting Flex Whips - Pre-assembled		5-8
Modular Wiring System (MWS) Components - Pre-manufactured		5-8
Commercial Indoor Fixtures - Wall Mounted - Up To 150 Watt	<i>(Updated)</i>	5-8
Surface Mount - Up to 300 Watt Ceiling Mounted	<i>(Updated)</i>	5-8
Pendant Mount - Up to 150 Watt		5-8
Pendant Mount - Up to 300 Watt		5-8
Recessed Prewired Hi-Hat Fixt, Can Light or Downlight	<i>(Updated)</i>	5-9
Pendent Mount	<i>(Updated)</i>	5-9
Light Track	<i>(Updated)</i>	5-9
Low Voltage Power Grid Lighting System	<i>(Updated)</i>	5-9
Wall Sconce / Vanity Light	<i>(Updated)</i>	5-9
Health Care Lighting	<i>(Updated)</i>	5-9
Ceiling Fans	<i>(Updated)</i>	5-10
Ceiling Fans - Low Velocity	<i>(Updated)</i>	5-10
High Bay Fixture Ultra- Efficient 2x4	<i>(Updated)</i>	5-10
Exit Fixtures		5-10
Exit Fixtures - Edge Lit		5-10
Exit Sign - Self Powered		5-10
Egress / Emergency Fixtures		5-10
Emergency Lighting Inverter Panels - up to 5000W		5-10
Power Pack w/ Dual Heads		5-10
Wall Packs - Wall Mounted		5-10
Bracket Mount - Wall Mounted		5-10
Surface Ceiling Mounted		5-10
Recessed H.I.D.		5-11
Fluorescent High Bay Fixture Ultra- Efficient 6 Lamp HO		5-11
High Bay Fixtures - Multi Vapor H.I.D Fixtures - 250 Watt - Without Lens		5-11
High Bay Fixtures - Multi Vapor H.I.D Fixtures - 400 Watt - Without Lens		5-11
High Bay Fixtures - Multi Vapor H.I.D Fixtures - 250 Watt - With Lens		5-11
High Bay Fixtures - Multi Vapor H.I.D Fixtures - 400 Watt - With Lens		5-11
High Bay Fixtures - Multi Vapor H.I.D Fixtures - 1000 Watt - With Lens		5-11
Multi Vapor H.I.D. Fixtures - Twin Mounted		5-11
Low Bay - Multi Vapor H.I.D. Fixtures - 250 Watt With Lens		5-11
Low Bay - Multi Vapor H.I.D. Fixtures - 400 Watt With Lens		5-11
Porcelain Enamel Reflector With Lens - Pendant Mounted		5-11
Porcelain Enamel Reflector - Vaportite - Surface Mounted		5-12
Porcelain Enamel Reflector - Vaportite - Pendant Mounted		5-12
High Bay with Prismatic Lens - Pendant Mounted		5-12
Outdoor Ground Mtd Fixture W/ Spikes		5-12






## Section 5 - Lighting Fixtures, Poles and Parking Lot Lighting Table of Contents

Swimming Pool & Fountain Lighting - Wet Niche Fixtures	<b>(Updated)</b>	5-12
Swimming Pool & Fountain Lighting - Dry Niche Fixtures	<b>(Updated)</b>	5-12
Recessed Fountain Fixtures	<b>(Updated)</b>	5-12
Submerged Fountain Fixtures	<b>(Updated)</b>	5-12
Post Top Mounted	<b>(Updated)</b>	5-13
Showroom Stage & Auditorium Fixtures - Recessed Fixtures Hi-Ceiling		5-13
Showroom Stage & Auditorium Fixtures - Surface Mounted Spot or Flood	<b>(Updated)</b>	5-13
Showroom Stage & Auditorium Fixtures - Stage Footlight Troughs - 3 Color		5-13
Showroom Stage & Auditorium Fixtures - Stage Hanging Borderlights - 3 Color		5-13
Colored Lamps In Stage Troughs or Stage Borderlights		5-13
Showroom Stage & Auditorium Fixtures - Hardware		5-13
Chandelier - Incandescent or Similar		5-13
Decorative Outdoor Fixture - Wall Mounted		5-13
Decorative Outdoor Fixtures - Pendant or Chain Supported		5-14
Wall Mounted Incandescent		5-14
Pendant Mounted Incandescent		5-14
Bollard Lights 36 Inch High (Round or Square)		5-14
Bollard Lights 42 Inch High (Round or Square)	<b>(Updated)</b>	5-14
Concrete Bases for Bollards:		5-14
Landscape Lighting - DC & AC Voltages	<b>(Updated)</b>	5-14
Parking Lot Lighting - Pre-Cast Concrete Bases w/ Hole and Gravel Fill		5-14
Parking Lot Lighting - Cast-In-Place Base		5-14
Walkway Lighting - Steel and Aluminum Poles		5-14
Parking Lot Lighting - Steel and Aluminum Poles		5-15
Parking Lot Lighting - Shoe Box		5-15
Parking Lot Lighting - Post Top		5-15
Parking Lot Lighting Accessories		5-15
Walk Way Lighting - Post Mounted H.I.D. Fixture		5-15
Walk Way Lighting - Hollow Wood Posts - Direct Bury		5-15
Walk Way Lighting - Concrete Posts - Direct Bury		5-15
Walk Way Lighting		5-15
Explosion Proof Fixtures: Fluorescent		5-15
Explosion Proof Fixtures: Incandescent		5-15
Explosion Proof Fixtures: H.I.D.		
Explosion Proof Fixtures: Guards		5-16
Industrial Vaportite Surface Mounted Lampholders		5-16
Industrial Vaportite Pendant Mounted Lampholders		5-16
Lamps	<b>(Updated)</b>	5-16
Fluorescent Ballast	<b>(Updated)</b>	5-16
RFI Filters		5-16
Remote Ballast		5-16
Retro-Fit		5-16
Remove and Package for Disposal		5-17
Socket Replacement		5-17
Lens Replacement	<b>(Updated)</b>	5-17
Remove and Package for Disposal		5-17
Fixture Cleaning		5-17
Lens Cleaning		5-17

Section 5 - Lighting Fixtures, Poles and Parking Lot Lighting


Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Lighting Fixtures 2' x 2' Surface Mount</b>						
 2 Lamp - Fluorescent		0.65	0.81	1.02		E
3 Lamp - Fluorescent		0.70	0.86	1.07		E
4 Lamp - Fluorescent		0.75	0.94	1.17		E
LED		0.70	0.86	1.07		E
<b>Lighting Fixtures 2' x 4' Surface Mount</b>						
2 Lamp - Fluorescent		0.75	0.91	1.12		E
3 Lamp - Fluorescent		0.80	0.86	1.17		E
4 Lamp - Fluorescent		0.85	1.04	1.27		E
LED		0.80	0.86	1.17		E
<b>Surface Mounted Light Fixture</b>						
24" Long 1-Lamp Fluorescent		0.65	0.81	1.02		E
24" Long 2-Lamp Fluorescent		0.70	0.86	1.08		E
24" Long 3-Lamp Fluorescent		0.80	1.00	1.25		E
24" Long 4-Lamp Fluorescent		0.90	1.13	1.41		E
24" Long - LED		0.75	0.94	1.18		E
36" Long 1-Lamp Fluorescent		0.70	0.88	1.09		E
36" Long 2-Lamp Fluorescent		0.75	0.94	1.17		E
36" Long 3-Lamp Fluorescent		0.85	1.06	1.33		E
36" Long 4-Lamp Fluorescent		0.95	1.19	1.48		E
36" Long - LED		0.80	1.00	1.25		E
48" Long 1-Lamp Fluorescent		0.80	1.00	1.25		E
48" Long 2-Lamp Fluorescent		0.85	1.06	1.33		E
48" Long 3-Lamp Fluorescent		0.95	1.19	1.48		E
48" Long 4-Lamp Fluorescent		1.05	1.31	1.64		E
48" Long - LED		0.90	1.13	1.40		E
72" Long 1-Lamp Fluorescent		0.95	1.19	1.48		E
72" Long 2-Lamp Fluorescent		1.00	1.25	1.56		E
72" Long 3-Lamp Fluorescent		1.10	1.38	1.72		E
72" Long 4-Lamp Fluorescent		1.15	1.44	1.80		E
72" Long 6-Lamp Fluorescent		1.25	1.56	1.95		E
72" Long - LED		1.10	1.38	1.72		E
96" Long 1-Lamp Fluorescent		1.05	1.31	1.64		E
96" Long 2-Lamp Fluorescent		1.10	1.38	1.72		E
96" Long 3-Lamp Fluorescent		1.15	1.44	1.80		E
96" Long 4-Lamp Fluorescent		1.20	1.50	1.88		E
96" Long 6-Lamp Fluorescent		1.30	1.63	2.03		E
96" Long - LED		1.15	1.44	1.80		E
<b>Wrap Around Light Fixture</b>						
24" Long 2-Lamp - Fluorescent		0.60	0.75	0.94		E
48" Long 2-Lamp - Fluorescent		0.65	0.81	1.02		E
48" Long 3-Lamp - Fluorescent		0.70	0.88	1.09		E
48" Long 4-Lamp - Fluorescent		0.75	0.94	1.17		E
24" - LED	X	0.60	0.75	0.94		E
48" - LED	X	0.65	0.81	1.02		E
<b>Surface Mount Vaportite - Indoor / Outdoor</b>						
24" Long 1-Lamp - Fluorescent	X	1.30	1.63	2.03		E
24" Long 2-Lamp - Fluorescent	X	1.35	1.69	2.11		E
24" Long LED	X	0.95	1.19	1.48		E
36" Long 1-Lamp - Fluorescent	X	1.40	1.75	2.19		E
36" Long 2-Lamp - Fluorescent	X	1.45	1.81	2.27		E
48" Long 1-Lamp - Fluorescent	X	1.50	1.88	2.34		E
48" Long 2-Lamp - Fluorescent	X	1.55	1.94	2.42		E
48" Long 3-Lamp - Fluorescent	X	1.60	2.00	2.50		E
48" Long 4-Lamp - Fluorescent	X	1.65	2.06	2.58		E
48" Long LED	X	1.20	1.50	1.88		E
96" Long 1-Lamp - Fluorescent	X	2.00	2.50	3.13		E
96" Long 2-Lamp - Fluorescent	X	2.05	2.56	3.20		E
96" Long 3-Lamp - Fluorescent	X	2.10	2.63	3.28		E
96" Long 4-Lamp - Fluorescent	X	2.15	2.69	3.36		E
<b>Lay-in (T-Bar) Fixtures - w/ Lens</b>						
1' X 4' 2-Lamp - Fluorescent		0.65	0.81	1.02		E
1' X 4' - LED		0.65	0.81	1.02		E
2' X 2' 2-Lamp - Fluorescent		0.60	0.75	0.94		E
2' X 2' 3-Lamp - Fluorescent		0.65	0.81	1.02		E
2' X 2' - LED		0.60	0.75	0.94		E
2' X 4' 2-Lamp - Fluorescent		0.70	0.88	1.09		E
2' X 4' 3-Lamp - Fluorescent		0.75	0.94	1.17		E
2' X 4' 4-Lamp - Fluorescent		0.80	1.00	1.25		E
2' X 4' - LED		0.75	0.94	1.17		E
Master to Slave Whip Adder (per Fixture)		0.10	0.13	0.16		E
Slave Fixture Labor Deduct (per Fixture)		-0.15	-0.19	-0.23		E

Section 5 - Lighting Fixtures, Poles and Parking Lot Lighting

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Fluorescent Lay-in Parabolic Fixtures</b>						
 1' X 4' 2-Lamp		0.85	1.06	1.33		E
2' X 2' 2-Lamp		0.80	1.00	1.25		E
2' X 2' 3-Lamp		0.85	1.06	1.33		E
2' X 2' 4-Lamp		0.90	1.13	1.41		E
2' X 4' 2-Lamp		0.90	1.13	1.41		E
2' X 4' 3-Lamp		0.95	1.19	1.48		E
2' X 4' 4-Lamp		1.00	1.25	1.56		E
<b>Fluorescent Lay-in Paracube Fixtures</b>						
 1' X 4' 2-Lamp		0.85	1.06	1.33		E
2' X 2' 2-Lamp		0.80	1.00	1.25		E
2' X 2' 3-Lamp		0.85	1.06	1.33		E
2' X 2' 4-Lamp		0.90	1.13	1.41		E
2' X 4' 2-Lamp		0.90	1.13	1.41		E
2' X 4' 3-Lamp		0.95	1.19	1.48		E
2' X 4' 4-Lamp		1.00	1.25	1.56		E
<b>Recess Mounted Gyp Bd Ceiling</b>						
 1' X 4' Trim Kit Accessory		0.50	0.63	0.78		E
2' X 2' Trim Kit Accessory		0.50	0.63	0.78		E
2' X 4' Trim Kit Accessory		0.60	0.75	0.94		E
1' X 4' 1-Lamp - Fluorescent		0.95	1.19	1.48		E
1' X 4' 2-Lamp - Fluorescent		1.00	1.25	1.56		E
1' X 4' - LED		0.95	1.19	1.48		E
2' X 2' 2-Lamp - Fluorescent		0.95	1.19	1.48		E
2' X 2' 3-Lamp - Fluorescent		1.00	1.25	1.56		E
2' X 2' 4-Lamp - Fluorescent		1.05	1.31	1.64		E
2' X 2' - LED		1.00	1.25	1.56		E
2' X 4' 2-Lamp - Fluorescent		1.05	1.31	1.64		E
2' X 4' 3-Lamp - Fluorescent		1.10	1.38	1.72		E
2' X 4' 4-Lamp - Fluorescent		1.15	1.44	1.80		E
2' X 4' - LED		1.10	1.38	1.72		E
<b>Recessed Mounted Vaportite Gyp Bd Ceiling</b>						
 1' X 4' Trim Kit Accessory		0.50	0.63	0.78		E
2' X 2' Trim Kit Accessory		0.50	0.63	0.78		E
2' X 4' Trim Kit Accessory		0.60	0.75	0.94		E
24" Long 1-Lamp		1.10	1.38	1.72		E
24" Long 2-Lamp		1.15	1.44	1.80		E
36" Long 1-Lamp		1.20	1.50	1.88		E
36" Long 2-Lamp		1.25	1.56	1.95		E
48" Long 1-Lamp		1.35	1.69	2.11		E
48" Long 2-Lamp		1.40	1.75	2.19		E
48" Long 3-Lamp		1.45	1.81	2.27		E
48" Long 4-Lamp		1.50	1.88	2.34		E
96" Long 1-Lamp		2.15	2.69	3.36		E
96" Long 2-Lamp		2.20	2.75	3.44		E
96" Long 3-Lamp		2.25	2.81	3.52		E
96" Long 4-Lamp		2.30	2.88	3.59		E
48" - LED	X	1.40	1.75	2.19		E
<b>Linear : Pendant, Stem or Aircraft Cable Mounted</b>						
 36" Long 1-Lamp - Fluorescent		1.00	1.25	1.56		E
36" Long 2-Lamp - Fluorescent		1.05	1.31	1.64		E
36" Long 3-Lamp - Fluorescent		1.10	1.38	1.72		E
36" Long 4-Lamp - Fluorescent		1.20	1.50	1.88		E
36" Long LED		1.05	1.31	1.64		E
48" Long 1-Lamp - Fluorescent		1.10	1.38	1.72		E
48" Long 2-Lamp - Fluorescent		1.15	1.44	1.80		E
48" Long 3-Lamp - Fluorescent		1.20	1.50	1.88		E
48" Long 4-Lamp - Fluorescent		1.25	1.56	1.95		E
48" Long LED		1.15	1.44	1.80		E
72" Long 1-Lamp - Fluorescent		1.35	1.69	2.11		E
72" Long 2-Lamp - Fluorescent		1.40	1.75	2.19		E
72" Long 3-Lamp - Fluorescent		1.45	1.81	2.27		E
72" Long LED		1.40	1.75	2.19		E
72" Long 4-Lamp - Fluorescent		1.50	1.88	2.34		E
96" Long 1-Lamp - Fluorescent		1.60	2.00	2.50		E
96" Long 2-Lamp - Fluorescent		1.65	2.06	2.58		E
96" Long 4-Lamp - Fluorescent		1.75	2.19	2.73		E
96" Long 6-Lamp - Fluorescent		1.85	2.31	2.89		E
96" Long LED		1.65	2.06	2.58		E












Section 5 - Lighting Fixtures, Poles and Parking Lot Lighting

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Industrial - Chain Hung Suspended from Ceiling</b>						
 24" Long 1-Lamp		0.60	0.75	0.94		E
24" Long 2-Lamp		0.65	0.81	1.02		E
36" Long 1-Lamp		0.70	0.88	1.09		E
36" Long 2-Lamp		0.75	0.94	1.17		E
48" Long 1-Lamp		0.80	1.00	1.25		E
48" Long 2-Lamp		0.85	1.06	1.33		E
48" Long 3-Lamp		0.90	1.13	1.41		E
48" Long 4-Lamp		0.95	1.19	1.48		E
72" Long 1-Lamp		1.00	1.25	1.56		E
72" Long 2-Lamp		1.05	1.31	1.64		E
72" Long 3-Lamp		1.10	1.38	1.72		E
72" Long 4-Lamp		1.15	1.44	1.80		E
96" Long 1-Lamp		1.15	1.44	1.80		E
96" Long 2-Lamp		1.20	1.50	1.88		E
96" Long 3-Lamp		1.25	1.56	1.95		E
96" Long 4-Lamp		1.30	1.63	2.03		E
24" Long - LED	X	0.65	0.81	1.02		E
48" Long - LED	X	0.85	1.06	1.33		E
96" Long - LED	X	1.20	1.50	1.88		E
24" Wire Guard		0.10	0.13	0.16		E
36" Wire Guard		0.12	0.15	0.19		E
48" Wire Guard		0.15	0.19	0.23		E
72" Wire Guard		0.18	0.23	0.28		E
96" Wire Guard		0.20	0.25	0.31		E
<b>Stem Mounted Vaportite</b>						
<b>Suspended from Ceiling (Includes Labor for Stems with Fixtures)</b>						
24" Long 1-Lamp		1.15	1.44	1.80		E
24" Long 2-Lamp		1.20	1.50	1.88		E
36" Long 1-Lamp		1.25	1.56	1.95		E
36" Long 2-Lamp		1.30	1.63	2.03		E
48" Long 1-Lamp		1.35	1.69	2.11		E
48" Long 2-Lamp		1.40	1.75	2.19		E
48" Long 3-Lamp		1.45	1.81	2.27		E
48" Long 4-Lamp		1.50	1.88	2.34		E
72" Long 1-Lamp		1.55	1.94	2.42		E
72" Long 2-Lamp		1.60	2.00	2.50		E
72" Long 3-Lamp		1.65	2.06	2.58		E
72" Long 4-Lamp		1.70	2.13	2.66		E
96" Long 1-Lamp		1.60	2.00	2.50		E
96" Long 2-Lamp		1.65	2.06	2.58		E
96" Long 3-Lamp		1.70	2.13	2.66		E
96" Long 4-Lamp		1.75	2.19	2.73		E
24" Long - LED	X	1.20	1.50	1.88		E
48" Long - LED	X	1.40	1.75	2.19		E
98" Long - LED	X	1.65	2.06	2.58		E
<b>Under Counter Lights</b>						
18" - Fluorescent		0.80	1.00	1.25		E
24" - Fluorescent		0.80	1.00	1.25		E
36" - Fluorescent		0.90	1.13	1.41		E
48" - Fluorescent		0.90	1.13	1.41		E
18" - LED	X	0.80	1.00	1.25		E
24" - LED	X	0.80	1.00	1.25		E
36" - LED	X	0.90	1.13	1.41		E
48" - LED	X	0.90	1.13	1.41		E
LED Remote Driver	X	0.50	0.63	0.78		E
<b>Commercial Grade Wall or Cove Mounted</b>						
18" Long 1-Lamp		0.65	0.81	1.02		E
18" Long 2-Lamp		0.70	0.88	1.09		E
24" Long 1-Lamp		0.75	0.94	1.17		E
24" Long 2-Lamp		0.80	1.00	1.25		E
36" Long 1-Lamp		0.85	1.06	1.33		E
36" Long 2-Lamp		0.90	1.13	1.41		E
48" Long 1-Lamp		0.95	1.19	1.48		E
48" Long 2-Lamp		1.00	1.25	1.56		E
48" Long 3-Lamp		1.05	1.31	1.64		E
48" Long 4-Lamp		1.10	1.38	1.72		E
72" Long 1-Lamp		1.10	1.38	1.72		E
72" Long 2-Lamp		1.15	1.44	1.80		E
72" Long 3-Lamp		1.20	1.50	1.88		E
72" Long 4-Lamp		1.25	1.56	1.95		E
96" Long 1-Lamp		1.20	1.50	1.88		E
96" Long 2-Lamp		1.25	1.56	1.95		E
96" Long 3-Lamp		1.30	1.63	2.03		E
96" Long 4-Lamp		1.35	1.69	2.11		E
12" Long - LED	X	0.60	0.75	0.94		E
24" Long - LED	X	0.80	1.00	1.25		E
36" Long - LED	X	0.90	1.13	1.41		E
48" Long - LED	X	1.00	1.25	1.56		E
60" Long - LED	X	1.10	1.38	1.72		E
LED Remote Driver	X	0.50	0.63	0.78		E
*** Note for Recessed Cove Lighting add 20% for Labor	X					

Section 5 - Lighting Fixtures, Poles and Parking Lot Lighting

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Surface Mount Strip</b>						
18" Long 1-Lamp		0.50	0.63	0.78		E
18" Long 2-Lamp		0.55	0.69	0.86		E
24" Long 1-Lamp		0.55	0.69	0.86		E
24" Long 2-Lamp		0.60	0.75	0.94		E
36" Long 1-Lamp		0.60	0.75	0.94		E
36" Long 2-Lamp		0.65	0.81	1.02		E
48" Long 1-Lamp		0.70	0.88	1.09		E
48" Long 2-Lamp		0.75	0.94	1.17		E
48" Long 3-Lamp		0.80	1.00	1.25		E
48" Long 4-Lamp		0.85	1.06	1.33		E
72" Long 1-Lamp		0.85	1.06	1.33		E
72" Long 2-Lamp		0.90	1.13	1.41		E
72" Long 3-Lamp		0.95	1.19	1.48		E
72" Long 4-Lamp		1.00	1.25	1.56		E
96" Long 1-Lamp		1.10	1.38	1.72		E
96" Long 2-Lamp		1.15	1.44	1.80		E
96" Long 3-Lamp		1.20	1.50	1.88		E
96" Long 4-Lamp		1.25	1.56	1.95		E
24" Long - LED	X	0.60	0.75	0.94		E
48" Long - LED	X	0.75	0.94	1.17		E
98" Long - LED	X	1.15	1.44	1.80		E
18" Wire Guard		0.10	0.13	0.16		E
24" Wire Guard		0.10	0.13	0.16		E
36" Wire Guard		0.10	0.13	0.16		E
48" Wire Guard		0.20	0.25	0.31		E
72" Wire Guard		0.20	0.25	0.31		E
96" Wire Guard		0.20	0.25	0.31		E
<b>Weatherproof Fluorescent Fixture - Outdoor</b>						
48" Long 1-Lamp		1.50	1.88	2.34		E
48" Long 2-Lamp		1.55	1.94	2.42		E
72" Long 1-Lamp		1.75	2.19	2.73		E
72" Long 2-Lamp		1.80	2.25	2.81		E
96" Long 1-Lamp		2.00	2.50	3.13		E
96" Long 2-Lamp		2.05	2.56	3.20		E
<b>Fixture Mounting Accessories</b>						
Quake Clips		0.15	0.19	0.23		E
Fixture Chain Set - 4 Foot	X	0.30	0.31	0.39		E
Aircraft Cable with Quick Grip Tensioner	X	0.25	0.31	0.39		E
Fixture Seismic Wire		0.25	0.31	0.39		E
Tek Screw to T-Bar		0.10	0.13	0.16		E
<b>Lighting Flex Whips - Pre-assembled</b>						
6' 3-Wire Flex Whip		0.25	0.31	0.39		E
6' 4-Wire Flex Whip		0.35	0.44	0.55		E
6' 5-Wire Flex Whip		0.35	0.44	0.55		E
<b>Modular Wiring System (MWS) Components - Pre-manufactured</b>						
Circuit Distributor Box		0.30	0.40	0.50		E
Cable Extender to 15'L		0.35	0.45	0.60		E
Cable Extender from 20'L to 35'L		0.45	0.55	0.70		E
Circuit Selector Unit		0.30	0.40	0.50		E
Switch or Receptacle Drop Cable		0.35	0.45	0.60		E
Power or Switching Tee		0.35	0.45	0.60		E
Splitter Splice		0.20	0.30	0.40		E
Standard Selector Cable		0.40	0.45	0.50		E
Fluorescent Ballast Disconnect		0.15	0.20	0.23		E
<b>Commercial Indoor Fixtures -</b>						
<b>Wall Mounted - Up To 150 Watt</b>						
1-Lamp		0.75	0.94	1.17		E
2-Lamp		1.00	1.25	1.56		E
LED	X	1.00	1.25	1.56		E
<b>Surface Mount - Up to 300 Watt</b>						
<b>Ceiling Mounted</b>						
150 Watt		1.00	1.25	1.56		E
200 Watt		1.50	1.88	2.34		E
300 Watt		2.00	2.50	3.13		E
LED	X	1.50	1.88	2.34		E
<b>Pendant Mount - Up to 150 Watt</b>						
1-Lamp		1.25	1.56	1.95		E
2-Lamp		1.50	1.88	2.34		E
<b>Pendant Mount - Up to 300 Watt</b>						
1-Lamp		1.50	1.88	2.34		E
2-Lamp		1.75	2.19	2.73		E

Section 5 - Lighting Fixtures, Poles and Parking Lot Lighting

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
	<b>Recessed Prewired Hi-Hat Fixt, Can Light or Downlight</b>					
150 Watt		1.25	1.56	1.95		E
300 Watt		1.50	1.88	2.34		E
500 Watt		1.75	2.19	2.73		E
1-Lamp Compact Fluorescent		1.25	1.56	1.95		E
2-Lamp Compact Fluorescent		1.70	2.13	2.66		E
LED	X	1.25	1.56	1.95		E
Ceiling Tile Cut Out		0.25	0.31	0.39		E
	<b>Porcelain Keyless Receptacles and Light Socket</b>					
		0.50	0.63	0.78		E
	<b>Pendent Mount</b>					
Incandescent - 1 Lamp	X	1.25	1.56	1.95		E
Incandescent - 2 Lamp	X	1.50	1.88	2.34		E
Fluorescent - 1 Lamp	X	1.50	1.88	2.34		E
Fluorescent - 2 Lamp	X	1.75	2.19	2.73		E
LED	X	1.75	2.19	2.73		E
	<b>Light Track</b>					
2' Length - Surface		1.00	1.25	1.56		E
4' Length - Surface		1.25	1.56	1.95		E
8' Length - Surface		1.50	1.88	2.34		E
12' Length - Surface		2.00	2.50	3.13		E
Coupling		0.30	0.38	0.47		E
Blank End Cap		0.30	0.38	0.47		E
Live End Feed		1.00	1.25	1.56		E
Cut Track		1.00	1.25	1.56		E
Ells		0.30	0.38	0.47		E
Tees		0.50	0.63	0.78		E
	<b>Recessed Housing</b>					
2' Length - Recessed		1.25	1.56	1.95		E
4' Length - Recessed		1.50	1.88	1.95		E
8' Length - Recessed		1.75	2.19	2.34		E
12' Length - Recessed		2.25	2.81	3.13		E
Recessed Housing Couplings		0.30	0.38	0.47		E
Recessed Housing Ells		0.30	0.38	0.47		E
Recessed Housing Tees		0.50	0.63	0.78		E
	<b>Rigid Pendant 1-10'</b>					
		1.50	1.88	2.34		E
<b>Cable Pendant</b>		1.25	1.56	1.95		E
<b>Track Mounted Fixture Head</b>	X	0.60	0.75	0.94		E
<b>Pendant Mounted Fixture Head</b>	X	1.00	1.25	1.56		E
<b>Aiming of Track Fixture</b>		0.50	0.63	0.78		E
	<b>Low Voltage Power Grid Lighting System</b>					
Grid Beam - Powered - 6'	X	1.50	1.88	2.34		E
Grid Beam - Powered - 8'	X	1.75	2.19	2.73		E
Grid Beam - Powered - 10'	X	2.00	2.50	3.13		E
Grid Beam - Powered - 12'	X	2.25	2.81	3.52		E
Grid Beam - Non-Powered - 6'	X	1.25	1.56	1.95		E
Grid Beam - Non-Powered - 8'	X	1.50	1.88	2.34		E
Grid Beam - Non-Powered - 10'	X	1.75	2.19	2.73		E
Grid Beam - Non-Powered - 12'	X	2.00	2.50	3.13		E
Grid - Elbow	X	0.30	0.38	0.47		E
Grid - Tee	X	0.50	0.63	0.78		E
Grid - Cross ("X")	X	0.50	0.63	0.78		E
Power Server / Power Supply	X	2.00	2.50	3.13		E
DC Grid Cable - to Fixture	X	0.35	0.44	0.55		E
DC Grid Cable - to Grid	X	0.25	0.31	0.39		E
DC Grid Cable - to Power Server	X	0.35	0.44	0.55		E
	<b>Wall Sconce / Vanity Light</b>					
Incandescent - 1 Lamp	X	1.00	1.25	1.56		E
Incandescent - 2 Lamp	X	1.25	1.56	1.95		E
Fluorescent - 1 Lamp	X	1.25	1.56	1.95		E
Fluorescent - 2 Lamp	X	1.50	1.88	2.34		E
LED	X	1.50	1.88	2.34		E
	<b>Health Care Lighting</b>					
Alert Sign (X-Ray In Use)	X	1.50	1.88	2.34		E
Patient Headwall Fixture	X	1.50	1.88	2.34		E
Patient Ambient / Exam / Reading Fixture	X	2.00	2.50	3.13		E
Patient Room Night Light / Step Light	X	0.75	0.94	1.17		E
Exam Fixture	X	4.00	5.00	6.25		E
Surgical Suite - Recessed 2x2	X	1.75	2.19	2.73		E
Surgical Suite - Recessed 2x4	X	2.00	2.50	3.13		E
X-Ray Illuminator	X	1.50	1.88	2.34		E

Section 5 - Lighting Fixtures, Poles and Parking Lot Lighting

5









Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Ceiling Fans</b>						
up to 36" Diameter Ceiling Fan	X	1.50	1.88	2.34		E
37"-48" Diameter Ceiling Fan	X	2.50	3.13	3.91		E
49"-55" Diameter Ceiling Fan	X	3.50	4.38	5.47		E
60" Diameter Ceiling Fan	X	4.50	5.63	7.03		E
72" Diameter Ceiling Fan	X	5.00	6.25	7.81		E
80" Diameter Ceiling Fan	X	6.00	7.50	9.38		E
<b>Ceiling Fans - Low Velocity</b>						
Low Velocity Ceiling Fan - Up to 12' Diameter	X	7.00	8.75	10.94		E
Low Velocity Ceiling Fan - 14-16' Diameter	X	9.00	11.25	14.06		E
Low Velocity Ceiling Fan - 18-20' Diameter	X	12.00	15.00	18.75		E
Low Velocity Ceiling Fan - 24' Diameter	X	16.00	20.00	25.00		E
Low Velocity Ceiling Fan - Remote Speed Controller	X	1.50	1.88	2.34		E
<b>High Bay Fixture Ultra- Efficient 2x4</b>						
T5 HO 6 Lamps	X	1.75	2.19	2.71		E
T8 HO 6 Lamps	X	1.85	2.31	2.89		E
LED	X	1.75	2.19	2.73		E
<b>Exit Fixtures</b>						
Surface Mount - Standard or LED		1.00	1.25	1.56		E
Pendant Mount - Standard or LED		1.50	1.88	2.34		E
Recessed Mount - Standard or LED		1.25	1.56	1.95		E
<b>Exit Fixtures - Edge Lit</b>						
Surface Mount - Standard or LED		1.50	1.88	2.34		E
Pendant Mount - Standard or LED		2.00	2.50	3.13		E
Recessed Mount - Standard or LED		1.75	2.19	2.73		E
<b>Exit Sign - Self Powered</b>						
		0.70	0.88	1.09		E
<b>Egress / Emergency Fixtures</b>						
Self Contained Dual Head		1.20	1.50	1.88		E
Remote Single Head		0.60	0.75	0.94		E
Remote Double Head		0.70	0.88	1.09		E
Recessed Emergency Fixtures		1.50	1.88	2.34		E
Emergency Ballasts - Field Installed		0.75	0.94	1.17		E
<b>Emergency Lighting Inverter Panels - up to 5000W</b>						
Small Emergency Lighting Inverter Panel - Surface Mtd		2.00	2.50	3.12		E
Small Emergency Lighting Inverter Panel - Recessed Mtd		2.50	3.13	3.91		E
Small Emergency Lighting Inverter Panel - Ceiling Mtd		3.00	3.75	4.69		E
<b>Power Pack w/ Dual Heads</b>						
36 Watt		1.10	1.38	1.72		E
54 Watt		1.30	1.63	2.03		E
80 Watt		1.40	1.75	2.19		E
110 Watt		1.50	1.88	2.34		E
160 Watt		1.70	2.13	2.66		E
200 Watt		1.90	2.38	2.97		E
Mounting Shelf		1.00	1.25	1.56		E
<b>Wall Packs - Wall Mounted</b>						
35 Watt H.I.D.		1.25	1.56	1.95		E
50 Watt H.I.D.		1.25	1.56	1.95		E
70 Watt H.I.D.		1.25	1.56	1.95		E
100 Watt H.I.D.		1.25	1.56	1.95		E
150 Watt H.I.D.		1.75	2.19	2.73		E
250 Watt H.I.D.		2.00	2.50	3.13		E
400 Watt H.I.D.		3.00	3.75	4.69		E
LED		1.25	1.56	1.95		E
<b>Bracket Mount - Wall Mounted</b>						
250 Watt H.I.D.		3.50	4.38	5.47		E
400 Watt H.I.D.		4.25	5.31	6.64		E
1000 Watt H.I.D.		5.00	6.25	7.81		E
1500 Watt H.I.D.		6.00	7.50	9.38		E
LED		3.50	4.38	5.47		E
Build Fixture Backing		1.50	1.88	2.34		E
<b>Surface Ceiling Mounted</b>						
70 Watt H.I.D.		1.50	1.88	2.34		E
100 Watt H.I.D.		1.50	1.88	2.34		E
150 Watt H.I.D.		2.00	2.50	3.13		E
250 Watt H.I.D.		2.50	3.13	3.91		E
400 Watt H.I.D.		3.50	4.38	5.47		E
1500 Watt H.I.D.		6.00	7.50	9.38		E

Section 5 - Lighting Fixtures, Poles and Parking Lot Lighting


Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Recessed H.I.D.</b>						
50 Watt H.I.D.		1.75	2.19	2.73		E
70 Watt H.I.D.		1.75	2.19	2.73		E
100 Watt H.I.D.		2.00	2.50	3.13		E
150 Watt H.I.D.		2.25	2.81	3.52		E
250 Watt H.I.D.		2.75	3.44	4.30		E
400 Watt H.I.D.		3.75	4.69	5.86		E
<b>Fluorescent High Bay Fixture Ultra- Efficient 6 Lamp HO</b>						
T5 HO Lamps		1.75	2.19	2.71		E
T8 HO Lamps		1.85	2.31	2.89		E
<b>High Bay Fixtures - Multi Vapor H.I.D Fixtures - 250 Watt - Without Lens</b>						
18" Reflector (25 Lb)		1.75	2.19	2.73		E
20" Reflector (35 Lb)		2.00	2.50	3.13		E
24" Reflector (45 Lb)		2.25	2.81	3.52		E
30" Reflector (55 Lb)		2.50	3.13	3.91		E
<b>High Bay Fixtures - Multi Vapor H.I.D Fixtures - 400 Watt - Without Lens</b>						
20" Reflector (40 Lb)		2.25	2.81	3.52		E
24" Reflector (50 Lb)		2.50	3.13	3.91		E
30" Reflector (60 Lb)		2.75	3.44	4.30		E
<b>High Bay Fixtures - Multi Vapor H.I.D Fixtures - 250 Watt - With Lens</b>						
18" Reflector (30 Lb)		2.00	2.50	3.13		E
20" Reflector (40 Lb)		2.25	2.81	3.52		E
24" Reflector (50 Lb)		2.50	3.13	3.91		E
<b>High Bay Fixtures - Multi Vapor H.I.D Fixtures - 400 Watt - With Lens</b>						
18" Reflector (35 Lb)		2.25	2.81	3.52		E
20" Reflector (45 Lb)		2.50	3.13	3.91		E
24" Reflector (55 Lb)		2.75	3.44	4.30		E
30" Reflector (65 Lb)		3.00	3.75	4.69		E
<b>High Bay Fixtures - Multi Vapor H.I.D Fixtures - 1000 Watt - With Lens</b>						
20" Reflector (50 Lb)		2.75	3.44	4.30		E
24" Reflector (60 Lb)		3.00	3.75	4.69		E
30" Reflector (70 Lb)		3.50	4.38	5.47		E
<b>Multi Vapor H.I.D. Fixtures - Twin Mounted</b>						
400 Watt Twin Fixture w/o Lens		4.00	5.00	6.25		E
400 Watt Twin Fixture with Lens		4.50	5.63	7.03		E
<b>Low Bay - Multi Vapor H.I.D. Fixtures - 250 Watt With Lens</b>						
18" Reflector (30 Lb)		1.85	2.31	2.89		E
20" Reflector (40 Lb)		2.00	2.50	3.13		E
24" Reflector (50 Lb)		2.25	2.81	3.52		E
30" Reflector (55 Lb)		2.50	3.13	3.91		E
<b>Low Bay - Multi Vapor H.I.D. Fixtures - 400 Watt With Lens</b>						
18" Reflector (35 Lb)		1.95	2.44	3.05		E
20" Reflector (45 Lb)		2.15	2.69	3.36		E
24" Reflector (55 Lb)		2.40	3.00	3.75		E
30" Reflector (65 Lb)		2.60	3.25	4.06		E
<b>Porcelain Enamel Reflector With Lens - Pendant Mounted</b>						
150 Watt		1.00	1.25	1.56		E
300 Watt		1.15	1.44	1.78		E
500 Watt		1.25	1.56	1.94		E
750 Watt		1.35	1.69	2.16		E
1000 Watt		1.50	1.88	2.38		E

Section 5 - Lighting Fixtures, Poles and Parking Lot Lighting


5

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>Porcelain Enamel Reflector - Vaportite - Surface Mounted</b>						
150 Watt		1.10	1.38	1.72		E
300 Watt		1.25	1.56	1.95		E
500 Watt		1.35	1.69	2.11		E
750 Watt		1.50	1.88	2.34		E
1000 Watt		1.75	2.19	2.73		E
 <b>Porcelain Enamel Reflector - Vaportite - Pendant Mounted</b>						
150 Watt		1.25	1.56	1.95		E
300 Watt		1.35	1.69	2.11		E
500 Watt		1.50	1.88	2.34		E
750 Watt		1.75	2.19	2.73		E
1000 Watt		2.00	2.50	3.13		E
 <b>High Bay with Prismatic Lens - Pendant Mounted</b>						
200 Watt		1.25	1.56	1.95		E
300 Watt		1.25	1.56	1.95		E
500 Watt		1.50	1.88	2.34		E
750 Watt		1.50	1.88	2.34		E
1000 Watt		1.75	2.19	2.73		E
1500 Watt		1.75	2.19	2.73		E
Pendant High Bay - Safety Cable or Chain Assembly		0.15	0.25	0.33		E
 <b>Outdoor Ground Mtd Fixture W/ Spikes</b>						
2' 1-Lamp - Fluorescent		0.75	0.94	1.17		E
3' 1-Lamp - Fluorescent		0.95	1.19	1.48		E
4' 1-Lamp - Fluorescent		1.20	1.50	1.88		E
LED - 14"		0.75	0.94	1.17		E
LED - 23"		0.75	0.94	1.17		E
 <b>Swimming Pool &amp; Fountain Lighting - Wet Niche Fixtures</b>						
100 Watt		2.00	2.50	3.13		E
300 Watt		2.25	2.81	3.52		E
500 Watt		2.50	3.13	3.91		E
750 Watt		2.75	3.44	4.30		E
LED	X	2.25	2.81	3.52		E
 <b>Swimming Pool &amp; Fountain Lighting - Dry Niche Fixtures</b>						
100 Watt		3.00	3.75	4.69		E
300 Watt		3.25	4.06	5.08		E
500 Watt		3.50	4.38	5.47		E
750 Watt		4.00	5.00	6.25		E
LED	X	3.25	4.06	5.08		E
 <b>Recessed Fountain Fixtures</b>						
100 Watt		3.00	3.75	4.69		E
300 Watt		3.25	4.06	5.08		E
750 Watt		3.75	4.69	5.86		E
LED	X	3.25	4.06	5.08		E
 <b>Submerged Fountain Fixtures</b>						
1-Lamp 100 Watt		1.00	1.25	1.56		E
1-Lamp 300 Watt		1.10	1.38	1.72		E
2-Lamp 100 Watt		1.20	1.50	1.88		E
2-Lamp 300 Watt		1.50	1.88	2.34		E
3-Lamp 100 Watt		1.60	2.00	2.50		E
3-Lamp 300 Watt		2.00	2.50	3.13		E
4-Lamp 100 Watt		2.25	2.81	3.52		E
4-Lamp 300 Watt		2.50	3.13	3.91		E
5-Lamp 100 Watt		2.75	3.44	4.30		E
5-Lamp 300 Watt		3.00	3.75	4.69		E
6-Lamp 100 Watt		3.50	4.38	5.47		E
6-Lamp 300 Watt		4.00	5.00	6.25		E
LED - 1 Head	X	1.00	1.25	1.56		E
LED - 2 Head	X	1.20	1.50	1.88		E
LED - 3 Head	X	1.60	2.00	2.50		E
LED - 4 Head	X	2.25	2.81	3.52		E
LED - 5 Head	X	2.75	3.44	4.30		E
LED - 6 Head	X	3.50	4.38	5.47		E

Section 5 - Lighting Fixtures, Poles and Parking Lot Lighting

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Post Top Mounted</b>						
 100 Watt	X	2.00	2.50	3.13		E
200 Watt	X	2.50	5.00	6.25		E
250 Watt		3.00	3.75	4.69		E
400 Watt		4.00	5.00	6.25		E
1000 Watt		6.00	7.50	9.38		E
1500 Watt		8.00	10.00	12.50		E
LED		4.00	5.00	6.25		E
Fixture Aiming	X	1.50	1.88	2.34		E
<b>Showroom Stage &amp; Auditorium Fixtures - Recessed Fixtures Hi-Ceiling</b>						
300 Watt		5.00	6.25	7.81		E
500 Watt		5.00	6.25	7.81		E
1000 Watt		7.00	8.75	10.94		E
1500 Watt		8.00	10.00	12.50		E
<b>Showroom Stage &amp; Auditorium Fixtures - Surface Mounted Spot or Flood</b>						
300 Watt		2.00	2.50	3.13		E
500 Watt		2.50	3.13	3.91		E
1000 Watt		3.50	4.38	5.47		E
1500 Watt		4.00	5.00	6.25		E
Safety Cable		0.50	0.63	0.78		E
Fixture Aiming	X	1.50	1.88	2.34		E
<b>Showroom Stage &amp; Auditorium Fixtures - Stage Footlight Troughs - 3 Color</b>						
6 Ft Long		6.00	7.50	9.38		E
8 Ft Long		7.00	8.75	10.94		E
10 Ft Long		8.00	10.00	12.50		E
12 Ft Long		10.00	12.50	15.63		E
16 Ft Long		12.00	15.00	18.75		E
20 Ft Long		14.00	17.50	21.88		E
<b>Showroom Stage &amp; Auditorium Fixtures - Stage Hanging Borderlights - 3 Color</b>						
6 Ft Long		8.00	10.00	12.50		E
8 Ft Long		9.00	11.25	14.06		E
10 Ft Long		10.00	12.50	15.63		E
12 Ft Long		12.00	15.00	18.75		E
16 Ft Long		14.00	17.50	21.88		E
20 Ft Long		16.00	20.00	25.00		E
<b>Colored Lamps In Stage Troughs or Stage Borderlights</b>						
Up to 300 Watt		0.20	0.25	0.31		E
<b>Showroom Stage &amp; Auditorium Fixtures - Hardware</b>						
10 Ft. Connector Strip Gutter		4.00	5.00	6.25		E
End Cap		0.50	0.63	0.78		E
Light Outlet		0.40	0.50	0.63		E
Power Feed Per Ckt.		0.50	0.63	0.78		E
Coupling		0.50	0.63	0.78		E
2" Pipe Batten		0.10	0.13	0.16		LF
Fixed Pendant Support		3.00	3.75	4.69		E
<b>Chandelier - Incandescent or Similar</b>						
8 Lamp or 25 Lb		16.00	20.00	25.00		E
12 Lamp or 50 Lb		20.00	25.00	31.25		E
16 Lamp or 75 Lb		24.00	30.00	37.50		E
20 Lamp or 100 Lb		30.00	37.50	46.88		E
24 Lamp or 150 Lb		36.00	45.00	56.25		E
30 Lamp or 200 Lb		48.00	60.00	75.00		E
36 Lamp or 300 Lb		60.00	75.00	93.75		E
<b>Decorative Outdoor Fixture - Wall Mounted</b>						
20 Lb		3.00	3.75	4.69		E
30 Lb		3.50	4.38	5.47		E
40 Lb		4.00	5.00	6.25		E
50 Lb		4.50	5.63	7.03		E
60 Lb		5.00	6.25	7.81		E
70 Lb		5.50	6.88	8.59		E
80 Lb		6.00	7.50	9.38		E
90 Lb		6.50	8.13	10.16		E
100 Lb		8.00	10.00	12.50		E

Section 5 - Lighting Fixtures, Poles and Parking Lot Lighting

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Decorative Outdoor Fixtures - Pendant or Chain Supported</b>						
 20 Lb		4.00	5.00	6.25		E
30 Lb		4.50	5.63	7.03		E
40 Lb		5.00	6.25	7.81		E
50 Lb		5.50	6.88	8.59		E
60 Lb		6.00	7.50	9.38		E
70 Lb		6.50	8.13	10.16		E
80 Lb		7.00	8.75	10.94		E
90 Lb		8.00	10.00	12.50		E
100 Lb		9.00	11.25	14.06		E
<b>Wall Mounted Incandescent</b>						
1-Lamp 200 Watt		1.00	1.25	1.56		E
1-Lamp 300 Watt		1.25	1.56	1.95		E
1-Lamp 500 Watt		1.50	1.88	2.34		E
2-Lamp 200 Watt/Lamp		1.25	1.56	1.95		E
2-Lamp 300 Watt/Lamp		1.50	1.88	2.34		E
2-Lamp 500 Watt/Lamp		1.75	2.19	2.73		E
<b>Pendant Mounted Incandescent</b>						
200 Watt		1.50	1.88	2.34		E
300 Watt		2.00	2.50	3.13		E
500 Watt		2.50	3.13	3.91		E
<b>Bollard Lights 36 Inch High (Round or Square)</b>						
Incandescent up to 150 Watt		1.40	1.75	2.19		E
H.I.D. 35 - 50 Watt		2.10	2.63	3.28		E
H.I.D. 70 - 100 Watt		2.25	2.81	3.52		E
H.I.D. 150 Watt		2.35	2.94	3.67		E
Fluorescent 1-PL26		1.20	1.50	1.88		E
Fluorescent 2-PL26		1.30	1.63	2.03		E
<b>Bollard Lights 42 Inch High (Round or Square)</b>						
Incandescent up to 150 Watt		1.45	1.81	2.27		E
H.I.D. 35 - 50 Watt		2.10	2.63	3.28		E
H.I.D. 70 - 100 Watt		2.30	2.88	3.59		E
H.I.D. 150 Watt		2.45	3.06	3.83		E
Fluorescent 1-PL26		1.65	2.06	2.58		E
Fluorescent 2-PL26		1.75	2.19	2.73		E
LED	X	2.00	2.50	3.13		E
<b>Concrete Bases for Bollards:</b>						
12"X12"X12"		2.20	2.75	3.44		E
18"X18"X18"		2.90	3.63	4.53		E
<b>Landscape Lighting - DC &amp; AC Voltages</b>						
Recessed in Earth	X	1.75	2.09	2.61		E
Spike Mounted		0.40	0.50	0.63		E
J-Box Mounted		1.00	1.25	1.56		E
50 watt Fiberglass or Aluminum WP Transformer		1.00	1.25	1.56		E
<b>Parking Lot Lighting - Pre-Cast Concrete Bases w/ Hole and Gravel Fill</b>						
18" X 36" Base		4.00	5.00	6.25		E
18" X 48" Base		4.50	5.63	7.03		E
18" X 60" Base		5.00	6.25	7.81		E
24" X 48" Base		5.00	6.25	7.81		E
24" X 60" Base		6.00	7.50	9.38		E
24" X 72" Base		7.00	8.75	10.94		E
24" X 84" Base		8.00	10.00	12.50		E
Ground Rod Installed In or Exterior to Concrete Base		1.00	1.25	1.56		E
<b>Parking Lot Lighting - Cast-In-Place Base</b>						
24" X 48" Base		12.00	15.00	18.75		E
24" X 60" Base		13.00	16.25	20.31		E
24" X 72" Base		15.00	18.75	23.44		E
24" X 84" Base		16.00	20.00	25.00		E
<b>Walkway Lighting - Steel and Aluminum Poles</b>						
8 Ft.		3.00	3.75	4.69		E
10 Ft.		3.25	4.06	5.08		E
12 Ft.		3.50	4.38	5.47		E
14 Ft.		4.00	5.00	6.25		E
15 Ft.		4.50	5.63	7.03		E



Section 5 - Lighting Fixtures, Poles and Parking Lot Lighting

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Parking Lot Lighting - Steel and Aluminum Poles</b>						
 5" X 16 Ft.		5.00	6.25	7.81		E
5" X 20 Ft.		6.00	7.50	9.38		E
5" X 24 Ft.		8.00	10.00	12.50		E
5" X 28 Ft.		8.50	10.63	13.28		E
5" X 32 Ft.		9.00	11.25	14.06		E
5" X 36 Ft.		9.50	11.88	14.84		E
6" X 40 Ft.		10.00	12.50	15.63		E
6" X 44 Ft.		13.00	16.25	20.31		E
8" X 48 Ft.		15.00	18.75	23.44		E
8" X 52 Ft.		17.00	21.25	26.56		E
8" X 60 Ft.		20.00	25.00	31.25		E
<b>Parking Lot Lighting - Shoe Box</b>						
150 Watt		2.00	2.50	3.13		E
250 Watt		3.00	3.75	4.69		E
400 Watt		4.00	5.00	6.25		E
1000 Watt		6.00	7.50	9.38		E
LED		3.00	3.75	4.69		E
<b>Parking Lot Lighting - Post Top</b>						
250 Watt		4.00	5.00	6.25		E
400 Watt		5.00	6.25	7.81		E
1000 Watt		8.00	10.00	12.50		E
LED		4.00	5.00	6.25		E
<b>Parking Lot Lighting Accessories</b>						
Pre-Wired Photo Cell		0.50	0.63	0.78		E
120V Receptacle		1.00	1.25	1.56		E
<b>Walk Way Lighting - Post Mounted H.I.D. Fixture</b>						
100 Watt		2.00	2.50	3.13		E
150 Watt		2.50	3.13	3.91		E
250 Watt		3.00	3.75	4.69		E
<b>Walk Way Lighting - Hollow Wood Posts - Direct Bury</b>						
10'		4.00	5.00	6.25		E
15'		4.50	5.63	7.03		E
18'		6.00	7.50	9.38		E
<b>Walk Way Lighting - Concrete Posts - Direct Bury</b>						
10'		6.00	7.50	9.38		E
15'		8.00	10.00	12.50		E
20'		10.00	12.50	15.63		E
<b>Walk Way Lighting</b>						
Fixture Aiming		1.50	1.88	2.34		E
<b>Explosion Proof Fixtures: Fluorescent</b>						
36" 1-Lamp		2.40	3.00	3.75		E
36" 2-Lamp		2.85	3.56	4.45		E
36" 3-Lamp		3.35	4.19	5.23		E
36" 4-Lamp		3.80	4.75	5.94		E
48" 1-Lamp		2.85	3.56	4.45		E
48" 2-Lamp		3.35	4.19	5.23		E
48" 3-Lamp		3.80	4.75	5.94		E
48" 4-Lamp		4.30	5.38	6.72		E
72" 1-Lamp		3.80	4.75	5.94		E
72" 2-Lamp		4.25	5.31	6.64		E
72" 3-Lamp		4.75	5.94	7.42		E
72" 4-Lamp		5.20	6.50	8.13		E
Surface Exit		1.50	1.88	2.34		E
<b>Explosion Proof Fixtures: Incandescent</b>						
100 Watt Wall Mount		1.35	1.69	2.11		E
300 Watt Wall Mount		1.55	1.94	2.42		E
500 Watt Wall Mount		1.75	2.19	2.73		E
100 Watt Ceiling Mount		1.45	1.81	2.27		E
300 Watt Ceiling Mount		1.65	2.06	2.58		E
500 Watt Ceiling Mount		1.85	2.31	2.89		E
100 Watt Pendant Mount		1.65	2.06	2.58		E
300 Watt Pendant Mount		1.85	2.31	2.89		E
500 Watt Pendant Mount		2.05	2.56	3.20		E

Section 5 - Lighting Fixtures, Poles and Parking Lot Lighting

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>Explosion Proof Fixtures: H.I.D.</b>						
250 Watt Wall Mount		2.50	3.13	3.91		E
400 Watt Wall Mount		2.90	3.63	4.53		E
1000 Watt Wall Mount		3.60	4.50	5.63		E
250 Watt Ceiling Mount		3.00	3.75	4.69		E
400 Watt Ceiling Mount		3.40	4.25	5.31		E
1000 Watt Ceiling Mount		4.00	5.00	6.25		E
100 Watt Reflectors		1.75	2.19	2.73		E
250 Watt Reflectors		1.90	2.38	2.97		E
400 Watt Reflectors		2.10	2.63	3.28		E
1000 Watt Reflectors		2.50	3.13	3.91		E
<b>Explosion Proof Fixtures: Guards</b>						
100 - 250 Watt		0.20	0.23	0.26		E
400 - 1000 Watt		0.25	0.28	0.30		E
<b>Industrial Vaportite Surface Mounted Lampholders</b>						
150 Watt W/O Metal Cover		0.68	0.85	1.06		E
300 Watt W/O Metal Cover		0.68	0.85	1.06		E
500 Watt W/O Metal Cover		0.78	0.98	1.22		E
150 Watt W/ Metal Cover		0.69	0.86	1.08		E
300 Watt W/ Metal Cover		0.78	0.98	1.22		E
500 Watt W/ Metal Cover		0.88	1.10	1.38		E
<b>Industrial Vaportite Pendant Mounted Lampholders</b>						
150 Watt W/O Metal Cover		0.77	0.96	1.20		E
300 Watt W/O Metal Cover		0.87	1.09	1.36		E
500 Watt W/O Metal Cover		0.96	1.20	1.50		E
150 Watt W/ Metal Cover		0.88	1.10	1.38		E
300 Watt W/ Metal Cover		0.97	1.21	1.52		E
500 Watt W/ Metal Cover		1.07	1.34	1.67		E
<b>Lamps</b>						
Incandescent up to 75w	X	0.08	0.10	0.13		E
Incandescent up to 100 to 300W	X	0.15	0.19	0.23		E
Fluorescent Tube - up to 36"	X	0.08	0.10	0.13		E
Fluorescent Tube - 48"	X	0.10	0.13	0.16		E
Fluorescent Tube - 72"-96"	X	0.14	0.18	0.22		E
Compact Fluorescent (Twin or Quad Tube)	X	0.05	0.06	0.08		E
Mercury Vapor / Metal Halide - up to 175W	X	0.14	0.18	0.22		E
Mercury Vapor / Metal Halide - 250 to 1000W	X	0.25	0.31	0.39		E
High Pressure Sodium - up to 100W	X	0.10	0.13	0.16		E
High Pressure Sodium - 150 to 250W	X	0.20	0.25	0.31		E
High Pressure Sodium - 400 to 1000W	X	0.30	0.38	0.47		E
<b>Fluorescent Ballast</b>						
2' Lamp	X	0.35	0.50	0.60		E
4' Lamp	X	0.50	0.50	0.60		E
8' Lamp	X	0.75	0.60	0.75		E
Dimming - 2' Lamp	X	0.45	0.56	0.70		E
Dimming - 4' Lamp	X	0.60	0.75	0.94		E
Dimming - 8' Lamp	X	0.90	1.13	1.41		E
Fluorescent Ballast Disconnect		0.15	0.20	0.23		E
<b>RFI Filters</b>						
Small		0.75	1.00	1.25		E
Large		1.25	1.65	2.10		E
<b>Remote Ballast</b>						
Fluorescent 4'		1.00	1.20	1.50		E
Fluorescent 8'		1.40	1.70	2.10		E
<b>Remote Ballast</b>						
HID Up to 150 Watt		1.25	1.50	1.90		E
HID Up to 400 Watt		1.75	2.10	2.60		E
HID Up to 1000 Watt		2.25	2.70	3.35		E
<b>Retro-Fit</b>						
4' Lamps		0.65	0.90	1.25		E
8' Lamps		0.70	1.00	1.20		E
<b>Retro-Fit</b>						
4' Ballast		0.45	0.65	0.85		E
8' Ballast		0.45	0.65	0.85		E

## Section 5 - Lighting Fixtures, Poles and Parking Lot Lighting

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Remove and Package for Disposal</b>						
4' Tube		0.15	0.18	0.22		E
8' Tube		0.20	0.24	0.30		E
<b>Remove and Package for Disposal</b>						
4' Ballast		0.40	0.50	0.60		E
8' Ballast		0.45	0.55	0.70		E
<b>Socket Replacement</b>						
2-PIN Fluorescent		0.25	0.30	0.40		E
Slimline or H.O.		0.30	0.36	0.45		E
Incandescent		0.35	0.42	0.50		E
HID		1.00	1.50	2.00		E
Quartz		1.00	1.50	2.00		E
<b>Lens Replacement</b>						
Flat Acrylic 1x4 Lens Replacement		0.15	0.20	0.25		E
Flat Acrylic 2x2 Lens Replacement		0.20	0.25	0.35		E
Flat Acrylic 2x 4 Lens Replacement		0.25	0.30	0.40		E
Flat Acrylic 4x 4 Lens Replacement		0.40	0.50	0.60		E
Paracube 1x4 Lens Replacement	X	0.25	0.40	0.50		E
Paracube 2x2 Lens Replacement	X	0.30	0.50	0.70		E
Paracube 2x4 Lens Replacement		0.40	0.60	0.90		E
Paracube 4x4 Lens Replacement		0.70	1.00	1.50		E
Parabolic 1x4 Lens Replacement		0.30	0.40	0.50		E
Parabolic 2x2 Lens Replacement		0.35	0.55	0.80		E
Parabolic 2x4 Lens Replacement		0.50	0.70	1.20		E
Parabolic 4x4 Lens Replacement		0.80	1.20	1.50		E
<b>Remove and Package for Disposal</b>						
4' Tube		0.15	0.18	0.22		E
8' Tube		0.20	0.24	0.30		E
4' Ballast		0.40	0.50	0.60		E
8' Ballast		0.45	0.55	0.70		E
<b>Fixture Cleaning</b>						
2x2		0.25	0.30	0.40		E
2x4		0.35	0.40	0.50		E
4x4		0.50	0.60	0.75		E
1x4 Strip		0.20	0.30	0.40		E
1x8 Strip		0.35	0.50	0.60		E
<b>Lens Cleaning</b>						
2x2		0.15	0.25	0.35		E
2x4		0.15	0.25	0.35		E
4x4		0.25	0.30	4.00		E



# SECTION 6

## WIRING DEVICES

### General Information

The labor units in this section include the installation of the wiring device in a box already in place and the termination of copper conductors on the wiring device. The labor units for wiring devices which are factory mounted in enclosures include the installation of the enclosure and the termination of copper conductors. When aluminum conductors are terminated on wiring devices the labor units in this section must be increased.

### Scope of These Labor Units

The Introduction section includes details on the scope of labor units across the manual. Some items included are:

- Drawing and specification study
- Layout, measuring and marking installation location
- Material unloading, storage and delivery to the installation area
- Tool acquisition and return to storage
- Device installation in appropriate boxes already in place
- Clean-up of electrical contractor furnished excess material and cardboard containers
- Normal non-productive labor

### Work Operations Not Included In These Labor Units

- Field supervision
- Wire or cable installation
- Clean-out boxes containing water, dirt, plaster, concrete, etc.
- Replacing devices damaged by other crafts
- Removing and reinstalling devices or covers due to painting or plastering
- Painting device boxes, enclosures, or covers
- Measurement and alignment more precise than normal industry standards

### Labor Adjustments for Non-Typical Conditions

See the Introduction section for details.

### Application Instructions

- The labor units in this section are based on the following 600-volt rated copper single conductor building wire types THHN, THWN, or RHW
  - #14 AWG for 15 Amp rated circuits and wiring devices
  - #12 AWG for 20 Amp rated circuits and wiring devices
  - #10 AWG for 30 Amp rated circuits and wiring devices
  - # 8 AWG for 50 Amp rated circuits and wiring devices
  - # 6 AWG for 60 Amp rated circuits and wiring devices
- The labor tables in this section do not identify the mechanical operation of the wiring device. For example, the labor units for general use snap switches are applicable for toggle, mercury, silent, pressure, lighted handle, key operated and other types when a large quantity is required. When only a few of these special types of switches are required, a minimum of one hour is usually required to install each special switch.
- The labor units in this section are based on the installation of specification grade wiring devices. When “competitive” grade wiring devices are used the labor units may need to be adjusted.
- The labor units for wall mounted items in this manual are based on wood screws being used to fasten the items to a wood surface installed by others. If a plywood surface is installed by the electrical contractor, a separate labor allowance must be added for the plywood installation. If other than wood screws are required to mount any item in this manual, a separate material cost and labor allowance must be added.




## Section 6 - Wiring Devices Table of Contents

Single Receptacle - Straight Blade or Twist Lock		6-5
Duplex Receptacle - Straight Blade	<b>(Updated)</b>	6-5
Split Wired Receptacle - Straight Blade		6-5
Plugtail Wired Receptacles-Straight Blade	<b>(Updated)</b>	6-5
Plugtail Wired Switches	<b>(Updated)</b>	6-5
Plugtail Connectors		6-5
Pin Type Circuit Breaking Polarized Receptacles		6-6
Pin Type Convenience Single Receptacle Outlet		6-6
Pedestal Receptacle Outlet		6-6
Switches, General Use Toggle Switches, Keyed Switches		6-6
Switch and Receptacle Combination - 20 Amp		6-7
Push Button Station NEMA-1 Non Assembled		6-7
Push Button Station NEMA-4 Non Assembled		6-7
Double Throw Switches - Maintained Contact 2 Circuit 3 Position		6-7
Manual Motor Starter 120/230 Volt AC - Box Mounted Toggle Switch W/O Enclosure		6-7
Manual Motor Starter W/ Enclosure		6-7
Dimmer Switch		6-7
Wiring Device Cover Plates		6-7
Wiring Device Cover Plates - Decorative & Engraved		6-7
Waterproof Covers		6-8
Floor Box Device Cover Plates		6-8
Time Clocks and Lighting Contactors	<b>(Updated)</b>	6-8
Photocell		6-8
Occupancy Sensors		6-8









## Section 6 - Wiring Devices

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Single Receptacle - Straight Blade or Twist Lock</b>						
 15 Amp 3 Wire		25.00	31.25	37.50		C
20 Amp 3 Wire		30.00	37.50	45.00		C
20 Amp 4 Wire		35.00	43.75	52.50		C
20 Amp 5 Wire		40.00	50.00	60.00		C
30 Amp 3 Wire		40.00	50.00	60.00		C
30 Amp 4 Wire		45.00	56.25	67.50		C
30 Amp 5 Wire		50.00	62.50	75.00		C
50 Amp 3 Wire		50.00	62.50	75.00		C
50 Amp 4 Wire		55.00	68.75	82.50		C
60 Amp 3 Wire		60.00	75.00	90.00		C
60 Amp 4 Wire		70.00	87.50	105.00		C
<b>Duplex Receptacle - Straight Blade</b>						
15 Amp 3 Wire		25.00	31.25	37.50		C
15 Amp GFCI or AFCI	X	30.00	37.50	45.00		C
20 Amp 3 Wire		30.00	37.50	45.00		C
20 Amp GFCI or AFCI	X	35.00	43.75	52.50		C
15 Amp 3 Wire with USB Ports	X	25.00	31.25	37.50		C
20 Amp 3 Wire with USB Ports	X	30.00	37.50	45.00		C
GFCI - Blank Face	X	30.00	37.50	45.00		C
<b>Split Wired Receptacle - Straight Blade</b>						
15 Amp 3 Wire		35.00	43.75	52.50		C
20 Amp 3 Wire		40.00	50.00	60.00		C
<b>Plugtail Wired Receptacles-Straight Blade</b>						
15 Amp 3 Wire	X	15.00	18.75	23.44		C
15 Amp GFCI	X	20.00	25.00	31.25		C
20 Amp 3 Wire	X	20.00	25.00	31.25		C
20 Amp GFCI	X	25.00	31.25	39.00		C
<b>Plugtail Wired Switches</b>						
15 Amp 1 pole	X	10.00	12.50	15.00		C
20 Amp 1 pole	X	15.00	18.75	22.50		C
15 Amp 2 pole		20.00	25.00	30.00		C
20 Amp 2 pole		25.00	31.25	37.50		C
15 Amp 3 Way		25.00	31.25	37.50		C
20 Amp 3 Way		30.00	37.50	45.00		C
15 Amp 4 Way		30.00	37.50	45.00		C
20 Amp 4 Way		35.00	43.75	52.50		C
<b>Plugtail Connectors</b>						
6" angle solid wire		10.00	12.50	15.00		C
6" stranded wire		10.00	12.50	15.00		C
6" angle solid wire with wago connector		10.00	12.50	15.00		C
6" angle stranded wire with wago connector		10.00	12.50	15.00		C

## Section 6 - Wiring Devices

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Pin Type Circuit Breaking Polarized Receptacles</b>						
 20 Amp 2 Wire (#12 AWG 20 Amp Circuit)		0.85	1.06	1.28		E
20 Amp 3 Wire (#12 AWG 20 Amp Circuit)		0.95	1.19	1.43		E
20 Amp 4 Wire (#12 AWG 20 Amp Circuit)		1.05	1.31	1.58		E
20 Amp 5 Wire (#12 AWG 20 Amp Circuit)		1.15	1.44	1.73		E
30 Amp 2 Wire (#10 AWG 30 Amp Circuit)		0.90	1.13	1.35		E
30 Amp 3 Wire (#10 AWG 30 Amp Circuit)		1.00	1.25	1.50		E
30 Amp 4 Wire (#10 AWG 30 Amp Circuit)		1.10	1.38	1.65		E
30 Amp 5 Wire (#10 AWG 30 Amp Circuit)		1.20	1.50	1.80		E
60 Amp 2 Wire (#8 AWG 50 Amp Circuit)		1.15	1.44	1.73		E
60 Amp 3 Wire (#8 AWG 50 Amp Circuit)		1.30	1.63	1.95		E
60 Amp 4 Wire (#8 AWG 50 Amp Circuit)		1.45	1.81	2.18		E
60 Amp 5 Wire (#8 AWG 50 Amp Circuit)		1.60	2.00	2.40		E
60 Amp 2 Wire (#6 AWG 60 Amp Circuit)		1.40	1.75	2.10		E
60 Amp 3 Wire (#6 AWG 60 Amp Circuit)		1.60	2.00	2.40		E
60 Amp 4 Wire (#6 AWG 60 Amp Circuit)		1.80	2.25	2.70		E
60 Amp 5 Wire (#6 AWG 60 Amp Circuit)		2.00	2.50	3.00		E
100 Amp 2 Wire (#4 AWG 75 Amp Circuit)		1.65	2.06	2.48		E
100 Amp 3 Wire (#4 AWG 75 Amp Circuit)		1.85	2.31	2.78		E
100 Amp 4 Wire (#4 AWG 75 Amp Circuit)		2.00	2.50	3.00		E
100 Amp 5 Wire (#4 AWG 75 Amp Circuit)		2.25	2.81	3.38		E
100 Amp 2 Wire (#2 AWG 75 Amp Circuit)		2.00	2.50	3.00		E
100 Amp 3 Wire (#2 AWG 75 Amp Circuit)		2.25	2.81	3.38		E
100 Amp 4 Wire (#2 AWG 75 Amp Circuit)		2.50	3.13	3.75		E
100 Amp 5 Wire (#2 AWG 75 Amp Circuit)		2.75	3.44	4.13		E
200 Amp 2 Wire (#1 AWG 125 Amp Circuit)		2.50	3.13	3.75		E
200 Amp 3 Wire (#1 AWG 125 Amp Circuit)		2.75	3.44	4.13		E
200 Amp 4 Wire (#1 AWG 125 Amp Circuit)		3.00	3.75	4.50		E
200 Amp 5 Wire (#1 AWG 125 Amp Circuit)		3.25	4.06	4.88		E
200 Amp 2 Wire (1/0 AWG 150 Amp Circuit)		2.75	3.44	4.13		E
200 Amp 3 Wire (1/0 AWG 150 Amp Circuit)		3.25	4.06	4.88		E
200 Amp 4 Wire (1/0 AWG 150 Amp Circuit)		3.75	4.69	5.63		E
200 Amp 5 Wire (1/0 AWG 150 Amp Circuit)		4.25	5.31	6.38		E
200 Amp 2 wire (2/0 AWG 175 Amp Circuit)		3.00	3.75	4.50		E
200 Amp 3 wire (2/0 AWG 175 Amp Circuit)		3.50	4.38	5.25		E
200 Amp 4 wire (2/0 AWG 175 Amp Circuit)		4.00	5.00	6.00		E
200 Amp 5 wire (2/0 AWG 175 Amp Circuit)		4.50	5.63	6.75		E
200 Amp 2 Wire (3/0 AWG 200 Amp Circuit)		3.50	4.38	5.25		E
200 Amp 3 Wire (3/0 AWG 200 Amp Circuit)		4.00	5.00	6.00		E
200 Amp 4 Wire (3/0 AWG 200 Amp Circuit)		4.50	5.63	6.75		E
200 Amp 5 Wire (3/0 AWG 200 Amp Circuit)		5.00	6.25	7.50		E
<b>Pin Type Convenience Single Receptacle Outlet</b>						
 2-Wire 10 Amp		0.60	0.75	0.90		E
2-Wire 15 Amp		0.65	0.81	0.98		E
2-Wire 20 Amp		0.70	0.88	1.05		E
3-Wire 10 Amp		0.70	0.88	1.05		E
3-Wire 15 Amp		0.75	0.94	1.13		E
3-Wire 20 Amp		0.80	1.00	1.20		E
3-Wire 30 Amp		0.90	1.13	1.35		E
4-Wire 10 Amp		0.80	1.00	1.20		E
4-Wire 15 Amp		0.85	1.06	1.28		E
4-Wire 20 Amp		0.90	1.13	1.35		E
4-Wire 30 Amp		1.00	1.25	1.50		E
5-Wire 20 Amp		1.10	1.38	1.65		E
6-Wire 20 Amp		1.20	1.50	1.80		E
<b>Pedestal Receptacle Outlet</b>						
 3-Wire 15 Amp		0.40	0.50	0.60		E
3-Wire 20 Amp		0.45	0.56	0.68		E
3-Wire 30 Amp		0.50	0.63	0.75		E
3-Wire 50 Amp		0.70	0.88	1.05		E
3-Wire 60 Amp		0.90	1.13	1.35		E
4-Wire 15 Amp		0.50	0.63	0.75		E
4-Wire 20 Amp		0.55	0.69	0.83		E
4-Wire 30 Amp		0.60	0.75	0.90		E
4-Wire 50 Amp		0.80	1.00	1.20		E
4-Wire 60 Amp		1.00	1.25	1.50		E
<b>Switches, General Use Toggle Switches, Keyed Switches</b>						
 1-Pole 15 Amp		20.00	25.00	30.00		C
1-Pole 20 Amp		25.00	31.25	37.50		C
1-Pole 30 Amp		30.00	37.50	45.00		C
2-Pole 15 Amp		30.00	37.50	45.00		C
2-Pole 20 Amp		35.00	43.75	52.50		C
2-Pole 30 Amp		40.00	50.00	60.00		C
3-Way 15 Amp		35.00	43.75	52.50		C
3-Way 20 Amp		40.00	50.00	60.00		C
3-Way 30 Amp		45.00	56.25	67.50		C
4-Way 15 Amp		40.00	50.00	60.00		C
4-Way 20 Amp		45.00	56.25	67.50		C
4-Way 30 Amp		50.00	62.50	75.00		C

## Section 6 - Wiring Devices

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
						
<b>Switch and Receptacle Combination - 20 Amp</b>						
Single Pole		25.00	31.25	37.50		C
Double Pole		35.00	43.75	52.50		C
Three-Way		40.00	50.00	60.00		C
Four-Way		45.00	56.25	67.50		C
						
<b>Push Button Station NEMA-1 Non Assembled (Button, Sel. Sw., Pilot Lt., Contact Block &amp; Legend Plate)</b>						
1-Button		1.00	1.25	1.50		E
2-Button		1.30	1.63	1.95		E
3-Button		1.60	2.00	2.40		E
4-Button		2.00	2.50	3.00		E
5-Button		2.50	3.13	3.75		E
6-Button		3.00	3.75	4.50		E
						
<b>Push Button Station NEMA-4 Non Assembled (Button, Sel. Sw., Pilot Lt., Contact Block &amp; Legend Plate)</b>						
1-Button		1.30	1.63	1.95		E
2-Button		1.60	2.00	2.40		E
3-Button		2.00	2.50	3.00		E
4-Button		2.50	3.13	3.75		E
5-Button		3.00	3.75	4.50		E
6-Button		3.50	4.38	5.25		E
						
<b>Double Throw Switches Maintained Contact 2 Circuit 3 Position</b>						
1-Pole 10 Amp		0.35	0.44	0.53		E
1-Pole 15 Amp		0.35	0.44	0.53		E
1-Pole 20 Amp		0.35	0.44	0.53		E
2-Pole 10 Amp		0.50	0.63	0.75		E
2-Pole 15 Amp		0.50	0.63	0.75		E
2-Pole 20 Amp		0.50	0.63	0.75		E
						
<b>Manual Motor Starter 120/230 Volt AC Box Mounted Toggle Switch W/O Enclosure</b>						
1-Pole 1/4HP		0.30	0.38	0.45		E
1-Pole 1/2HP		0.35	0.44	0.53		E
1-Pole 1HP		0.40	0.50	0.60		E
2-Pole 1/4HP		0.35	0.44	0.53		E
2-Pole 1/2HP		0.40	0.50	0.60		E
2-Pole 1HP		0.45	0.56	0.68		E
3-Pole 1/2HP		0.40	0.50	0.60		E
3-Pole 1HP		0.45	0.56	0.68		E
3-Pole 2HP		0.50	0.63	0.75		E
						
<b>Manual Motor Starter W/ Enclosure</b>						
1-Pole 1/4 HP		0.55	0.69	0.83		E
1-Pole 1/2 HP		0.60	0.75	0.90		E
1-Pole 1 HP		0.65	0.81	0.98		E
2-Pole 1/4 HP		0.60	0.75	0.90		E
2-Pole 1/2 HP		0.65	0.81	0.98		E
2-Pole 1 HP		0.70	0.88	1.05		E
3-Pole 1/4 HP		0.65	0.81	0.98		E
3-Pole 1/2 HP		0.70	0.88	1.05		E
3-Pole 1 HP		0.75	0.94	1.13		E
						
<b>Dimmer Switch</b>						
1-Pole 600 Watt		0.40	0.50	0.60		E
1-Pole 1000 Watt		0.50	0.63	0.75		E
1 Pole - 1500 Watt		0.55	0.69	0.83		E
1 Pole - 2000 Watt		0.60	0.75	0.90		E
3-Way 600 Watt		0.70	0.88	1.05		E
3-Way 1000 Watt		0.85	1.06	1.28		E
3 Way - 1500 Watt		0.85	1.06	1.28		E
3 Way - 2000 Watt		0.90	1.13	1.35		E
						
<b>Wiring Device Cover Plates</b>						
1-Gang		10.00	12.50	15.00		C
2-Gang		12.00	15.00	18.00		C
3-Gang		14.00	17.50	21.00		C
4-Gang		17.00	21.25	25.50		C
5-Gang		20.00	25.00	30.00		C
6-Gang		24.00	30.00	36.00		C
						
<b>Wiring Device Cover Plates - Decorative &amp; Engraved</b>						
1-Gang		20.00	25.00	30.00		C
2-Gang		25.00	31.25	37.50		C
3-Gang		30.00	37.50	45.00		C
4-Gang		35.00	43.75	52.50		C
50 & 60 Amp Single Receptacle Cover Plates		25.00	31.25	37.50		C
Telephone TV & Blank Cover Plates		12.00	15.00	18.00		C

## Section 6 - Wiring Devices

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Waterproof Covers</b>						
 1G Vertical In-Use Cover		20.00	25.00	30.00		C
1G Horizontal In-Use Cover		20.00	25.00	30.00		C
2G In-Use Cover		25.00	31.25	37.50		C
WP Blank Bell Cover		10.00	12.50	15.00		C
WP 1G SW Bell Cover		12.00	15.00	18.00		C
WP Duplex Vertical Bell Cover		12.00	15.00	18.00		C
WP Duplex Horizontal Bell Cover		12.00	15.00	18.00		C
WP 2G Blank Bell Cover		13.00	16.25	19.50		C
WP 2G SW/Receptacle Bell Cover		14.00	17.50	21.00		C
WP 2G SW/SW Bell Cover		14.00	17.50	21.00		C
WP Vertical GFCI Bell Cover		15.00	18.75	22.50		C
WP Horizontal GFCI Bell Cover		15.00	18.75	22.50		C
<b>Floor Box Device Cover Plates</b>						
1-Gang		20.00	25.00	30.00		C
2-Gang		30.00	37.50	45.00		C
3-Gang		40.00	50.00	60.00		C
4-Gang		50.00	62.50	75.00		C
<b>Time Clocks and Lighting Contactors</b>						
120 Volt 24-Hour timer, multi-pole	X	1.60	2.00	2.50		E
120 Volt 24Hr- Programmable Astronomical Switch	X	2.25	2.81	3.52		E
Lighting Contactor up to 4 Pole	X	0.80	1.00	1.25		E
Lighting Contactor: 6-8 Pole	X	1.25	1.56	1.95		E
****Note: Labor units for contactors do not include enclosure if applicable	X					
****Note: For an expanded list of lighting contractors refer to Section 4	X					
<b>Photocell</b>						
Photocell Relay - Fixture Mounted		0.65	0.81	0.98		E
Photocell Relay - Box Mounted		0.65	0.81	0.98		E
<b>Occupancy Sensors</b>						
Ceiling Mounted Sensor		0.50	0.63	0.75		E
Passive Infrared Occupancy Sensor		0.50	0.63	0.75		E
<b>Automatic Wall Switch</b>						
Automatic Wall Switch		0.35	0.44	0.53		E
<b>Intelligent Power Pack</b>						
Intelligent Power Pack		0.75	0.94	1.13		E
****Note: for Low Voltage Lighting Controls see Section 1 of this manual.						

# SECTION 7

## HAZARDOUS SYSTEMS

### General Information

The labor units in this section are applicable for hazardous location electrical systems more commonly referred to as explosion proof equipment. See Section 2 of this manual for metal conduit and fastener labor units.

### Scope of These Labor Units

The Introduction section includes details on the scope of labor units across the manual. Some items included are:

- Material unloading, jobsite storage and delivery to the installation area
- Drawing and specification study
- Layout, measuring and marking the installation location
- Tool acquisition and return to storage
- Material assembly and installation
- Clean-up of electrical contractor furnished excess material
- Circuit testing for continuity
- Normal non-productive labor

7

### Work Operations Not Included In These Labor Units

- Field supervision
- Hanger or fastener installation
- Welding or painting
- Measurement and alignment more precise than normal industry standards
- Conductor installation (wire pulling)
- Testing other than circuit continuity testing

### Labor Adjustments for Non-Typical Conditions

See the Introduction section for details.

### Application Instructions

- Labor units under the “Normal” column are for heights up to eight feet above a smooth, hard floor. Labor units under the “Difficult” column are for heights up to 12 feet. Labor units under the “Very Difficult” column are for heights up to 16 feet.
- Labor units for conduit, pull boxes, receptacles, switches, circuit breakers and panel boards in this section exclude supports, straps, hangers, anchors and fasteners other than wood screws.
- Labor unit tables do not include every type and size of explosion proof items available. When labor units are required for items not listed, an approximate labor unit may be obtained from the tables for a similar item of about the same weight, dimensions and conductor terminations.
- All the labor units in this section are based on using the most efficient tools and equipment available. When the anticipated jobsite conditions will prevent the optimum use of tools and equipment, an appropriate additional labor allowance in proportion to the anticipated difficulties is necessary.
- Labor units in this manual are for new work only and for a complete electrical installation. For remodeling or change order situations these labor units need to be substantially increased.



## Section 7 - Hazardous Systems Table of Contents

Sealing Hub Listed by Female Hub Size	7-5
Conduit Seal Fittings with or without Drain Fittings	7-5
Sealing Compound	7-5
Steel Conduit Unions	7-5
Flexible Steel Couplings	7-5
Breather/Drain Fittings	7-5
Explosion Proof Conduit Bodies 2-Hub	7-5
Explosion Proof Conduit Bodies 3-Hub	7-5
2-Hub Round Junction Boxes	7-6
3-Hub Round Junction Boxes	7-6
Explosion Proof Junction Boxes with Hubs Up to 5" x 5"	7-6
Explosion Proof Junction Boxes with Hubs Up to 10 x 10"	7-6
Explosion Proof Junction Boxes with Hubs up to 12 x 12"	7-6
Drill and Tap for Hubs	7-6
Control & Instrument Enclosures 2-Hubs	7-6
Control & Instrument Enclosures 3-Hub	7-6
Explosion Proof Large Junction Boxes	7-6
Explosion Proof Single Receptacles	7-6
Explosion Proof Single Receptacles with Factory Seal	7-7
Explosion Proof Polarized Pin Receptacles	7-7
Explosion Proof Receptacle Male Attachment Cap	7-7
Explosion Proof Snap Switches	7-7
Explosion Proof Snap Switches with Factory Seal	7-7
Explosion Proof Receptacles with Interlocked Switches	7-7
Push Button Station - Wall Mounted - 120 Volt - Explosion Proof Enclosure	7-7
Explosion Proof 2-Wire Safety Switches	7-7
Explosion Proof 3-Wire Safety Switches	7-8
Explosion Proof 4-Wire Safety Switches	7-8
1-Pole Circuit Breakers with Spin Top Covers	7-8
2-Pole Circuit Breakers with Spin Top Covers	7-8
3-Pole Circuit Breakers with Spin Top Covers	7-8
Panelboard Class 1 Div 2 up to 30 Circuit Breakers Style D2L	7-8
Panelboard Class 1 Div 1 up to 30 Circuits Style LP-1	7-8
One Speed Non-Reversing Combination Motor Starters - 2-Pole	7-8
One Speed Non-Reversing Combination Motor Starters - 3-Pole	7-9
One Speed Non-Reversing Combination Motor Starters - 4-Pole	7-9
One Speed Reversing Combination Motor Starters - 2-Pole	7-9
One Speed Reversing Combination Motor Starters - 3-Pole	7-9
One Speed Reversing Combination Motor Starters - 4-Pole	7-9
Multi Speed Non-Reversing Combination Motor Starters - 2-Pole	7-9
Multi Speed Non-Reversing Combination Motor Starters - 3-Pole	7-9
Multi Speed Non-Reversing Combination Motor Starters - 4-Pole	7-9
Multi Speed Reversing Combination Motor Starters - 2-Pole	7-9
Multi Speed Reversing Combination Motor Starters - 3-Pole	7-9












Section 7 - Hazardous Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Sealing Hub Listed by Female Hub Size</b>						
		0.55	0.68	0.80		E
1/2"		0.55	0.68	0.80		E
3/4"		0.60	0.75	0.90		E
1"		0.70	0.87	1.05		E
1 1/4"		0.80	1.00	1.20		E
1 1/2"		0.90	1.12	1.35		E
2"		1.00	1.25	1.50		E
2 1/2"		1.20	1.50	1.80		E
3"		1.40	1.75	2.10		E
3 1/2"		1.70	2.10	2.55		E
4"		2.00	2.50	3.00		E
<b>Conduit Seal Fittings with or without Drain Fittings</b>						
		0.55	0.68	0.80		E
1/2"		0.55	0.68	0.80		E
3/4"		0.60	0.75	0.90		E
1"		0.70	0.87	1.05		E
1 1/4"		0.80	1.00	1.20		E
1 1/2"		0.90	1.12	1.35		E
2"		1.00	1.25	1.50		E
2 1/2"		1.20	1.50	1.80		E
3"		1.40	1.75	2.10		E
3 1/2"		1.70	2.10	2.55		E
4"		2.00	2.50	3.00		E
<b>Sealing Compound</b>						
		0.18	0.25	0.30		E
1/2" Fittings		0.18	0.25	0.30		E
3/4" Fittings		0.22	0.28	0.33		E
1" Fittings		0.28	0.35	0.42		E
1 1/4" Fittings		0.32	0.40	0.48		E
1 1/2" Fittings		0.35	0.44	0.53		E
2" Fittings		0.40	0.50	0.60		E
2 1/2" Fittings		0.43	0.54	0.65		E
3" Fittings		0.45	0.56	0.68		E
3 1/2" Fittings		0.47	0.59	0.71		E
4" Fittings		0.50	0.63	0.75		E
<b>Steel Conduit Unions</b>						
		0.45	0.56	0.67		E
1/2"		0.45	0.56	0.67		E
3/4"		0.50	0.62	0.75		E
1"		0.60	0.75	0.90		E
1 1/4"		0.70	0.87	1.05		E
1 1/2"		0.80	1.00	1.20		E
2"		1.00	1.25	1.50		E
2 1/2"		1.20	1.50	1.80		E
3"		1.40	1.75	2.10		E
3 1/2"		1.70	2.10	2.55		E
4"		2.00	2.50	3.00		E
<b>Flexible Steel Couplings</b>						
		0.45	0.56	0.67		E
1/2"		0.45	0.56	0.67		E
3/4"		0.50	0.62	0.75		E
1"		0.60	0.75	0.90		E
1 1/4"		0.70	0.87	1.05		E
1 1/2"		0.80	1.00	1.20		E
2"		0.90	1.12	1.35		E
2 1/2"		1.00	1.25	1.50		E
3"		1.20	1.50	1.80		E
3 1/2"		1.50	1.85	2.25		E
4"		1.80	2.25	2.70		E
<b>Breather/Drain Fittings</b>						
		0.35	0.43	0.52		E
1/2"		0.35	0.43	0.52		E
<b>Explosion Proof Conduit Bodies 2-Hub</b>						
		0.60	0.75	0.90		E
1/2"		0.60	0.75	0.90		E
3/4"		0.70	0.87	1.05		E
1"		0.90	1.12	1.35		E
1 1/4"		1.10	1.35	1.65		E
1 1/2"		1.40	1.75	2.10		E
2"		1.80	2.25	2.70		E
<b>Explosion Proof Conduit Bodies 3-Hub</b>						
		0.70	0.87	1.05		E
1/2"		0.70	0.87	1.05		E
3/4"		0.80	1.00	1.20		E
1"		1.00	1.25	1.50		E
1 1/4"		1.30	1.60	1.90		E
1 1/2"		1.60	2.00	2.40		E
2"		2.00	2.50	3.00		E









Section 7 - Hazardous Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>2-Hub Round Junction Boxes</b>						
 1/2"		0.60	0.75	0.90		E
3/4"		0.70	0.87	1.05		E
1"		0.90	1.12	1.35		E
1 1/4"		1.10	1.35	1.65		E
1 1/2"		1.40	1.75	2.10		E
2"		1.80	2.25	2.70		E
<b>3-Hub Round Junction Boxes</b>						
1/2"		0.70	0.87	1.05		E
3/4"		0.80	1.00	1.20		E
1"		1.00	1.25	1.50		E
1 1/4"		1.30	1.60	1.90		E
1 1/2"		1.60	2.00	2.40		E
2"		2.00	2.50	3.00		E
<b>Explosion Proof Junction Boxes with Hubs Up to 5" x 5"</b>						
1/2"		1.75	2.15	2.60		E
3/4"		2.00	2.50	3.00		E
1"		2.25	2.80	3.40		E
1 1/4"		2.60	3.25	3.90		E
1 1/2"		3.00	3.75	4.50		E
2"		3.50	4.35	5.25		E
<b>Explosion Proof Junction Boxes with Hubs Up to 10 x 10"</b>						
1/2"		2.50	3.10	3.75		E
3/4"		2.75	3.40	4.10		E
1"		3.00	3.75	4.50		E
1 1/4"		3.30	4.10	5.00		E
1 1/2"		3.60	4.50	5.50		E
2"		4.00	5.00	6.00		E
<b>Explosion Proof Junction Boxes with Hubs up to 12 x 12"</b>						
3/4"		3.30	4.10	5.00		E
1"		3.60	4.50	5.50		E
1 1/4"		4.00	5.00	6.00		E
1 1/2"		4.50	5.60	6.75		E
2"		5.00	6.25	7.50		E
<b>Drill and Tap for Hubs</b>						
1/2"		0.90	1.13	1.35		E
3/4"		0.95	1.19	1.43		E
1"		1.15	1.44	1.73		E
1 1/4"		1.20	1.50	1.80		E
1 1/2"		1.25	1.56	1.88		E
2"		1.75	2.19	2.63		E
<b>Control &amp; Instrument Enclosures 2-Hubs</b>						
 5" x 5"		2.00	2.50	3.00		E
 6 1/2" x 7"		2.50	3.10	3.75		E
8" x 10"		2.75	3.40	4.10		E
12" x 12"		3.25	4.00	4.80		E
17" x 17"		4.00	5.00	6.00		E
<b>Control &amp; Instrument Enclosures 3-Hub</b>						
 5" x 5"		2.25	2.80	3.40		E
 6 1/2" x 7"		2.60	3.25	3.90		E
8" x 10"		3.00	3.75	4.50		E
12" x 12"		3.50	4.35	5.25		E
17" x 17"		4.25	5.30	6.35		E
<b>Explosion Proof Large Junction Boxes</b>						
 Up to 10 x 10"		3.00	3.75	4.50		E
Up to 15 x 15"		3.75	4.50	5.50		E
Up to 20 x 20"		4.50	5.50	6.50		E
Up to 24 x 24"		6.5	7.5	8.5		E
<b>Explosion Proof Single Receptacles</b>						
 20 Amp 2 Wire		0.80	1.00	1.20		E
20 Amp 3 Wire		0.85	1.05	1.27		E
20 Amp 4 Wire		0.90	1.10	1.35		E
30 Amp 2 Wire		0.85	1.05	1.27		E
30 Amp 3 Wire		0.90	1.10	1.35		E
30 Amp 4Wire		1.00	1.25	1.50		E
50 Amp 3 Wire		1.10	1.35	1.65		E
50 Amp 4 Wire		1.20	1.50	1.80		E
60 Amp 3 Wire		1.40	1.75	2.10		E
60 Amp 4 Wire		1.50	1.90	2.25		E











## Section 7 - Hazardous Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Explosion Proof Single Receptacles with Factory Seal</b>						
 20 Amp 2 Wire		0.75	0.94	1.13		E
20 Amp 3 Wire		0.80	1.00	1.20		E
20 Amp 4 Wire		0.85	1.05	1.27		E
30 Amp 2 Wire		0.90	1.10	1.35		E
30 Amp 3 Wire		0.85	1.05	1.27		E
30 Amp 4Wire		0.90	1.10	1.35		E
50 Amp 3 Wire		1.00	1.25	1.50		E
50 Amp 4 Wire		1.10	1.35	1.65		E
60 Amp 3 Wire		1.20	1.50	1.80		E
60 Amp 4 Wire		1.40	1.75	2.10		E
<b>Explosion Proof Polarized Pin Receptacles</b>						
20 Amp 2 Wire		0.90	1.10	1.35		E
20 Amp 3 Wire		1.00	1.25	1.50		E
20 Amp 4 Wire		1.10	1.35	1.65		E
20 Amp 5 Wire		1.20	1.50	1.80		E
30 Amp 2 Wire		1.00	1.25	1.50		E
30 Amp 3 Wire		1.10	1.35	1.65		E
30 Amp 4Wire		1.20	1.50	1.80		E
30 Amp 5 Wire		1.30	1.60	1.95		E
60 Amp 3 Wire		1.40	1.75	2.10		E
60 Amp 4 Wire		1.50	1.90	2.25		E
<b>Explosion Proof Receptacle Male Attachment Cap</b>						
20 Amp 2 Wire		0.25	0.31	0.39		E
20 Amp 3 Wire		0.30	0.38	0.47		E
20 Amp 4 Wire		0.33	0.41	0.52		E
20 Amp 5 Wire		0.40	0.50	0.63		E
30 Amp 3 Wire		0.25	0.31	0.39		E
30 Amp 4 Wire		0.30	0.38	0.47		E
30 Amp 5 Wire		0.33	0.41	0.52		E
60 Amp 3 Wire		0.50	0.63	0.78		E
60 Amp 4 Wire		0.60	0.75	0.94		E
<b>Explosion Proof Snap Switches</b>						
1-Pole 15 Amp		0.80	1.00	1.20		E
1-Pole 20 Amp		0.85	1.05	1.27		E
1-Pole 30 Amp		0.90	1.10	1.35		E
2-Pole 15 Amp		1.00	1.25	1.50		E
2-Pole 20 Amp		1.05	1.30	1.55		E
2-Pole 30 Amp		1.10	1.35	1.60		E
3-Way 15 Amp		1.15	1.40	1.70		E
3-Way 20 Amp		1.20	1.50	1.80		E
3-Way 30 Amp		1.25	1.55	1.90		E
4-Way 15 Amp		1.30	1.65	2.00		E
4-Way 20 Amp		1.35	1.70	2.10		E
4-Way 30 Amp		1.40	1.80	2.20		E
<b>Explosion Proof Snap Switches with Factory Seal</b>						
1-Pole 15 Amp		0.75	0.94	1.13		E
1-Pole 20 Amp		0.80	1.00	1.20		E
1-Pole 30 Amp		0.85	1.05	1.27		E
2-Pole 15 Amp		0.90	1.10	1.35		E
2-Pole 20 Amp		1.00	1.25	1.50		E
2-Pole 30 Amp		1.05	1.30	1.55		E
3-Way 15 Amp		1.10	1.35	1.60		E
3-Way 20 Amp		1.15	1.40	1.70		E
3-Way 30 Amp		1.20	1.50	1.80		E
4-Way 15 Amp		1.25	1.55	1.90		E
4-Way 20 Amp		1.30	1.65	2.00		E
4-Way 30 Amp		1.35	1.70	2.10		E
<b>Explosion Proof Receptacles with Interlocked Switches</b>						
20-Amp 2-Wire		2.00	2.50	3.00		E
20-Amp 3-Wire		2.30	2.90	3.50		E
20-Amp 4-Wire		2.60	3.30	4.00		E
30-Amp 2-Wire		2.30	2.90	3.50		E
30-Amp 3-Wire		2.60	3.30	4.00		E
30-Amp 4-Wire		3.00	3.75	4.50		E
<b>Push Button Station - Wall Mounted - 120 Volt - Explosion Proof Enclosure</b>						
1-Button or Pilot Light		1.50	1.88	2.25		E
2-Button or Pilot Light		1.80	2.25	2.70		E
3-Button or Pilot Light		2.10	2.63	3.15		E
4-Button or Pilot Light		2.50	3.13	3.75		E
<b>Explosion Proof 2-Wire Safety Switches</b>						
30 Amp		3.00	3.75	4.50		E
60 Amp		3.50	4.35	5.25		E
100 Amp		4.50	5.60	6.75		E
150 Amp		5.50	6.85	8.25		E
200 Amp		6.50	8.10	9.75		E

## Section 7 - Hazardous Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Explosion Proof 3-Wire Safety Switches</b>						
 30 Amp		3.50	4.35	5.25		E
60 Amp		4.00	5.00	6.00		E
100 Amp		5.00	6.25	7.50		E
150 Amp		6.00	7.50	9.00		E
200 Amp		7.00	8.75	10.00		E
<b>Explosion Proof 4-Wire Safety Switches</b>						
 30 Amp		4.00	5.00	6.00		E
60 Amp		4.50	5.60	6.75		E
100 Amp		5.50	6.85	8.25		E
150 Amp		6.50	7.10	9.75		E
200 Amp		7.50	9.35	11.25		E
<b>1-Pole Circuit Breakers with Spin Top Covers</b>						
 20 Amp		2.00	2.50	3.00		E
30 Amp		2.25	2.80	3.35		E
40 Amp		2.50	3.10	3.75		E
50 Amp		2.70	3.35	4.00		E
70 Amp		3.25	4.05	4.85		E
90 Amp		3.75	4.65	5.60		E
100 Amp		4.00	5.00	6.00		E
<b>2-Pole Circuit Breakers with Spin Top Covers</b>						
 30 Amp		2.50	3.10	3.75		E
40 Amp		2.75	3.40	4.10		E
50 Amp		3.00	3.75	4.50		E
70 Amp		3.50	4.35	5.25		E
90 Amp		4.00	5.00	6.00		E
100 Amp		4.50	5.60	6.75		E
125 Amp		5.00	6.25	7.50		E
150 Amp		5.50	6.85	8.25		E
175 Amp		6.00	7.50	9.00		E
200 Amp		7.00	8.75	10.50		E
225 Amp		8.00	10.00	12.00		E
250 Amp		9.00	11.25	13.50		E
300 Amp		10.00	12.50	15.00		E
400 Amp		12.00	15.00	18.00		E
<b>3-Pole Circuit Breakers with Spin Top Covers</b>						
 30 Amp		2.75	3.44	4.13		E
40 Amp		3.00	3.75	4.50		E
50 Amp		3.50	4.38	5.25		E
70 Amp		4.00	5.00	6.00		E
90 Amp		4.50	5.63	6.75		E
100 Amp		5.00	6.25	7.50		E
125 Amp		5.50	6.88	8.25		E
150 Amp		6.00	7.50	9.00		E
175 Amp		7.00	8.75	10.50		E
200 Amp		8.00	10.00	12.00		E
225 Amp		9.00	11.25	13.50		E
250 Amp		10.00	12.50	15.00		E
300 Amp		12.00	15.00	18.00		E
400 Amp		14.00	17.50	21.00		E
<b>Panelboard Class 1 Div 2 up to 30 Circuit Breakers Style D2L</b>						
 6 Single Pole Spaces		10.00	12.50	15.00		E
12 Single Pole Spaces		10.50	13.13	15.75		E
18 Single Pole Spaces		11.00	13.75	16.50		E
24 Single Pole Spaces		11.50	14.38	17.25		E
30 Single Pole Spaces		12.00	15.00	18.00		E
<b>Panelboard Class 1 Div 1 up to 30 Circuits Style LP-1</b>						
 6 Single Pole Spaces		11.00	13.75	16.50		E
12 Single Pole Spaces		11.50	14.38	17.25		E
18 Single Pole Spaces		12.00	15.00	18.00		E
24 Single Pole Spaces		12.50	15.63	18.75		E
30 Single Pole Spaces		13.00	16.25	19.50		E
36 Single Pole Spaces		13.50	16.88	20.25		E
<b>One Speed Non-Reversing Combination Motor Starters - 2-Pole</b>						
 NEMA 0		3.50	4.30	5.20		E
NEMA 1		4.00	5.00	6.00		E
NEMA 2		5.00	6.20	7.50		E

### Section 7 - Hazardous Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>One Speed Non-Reversing Combination Motor Starters - 3-Pole</b>						
NEMA 0		4.00	5.00	6.00		E
NEMA 1		4.50	5.70	6.70		E
NEMA 2		6.00	7.50	9.00		E
NEMA 3		8.00	10.00	12.00		E
NEMA 4		10.00	12.50	15.00		E
 <b>One Speed Non-Reversing Combination Motor Starters - 4-Pole</b>						
NEMA 0		5.00	6.20	7.50		E
NEMA 1		6.00	7.50	9.00		E
NEMA 2		8.00	10.00	12.00		E
NEMA 3		10.00	12.50	15.00		E
NEMA 4		12.00	15.00	18.00		E
 <b>One Speed Reversing Combination Motor Starters - 2-Pole</b>						
NEMA 0		4.00	5.00	6.00		E
NEMA 1		4.50	5.70	6.70		E
NEMA 2		5.50	6.80	8.20		E
 <b>One Speed Reversing Combination Motor Starters - 3-Pole</b>						
NEMA 0		4.50	5.70	6.70		E
NEMA 1		5.00	6.20	7.50		E
NEMA 2		7.00	8.50	10.00		E
NEMA 3		9.00	11.20	13.50		E
NEMA 4		12.00	15.00	18.00		E
 <b>One Speed Reversing Combination Motor Starters - 4-Pole</b>						
NEMA 0		6.00	7.50	9.00		E
NEMA 1		7.00	8.50	10.00		E
NEMA 2		9.00	11.20	13.50		E
NEMA 3		12.00	15.00	18.00		E
NEMA 4		15.00	18.70	22.50		E
 <b>Multi Speed Non-Reversing Combination Motor Starters - 2-Pole</b>						
NEMA 0		5.00	6.20	7.50		E
NEMA 1		6.00	7.50	9.00		E
NEMA 2		8.00	10.00	12.00		E
 <b>Multi Speed Non-Reversing Combination Motor Starters - 3-Pole</b>						
NEMA 0		6.00	7.50	9.00		E
NEMA 1		7.00	8.50	10.00		E
NEMA 2		9.00	11.20	13.50		E
NEMA 3		12.00	15.00	18.00		E
 <b>Multi Speed Non-Reversing Combination Motor Starters - 4-Pole</b>						
NEMA 0		8.00	10.00	12.00		E
NEMA 1		9.00	11.20	13.50		E
NEMA 2		10.00	12.50	15.00		E
NEMA 3		13.00	16.00	19.00		E
 <b>Multi Speed Reversing Combination Motor Starters - 2-Pole</b>						
NEMA 0		6.00	7.50	9.00		E
NEMA 1		7.00	8.50	10.00		E
NEMA 2		9.00	11.20	13.50		E
 <b>Multi Speed Reversing Combination Motor Starters - 3-Pole</b>						
NEMA 0		7.00	8.50	10.00		E
NEMA 1		8.00	10.00	12.00		E
NEMA 2		10.00	12.50	15.00		E
NEMA 3		13.00	16.00	19.00		E

7



# SECTION 8

## GROUNDING AND LIGHTNING PROTECTION SYSTEMS

### General Information

The labor units in this section are applicable for the installation of exposed indoor grounding systems and outdoor buried grounding systems. These labor units do not include the excavation or backfilling for outdoor grounding systems.

### Scope of These Labor Units

The Introduction section includes details on the scope of labor units across the manual. Some items included are:

- Material unloading, jobsite storage and delivery to the installation area
- Drawing and specification study
- Layout, measuring and marking the installation location
- Tool acquisition and return to storage
- Grounding materials installation
- Grounding conductor terminations on grounding bushings and clamps
- Clean-up of electrical contractor furnished excess material
- Normal non-productive labor

### Work Operations Not Included In These Labor Units

- Field supervision
- Conduit or physical protection for grounding conductors
- Lug installation for conductor terminations
- Testing of any type
- Electrical equipment enclosure grounding conductor terminations
- Excavation or backfilling for indoor or outdoor grounding systems

### Labor Adjustments for Non-Typical Conditions

See the Introduction section for details.

### Application Instructions

- Labor units under the “Normal” column are for locations with good access, no obstructions and large quantities of grounding conductors. Labor units under the “Difficult” column are for locations with less than good access, a few minor obstructions and large quantities of grounding conductors. Labor units under the “Very Difficult” column are for locations with poor access or require the use of a ladder, numerous obstructions, limited space, or small quantities of grounding materials.
- Labor units for driving grounding rods are for locations with loam, hard clay, or loose shale the full depth of the rods. For other locations the labor units must be increased in proportion to the density of the soil encountered.
- All the labor units in this section are based on using the most efficient tools and equipment available. When the anticipated jobsite conditions will prevent the optimum use of tools and equipment, an appropriate additional labor allowance in proportion to the anticipated difficulties is necessary.
- Labor units in this manual are for new work only and for a complete electrical installation. For remodeling or change order situations these labor units need to be substantially increased.





## Section 8 - Grounding & Lightning Protection Systems Table of Contents

Bare Copper Grounding Conductors - Buried - Outdoors	8-5
Bare and Insulated Copper Grounding Conductors - Indoors - Exposed or In Cable Trays	8-5
Conduit Grounding Wedges	8-5
Conduit Grounding Bushings or Locknuts	8-5
Conductor Grounding Clamps	8-5
Conduit Grounding Clamps	8-6
Pedestal Grounding Clamp-Raised Floor	8-6
Grounding Rods	8-6
Sectional Ground Rods	8-6
Flexible Braid Grounding Strap	8-6
AL Flexible Braid Conductor	8-6
CU Flexible Braid Conductor	8-6
AL Rod Conductor	8-6
CU Rod Conductor	8-6
AL Flexible Braid Conductor	8-6
Ground Bar Assembly	8-7
Electrolytic Grd Rod	8-7
3/4" Perforated Grounding Strap with Compression Lugs	8-7
Braided Copper Bonding Jumpers	8-8
Ground Pigtail for Boxes	8-8
Grounding Wire Connectors	8-8
One-shot Conductor to Ground Rod-Cadweld	8-8
Single Conductor to Ground Rod	8-8
Tri-line Conductor to Ground Rod	8-8
Tee Conductor to Ground Rod	8-8
In-Line Splices-Cadweld Splices	8-8
Tee or Wye Cadwelds	8-8
Cross (4 Way) Cadwelds	8-9
Conductor to Steel - Cadweld	8-9
Cadweld To Ground Rod	8-9
Cadweld Bare Copper Wire To Rebar	8-9
Irreversible Compression Ground System	8-9
Ground Grid Cross Connector	8-9
Compression Ground Rod with 1ea Tap Connectors	8-9
Compression Ground Rod with 2ea Tap Connectors	8-9
Compression Ground Rod with 3ea Tap Connectors	8-9
Double H-Tap Connector	8-10
"C" Compression Ground Tap Connector	8-10
Grounding Plate Insert for Concrete	8-10
Steel Structural Compression Connector	8-10
Main and Secondary Conductor AL	8-10
Main and Secondary Conductor CU	8-10
AL Bus Bar	8-10
CU Bus Bar	8-10
Lightning Protection	8-11
AL Flat Conductor	8-11
CU Flat Conductor	8-11
Bonding Plates	8-11
Adhesive Cable Holder	8-11
Cable Fastener (Masonry)	8-11
Cable Fasteners	8-11
Cable Splicers	8-11
Tee Cable Splicers	8-11
Three Way Splicer	8-11
Cross Run Splicer	8-11
Straight Splicer	8-11
Bonding Lug	8-11


## Section 8 - Grounding & Lightning Protection Systems Table of Contents

Thru Roof Point Adapt	8-12
Thru Wall or Roof Cable Connector	8-12
Swivel Adapt AL	8-12
Swivel Adapt CU	8-12
AL Points	8-12
CU Points	8-12
Ridge or Flat Point Base	8-12
Side Ridge Point Base	8-12
Flue Liner Point Base	8-12
Tee Point Base	8-12
Straight Point Base	8-13
Comb. Point Base	8-13
Adhesive Point Base	8-13
Offset Wall Point Base	8-13
Metal Mount Point Base	8-13
Reglet Mount Point Base	8-13
Flat Surface Point Base	8-13
Cone Vent Point Base	8-13
Coupling and Adapters for Point AL	<b>(Updated)</b> 8-13
Coupling and Adapters for Point CU	8-14
Ground Rod for Down Spout	8-14
Cable Protectors CU	8-14
Cable Protectors PVC Pipe	8-14
Cable Protectors Galv Steel	8-14
Cable Protectors Wood	8-14
Cable Protectors Strap Pipe	8-14
Electronically Activated Streamer Emission Air Terminal	8-14
Cathodic Protection	<b>(Updated)</b> 8-15







## Section 8 - Grounding & Lightning Protection Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Bare Copper Grounding Conductors -</b>						
<b>Buried - Outdoors - Does not Include Excavation</b>						
#12, #10		8.00	10.00	12.00		M
#8, #6		12.00	15.00	18.00		M
#4, #3		16.00	20.00	24.00		M
#2, #1		20.00	25.00	30.00		M
1/0		26.00	32.50	39.00		M
2/0		29.00	36.20	43.00		M
3/0		32.00	40.00	48.00		M
4/0		35.00	43.00	52.00		M
250 kcmil		38.00	47.00	57.00		M
300 kcmil		41.00	51.00	61.00		M
350 kcmil		44.00	55.00	66.00		M
400 kcmil		48.00	60.00	72.00		M
500 kcmil		52.00	65.00	78.00		M
600 kcmil		56.00	70.00	84.00		M
750 kcmil		62.00	77.00	93.00		M
1000 kcmil		70.00	85.00	100.00		M
<b>Bare and Insulated Copper Grounding Conductors -</b>						
<b>Indoors - Exposed or In Cable Trays</b>						
#12, #10		8.00	10.00	12.00		M
#8, #6		12.00	15.00	18.00		M
#4, #3		16.00	20.00	24.00		M
#2, #1		20.00	25.00	30.00		M
1/0		35.00	43.00	52.00		M
2/0		40.00	50.00	60.00		M
3/0		45.00	56.00	67.00		M
4/0		50.00	62.00	75.00		M
250 kcmil		55.00	68.00	82.00		M
300 kcmil		60.00	75.00	90.00		M
350 kcmil		65.00	81.00	95.00		M
400 kcmil		70.00	85.00	100.00		M
500 kcmil		75.00	93.00	110.00		M
600 kcmil		80.00	100.00	120.00		M
750 kcmil		88.00	110.00	135.00		M
1000 kcmil		100.00	125.00	150.00		M
<i>Note: Modify rates based on cable tray types (ie: ladder, centerhung)</i>						
<i>Modify rates for stacked cable tray runs</i>						
<b>Conduit Grounding Wedges</b>						
3/4"		0.16	0.20	0.25		E
1"		0.18	0.23	0.28		E
1 1/4"		0.22	0.28	0.34		E
1 1/2"		0.23	0.29	0.36		E
2"		0.24	0.30	0.38		E
2 1/2"		0.26	0.33	0.41		E
3"		0.29	0.36	0.45		E
3 1/2"		0.32	0.40	0.50		E
4"		0.36	0.45	0.56		E
<b>Conduit Grounding Bushings or Locknuts</b>						
3/4"		0.20	0.25	0.30		E
1"		0.22	0.27	0.33		E
1 1/4"		0.24	0.29	0.36		E
1 1/2"		0.26	0.32	0.39		E
2"		0.28	0.35	0.42		E
2 1/2"		0.30	0.37	0.45		E
3"		0.33	0.41	0.50		E
3 1/2"		0.36	0.45	0.55		E
4"		0.40	0.50	0.60		E
5"		0.70	0.88	1.09		E
6"		0.77	0.96	1.20		E
<i>Note: Cutting and threading conduit is not included</i>						
<b>Conductor Grounding Clamps</b>						
3/4"		0.40	0.50	0.60		E
1"		0.44	0.55	0.66		E
1 1/4"		0.48	0.60	0.72		E
1 1/2"		0.52	0.65	0.78		E
2"		0.56	0.70	0.84		E
2 1/2"		0.60	0.75	0.90		E
3"		0.64	0.80	0.96		E
3 1/2"		0.68	0.85	1.02		E
4"		0.72	0.90	1.08		E
5"		0.76	0.95	1.14		E
6"		0.80	1.00	1.20		E










## Section 8 - Grounding & Lightning Protection Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Conduit Grounding Clamps</b>						
 3/4"		0.60	0.75	0.90		E
1"		0.64	0.80	0.96		E
1 1/4"		0.72	0.85	1.02		E
1 1/2"		0.80	0.90	1.08		E
2"		0.88	0.95	1.14		E
2 1/2"-4" (universal size)		1.10	1.35	1.60		E
5"		1.25	1.55	1.85		E
6"		1.40	1.75	2.10		E
<b>Pedestal Grounding Clamp-Raised Floor</b>						
Round up to 3/4" - #8 to #2		0.25	0.35	0.45		E
Round up to 1" - #8 to #2		0.30	0.40	0.50		E
Square up to 5/8" - #8 to #2		0.25	0.35	0.45		E
Square up to 7/8" - #8 to #2		0.30	0.40	0.50		E
<b>Grounding Rods</b>						
Grounding Rod with Clamp		1.60	2.00	2.50		E
<i>Note: Verify Soil Conditions</i>						
<b>Sectional Ground Rods</b>						
First Rod		1.60	2.00	2.50		E
Second Rod		2.10	2.63	3.28		E
Third Rod		2.60	3.25	4.06		E
Drive Stud		0.10	0.13	0.16		E
Rod Coupling		0.10	0.13	0.16		E
<i>(Based on total length of 30')</i>						
<i>Note: Verify Soil Conditions</i>						
<i>Labor units based on the use of air or electrical hammer</i>						
<i>Use Drive Stud to prevent damaging threads</i>						
<b>Flexible Braid Grounding Strap</b>						
100 Amp		1.00	1.25	1.50		E
200 Amp		1.10	1.37	1.65		E
300 Amp		1.20	1.50	1.80		E
500 Amp		1.35	1.65	2.00		E
800 Amp		1.50	1.85	2.25		E
1000 Amp		1.70	2.10	2.55		E
1600 Amp		2.00	2.50	3.00		E
<b>AL Flexible Braid Conductor</b>						
AL Flexible Braid Conductor #2		0.75	0.90	1.10		E
<b>CU Flexible Braid Conductor</b>						
CU Flexible Braid Conductor #6		0.55	0.75	0.85		E
CU Flexible Braid Conductor #4		0.70	0.90	1.15		E
CU Flexible Braid Conductor #2		0.85	1.05	1.35		E
CU Flexible Braid Conductor #1/0		1.10	1.35	1.70		E
<b>AL Rod Conductor</b>						
AL Rod Conductor 3/8" Dia.		1.25	1.50	1.75		E
AL Rod Conductor 1/2" Dia.		1.75	2.00	2.25		E
<b>CU Rod Conductor</b>						
CU Rod Conductor 3/8" Dia.		1.50	2.00	2.50		E
CU Rod Conductor 1/2" Dia.		2.00	2.50	3.00		E
<b>AL Flexible Braid Conductor</b>						
AL Flexible Braid Cond. #2		0.75	0.90	1.10		E

Section 8 - Grounding & Lightning Protection Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Ground Bar Assembly</b>						
<i>Copper ground bar with wall/floor mounting brackets and insulated standoffs</i>						
<i>Bus can be ordered in different thickness, width, length and hole pattern</i>						
<i>Plexiglass covers are available including engraving</i>						
<i>Wire terminations are not included in the labor for this assembly</i>						
	1/4" x 4" x 12" ground bus assembly		1.50	1.88	2.34	E
	1/4" x 4" x 18" ground bus assembly		1.75	2.19	2.73	E
	1/4" x 4" x 24" ground bus assembly		2.00	2.50	3.13	E
	1/4" x 4" x 30" ground bus assembly		2.25	2.81	3.52	E
	1/4" x 4" x 36" ground bus assembly		2.50	3.13	3.91	E
	1/4" x 4" x 42" ground bus assembly		3.00	3.75	4.69	E
	1/4" x 4" x 48" ground bus assembly		3.50	4.38	5.47	E
	1/4" x 6" x 12" ground bus assembly		1.75	2.19	2.73	E
	1/4" x 6" x 18" ground bus assembly		2.00	2.50	3.13	E
	1/4" x 6" x 24" ground bus assembly		2.25	2.81	3.52	E
	1/4" x 6" x 30" ground bus assembly		2.50	3.13	3.91	E
	1/4" x 6" x 36" ground bus assembly		2.75	3.44	4.30	E
	1/4" x 6" x 42" ground bus assembly		3.25	4.06	5.08	E
	1/4" x 6" x 48" ground bus assembly		3.75	4.69	5.86	E
	4" x 12" Plexiglass cover		0.50	0.63	0.78	E
	4" x 18" Plexiglass cover		0.50	0.63	0.78	E
	4" x 24" Plexiglass cover		0.60	0.75	0.94	E
	4" x 30" Plexiglass cover		0.60	0.75	0.94	E
	4" x 36" Plexiglass cover		0.65	0.81	1.02	E
	4" x 40" Plexiglass cover		0.70	0.88	1.09	E
	4" x 48" Plexiglass cover		0.75	0.94	1.17	E
	6" x 12" Plexiglass cover		0.55	0.69	0.86	E
	6" x 18" Plexiglass cover		0.55	0.69	0.86	E
	6" x 24" Plexiglass cover		0.65	0.81	1.02	E
	6" x 30" Plexiglass cover		0.65	0.81	1.02	E
	6" x 36" Plexiglass cover		0.70	0.88	1.09	E
	6" x 42" Plexiglass cover		0.75	0.94	1.17	E
	6" x 48" Plexiglass cover		0.80	1.00	1.25	E
<b>Electrolytic Grd Rod</b>						
<i>Electrolytic Ground Rods with 18" copper pigtail (#2, 1/0, 2/0, 4/0, #500, #750)</i>						
<i>Please note auger, trench and bentonite mixture is not included in the labor units</i>						
<i>Size, spacing and location can vary depending upon soil type, moisture content and chemical content</i>						
<i>Contact manufacturer for design of low resistance ground system</i>						
<i>Straight electrolytic ground notes</i>						
<i>Auger 10" dia. Hole 6" deeper than length of electrolytic ground rod</i>						
<i>Backfill with soil, bentonite and water mixture per manufacturer's recommendation</i>						
<i>10' rod will utilize approximately 50lbs per hole and takes approximately 1 hour to mix and install the bentonite utilizing a cement mixer</i>						
<i>Ground system should be checked annually. Rods can be recharges as required with the bentonite mixture</i>						
	Straight 10' rod with #2 pigtail		2.50	3.13	3.91	E
	L-shaped 10' rod with # pigtail		3.00	3.75	4.69	E
	Straight 20' rod with #2 pigtail		4.00	5.00	6.25	E
	L-shaped 20' rod with #2 pigtail		5.00	6.25	7.81	E
	10" x 22" polyethylene inspection well		1.50	1.88	2.34	E
	10" x 12" concrete inspection well		2.00	2.50	3.13	E
	10" x 12" concrete extension		1.00	1.25	1.56	E
<b>3/4" Perforated Grounding Strap with Compression Lugs</b>						
	#14 to #10		0.20	0.25	0.30	E
	#8 to #4		0.25	0.31	0.37	E
	#3 to #1		0.30	0.37	0.45	E
	1/0 to 2/0		0.40	0.50	0.60	E
	3/0 to 4/0		0.50	0.62	0.75	E
	250 kcmil		0.60	0.75	0.90	E
	300 kcmil		0.70	0.87	1.05	E
	500 kcmil		0.85	1.05	1.25	E
400 kcmil		1.00	1.25	1.50	E	

## Section 8 - Grounding & Lightning Protection Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Braided Copper Bonding Jumpers</b>						
 3/4" Conduit		0.80	1.00	1.20		E
1" Conduit		0.85	1.05	1.25		E
1 1/4" Conduit		0.90	1.12	1.35		E
1 1/2" Conduit		1.00	1.25	1.50		E
2" Conduit		1.10	1.37	1.65		E
2 1/2" Conduit		1.20	1.50	1.80		E
3" Conduit		1.30	1.62	1.95		E
3 1/2" Conduit		1.40	1.75	2.10		E
4" Conduit		1.60	2.00	2.40		E
5" Conduit		1.80	2.25	2.70		E
6" Conduit		2.00	2.50	3.00		E
<b>Ground Clips for Boxes</b>						
 Ground clip		0.06	0.08	0.10		E
<b>Ground Pigtail for Boxes</b>						
 Ground pigtail		0.06	0.08	0.10		E
<b>Grounding Wire Connectors</b>						
<b>Accepts 2 - #14 TO 5 - #12'S</b>						
 Grounding wire connector		0.08	0.10	0.12		E
<b>One-shot Conductor to Ground Rod-Cadweld</b>						
<b>Single Conductor to Ground Rod</b>						
 #8 - #4 to 5/8" or 3/4" ground rod		0.37	0.46	0.58		E
#1 - #3 to 5/8" or 3/4" ground rod		0.42	0.53	0.66		E
#1/0 - #4/0 to 5/8" or 3/4" ground rod		0.47	0.59	0.73		E
<b>Tri-line Conductor to Ground Rod</b>						
 #8 - #4 to 5/8" or 3/4" ground rod		0.47	0.59	0.73		E
#1 - #3 to 5/8" or 3/4" ground rod		0.52	0.65	0.81		E
#1/0 - #4/0 to 5/8" or 3/4" ground rod		0.57	0.71	0.89		E
<b>Tee Conductor to Ground Rod</b>						
 #8 - #4 to 5/8" or 3/4" ground rod		0.57	0.71	0.89		E
#1 - #3 to 5/8" or 3/4" ground rod		0.62	0.78	0.97		E
#1/0 - #4/0 to 5/8" or 3/4" ground rod		0.67	0.84	1.05		E
<b>In-Line Splices-Cadweld Splices</b>						
 Up to #6		1.00	1.25	1.50		E
#4		1.05	1.30	1.55		E
#3		1.10	1.35	1.60		E
#2		1.15	1.40	1.70		E
#1		1.20	1.50	1.80		E
1/0		1.25	1.60	1.90		E
2/0		1.30	1.70	2.00		E
3/0		1.40	1.80	2.10		E
4/0		1.50	1.90	2.25		E
250 kcmil		1.60	2.00	2.40		E
300-350 kcmil		1.70	2.10	2.55		E
400-500 kcmil		1.80	2.20	2.70		E
600-750 kcmil		1.90	2.35	2.85		E
1000 kcmil		2.00	2.50	3.00		E
<b>Tee or Wye Cadwelds</b>						
 Up to #6		1.10	1.35	1.60		E
#4		1.15	1.40	1.70		E
#3		1.20	1.50	1.80		E
#2		1.25	1.60	1.80		E
#1		1.30	1.70	2.00		E
1/0		1.40	1.80	2.10		E
2/0		1.50	1.90	2.25		E
3/0		1.60	2.00	2.40		E
4/0		1.70	2.10	2.55		E
250-300 kcmil		1.80	2.20	2.70		E
350-400 kcmil		1.90	2.35	2.85		E
500-600 kcmil		2.00	2.50	3.00		E
750 kcmil		2.10	2.65	3.15		E
1000 kcmil		2.25	2.80	3.35		E

## Section 8 - Grounding & Lightning Protection Systems
















































Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Cross (4 Way) Cadwelds</b>						
Up to #6		1.20	1.50	1.80		E
#4		1.25	1.60	1.90		E
#3		1.30	1.70	2.00		E
#2		1.40	1.80	2.10		E
#1		1.50	1.90	2.25		E
1/0		1.60	2.00	2.40		E
2/0		1.70	2.10	2.55		E
3/0		1.80	2.20	2.70		E
4/0		1.90	2.35	2.85		E
250-300 kcmil		2.00	2.50	3.00		E
350-400 kcmil		2.10	2.65	3.15		E
500-600 kcmil		2.20	2.80	3.30		E
750 kcmil		2.35	2.95	3.50		E
1000 kcmil		2.50	3.10	3.75		E
<b>Conductor to Steel - Cadweld</b>						
Up to #6		1.00	1.25	1.50		E
#4		1.05	1.30	1.55		E
#3		1.10	1.35	1.60		E
#2		1.15	1.40	1.70		E
#1		1.20	1.50	1.80		E
1/0		1.25	1.60	1.90		E
2/0		1.30	1.70	2.00		E
3/0		1.40	1.80	2.10		E
4/0		1.50	1.90	2.25		E
250 - 300 kcmil		1.60	2.00	2.40		E
350 -400 kcmil		1.70	2.10	2.55		E
500 - 600 kcmil		1.80	2.20	2.70		E
750 kcmil		1.90	2.35	2.85		E
1000 kcmil		2.00	2.50	3.00		E
<i>Note: Add 15% for Cadweld round surface</i>						
<b>Cadweld To Ground Rod</b>						
#6		1.00	1.25	1.50		E
#4		1.05	1.31	1.57		E
#2		1.15	1.43	1.72		E
#1/0		1.25	1.56	1.87		E
#2/0		1.30	1.62	1.95		E
#3/0		1.35	1.68	2.00		E
#4/0		1.40	1.75	2.10		E
#250 kcmil		1.45	1.81	2.17		E
<i>Note: See Section 11 for hand holes for test wells</i>						
<b>Cadweld Bare Copper Wire To Rebar</b>						
#6		1.10	1.37	1.65		E
#4		1.15	1.43	1.72		E
#2		1.25	1.56	1.87		E
#1/0		1.35	1.68	2.00		E
#2/0		1.40	1.75	2.19		E
#3/0		1.45	1.81	2.27		E
<b>Irreversible Compression Ground System</b>						
<b>Ground Grid Cross Connector</b>						
#6 - #2 conductor to #6 - #2 conductor		0.45	0.56	0.70		E
#1 - #250 conductor to #6 - #2 conductor		0.75	0.94	1.17		E
#2 - #250 conductor to #6 - #2 conductor		0.97	1.21	1.52		E
#250 - #500 conductor to #6 - #2 conductor		1.03	1.29	1.61		E
#250 - #500 conductor to #2 - #250 conductor		1.18	1.48	1.84		E
#250 - #500 conductor to #250 - #500 conductor		1.28	1.60	2.00		E
1/2" - 5/8" rod to #6 - #2 conductor		0.65	0.81	1.02		E
1/2" - 5/8" rod to #2 - #250 conductor		0.85	1.06	1.33		E
5/8" - 3/4" rod to #6 - #2 conductor		0.75	0.94	1.17		E
5/8" - 3/4" rod to #2 - #250 conductor		0.95	1.19	1.48		E
5/8" - 3/4" rod to #200 - #500 conductor		1.15	1.44	1.80		E
<b>Compression Ground Rod with 1ea Tap Connectors</b>						
1/2" - 5/8" rod to #2-2/0 tap		0.60	0.75	0.94		E
1/2" - 5/8" rod to #4/0-250 tap		0.75	0.94	1.17		E
5/8" rod to #300-#500 tap		0.95	1.19	1.48		E
3/4" - 1" rod to #2-2/0 tap		0.70	0.88	1.09		E
3/4" - 1" rod to #4/0-250 tap		0.85	1.06	1.33		E
3/4" - 1" rod to #300-#500 tap		1.05	1.31	1.64		E
<b>Compression Ground Rod with 2ea Tap Connectors</b>						
1/2" - 5/8" rod to 2ea		0.85	1.06	1.33		E
<b>Compression Ground Rod with 3ea Tap Connectors</b>						
5/8" rod to 3ea #2 tap		1.00	1.25	1.56		E

## Section 8 - Grounding & Lightning Protection Systems











Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Double H-Tap Connector</b>						
#9,8 Rebar/1" rod main to #2-250 tap		0.85	1.06	1.33		E
1" rod/#500 main to #350-#500 tap		1.15	1.44	1.80		E
#6 Rebar/1" rod/3350-500 main to #350-#500 tap		1.25	1.56	1.95		E
#6 Rebar / 3/4" rod/#250-400 main to #4/0-400 tap		1.10	1.38	1.72		E
#6 Rebar / 3/4" rod/#4/0 main to #1/0 - 3/0 tap		1.00	1.25	1.56		E
<b>"C" Compression Ground Tap Connector</b>						
#6-#2 Main to #6-#2 tap		0.35	0.44	0.55		E
#1-#2/0 main to #6-#2 tap		0.50	0.63	0.78		E
#1-#2/0 main to #1-#2/0 tap		0.60	0.75	0.94		E
#3/0-#250 main to #6-#2/0 tap		0.65	0.81	1.02		E
#3/0-#250 main to #3-#2/0 tap		0.85	1.06	1.33		E
#300-#500 main to #6-#2/0 tap		0.70	0.88	1.09		E
#300-#500 main to #3/0-#250 tap		1.00	1.25	1.56		E
#300-#500 main to #300-#500 tap		1.20	1.50	1.88		E
<b>Grounding Plate Insert for Concrete</b>						
#2-250 "C" tap and ground plate		1.00	1.25	1.56		E
#250-500 "C" tap and ground plate		1.10	1.38	1.72		E
<b>Steel Structural Compression Connector with 2ea studs, washers, lock washers, nuts to accept a 2-hole compression lug compress</b>						
3" long steel structural compress connector to 1/4" to 1/2" thick steel flange		1.50	1.88	2.34		E
3" long steel structural compress connector to 1/2" to 1/4" thick steel flange		1.75	2.19	2.73		E
6" long steel structural compress connector to 1/4" to 1/2" thick steel flange		2.00	2.50	3.13		E
6" long steel structural compress connector to 1/2" to 1/4" thick steel flange		2.25	2.81	3.52		E
<b>Main and Secondary Conductor AL</b>						
AL #4		10.00	12.50	15.00		M
AL #3		11.00	13.50	16.00		M
AL #2		12.00	14.50	17.00		M
AL #1 98.5K CIR. MIL.		13.00	15.50	18.00		M
AL #1/0 106.8K CIR. MIL.		14.00	17.50	20.00		M
AL #2/0 115K CIR. MIL.		15.00	20.00	24.00		M
AL #4/0 211.6 CIR. MIL.		18.00	22.50	28.00		M
<b>Main and Secondary Conductor CU</b>						
CU #6 26.0K CIR.MIL.		9.00	11.50	14.00		M
CU #3 61.4K CIR. MIL.		12.00	14.50	17.00		M
CU #2 65.5K CIR. MIL.		14.00	17.50	20.00		M
CU #2 69.6K CIR. MIL.		14.50	18.00	20.50		M
CU #2 73.7K CIR.MIL.		15.00	18.50	21.00		M
CU #1 81.9K CIR. MIL.		16.00	19.00	21.50		M
CU #1 86.6K CIR. MIL.		16.50	19.50	22.00		M
CU #1/0 98.5K CIR. MIL.		18.00	21.00	24.00		M
CU #1/0 115K CIR. MIL.		18.50	21.50	24.50		M
CU #2/0 131.6K CIR. MIL.		20.00	25.00	30.00		M
CU #4/0 211.6K CIR. MIL.		24.00	30.00	36.00		M
<b>AL Bus Bar</b>						
AL Bus Bar 1/8"x 1"W		0.25	0.28	0.35		FT
AL Bus Bar 1/8"x 3/4"W		0.25	0.28	0.35		FT
AL Bus Bar 1/8"x 1/2"W		0.30	0.36	0.45		FT
AL Bus Bar 1/8"x 2"W		0.35	0.42	0.50		FT
AL Bus Bar 1/4"x 3/4"W		0.30	0.36	0.45		FT
AL Bus Bar 1/4"x 1"W		0.35	0.42	0.50		FT
AL Bus Bar 1/4"x 1 1/2"W		0.40	0.48	0.58		FT
AL Bus Bar 1/4"x 2"W		0.45	0.53	0.63		FT
<b>CU Bus Bar</b>						
CU Bus Bar 1/16"x 1"W		0.23	0.28	0.35		FT
CU Bus Bar 1/8"x 1"W		0.23	0.28	0.35		FT
CU Bus Bar 1/8"x 3/4"W		0.32	0.39	0.47		FT
CU Bus Bar 1/8"x 1 1/2"W		0.37	0.45	0.55		FT
CU Bus Bar 1/8"x 2"W		0.45	0.55	0.65		FT
CU Bus Bar 1/4"x 3/4"W		0.45	0.55	0.70		FT
CU Bus Bar 1/4"x 1"W		0.50	0.60	0.75		FT
CU Bus Bar 1/4"x 1 1/2"W		0.55	0.65	0.85		FT
CU Bus Bar 1/4"x 2"W		0.60	0.72	0.90		FT
<i>Note: Bending not included, add .25 for each isolation standoff that is required</i>						












## Section 8 - Grounding & Lightning Protection Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Lightning Protection</b>						
<b>AL Flat Conductor</b>						
 AL Flat Conductor 14GA x 5/8"W		8.00	10.00	12.00		C
 AL Flat Conductor 12GA x 1"W		9.00	11.30	13.50		C
 AL Flat Conductor 12GA x 1 1/4"W		10.00	12.50	15.00		C
<b>CU Flat Conductor</b>						
 CU Flat Conductor 16GA x 1/2"W		8.00	10.00	12.00		C
 CU Flat Conductor 14GA x 1"W		10.00	12.50	15.00		C
 CU Flat Conductor 14GA x 1 1/4"W		12.00	15.00	18.00		C
 CU Flat Conductor 0.129" x 3/4"W		14.00	17.50	21.00		C
<b>Bonding Plates</b>						
 Bonding Plates AL #2 - 1/0		0.50	0.75	0.80		E
 Bonding Plates AL 2/0 - 1/0		0.65	0.80	1.00		E
 Bonding Plates CU #6 - #2		0.50	0.65	0.85		E
 Bonding Plates CU #1 - 4/0		0.80	0.95	1.15		E
<b>Adhesive Cable Holder</b>						
 Adhesive Cable Holder AL #2 - 1/0		0.30	0.40	0.55		E
 Adhesive Cable Holder AL #2/0 - 4/0		0.50	0.60	0.75		E
 Adhesive Cable Holder CU #6 - #2		0.35	0.45	0.60		E
 Adhesive Cable Holder CU #1 - 4/0		0.60	0.70	0.85		E
<b>Cable Fastener (Masonry)</b>						
 Cable Fastener (Masonry) AL #2 - 1/0		0.18	0.23	0.30		E
 Cable Fastener (Masonry) AL 2/0 - 4/0		0.23	0.28	0.35		E
 Cable Fastener (Masonry) CU #6 - #2		0.20	0.25	0.33		E
 Cable Fastener (Masonry) CU #1 - 4/0		0.25	0.30	0.38		E
<b>Cable Fasteners</b>						
 Cable Fasteners AL #2 - 1/0		0.12	0.14	0.20		E
 Cable Fasteners AL 2/0 - 4/0		0.15	0.20	0.25		E
 Cable Fasteners CU #6 - #2		0.13	0.17	0.23		E
 Cable Fasteners CU #1 - 4/0		0.18	0.22	0.28		E
<b>Cable Splicers</b>						
 Cable Splicers AL #2 - 1/0		0.28	0.34	0.43		E
 Cable Splicers AL 2/0 - 4/0		0.40	0.48	0.60		E
 Cable Splicers CU #6 - #2		0.30	0.37	0.45		E
 Cable Splicers CU #1 - 4/0		0.43	0.51	0.63		E
<b>Tee Cable Splicers</b>						
 Tee Cable Splicers AL #2 - 1/0		0.55	0.68	0.83		E
 Tee Cable Splicers AL 2/0 - 4/0		0.80	0.95	1.15		E
 Tee Cable Splicers CU #6 - #2		0.60	0.73	0.90		E
 Tee Cable Splicers CU #1 - 4/0		0.90	1.08	1.30		E
<b>Three Way Splicer</b>						
 Three Way Splicer AL #2 - 1/0		0.75	0.90	1.10		E
 Three Way Splicer AL 2/0 - 4/0		1.15	1.35	1.65		E
 Three Way Splicer CU #6 - #2		0.90	1.08	1.30		E
 Three Way Splicer CU #1 - 4/0		1.30	1.53	1.85		E
<b>Cross Run Splicer</b>						
 Cross Run Splicer AL #2 - 1/0		0.80	0.95	1.20		E
 Cross Run Splicer AL 2/0 - 4/0		1.20	1.45	1.80		E
 Cross Run Splicer CU #6 - #2		1.00	1.20	1.50		E
 Cross Run Splicer CU #1 - 4/0		1.50	1.80	2.25		E
<b>Straight Splicer</b>						
 Straight Splicer AL #2 - 1/0		0.60	0.72	0.90		E
 Straight Splicer AL 2/0 - 4/0		0.90	1.10	1.35		E
 Straight Splicer CU #6 - #2		0.65	0.80	1.00		E
 Straight Splicer CU #1 - 4/0		0.95	1.15	1.45		E
<b>Bonding Lug</b>						
 Bonding Lug AL #2 - 1/0		0.30	0.40	0.53		E
 Bonding Lug AL 2/0 - 4/0		0.53	0.65	0.80		E
 Bonding Lug CU #6 - #2		0.35	0.45	0.58		E
 Bonding Lug CU #1 - 4/0		0.55	0.68	0.85		E


## Section 8 - Grounding & Lightning Protection Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
						
<b>Thru Roof Point Adapt</b>						
Thru Roof Point Adapt AL 3/8"		0.83	0.95	1.15		E
Thru Roof Point Adapt AL 1/2"		1.08	1.28	1.53		E
Thru Roof Point Adapt AL 5/8"		1.32	1.58	1.90		E
Thru Roof Point Adapt CU 3/8"		0.75	0.90	1.10		E
Thru Roof Point Adapt CU 1/2"		1.13	1.33	1.60		E
Thru Roof Point Adapt CU 5/8"		1.38	1.63	2.05		E
						
<b>Thru Wall or Roof Cable Connector</b>						
Thru Wall or Roof Cable Connector AL 3/8"		0.70	0.85	1.03		E
Thru Wall or Roof Cable Connector AL 1/2"		1.08	1.28	1.53		E
Thru Wall or Roof Cable Connector 5/8"		1.33	1.58	1.90		E
Thru Wall or Roof Cable Connector CU 3/8"		0.75	0.90	1.10		E
Thru Wall or Roof Cable Conn CU 1/2"		1.13	1.32	1.60		E
Thru Wall or Roof Cable Connector CU 5/8"		1.38	1.63	2.05		E
						
<b>Swivel Adapt AL</b>						
Swivel Adapt AL 1/2\"F to 1/2\"F		0.45	0.50	0.60		E
Swivel Adapt AL 1/2\"F to 1/2\"M		0.50	0.60	0.70		E
Swivel Adapt AL 1/2\"F to 5/8\"F		0.50	0.60	0.70		E
Swivel Adapt AL 1/2\"M to 5/8\"F		0.60	0.70	0.85		E
						
<b>Swivel Adapt CU</b>						
Swivel Adapt CU 1/2\"F to 3/8\"F		0.45	0.55	0.75		E
Swivel Adapt CU 1/2\"F to 3/8\"M		0.55	0.70	0.90		E
Swivel Adapt CU 1/2\"F to 1/2\"F		0.50	0.60	0.75		E
Swivel Adapt CU 1/2\"M to 1/2\"F		0.60	0.70	0.80		E
Swivel Adapt CU 1/2\"F to 5/8\"F		0.65	0.75	0.95		E
Swivel Adapt CU 1/2\"M to 5/8\"F		0.75	0.85	1.00		E
						
<b>AL Points</b>						
AL Points 1/2\" Dia. x 10\"L thru 30"		0.40	0.48	0.60		E
AL Points 1/2\" Dia. x 36\"L thru 60"		0.50	0.60	0.75		E
AL Points 5/8\" Dia. x 10\"L thru 36"		0.40	0.48	0.60		E
AL Points 5/8\" Dia. x 48\"L		0.50	0.60	0.75		E
AL Points 5/8\" Dia. x 60\"L		0.60	0.72	0.90		E
						
<b>CU Points</b>						
CU Points 3/8\" Dia x 10\"L thru 30"		0.40	0.48	0.60		E
CU Points 3/8\" Dia x 36\"L thru 60"		0.50	0.60	0.75		E
CU Points 1/2\" Dia.x 10\"L thru 30"		0.40	0.48	0.60		E
CU Points 1/2\" Dia.x 36\"L thru 48"		0.50	0.60	0.75		E
CU Points 1/2\" Dia.x 60\"L		0.60	0.72	0.90		E
CU Points 5/8\" Dia.x 10\"L thru 36"		0.50	0.60	0.75		E
CU Pomts 5/8\" Dia.x 48\"L		0.60	0.72	0.90		E
CU Points 5/8\" Dia.x 60\"L		0.70	0.80	1.00		E
						
<b>Ridge or Flat Point Base</b>						
Ridge or Flat Point Base AL 3/8"		1.00	1.20	1.45		E
Ridge or Flat Point Base AL 1/2"		1.00	1.20	1.45		E
Ridge or Flat Point Base AL 5/8"		1.00	1.20	1.45		E
Ridge or Flat Point Base CU 3/8"		1.00	1.20	1.45		E
Ridge or Flat Point Base CU 1/2"		1.00	1.20	1.45		E
Ridge or Flat Point Base CU 5/8"		1.00	1.20	1.45		E
						
<b>Side Ridge Point Base</b>						
Side Ridge Point Base AL 3/8"		1.00	1.20	1.45		E
Side Ridge Point Base AL 1/2"		1.00	1.20	1.45		E
Side Ridge Point Base AL 5/8"		1.00	1.20	1.45		E
Side Ridge Point Base CU 3/8"		1.00	1.20	1.45		E
Side Ridge Point Base CU 1/2"		1.00	1.20	1.45		E
Side Ridge Point Base CU 5/8"		1.00	1.20	1.45		E
						
<b>Flue Liner Point Base</b>						
Flue Liner Point Base AL 3/8"		1.00	1.20	1.45		E
Flue Liner Point Base AL 1/2"		1.00	1.20	1.45		E
Flue Liner Point Base AL 5/8"		1.00	1.20	1.45		E
Flue Liner Point Base CU 3/8"		1.00	1.20	1.45		E
Flue Liner Point Base CU 1/2"		1.00	1.20	1.45		E
Flue Liner Point Base CU 5/8"		1.00	1.20	1.45		E
						
<b>Tee Point Base</b>						
Tee Point Base AL 3/8"		0.48	0.60	0.75		E
Tee Point Base AL 1/2"		0.60	0.75	0.93		E
Tee Point Base AL 5/8"		0.73	0.90	1.10		E
Tee Point Base CU 3/8"		0.52	0.65	0.82		E
Tee Point Base CU 1/2"		0.65	0.80	1.00		E
Tee Point Base CU 5/8"		0.78	0.95	1.18		E

## Section 8 - Grounding & Lightning Protection Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Straight Point Base</b>						
 Straight Point Base AL 3/8"		0.60	0.72	0.90		E
Straight Point Base AL 1/2"		0.80	0.95	1.20		E
Straight Point Base AL 5/8"		1.00	1.20	1.50		E
Straight Point Base CU 3/8"		0.70	0.85	1.05		E
Straight Point Base CU 1/2"		0.90	1.10	1.35		E
Straight Point Base CU 5/8"		1.10	1.35	1.65		E
<b>Comb. Point Base</b>						
 Comb. Point Base AL 3/8"		0.90	1.10	1.35		E
Comb. Point Base AL 1/2"		1.10	1.35	1.65		E
Comb. Point Base AL 5/8"		1.30	1.55	1.95		E
Comb. Point Base CU 3/8"		1.00	1.20	1.50		E
Comb. Point Base CU 1/2"		1.20	1.45	1.80		E
Comb. Point Base CU 5/8"		1.40	1.70	2.10		E
<b>Adhesive Point Base</b>						
 Adhesive Point Base AL 3/8"		0.60	0.75	0.93		E
Adhesive Point Base AL 1/2"		0.75	0.93	1.13		E
Adhesive Point Base AL 5/8"		0.90	1.08	1.33		E
Adhesive Point Base CU 3/8"		0.65	0.80	1.00		E
Adhesive Point Base CU 1/2"		0.80	0.98	1.20		E
Adhesive Point Base CU 5/8"		0.95	1.15	1.40		E
<b>Offset Wall Point Base</b>						
 Offset Wall Point Base AL 3/8"		0.80	0.98	1.18		E
Offset Wall Point Base AL 1/2"		1.00	1.13	1.38		E
Offset Wall Point Base AL 5/8"		1.10	1.30	1.58		E
Offset Wall Point Base CU 3/8"		0.85	1.03	1.25		E
Offset Wall Point Base CU 1/2"		1.00	1.20	1.45		E
Offset Wall Point Base CU 5/8"		1.15	1.38	1.65		E
<b>Metal Mount Point Base</b>						
 Metal Mount Point Base AL 3/8"		0.70	0.85	1.03		E
Metal Mount Point Base AL 1/2"		0.90	1.03	1.23		E
Metal Mount Point Base AL 5/8"		1.00	1.18	1.43		E
Metal Mount Point Base CU 3/8"		0.75	0.90	1.10		E
Metal Mount Point Base CU 1/2"		0.90	1.08	1.30		E
Metal Mount Point Base CU 5/8"		1.05	1.25	1.50		E
<b>Reglet Mount Point Base</b>						
 Reglet Mount Point Base AL 3/8"		0.70	0.85	1.05		E
Reglet Mount Point Base AL 1/2"		0.85	1.03	1.25		E
Reglet Mount Point Base AL 5/8"		1.00	1.20	1.45		E
Reglet Mount Point Base CU 3/8"		0.75	0.93	1.13		E
Reglet Mount Point Base CU 1/2"		0.90	1.08	1.33		E
Reglet Mount Point Base CU 5/8"		1.05	1.25	1.53		E
<b>Flat Surface Point Base</b>						
 Flat Surface Point Base AL 3/8"		0.80	0.95	1.15		E
Flat Surface Point Base AL 1/2"		0.95	1.13	1.35		E
Flat Surface Point Base AL 5/8"		1.10	1.30	1.55		E
Flat Surface Point Base CU 3/8"		0.85	1.03	1.23		E
Flat Surface Point Base CU 1/2"		1.00	1.18	1.43		E
Flat Surface Point Base CU 5/8"		1.15	1.35	1.63		E
<b>Cone Vent Point Base</b>						
 Cone Vent Point Base AL 3/8"		0.65	0.80	0.98		E
Cone Vent Point Base AL 1/2"		0.80	0.98	1.18		E
Cone Vent Point Base AL 5/8"		0.95	1.13	1.38		E
Cone Vent Point Base CU 3/8"		0.70	0.85	1.05		E
Cone Vent Point Base CU 1/2"		0.85	1.03	1.25		E
Cone Vent Point Base CU 5/8"		1.00	1.20	1.45		E
<b>Coupling and Adapters for Point AL</b>						
 1/2\"F to 1/2\"F		0.12	0.15	0.20		E
5/8\"F to 5/8\"F		0.18	0.21	0.30		E
1/2\"F to 5/8\"F		0.18	0.21	0.30		E
1/2\"F to 1/2\"M	X	0.12	0.15	0.20		E
5/8\"F to 5/8\"M		0.18	0.21	0.30		E
1/2\"F to 5/8\"M		0.18	0.21	0.30		E
5/8\"F to 1/2\"M		0.18	0.21	0.30		E
1/2\"M to 1/2\"M		0.12	0.15	0.20		E
5/8\"M to 5/8\"M		0.18	0.21	0.30		E
1/2\"M to 5/8\"M		0.18	0.21	0.30		E

## Section 8 - Grounding & Lightning Protection Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Coupling and Adapters for Point CU</b>						
 3/8"F to 3/8"F		0.10	0.12	0.15		E
1/2"F to 1/2"F		0.15	0.18	0.25		E
1/2"F to 3/8"F		0.15	0.18	0.25		E
5/8"F to 5/8"F		0.20	0.25	0.30		E
1/2"F to 5/8"F		0.20	0.25	0.30		E
3/8:F to 3/8*M		0.10	0.12	0.15		E
1/2"F to 1/2*M		0.15	0.18	0.25		E
1/2"F to 3/8*M		0.15	0.18	0.25		E
3/8"F to 1/2*M		0.15	0.18	0.25		E
5/8"F to 5/8*M		0.20	0.25	0.30		E
1/2"F to 5/8*M		0.20	0.25	0.30		E
5/8"F to 1/2*M		0.20	0.25	0.30		E
3/8*M to 3/8*M		0.10	0.12	0.15		E
1/2*M to 1/2*M		0.15	0.18	0.25		E
1/2:M to 3/8*M		0.15	0.18	0.25		E
5/8*M to 5/8*M		0.20	0.25	0.30		E
1/2*M to 5/8*M		0.20	0.25	0.30		E
<b>Ground Rod for Down Spout</b>						
Ground Rod 1/2" Dia. X 8'		1.00	1.20	1.50		E
Ground Rod 1/2" Dia. X 10'		1.25	1.50	1.90		E
Ground Rod 5/8" Dia. X 6'		1.10	1.35	1.65		E
Ground Rod 5/8" Dia. X 8'		1.35	1.60	2.00		E
Ground Rod 5/8" Dia. X 10'		1.75	2.10	2.60		E
Ground Rod 3/4" Dia. X 6'		1.25	1.50	1.90		E
Ground Rod 3/4" Dia. X 8'		1.50	1.80	2.25		E
Ground Rod 3/4" Dia. X 10'		2.00	2.40	3.00		E
Ground Rod 1" Dia. X 10'		2.50	3.00	3.75		E
<b>Cable Protectors CU</b>						
Cable Protectors CU Pipe 5/8" Dia. X 7"L		0.75	0.90	1.15		E
Cable Protectors CU Pipe 3/4" Dia. X 7"L		0.95	1.15	1.30		E
Cable Protectors CU Pipe 7/8" Dia. X 7"L		1.25	1.50	1.90		E
<b>Cable Protectors PVC Pipe</b>						
Cable Protectors PVC Pipe 1/2" IPS x 10'L		0.50	0.60	0.75		E
Cable Protectors PVC Pipe 3/4" IPS x 10'L		0.75	0.90	1.15		E
<b>Cable Protectors Galv Steel</b>						
Cable Protectors Galv Steel 3/4" Dia. x 8'L		1.50	1.80	2.25		E
<b>Cable Protectors Wood</b>						
Cable Protectors Wood 3/4" Dia. X 8'L		0.80	0.95	1.20		E
<b>Cable Protectors Strap Pipe</b>						
Cable Protectors Strap Pipe 5/8"		0.20	0.25	0.30		E
Cable Protectors Strap Pipe 3/4"		0.25	0.30	0.40		E
Cable Protectors Strap Pipe 1"		0.25	0.30	0.40		E
<b>Electronically Activated Streamer Emission Air Terminal.</b>						
<i>Most streamer emission systems cannot offer an UL Master label, check with manufacturer for details.</i>						
<i>Roof repair and sealing is not included.</i>						
<i>It is recommended to test this system once a year, check with manufacturer for details.</i>						
<i>Check FAA requirements for obstruction warning lights.</i>						
<i>Stainless steel bolts, washers and nuts are recommended.</i>						
<i>Install down load per manufacturer's instructions.</i>						
Streamer emission air terminal		4.00	5.00	6.25		E
Mast-8' tall, 3" top dia, 4" butt dia		2.00	2.50	3.13		E
Mast-10' tall, 3" top dia, 4" butt dia		2.25	2.81	3.52		E
Mast-12' tall, 3" top dia, 4" butt dia		2.50	3.13	3.91		E
Mast-14' tall, 3" top dia, 4" butt dia		2.75	3.44	4.30		E
Mast-16' tall, 3" top dia, 4" butt dia		3.00	3.75	4.69		E
Mast-18' tall, 3" top dia, 4" butt dia		3.25	4.06	5.08		E
Mast-20' tall, 3" top dia, 4" butt dia		3.50	4.38	5.47		E
18" welding adapter plate		2.00	2.50	3.13		E
12'X12" pre-cast/concrete adapter plate		2.00	2.50	3.13		E

## Section 8 - Grounding & Lightning Protection Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Cathodic Protection</b>						
 Corrosion monitoring concrete structure	X	0.50	0.63	0.68		E
 Flange Kit	X	1.00	1.25	1.35		E
 Insulating sleeves	X	0.70	0.88	0.95		E
 Monitoring probe underground soil	X	1.50	1.88	2.03		E
 Platinodes Anodes	X	1.50	1.88	2.03		E
 Rectifiers	X	4.00	5.00	5.40		E
 Remote monitoring	X	16.00	20.00	21.60		E
 Remote monitoring sulfuric acid probe	X	2.00	2.50	2.70		E
 Remote water tank monitoring probe	X	2.00	2.50	2.70		E
 Sacrificial Anode	X	2.00	2.50	2.70		E
 Sealing gasket	X	1.50	1.88	2.03		E
 Special application gaskets	X	2.00	2.50	2.70		E
 Test station	X	4.00	5.00	5.40		E
 Supergrip Top						



# SECTION 9

## HEATING EQUIPMENT CONNECTIONS

### General Information

The labor units in this section are applicable for the installation of electrical heating equipment and their controls. A separate labor unit table is included for the power conductor termination labor on other heating, ventilating, air conditioning and related items not listed in this manual. For electric motor conductor termination labor units, see Section 12.

### Scope of These Labor Units

The Introduction section includes details on the scope of labor units across the manual. Some items included are:

- Material unloading at jobsite
- Moving material to the point of installation
- Plan study, layout and marking of installation location
- Actual material installation time
- Appropriate fastening to existing supports
- Power and grounding conductor connections
- Clean-up of electrical contractor furnished excess material
- Normal non-productive labor

### Work Operations Not Included In These Labor Units

- Field supervision
- Raceway terminations
- Welding or painting
- Testing of any type
- Installation of branch circuits, including such items as pull boxes, flexible conduit, wire, etc.
- Control wiring
- Mounting of motors when shipped separately with equipment
- Sheet metal ducting
- Design of electric heating systems
- Fabrication or installation of supports
- Adjustment of air flow, equipment calibration and similar environmental system testing

### Labor Adjustments for Non-Typical Conditions

See the Introduction section for details.

### Application Instructions

- Labor units under the “Normal” column are for heights up to eight feet above a smooth, hard floor. Labor units under the “Difficult” column are for heights up to 12 feet. Labor units under the “Very Difficult” column are for heights up to 16 feet.
- Labor unit tables do not include every type and size of items available. When labor units are required for items not listed, an approximate labor unit may be obtained from the tables for a similar item of about the same weight, dimensions and conductor terminations.
- All the labor units in this section are based on using the most efficient tools and equipment available. When the anticipated jobsite conditions will prevent the optimum use of tools and equipment, an appropriate additional labor allowance in proportion to the anticipated difficulties is necessary.
- Labor units in this manual are for new work only and for a complete electrical installation. For remodeling or change order situations these labor units need to be substantially increased.






## Section 9 - Heating Equipment Connections Table of Contents

Baseboard Heaters	9-5
Blank Baseboard Section	9-5
Baseboard Section - Electrical Accys	9-5
Radiant Heat Panels	9-5
Radiant Heat Panel Frames	9-5
Electric 120 Volt Wall Heaters	9-5
Electric 240 Volt Wall Heaters	9-5
One Conductor 600 Volt Heating Cable	9-5
Heat Tape and Accessories	9-5
Electric Snow Melting Mats-12" Wide	9-6
Electric Snow Melting Mats-24" Wide	9-6
Electric Snow Melting Mats-36" Wide	9-6
Electric Snow Melting Mats-48" Wide	9-6
Electric Snow Melting Mats-60" Wide	9-6
125 Volt Duct Heaters	9-6
250 Volt Duct Heaters	9-7
125 Volt and 250 Volt Unit Heaters with Blowers	9-7
Recessed Heating Fixtures	9-7
Thermostats	9-7
Electronic Air Filters-120 Volt	9-7
Heating Controls	9-7
Step Controllers-20 Amp per Step	9-8
Power Connections to Equipment Installed by Others - Copper 600 Volt Cond.	9-8
Power Connections to Equipment Installed by Others - Aluminum 600 Volt Cond.	9-8







(Updated)




### Section 9 - Heating Equipment Connections

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Baseboard Heaters</b>						
 24"		0.75	0.94	1.13		E
36"		0.80	1.00	1.20		E
48"		0.90	1.13	1.35		E
60"		1.00	1.25	1.50		E
72"		1.10	1.38	1.65		E
96"		1.25	1.56	1.88		E
120"		1.40	1.75	2.10		E
<b>Blank Baseboard Section</b>						
18"		0.30	0.38	0.45		E
24"		0.35	0.44	0.53		E
30"		0.40	0.50	0.60		E
36"		0.45	0.56	0.68		E
Splice Plate		0.12	0.13	0.15		E
End Section Cap		0.10	0.15	0.18		E
Inside & Outside Corners		0.30	0.50	0.60		E
<b>Baseboard Section - Electrical Accys</b>						
20 Amp 120 Volt Receptacle Section		0.60	0.75	0.90		E
240 Volt Air Conditioning Section		0.80	1.00	1.20		E
Thermostat Baseboard Section		0.60	0.75	0.90		E
<b>Radiant Heat Panels</b>						
2' x 2'		0.50	0.63	0.75		E
2' x 4'		0.75	0.94	1.13		E
2' x 8'		1.10	1.38	1.65		E
4' x 8'		1.60	2.00	2.40		E
<b>Radiant Heat Panel Frames</b>						
2' x 2'		0.40	0.50	0.60		E
2' x 4'		0.50	0.63	0.75		E
2' x 8'		0.70	0.88	1.05		E
4' x 8'		1.20	1.50	1.80		E
<b>Electric 120 Volt Wall Heaters</b>						
400 Watt		1.00	1.13	1.35		E
600 Watt		1.10	1.25	1.50		E
800 Watt		1.20	1.38	1.65		E
1000 Watt		1.30	1.50	1.80		E
1200 Watt		1.40	1.63	1.95		E
1400 Watt		1.50	1.75	2.10		E
1600 Watt		1.75	1.88	2.25		E
1800 Watt		1.85	2.06	2.48		E
2000 Watt		2.00	2.25	2.70		E
<b>Electric 240 Volt Wall Heaters</b>						
2500 Watt		2.00	2.25	2.70		E
3000 Watt		2.20	2.50	3.00		E
3500 Watt		2.30	2.75	3.30		E
4000 Watt		2.75	3.13	3.75		E
5000 Watt		3.25	3.75	4.50		E
<b>One Conductor 600 Volt Heating Cable</b>						
2 Watt/Ft Plastic Jacket		2.00	2.50	3.00		C
5 Watt/Ft Plastic Jacket		2.20	2.75	3.30		C
7 Watt/Ft Plastic Jacket		2.40	3.00	3.60		C
7 Watt/Ft Lead Jacket		2.60	3.25	3.90		C
10 Watt/Ft Plastic Jacket		2.60	3.25	3.90		C
15 Watt/Ft Plastic Jacket		2.80	3.50	4.20		C
20 Watt/FT Plastic Jacket		3.00	3.75	4.50		C
Radiant Heat Ceiling Panel Installation Only 12" to 24"		2.00	2.50	3.00		E
<b>Heat Tape and Accessories</b>						
Self Regulating Heat Tape		2.50	4.00	6.00		C
Power Connection Kit w/o J Box		0.50	0.75	1.00		E
Power Connection Kit with J Box		0.75	1.00	1.25		E
Splice Kit		0.50	0.75	1.00		E
Tee Kit		0.75	1.50	2.00		E
End Seal Kit		0.50	0.75	1.00		E
Ordinary Area Thermostats		1.00	1.50	2.00		E

### Section 9 - Heating Equipment Connections

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Electric Snow Melting Mats-12" Wide</b>						
 5'		0.60	0.75	0.90		E
10'		0.70	0.88	1.05		E
15'		0.80	1.00	1.20		E
20'		0.90	1.13	1.35		E
25'		1.00	1.25	1.50		E
30'		1.10	1.38	1.65		E
40'		1.30	1.63	1.95		E
50'		1.50	1.88	2.25		E
<b>Electric Snow Melting Mats-24" Wide</b>						
 5'		0.80	1.00	1.20		E
10'		0.90	1.13	1.35		E
15'		1.00	1.25	1.50		E
20'		1.10	1.38	1.65		E
25'		1.20	1.50	1.80		E
30'		1.30	1.63	1.95		E
40'		1.50	1.88	2.25		E
50'		1.70	2.13	2.55		E
<b>Electric Snow Melting Mats-36" Wide</b>						
 5'		1.00	1.25	1.50		E
10'		1.10	1.38	1.65		E
15'		1.20	1.50	1.80		E
20'		1.30	1.63	1.95		E
25'		1.40	1.75	2.10		E
30'		1.50	1.88	2.25		E
40'		1.75	2.19	2.63		E
50'		2.00	2.50	3.00		E
<b>Electric Snow Melting Mats-48" Wide</b>						
 5'		1.20	1.50	1.80		E
10'		1.30	1.63	1.95		E
15'		1.40	1.75	2.10		E
20'		1.50	1.88	2.25		E
25'		1.60	2.00	2.40		E
30'		1.75	2.19	2.63		E
40'		2.00	2.50	3.00		E
50'		2.25	2.81	3.38		E
<b>Electric Snow Melting Mats-60" Wide</b>						
 5'		1.40	1.75	2.10		E
10'		1.50	1.88	2.25		E
15'		1.60	2.00	2.40		E
20'		1.70	2.13	2.55		E
25'		1.80	2.25	2.70		E
30'		2.00	2.50	3.00		E
40'		2.25	2.81	3.38		E
50'		2.50	3.13	3.75		E
<b>125 Volt Duct Heaters</b>						
 1 Kw		1.00	1.25	1.50		E
2 KW		1.10	1.38	1.65		E
3 KW		1.20	1.50	1.80		E
4 KW		1.30	1.63	1.95		E
6 KW		1.40	1.75	2.10		E
8 KW		1.50	1.88	2.25		E
10 KW		1.60	2.00	2.40		E
15 KW		1.80	2.25	2.70		E
20 KW		2.00	2.50	3.00		E
30 KW		2.50	3.13	3.75		E
40 KW		3.00	3.75	4.50		E
50 KW		3.50	4.38	5.25		E
60 KW		4.00	5.00	6.00		E
80 KW		5.00	6.25	7.50		E
100 KW		6.00	7.50	9.00		E
150 KW		7.00	8.75	10.50		E
200 KW		8.00	10.00	12.00		E
400 KW		10.00	12.50	15.00		E
600 KW		12.00	15.00	18.00		E
800 KW		14.00	17.50	21.00		E

## Section 9 - Heating Equipment Connections

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>250 Volt Duct Heaters</b>						
 2 KW		0.90	1.13	1.35		E
3 KW		1.00	1.25	1.50		E
4 KW		1.10	1.38	1.65		E
6 KW		1.20	1.50	1.80		E
8 KW		1.35	1.69	2.03		E
10 KW		1.50	1.88	2.25		E
15 KW		1.70	2.13	2.55		E
20 KW		1.90	2.38	2.85		E
30 KW		2.30	2.88	3.45		E
40 KW		2.70	3.38	4.05		E
50 KW		3.10	3.88	4.65		E
60 KW		3.50	4.38	5.25		E
80 KW		4.50	5.63	6.75		E
100 KW		5.50	6.88	8.25		E
150 KW		6.50	8.13	9.75		E
200 KW		7.50	9.38	11.25		E
400 KW		9.00	11.25	13.50		E
600 KW		11.00	13.75	16.50		E
800 KW		13.00	16.25	19.50		E
<i>Note: See Equipment Installation &amp; Connections Section 12</i>						
<b>125 Volt and 250 Volt Unit Heaters with Blowers Including Hanger Mounting Brackets</b>						
1 to 2 KW		2.00	2.50	3.00		E
3 KW		2.50	3.13	3.75		E
4 KW		2.75	3.44	4.13		E
5 KW		3.00	3.75	4.50		E
6 KW		3.25	4.06	4.88		E
8 KW		3.50	4.38	5.25		E
10 KW		4.00	5.00	6.00		E
15 KW		5.00	6.25	7.50		E
20 KW		6.00	7.50	9.00		E
25 KW		8.00	10.00	12.00		E
30 KW		10.00	12.50	15.00		E
35 KW		12.00	15.00	18.00		E
40 KW		14.00	17.50	21.00		E
45 KW		16.00	20.00	24.00		E
50 KW		18.00	22.50	27.00		E
60 KW		20.00	25.00	30.00		E
75 KW		22.00	27.50	33.00		E
<b>Recessed Heating Fixtures</b>						
Single Heating Lamp Fixture		1.00	1.25	1.50		E
Twin Heating Lamp Fixture		1.20	1.50	1.80		E
Triple Heating Lamp Fixture		1.50	1.88	2.25		E
2-Lamp Heater & Exhaust Fan		1.40	1.75	2.10		E
1000 Watt Ceiling Heater w/o Fan		1.00	1.25	1.50		E
1000 Watt Ceiling Heater with Fan		1.20	1.50	1.80		E
1500 Watt Ceiling Heater with Fan		1.50	1.88	2.25		E
Combination 1000 W Ceil Htr w Light		1.60	2.00	2.40		E
Comb 1000 W Ceil Htr w/Light & Exh. Fan		2.00	2.50	3.00		E
Surface Mounted 1000 Watt Ceiling heater with fan		1.40	1.75	2.10		E
<b>Thermostats</b>						
Low Voltage 1-Circuit Thermostats		0.50	0.70	0.98		E
Low Voltage 2-Circuit Thermostats		0.60	0.84	1.18		E
Low Voltage 3-Circuit Thermostats		0.66	0.92	1.30		E
Line Voltage 1-Circuit Thermostats		0.60	0.84	1.18		E
Line Voltage 2-Circuit Thermostats		0.66	0.92	1.30		E
Line Voltage 3-Circuit Thermostats		0.72	1.00	1.40		E
Duct Mounted 1-Circuit Bulb Thermostats		0.70	0.98	1.37		E
Duct Mounted 2-Circuit Bulb Thermostats		0.84	1.18	1.65		E
Explosion proof LV 1-Circuit Thermostats		1.60	2.00	2.40		E
Explosion proof LV 2-Circuit Thermostats		1.70	2.13	2.55		E
Exp. Proof Line Voltage 1-Circuit Thermostats		1.80	2.25	2.70		E
Exp. Proof Line Voltage 2-Circuit Thermostats		1.90	2.38	2.85		E
<b>Electronic Air Filters-120 Volt</b>						
500 to 5000CFM-Wt 50-166Lbs		2.00	2.50	3.00		E
<b>Heating Controls</b>						
Humidistat 120 Volt Up to 20 Amp		1.00	1.25	1.50		E
Humidistat 120 Volt Up to 40 Amp		1.20	1.50	1.80		E
Low Voltage Thermal Relays Up to 20 Amp		1.00	1.25	1.50		E
Low Voltage Thermal Relays Up to 40 Amp		1.20	1.50	1.80		E
Sequence Controllers Up to 20 Amp		3.20	4.00	4.80		E
Sequence Controllers Up to 40 Amp		3.40	4.40	5.30		E
Combination Humidistate/Thermostat 120Volt		1.50	1.80	2.00		E



# SECTION 10

## TEMPORARY POWER AND LIGHTING

### General Information

The labor units in this section are applicable for the installation of temporary 600-volt power services and temporary lighting. For electric motor conductor termination labor units see Section 12 in this manual. The labor units for temporary portable electrical equipment in this section do not include the labor to fabricate or assemble the portable equipment. The labor units for temporary lighting, temporary receptacle outlets and temporary extension cords do not include labor to service, inspect, or maintain these items.

### Scope of These Labor Units

The Introduction section includes details on the scope of labor units across the manual. Some items included are:

- Material unloading at the jobsite
- Coordinating the location where each item is to be installed
- Moving material to the point of installation or usage
- Power and grounding conductor terminations
- Disconnecting conductor terminations for the removal of the item
- Material loading for removal from the jobsite
- Normal non-productive labor

### Work Operations Not Included In These Labor Units

- Field supervision
- Maintenance of any temporary equipment while at the jobsite
- Conduit or cable installation unless specifically noted otherwise
- Relocating temporary equipment after the initial installation
- Design or engineering of any temporary system
- Reconditioning used equipment
- Temporary barricades or fences
- Removal of temporary equipment

### Labor Adjustments for Non-Typical Conditions

See the Introduction section for details.

### Application Instructions

- Labor units under the “Normal” column are for locations with good access, no obstructions and a complete temporary system. Labor units under the “Difficult” column are for locations with less than good access, a few minor obstructions and a complete temporary system. Labor units under the “Very Difficult” column are for locations with poor access, limited space, work performed in bad weather or small quantities of materials.
- Labor units for driving temporary grounding rods and service pole installation are for locations with loam, hard clay or loose shale the full depth of the rods. For other locations the labor units must be increased in proportion to the density of the soil encountered.
- The labor units in Section 12 may be used for terminating temporary conductors on permanent power equipment.
- For temporary cable installation labor units, use the labor units in Section 3, plus an appropriate labor allowance for the cable removal.






## Section 10 - Temporary Power & Lighting Table of Contents









Temp Svc - 16 to 20 Ft Dim Lumber Pole	10-5
Temp Svc - 20 to 30 ft Std Pole & Arms	10-5
Temp Svc - Undergnd Feed 12-16Ft Pole	10-5
Fittings	10-5
Wall Mounted Watthour Sockets & Meters	10-5
Wall Mounted Watthour Meter & Main Breaker	10-5
Wall Mounted Watthour Meter with 20 Amp Branch Circuit Breakers	10-5
Grounding Rods	10-6
Bare Copper Grounding up to Wire-6 Ft Long	10-6
Portable Post Mounted 3-Wire Safety Switches	10-6
Portable Lighting Panelboards with 20 Amp 1 Pole S/N Branch Circuit Breakers	10-6
Portable Lighting Panelboards With Up to 30 Amp 2-Pole S/N Branch CB's	10-6
Portable Lighting Panelboards with up to 60 Amp 2-Pole S/N Branch CB's	10-6
100 Ft Extension Cord	10-6
Prefabbed Light Strings With Bulbs	10-6
Free Standing Temporary Light Standard	10-7
HID Temporary Light Fixtures	10-7
HID Temporary Light Fixture	10-7
Box Connected Pigtail, Lamp & Guard	10-7
Portable Post Mounted Lighting Fixtures - Outdoors	10-7
Portable Post Mounted Lighting Fixtures - Indoor Grade	10-7
Sidewalk Cover Lighting	10-7
48" Vaportite Fluorescent Fixtures	10-8
48" Weatherproof Fluorescent Fixtures	10-8
Wall Mounted WP Box & 20 Amp Snap Switch	10-8
240 Volt Portable Electric Heaters	10-8
Portable Electric Generators	10-8
Portable Power Distribution Center	10-8










## Section 10 - Temporary Power & Lighting

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
	<b>Temp Svc-16 to 20 Ft Dim Lumber Pole</b>					
<b>By Elec Cont. - OH Lines B Pwr Co.</b>						
Single Phase 100 Amp		8.00	10.00	12.50		E
Single Phase 150 Amp		12.00	15.00	18.75		E
Single Phase 200 Amp		12.00	15.00	18.75		E
<i>C/T Can Required for 400 AMPS and above</i>						
Single Phase 400 Amp		30.00	37.50	46.88		E
Single Phase 600 Amp		47.00	58.75	73.44		E
Single Phase 800 Amp		64.00	80.00	100.00		E
Three Phase 200 Amp		14.00	17.50	21.88		E
Three Phase 400 Amp		34.00	42.50	53.13		E
Three Phase 600 Amp		55.00	68.75	85.94		E
Three Phase 800 Amp		69.00	86.25	107.81		E
Three Phase 1000 Amp		80.00	100.00	125.00		E
<b>Temp Svc - 20 to 30 ft Std Pole &amp; Arms By Elec Cont. OH &amp; Trans by Util. Co.</b>						
Single Phase 200 Amp		14.00	17.50	21.88		E
Single Phase 400 Amp		34.00	42.50	53.13		E
Single Phase 600 Amp		51.00	63.75	79.69		E
Single Phase 800 Amp		68.00	85.00	106.25		E
Single Phase 1000 Amp		85.00	106.25	132.81		E
Three Phase 200 Amp		20.00	25.00	31.25		E
Three Phase 400 Amp		40.00	50.00	62.50		E
Three Phase 600 Amp		61.00	76.25	95.31		E
Three Phase 800 Amp		75.00	93.75	117.19		E
Three Phase 1000 Amp		86.00	107.50	134.38		E
Three Phase 1200 Amp		97.00	121.25	151.56		E
<b>Temp Svc-Undergnd Feed 12-16Ft Pole by Elec. Cont. UndGnd Cable by Util. Co.</b>						
<b>Single Phase 200 Amp</b>						
Single Phase 200 Amp		11.00	13.75	17.19		E
Single Phase 400 Amp		28.00	35.00	43.75		E
Single Phase 600 Amp		45.00	56.25	70.31		E
Single Phase 800 Amp		62.00	77.50	96.88		E
Single Phase 1000 Amp		83.00	103.75	129.69		E
Three Phase 200 Amp		12.00	15.00	18.75		E
Three Phase 400 Amp		32.00	40.00	50.00		E
Three Phase 600 Amp		53.00	66.25	82.81		E
Three Phase 800 Amp		67.00	83.75	104.69		E
Three Phase 1000 Amp		78.00	97.50	121.88		E
<b>Fittings</b>						
3 Spool Secondary Racks		1.00	1.25	1.56		E
4 Spool Secondary Racks		1.10	1.38	1.72		E
Screw Type Pin Insulator		0.25	0.31	0.39		E
Pin Type Pin Insulator		0.50	0.63	0.78		E
Screw Type Insulator		0.25	0.31	0.39		E
Pin Type Wire holder		0.25	0.31	0.39		E
Service Entrance Cap-Up to 2"		0.80	1.00	1.25		E
Service Entrance Cap-Up to 3"		1.50	1.88	2.34		E
Service Entrance Cap-Up to 4"		2.50	3.13	3.91		E
<b>Wall Mounted Watthour Sockets &amp; Meters</b>						
100 Amp Single Phase		2.00	2.50	3.13		E
100 Amp Three Phase		2.50	3.13	3.91		E
200 Amp Single Phase		3.00	3.75	4.69		E
200 Amp Three Phase		3.50	4.38	5.47		E
<b>Wall Mounted Watthour Meter &amp; Main Breaker</b>						
100 Amp Breaker; Single Phase		2.25	2.81	3.52		E
150 Amp Breaker; Single Phase		2.50	3.13	3.91		E
200 Amp Breaker; Single Phase		3.00	3.75	4.69		E
100 Amp Breaker; Three Phase		2.50	3.13	3.91		E
150 Amp Breaker; Three Phase		3.00	3.75	4.69		E
200 Amp Breaker; Three Phase		3.50	4.38	5.47		E
<b>Wall Mounted Watthour Meter with 20 Amp Branch Circuit Breakers</b>						
100 Amp Meter 4 Circuit Breakers		3.45	4.31	5.39		E
100 Amp Meter 6 Circuit Breakers		4.05	5.06	6.33		E
100 Amp Meter 8 Circuit Breakers		4.65	5.81	7.27		E
100 Amp Meter 10 Circuit Breakers		5.25	6.56	8.20		E
100 Amp Meter 12 Circuit Breakers		5.85	7.31	9.14		E
150 Amp Meter 4 Circuit Breakers		3.70	4.63	5.78		E
150 Amp Meter 6 Circuit Breakers		4.30	5.38	6.72		E
150 Amp Meter 8 Circuit Breakers		4.90	6.13	7.66		E
150 Amp Meter 10 Circuit Breakers		5.50	6.88	8.59		E
150 Amp Meter 12 Circuit Breakers		6.10	7.63	9.53		E
200 Amp Meter 4 Circuit Breakers		4.20	5.25	6.56		E
200 Amp Meter 6 Circuit Breakers		4.80	6.00	7.50		E
200 Amp Meter 8 Circuit Breakers		5.40	6.75	8.44		E
200 Amp Meter 10 Circuit Breakers		6.00	7.50	9.38		E
200 Amp Meter 12 Circuit Breakers		6.60	8.25	10.31		E





## Section 10 - Temporary Power & Lighting

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>Grounding Rods</b> Ground Rod With Clamp		1.13	1.41	1.77		E
 <b>Bare Copper Grounding up to Wire-6 Ft Long</b> #10		0.42	0.53	0.66		E
#8		0.46	0.58	0.72		E
#6		0.50	0.63	0.78		E
#4		0.53	0.66	0.83		E
#2		0.56	0.70	0.88		E
#1		0.60	0.75	0.94		E
1/0		0.70	0.88	1.09		E
2/0		0.80	1.00	1.25		E
 <b>Portable Post Mounted 3-Wire Safety Switches</b> 30 Amp		2.75	3.44	4.30		E
60 Amp		3.25	4.06	5.08		E
100 Amp		5.00	6.25	7.81		E
150 Amp		7.50	9.38	11.72		E
200 Amp		7.50	9.38	11.72		E
400 Amp		9.50	11.88	14.84		E
 <b>Portable Lighting Panelboards with 20 Amp 1 Pole S/N Branch Circuit Breakers</b> 100 Amp 4 CBs		4.50	5.63	7.03		E
100 Amp 6 CBs		4.70	5.88	7.34		E
100 Amp 8 CBs		5.00	6.25	7.81		E
150 Amp 4 CBs		6.00	7.50	9.38		E
150 Amp 6 CBs		6.20	7.75	9.69		E
150 Amp 8 CBs		6.50	8.13	10.16		E
200 Amp 6 CBs		7.00	8.75	10.94		E
200 Amp 8 CBs		7.20	9.00	11.25		E
200 Amp 10 CBs		7.50	9.38	11.72		E
 <b>Portable Lighting Panelboards With Up to 30 Amp 2-Pole S/N Branch CB's</b> 100 Amp 4 cbs		4.40	5.50	6.88		E
100 Amp 6 CBs		4.70	5.88	7.34		E
100 Amp 8 CBs		5.00	6.25	7.81		E
150 Amp 4 CBs		5.90	7.38	9.22		E
150 Amp 6 Cbs		6.20	7.75	9.69		E
150 Amp 8 CBs		6.50	8.13	10.16		E
200 Amp 6 CBs		6.90	8.63	10.78		E
200 Amp 8 CBs		7.20	9.00	11.25		E
200 Amp 10 CBs		7.50	9.38	11.72		E
 <b>Portable Lighting Panelboards with up to 60 Amp 2-Pole S/N Branch CB's</b> 150 Amp 4 CBs		7.10	8.88	11.09		E
150 Amp 6 CBs		7.50	9.38	11.72		E
150 Amp 8 CBs		7.90	9.88	12.34		E
200 Amp 6 Cbs		7.10	8.88	11.09		E
200 Amp 8 Cbs		7.50	9.38	11.72		E
200 Amp 10 CBs		7.90	9.88	12.34		E
225 Amp 6 CBs		7.60	9.50	11.88		E
225 Amp 8 CBs		8.00	10.00	12.50		E
225 Amp 10 CBs		8.40	10.50	13.13		E
 <b>100 Ft Extension Cord</b> 3/C 20 Amp		0.25	0.31	0.39		E
3/C 30 Amp		0.35	0.44	0.55		E
3/C 50 Amp		0.60	0.75	0.94		E
4/C 20 Amp		0.35	0.44	0.55		E
4/C 30 Amp		0.45	0.56	0.70		E
4/C 50 Amp		0.70	0.88	1.09		E
4/C 60 Amp		0.80	1.00	1.25		E
 <b>Prefabbed Light Strings With Bulbs</b> 50 Ft Prefab light Strings Bulbs & Guards		1.50	1.88	2.34		E
100 Ft Prefab Light Strings Bulbs & Grds		2.00	2.50	3.13		E
Relamping		0.05	0.06	0.08		E

## Section 10 - Temporary Power & Lighting

	Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit	
	<b>Free Standing Temporary Light Standard</b> (27" +36" Tall)							
	27" 150W Fluorescent-Coverage 10'		0.50	0.63	0.78		E	
	27" 425W Fluorescent-Coverage 20'		0.60	0.75	0.94		E	
	27" 850W Metal Halide-Coverage 30'		0.60	0.75	0.94		E	
	36" 500W Halogen-Coverage 16'-24'		0.60	0.75	0.94		E	
	36" 120W Fluorescent-Coverage 20'-28'		0.65	0.81	1.02		E	
	36" 175W Metal Halide-Coverage 30'-42'		0.65	0.81	1.02		E	
	36" 250W Metal Halide-Coverage 40'-56'		0.70	0.88	1.09		E	
	36" 400W Metal Halide-Coverage 78'-110'		0.75	0.94	1.17		E	
	Notes							
	120v-fed from 3/C extension cord to power inlet							
	Power outlet for tools or connecting additional light standards							
On/Off switch								
Repositions to original position when knocked down								
Polycarbonate dome protects lamp								
	<b>HID Temporary Light Fixtures</b> Scaffold not included Mount height = 20' Installation includes anchor and eyebolt Fixtures equipped with locking hook Fixtures equipped with 3' cord Power cable (20 amp) suspended with receptacle mounted by each fixture							
	400W HID Temporary Fixture		2.75	3.44	4.30		E	
	250W HID Temporary Fixture		2.50	3.13	3.91		E	
	150W HID Temporary Fixture		2.25	2.81	3.52		E	
	100W HID Temporary Fixture		2.00	2.50	3.13		E	
	50' Suspended cable with receptacle		3.50	4.38	5.47		E	
	100' Suspended cable with receptacle		6.30	7.88	9.84		E	
		<b>HID Temporary Light Fixture</b> Same as above except fixture is equipped with modular cable system adapter Modular cable system suspended from ceiling						
		400W HID Temporary Fixture		2.75	3.44	4.30		E
		250W HID Temporary Fixture		2.50	3.13	3.91		E
		150W HID Temporary Fixture		2.25	2.81	3.52		E
		100W HID Temporary Fixture		2.00	2.50	3.13		E
50' Suspended modular cable			2.50	3.13	3.91		E	
100' Suspended modular cable			5.00	6.25	7.81		E	
		<b>Box Connected Pigtail, Lamp &amp; Guard</b> Box Connected Pigtail, Lamp & Guard		0.40	0.50	0.63		E
		<b>Portable Post Mounted Lighting Fixtures</b> <b>Outdoors</b>						
		200 watt 1-Lamp		2.00	2.50	3.13		E
		200 Watt 2-Lamp		2.20	2.75	3.44		E
	200 Watt 4-Lamp		3.00	3.75	4.69		E	
	500 Watt 1-Lamp		2.50	3.13	3.91		E	
	500 Watt 2-Lamp		2.70	3.38	4.22		E	
	500 Watt 4-lamp		3.50	4.38	5.47		E	
	1000 Watt 1-Lamp		3.00	3.75	4.69		E	
	1000 Watt 2-lamp		3.30	4.13	5.16		E	
	1000 Watt 4-lamp		4.00	5.00	6.25		E	
		<b>Portable Post Mounted Lighting Fixtures</b> <b>Indoor Grade</b>						
		1-Single Fixture		1.50	1.88	2.34		E
2-Single Fixture			1.50	1.88	2.34		E	
4-Single Fixture			2.00	2.50	3.13		E	
1-Twin Fixtures			2.00	2.50	3.13		E	
2-Twin Fixtures			2.00	2.50	3.13		E	
4-Twin Fixtures			3.00	3.75	4.69		E	
	<b>Sidewalk Cover Lighting</b>							
	10 Feet of 1/2" EMT #12 Wire & KO boxes		4.00	5.00	6.25		E	
	10 Feet of 3/4" EMT #12 Wire & KO Boxes		4.40	5.50	6.88		E	
	10' of 1/2" rigid conduit #12 Wire & WP Boxes		5.00	6.25	7.81		E	
	10' of 3/4" rigid Conduit #12 Wire & WP Boxes		6.00	7.50	9.38		E	
	200 Watt Porcelain Enamel Reflectors		0.80	1.00	1.25		E	
	200 Watt Box Mounted Vaportite Lampholders		1.00	1.25	1.56		E	

### Section 10 - Temporary Power & Lighting

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>48" Vaportite Fluorescent Fixtures</b>						
1-Tube		1.00	1.25	1.56		E
2-Tube		1.10	1.38	1.72		E
4-Tube		1.30	1.63	2.03		E
 <b>48" Weatherproof Fluorescent Fixtures</b>						
1-Tube		1.10	1.38	1.72		E
2-Tube		1.20	1.50	1.88		E
4-Tube		1.50	1.88	2.34		
 <b>Wall Mounted WP Box &amp; 20 Amp Snap Switch</b>						
Wall Mounted WP Box & 20 Amp Snap Switch		1.90	2.38	2.97		E
<b>240 Volt Portable Electric Heaters</b>						
1 KW		2.00	2.50	3.13		E
3 KW		2.50	3.13	3.91		E
5 KW		3.00	3.75	4.69		E
10 KW		4.00	5.00	6.25		E
15 KW		6.00	7.50	9.38		E
20 KW		8.00	10.00	12.50		E
<b>Portable Electric Generators</b>						
5 KW		2.00	2.50	3.13		E
10 KW		2.50	3.13	3.91		E
15 KW		3.00	3.75	4.69		E
20 KW		4.00	5.00	6.25		E
50 KW		6.00	7.50	9.38		E
<i>Note:</i>						
1. Refuelling time not included						
2. Temporary grounding not included, check with local authority						
<b>Portable Power Distribution Center</b>						
<i>480V units consist of 480V panel, transformer, 120/208V panel mounted on portable steel frame. Center is equipped with 50/2 receptacle to feed 120/208/240 power center. 120/208/240 unit consists of panel mounted on portable steel frame</i>						
<i>Units equipped with GFI receptacle</i>						
<i>Spider units rated 50/2 125v/250v</i>						
 100/3 480v PDC with 75 KVA transformer and 200/3 120/208 panel		4.00	5.00	6.25		E
50/3 277/480 PDC with 45 KVA transformer and 100/3 120/208 panel		3.00	3.75	4.69		E
50/3 120/208 PDC		1.00	1.25	1.56		E
50/2 120/208 PDC		1.00	1.25	1.56		E
50/2 125/250 Spider		1.00	1.25	1.56		E
100' - 100/3 Power cable with terminations (Ceiling Suspended)		16.00	20.00	25.00		E
100' - 50/3 Power cable with terminations (Ceiling Suspended)		12.00	15.00	18.75		E
100' - 5C 50 amp Power cord (Ceiling Suspended)		10.00	12.50	15.63		E
100' - 4C 50 amp Power cord (Ceiling Suspended)		9.00	11.25	14.06		E

# SECTION 11

## OUTDOOR OVERHEAD AND UNDERGROUND SYSTEMS

### General Information

The labor units within Section 11 are intended for inside electrical contractors installing overhead and underground electrical systems permitted by their craft jurisdiction. The labor units within Section 11 (A) are applicable for electrical inside and line contractors installing up to and including 35 KV overhead or underground electrical power systems, if trained and certified with these medium voltage systems.

### Scope of These Labor Units

The Introduction section includes details on the scope of labor units across the manual. Some items included are:

- Labor units are for new construction, de-energized in compliance with NFPA 70E
- Safety measures indicated in NFPA 70E will need to be factored by contractor's resources
- Material unloading at the job site
- Moving material to the point of installation
- Plan study, layout and marking of installation location
- Actual material and installation time
- Normal clean-up of electrical contractor furnished excess material compliance with OSHA
- Normal non-productive labor

### Work Operations Not Included In These Labor Units

- Field supervision
- Drilling and blasting rock or boulders
- Heavy equipment operators' time
- Design of electric systems
- Grade and elevation stakes
- Seeding, sodding or protection against soil erosion
- Dewatering of open trench
- Measurement and alignment more precise than normal industry standards
- Rerouting due to structural or mechanical obstacles
- Coordination studies including fuse and circuit breaker sizing and settings, arc hazard analysis and fault current analysis
- Testing or Commissioning of any type
- High Altitude Electromagnetic Pulse (HEMP) or Electro Magnetic Pulse (EMP) Shielding

### Labor Adjustments for Non-Typical Conditions

See the Introduction section for details.

### Application Instructions

- Labor units under the "Normal" column could apply to installations during the spring and fall months, substantial quantities of materials and typical jobsite conditions. Labor units under the "Difficult" column could apply to installations during the summer months, substantial quantities of materials and slightly poorer than typical jobsite conditions. Labor units under the "Very Difficult" column could apply to installations during the winter months or rainy weather, small quantities of materials or abnormally difficult jobsite conditions.
- The labor units in this section do not include an allowance for situations that require dewatering of trenches or other excavations.
- When the installation specifications require the buried conduit or excavations to have a uniform slope, the labor units in this section must be increased in proportion to the tolerance of the slope requirements.

- The labor units in this section for work items that may be performed by crafts, such as laborers or carpenters, are included as a guide for estimating purposes only.
- The labor units for installing electrical cable in this section include a prorated amount of the normal equipment set-up labor. For abnormal situations, such as excessive changes in direction or physical obstacles, these labor units must be increased or a separate labor allowance must be added to allow for the non-typical conditions.



## Section 11 - Outdoor Overhead and Underground Systems Table of Contents

Traffic Signal Lights	11-11
Pedestrian Signal Lights	11-11
Signal Hangers	11-11
Concrete Sawing For Loop Detector Wire	11-11
Computerized Traffic Controller - Modules Wiring Harness Interconnected	11-11
Vehicle Detection	11-11
Emergency Preemption	11-11
Anchor Bolts (Set of 4) With Template	11-11
Excavation per Vert. Ft.	11-11
High Mast Fixtures Less Poles - H.I.D Fixtures (each Fixture)	(Updated) 11-11
Stadium Light Fixtures Less Poles/Brackets - H.I.D (each Fixture)	(Updated) 11-12
Steel Poles with Factory Assembled Arms or Brackets	(Updated) 11-12
Steel Pole Fixture Mounting Support Arms - Field Installed	(Updated) 11-12
Street Lighting Steel or Aluminum Poles	11-12
Street Lighting Concrete Poles	11-12
Street Lighting Class 3 Wood Pole	11-12
Street Light Poles - Mast Arm	11-12
Street Light Fixtures - Cobra Head	11-12
Steel or Aluminum Traffic Poles Foundations and Anchor Bolts Not Included	11-12
Steel or Aluminum Mast Arms	11-13
Pole Pedestals	11-13
High Mast Lighting - Per Head	11-13
High Mast Steel Poles With Fixture Raising & Lowering Device	11-13
Miscellaneous	11-13
Airport Runway Lighting-200 Watt HID	11-13
Aircraft Lighted Guide Signs	11-13
Obstruction Lights	11-13
Rotating Beacons-120 Volts	11-13
Obstruction Twin Light & Tower - Factory Assembled	11-13
Obstruction Twin Light & Tower - Field Assembled	11-14
Trimmed-Out Pole in Place with 1-Cross Arm, 3-Pin Insulators, Hdwe & Pwr Augered Hose	11-14
Trimmed Out Pole with 2 Cross Arms, 3-HV, Ins., Hdwe, & Power Augered Hole	11-14
Hand Dug Post Holes	11-14
Post Hole Excavation With Truck Auger	11-15
Wood Pole Installation	11-15
Steel or Aluminum Pole Installation	11-15
Concrete Pole Installation	11-15
Single Wooden Cross Arms	11-15
Double Wooden Cross Arms	11-16
Single Steel Cross Arms	11-16
Cross Arm Pins	11-16
Porcelain Spool Insulators	11-16
Porcelain LV Pin Insulators	11-16
Porcelain Screw Type Wireholders	11-16
Wood Pole Butt Plates	11-16
Grounding Rods	11-16
Bare Copper Grounding Conductors	11-16
Wood or Plastic Molding Over Grounding Conductors	11-16
Secondary Racks	11-16
Plate or Bladed Anchors (Excavation Add'l)	11-16
Screw Type Anchors-Power Driven	11-17
Threaded Anchor Rods	11-17
Threaded Eye Bolts	11-17
Cross Arm Braces 26" to 32" Long	11-17
Alley Braces 5' to 7' Long	11-17
Steel Anchoring Cable with One Insulator	11-17
1/C ACSR Cable on Outdoor Poles	11-17
1/C 600 Volt Copper Polyethylene Cable on Pole	11-17
1/C 600 Volt Alum Polyethylene Cable on Poles	11-17
1/C Bare Copper Cable On Outdoor Poles	11-17

## Section 11 - Outdoor Overhead and Underground Systems Table of Contents

3/C 600 Volt Copper Primary Cable with Messenger Wire Support	11-18
3/C 600 Volt Alum Primary Cable with Messenger Wire Support	11-18
Pole Mounted Single Phase Transformers	11-18
Pole Mounted Three Phase Transformers	11-18
Pole Mounted Capacitors	11-18
Pole Mounted Air Break Switches	11-18
5-15KV Single Phase Pole Mounted Oil Switches	11-18
5-15KV Three Phase Pole Mounted Oil Switches	11-18
Pole Mounted Lightning Arrestors	11-18
Circuit Reclosures	11-18
Transformers Outdoor Type Up to 15 KV Primary, Unload, Inspect and Handling Labor Only	<b>(Updated)</b> 11-19
600 Amp Sectional Switches, Pad Mounted, Outdoor Type Up to 15 KV Primary	<b>(Updated)</b> 11-19
600-1200 Amp Pad Mounted Switchgear, Outdoor Type Up to 15 KV Primary	<b>(Updated)</b> 11-19
Hand Excavation of Small Trenches	11-19
Hand Trim Bottom of Machine Excavated Trenches	11-20
Inst. & Removal of Trench Shoring -	11-20
3/4" Plywood Shoring Both Sides & Steel Trench Jacks Bracing	11-20
3/4" Plywood Both Sides - 2x8 Vert Planks & Steel Trench Jacks	11-20
2x12's Laid Horiz. Both Sides - 2x8 Vert Planks & Steel Trench Jacks	11-20
Vert 2x12's Both Sides - 2x8 Horiz Headers & Steel Trench Jacks	11-20
Steel Shoring Both Sides w/ Either Steel Trench Jacks or 4x4 Horiz. Wood Bracing	11-20
2x12 Vert Planks Both Sides & Two Steel Trench Jacks or Two 4 x 4 Wood Braces	11-20
3" Deep Sand Bedding in Trenches	11-21
3" Deep Concrete Bedding in Trenches	11-21
Backfill & Compaction of Trenches	11-21
3/4" Plywood Forms for Duct Bank Concrete Encasement - One Side Only	11-21
3/4" Plywood Forms for Duct Bank Concrete Encasement - Forms on Both Sides	11-21
Plastic Spacers in Duct Bank for Conduit	11-21
Pouring Concrete Directly From Ready Mix Trucks Into Duct Banks - Per Cubic Yard (CY)	11-21
Wood Forms For Concrete Slabs	11-21
Rented Steel Forms For Concrete Slabs	11-21
Sonotube Pole Foundation Forms - 48" High	11-22
Plywood Pole Foundation Forms - 48" High	11-22
Wire Reinforcing Mesh In Concrete Slabs	11-22
Steel Reinforcing Bars In Concrete Slabs	11-22
Steel Reinforcing Bars in Pole Foundations	11-22
Pour Concrete Slabs At Grade Elevation Directly From Ready Mix Trucks	11-22
Pouring Concrete In 48" High Pole Foundations	<b>(Updated)</b> 11-22
Hand Finish Concrete Slabs At Grade	11-22
Hand Finish Pole Foundations Above Grade	11-22
HDPE Polyethylene Plastic Laid In Trenches - Per LF With O-Rings	11-22
HDPE Coupling O-Ring Type	11-22
HDPE Conduit Adapter	11-22
PVC EB/DB Plastic Conduit Laid In Trenches - 10Ft & 20Ft Lengths With Glued Couplings	11-23
PVC EB/DB Plastic Conduit Laid In Trenches - Couplings - Glued Type	11-23
PVC EB/DB Plastic Conduit Laid In Trenches - 90 Degree Elbows	11-23
PVC EB/DB Plastic Conduit Laid In Trenches - Threaded End Conduit Adapters	11-23
PVC Duct Bank Conduit Spacers	11-23
Sch 40 PVC Conduit Laid In Trenches - 10Ft & 20Ft Len. w/ Glued Couplings	11-23
Sch 40 PVC Conduit Laid In Trenches - 90 Degree Elbows	11-23
Sch 40 PVC Conduit Laid In Trenches - Threaded Adapters	11-23
Sch 40 PVC Conduit Laid In Trenches - Expansion Couplings	11-24
Field Bend Sch 40 PVC Conduit & Installation	11-24
Sch 80 PVC Conduit Laid In Trenches - 10Ft & 20Ft Lengths w/ Glued Couplings	11-24
Sch 80 PVC Conduit Laid In Trenches - 90 Degree Elbows	11-24
Sch 80 PVC Conduit Laid In Trenches - Threaded Adapters	11-24
Sch 80 PVC Conduit Laid In Trenches - Expansion Couplings	11-24
Field Bend Sch 80 PVC Conduit & Installation	11-25
600 Volt Direct Burial Copper Cable	11-25
600 Volt Direct Burial Aluminum Cable	11-25

## Section 11 - Outdoor Overhead and Underground Systems Table of Contents

5 KV Direct Burial Copper Cable	11-25
5 KV Direct Burial Aluminum Cable	11-26
15 KV Direct Burial Copper Cable	11-26
15 KV Direct Burial Aluminum Cable	11-26
25 KV 1/C Direct Burial Copper Cable w/ Concentric Wire Neutral	11-26
25 KV 1/C Direct Burial Aluminum Cable w/ Concentric Wire Neutral	11-26
35 KV 1/C Direct Burial Copper Cable w/ Concentric Wire Neutral	11-27
35 KV 1/C Direct Burial Aluminum Cable w/ Concentric Wire Neutral	11-27
600 Volt Copper Cable Pulled Into Buried Conduit	11-27
600 Volt Aluminum Cable Pulled Into Buried Conduit	11-27
5KV Copper Cable Pulled Into Buried Conduit	11-27
5KV Aluminum Cable Pulled Into Buried Conduit	11-28
15KV Copper Cable Pulled Into Buried Conduit	11-28
15KV Aluminum Cable Pulled Into Buried Conduit	11-28
25 KV 1/C Direct Burial Copper Cable w/ Concentric Neutral Pulled Into Buried Conduit	11-28
25 KV 1/C Direct Burial Aluminum Cable w/ Concentric Neutral Pulled Into Buried Conduit	11-28
35 KV 1/C Direct Burial Copper Cable w/ Concentric Neutral Pulled Into Buried Conduit	11-29
35 KV 1/C Direct Burial Aluminum Cable w/ Concentric Neutral Pulled Into Buried Conduit	11-29
Excavation, Backfilling, & Soil Compaction For Manholes	11-29
8" Thick Concrete Foundation For Manholes	11-29
Hand Holes-Open Bottom	11-29
Concrete Man Holes Base, Cover and Riser - Excludes Excavation and Gravel Base	11-29
Manhole Racks Install in Manholes	11-29
3-Section Prefabricated Concrete Manholes	11-30
Trench Duct	(Updated) 11-30
Hydro Excavation	11-30
Jacking Steel Pipe Under Driveways	11-30
Equipment Set-Up Labor For Jacking Pipe	11-30

## Section 11 (A) - Outdoor Overhead and Underground Systems Table of Contents

<b>Installation of Items</b>	11-31
Wood Poles - Cedar or Pine	11-31
Wood Poles - Adder for Setting In Rock	11-31
Straighten Existing Poles	11-31
Add For Pole Set In Sidewalk or Pavement	11-31
Key Pole - Lof or Plank Key	11-31
Key Pole - Bottom Of Hole	11-31
Re-Roof Pole	11-31
Dig Poles Holes & Not Used	11-31
Haul Poles or Pick Up & Return To Storage	11-31
Barrel Holes - Per Pole	11-31
Cross Arms With Braces & Pins	11-32
Replace Steel Braces With Wood Braces	11-32
Conductor Attachments	11-32
Down Guys	11-32
Complete Guy With Anchor, Rod, Wire & Guard	11-32
Complete Overhead Guy	11-32
Bond Existing Overhead Guy	11-32
Transformer Platform	11-32
Primary Attachment	11-32
1/C Copper or Aluminum Cable - Bare or Insulated	11-32
Re-sag 1/C Copper or Aluminum Cable	11-32
3/C Triplex Secondary Cable	11-32
Re-sag 3/C Triplex Secondary Cable	11-33
Copperweld Conductors	11-33
Re-sag Copperweld Conductors	11-33
2/C Duplex Secondary Cable	11-33
Re-sag 2/C Duplex Secondary Cable	11-33
Aluminum Conductor Armor Rods	11-33
1/C ACSR Cable - Bare or Insulated	11-33
Re-sag 1/C ACSR Cable	11-33
Replace Sleeves In Existing Primary Cable	11-33
Copperweld	11-33
Temporary Installations & Cable Transfers	11-33
Cross Arms & Pins	11-34
Cutouts	11-34
Arresters	11-34
Perch Guard	11-34
Primary Jumpers	11-34
Primary Dead Ends	11-34
Neutral Dead Ends	11-34
Lightning Arrestors	11-34
Complete Pole Grounding Systems	11-34
Pole Grounding System Components	11-34
Disconnect Switches	11-34
Single Pole Mounted Transformers	11-34
Two Or More Pole Mounted Transformers	11-34
Single Pad Mounted Transformers - Pole Type Transformers	11-35
Two Or More Pad Mounted Transformers - Pole Type Transformers	11-35
Brackets For Cluster Mounted Transformers	11-35
Change Ratios on Dual Voltage Transformers	11-35
1/C Power Terminations on Transformers - 600 Volt Copper Cable	11-35
Secondary Service - Two Copper Conductors	11-35
Secondary Service - Three Copper Conductors	11-35
Secondary Service - Four Copper Conductors	11-35
Secondary Service - Five Copper Conductors	11-36
Secondary Copper Triplex Cable	11-36

**(Updated)**

## Section 11 (A) - Outdoor Overhead and Underground Systems Table of Contents

House Service	11-36
House Service - 2/C Service Entrance Cable - 30FT Length	11-36
House Service - 3/C Service Entrance Cable - 30FT Length	11-36
House Service - 4/C Service Entrance Cable - 30FT Length	11-36
House Service - Service Entrance Conduit Cap	11-36
House Service - Threaded Steel Conduit & Fasteners - 30Ft Length	11-36
House Service - EMT With Fasteners & WP Couplings Up to 30 Ft Length	11-36
House Service - Three Single Conductors Pulled Into Conduit - Up To 30 Ft Length	11-36
Apt & Comm WP Svc - 3-Wire Solid Neutral Meter Center Modules w/ Main CB or Main Disc. Switch	11-36
Apt & Comm WP Svc - Single Phase 125 Amp Meter Socket Modules	11-37
Apt & Comm WP Svc - Three Phase 125 Amp Meter Socket Modules	11-37
Street Lighting Systems - Metal Poles With Internal Wiring	11-37
Street Lighting Systems - Mast Arms Attached Before Pole Erection	11-37
Street Lighting Systems - Light Fixtures Attached Before Pole Erection	11-37
Street Lighting Systems - Upsweep Bracket On Pole	11-37
Street Lighting Systems - Pull Cable In Pole & Arm-Series Circuit	11-37
Street Lighting Systems - Pole Mounted Photo Switch With Relay	11-37
Street Lighting Systems - Metal Pole Transformer Base Housing	11-37
Street Lighting Systems - Constant Current Transformers	11-37
Street Lighting Systems - Street Lighting Transformers	11-37
Street Lighting Systems - Series Street Lighting Protectors	11-37
Street Lighting Systems - Street Lighting Controllers	11-38
Street Lighting Systems - Capacitor Banks - Up To 50 KVR	11-38
Street Lighting Systems - Spacer Cable Accessories	11-38
<b>Removal of Items</b>	11-39
Wood Poles - Cedar or Pine	11-39
Cross Arms With Braces & Pins	11-39
Replace Steel Braces With Wood Braces	11-39
Conductor Attachments	11-39
Complete Guy With Anchor, Rod, Wire & Guard	11-39
Complete Overhead Guy	11-39
Transformer Platform	11-39
Primary Attachment	11-39
1/C Copper or Aluminum Cable - Bare or Insulated	11-39
3/C Triplex Secondary Cable	11-39
Copperweld Conductors	11-39
Re-sag Copperweld Conductors	11-39
2/C Duplex Secondary Cable	11-40
Aluminum Conductor Armor Rods	11-40
1/C ACSR Cable - Bare or Insulated	11-40
Complete Pole Grounding Systems	11-40
Disconnect Switches	11-40
Single Pole Mounted Transformers	11-40
Two Or More Pole Mounted Transformers	11-40
Single Pad Mounted Transformers - Pole Type Transformers	11-40
Two Or More Pad Mounted Transformers - Pole Type Transformers	11-40
Brackets For Cluster Mounted Transformers	11-40
Secondary Service - Two Copper Conductors	11-40
Secondary Service - Three Copper Conductors	11-41
Secondary Service - Four Copper Conductors	11-41
Secondary Service - Five Copper Conductors	11-41
Secondary Copper Triplex Cable	11-41
Street Lighting Systems - Metal Poles With Internal Wiring	11-41
Street Lighting Systems - Mast Arms Attached Before Pole Erection	11-41
Street Lighting Systems - Light Fixtures Attached Before Pole Erection	11-42
Street Lighting Systems - Upsweep Bracket On Pole	11-42
Street Lighting Systems - Pull Cable In Pole & Arm-Series Circuit	11-42

## Section 11 (A) - Outdoor Overhead and Underground Systems Table of Contents

Street Lighting Systems - Pole Mounted Photo Switch With Relay	11-42
Street Lighting Systems - Metal Pole Transformer Base Housing	11-42
Street Lighting Systems - Constant Current Transformers	11-42
Street Lighting Systems - Street Lighting Transformers	11-42
Street Lighting Systems - Series Street Lighting Protectors	11-42
Street Lighting Systems - Street Lighting Controllers	11-42
Street Lighting Systems - Capacitor Banks - Up To 50 KVR	11-42
Street Lighting Systems - Spacer Cable Accessories	11-42
Remove Trees (Excluding Roots)	11-42
Remove Larger Tree Limb - No Obstacles	11-42
Remove Large Tree Limb Over Hot Wires or Over Other Obstacles	11-42
Trim Tree For Lighting Fixture Installation	11-42
<b>Transfer of Items</b>	11-43
Wood Poles - Cedar or Pine	11-43
Cross Arms With Braces & Pins	11-43
Conductor Attachments	11-43
Transfer One End Of Overhead Guy	11-43
Transformer Platform	11-43
Primary Attachment	11-43
1/C Copper or Aluminum Cable - Bare or Insulated	11-43
3/C Triplex Secondary Cable	11-43
Copperweld Conductors	11-43
Re-sag Copperweld Conductors	11-43
2/C Duplex Secondary Cable	11-43
Aluminum Conductor Armor Rods	11-44
1/C ACSR Cable - Bare or Insulated	11-44
Disconnect Switches	11-44
Single Pole Mounted Transformers	11-44
Two Or More Pole Mounted Transformers	11-44
Single Pad Mounted Transformers - Pole Type Transformers	11-44
Two Or More Pad Mounted Transformers - Pole Type Transformers	11-44
Brackets For Cluster Mounted Transformers	11-44
Secondary Service - Two Copper Conductors	11-44
Secondary Service - Three Copper Conductors	11-44
Secondary Service - Four Copper Conductors	11-45
Secondary Service - Five Copper Conductors	11-45
Secondary Copper Triplex Cable	11-45
Street Lighting Systems - Metal Poles With Internal Wiring	11-45
Street Lighting Systems - Mast Arms Attached Before Pole Erection	11-45
Street Lighting Systems - Light Fixtures Attached Before Pole Erection	11-45
Street Lighting Systems - Upsweep Bracket On Pole	11-45
Street Lighting Systems - Pull Cable In Pole & Arm-Series Circuit	11-45
Street Lighting Systems - Pole Mounted Photo Switch With Relay	11-45
Street Lighting Systems - Metal Pole Transformer Base Housing	11-45
Street Lighting Systems - Constant Current Transformers	11-46
Street Lighting Systems - Street Lighting Transformers	11-46
Street Lighting Systems - Series Street Lighting Protectors	11-46
Street Lighting Systems - Street Lighting Controllers	11-46
Street Lighting Systems - Capacitor Banks - Up To 50 KVR	11-46
Street Lighting Systems - Spacer Cable Accessories	11-46
<b>Maintenance and Protection of Traffic</b>	11-47
Illuminated Arrow Sign	(Updated) 11-47
Attenuator Barrels	(Updated) 11-47
Attenuator Truck	11-47
Barricade Lights	(Updated) 11-47
Barricade Horse	(Updated) 11-47

## Section 11 (A) - Outdoor Overhead and Underground Systems Table of Contents

Roll up work in progress alert signs	<i>(Updated)</i>	11-47
Flag Man Flag		11-47
Flag Man Traffic Paddle		11-47
Light Towers	<i>(Updated)</i>	11-47
Portable Traffic Light	<i>(Updated)</i>	11-47
Electric Message Boards	<i>(Updated)</i>	11-47
Sign Stands	<i>(Updated)</i>	11-47
<b>Watershed Protection</b>		11-48
Bio-Degradable Erosion Control Mat	<i>(Updated)</i>	11-48
Coir Wattles	<i>(Updated)</i>	11-48
De-Watering Filter Bags	<i>(Updated)</i>	11-48
De-Watering Tubes	<i>(Updated)</i>	11-48
De-Watering Filter Sock	<i>(Updated)</i>	11-48
Erosion Control Blankets	<i>(Updated)</i>	11-48
Filter Bags	<i>(Updated)</i>	11-48
Sand Bags	<i>(Updated)</i>	11-48
Silt Check	<i>(Updated)</i>	11-48
Silt Fence	<i>(Updated)</i>	11-48
Straw Wattles	<i>(Updated)</i>	11-48
Tree Trunk Protection	<i>(Updated)</i>	11-48















Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Traffic Signal Lights</b>						
 Signal Head 1 Section		3.00	3.60	4.32		E
 Signal Head 2 Section		3.00	3.60	4.32		E
 Signal Head 3 Section		4.00	4.80	5.76		E
Signal Head 4 Section		5.00	6.00	7.20		E
Signal Head 5 Section		6.00	7.20	8.64		E
Optically Programmed 3 Sec		8.00	9.60	11.52		E
<b>Pedestrian Signal Lights</b>						
Signal Head 1 Section		6.00	7.20	8.64		E
Signal Head 2 Section		8.00	9.60	11.52		E
Back Plate		1.00	1.20	1.44		E
Pedestrian Signal Head		3.00	3.60	4.32		E
Regulatory Sign - non-illuminated		3.00	3.60	4.32		E
Regulatory Sign - illuminated		8.00	9.60	11.52		E
Ped. Push Button - Includes Sign		2.50	3.00	3.60		E
<b>Signal Hangers</b>						
Astro Bracket		1.50	1.80	2.16		E
Span Wire Hangers with Tether Clamps		1.50	1.80	2.16		E
Span Wire		0.08	0.10	0.12		LF
Tether		0.04	0.05	0.06		LF
<b>Concrete Sawing For Loop Detector Wire</b>						
1/2 X 2" Deep		0.17	0.20	0.24		LF
1/2 X 3" Deep		0.20	0.24	0.29		LF
1/2 X 4" Deep		0.24	0.29	0.35		LF
5/8 X 2" Deep		0.20	0.24	0.29		LF
5/8 X 3" Deep		0.25	0.30	0.36		LF
5/8 X 4" Deep		0.30	0.36	0.43		LF
Epoxy Backfill for Loop Detector Trench		0.05	0.06	0.07		LF
600 Volt Loop Detector Wire		0.02	0.02	0.03		LF
Loop Detector Wire		2.00	2.50	3.00		C
Loop Detector Termination WP Box		2.00	2.40	2.88		E
Traffic Signal With Cabinet & Controller		16.00	19.20	23.04		E
<b>Computerized Traffic Controller</b>						
<b>Modules Wiring Harness Interconnected</b>						
Controller Modules		4.00	4.80	5.76		E
Loop Detector Amplifier		0.50	0.60	0.72		E
<b>Vehicle Detection</b>						
Magnetic Detectors		6.00	7.20	8.64		E
Microwave Detectors		2.50	3.00	3.60		E
Image Sensor Camera ***		24.00	28.80	34.56		E
*** The first camera includes hardware, terminations and testing - add for additional cameras		12.00	14.40	17.28		E
<b>Emergency Preemption</b>						
Emergency Detector		3.00	3.60	4.32		E
Confirmation Light		2.00	2.40	2.88		E
Amplifier		3.00	3.60	4.32		E
Preemption Cable per foot		10.00	12.50	15.00		M
<b>Anchor Bolts (Set of 4) With Template</b>						
3/4" to 24 "		1.50	1.80	2.16		E
1" to 48 "		2.00	2.40	2.88		E
1 1/4" to 54 "		2.50	3.00	3.60		E
1 1/2" to 60 "		4.00	4.60	5.32		E
2 " to 72 "		6.00	7.20	8.64		E
2 1/4 " to 72 "		8.00	10.20	12.64		E
<b>Excavation per Vert. Ft. - Units are designed for stable soil, no rock and do not include casings or dewatering</b>						
Up to 30 " diameter		1.00	1.20	1.44		LF
Up to 36 " diameter		1.50	1.80	2.16		LF
Up to 42 " diameter		2.50	3.00	3.60		LF
Up to 48 " diameter		3.00	3.60	4.32		LF
<b>High Mast Fixtures Less Poles - H.I.D Fixtures (each Fixture)</b>						
1000 Watt	X					E
1500 Watt	X	4.00	5.00	6.25		E
2000 Watt	X	5.00	6.25	7.81		E
2000 Watt	X	6.00	7.50	9.38		E
**** Note Add Additional Labor for Lowering Device Assembly	X					





## Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
	<b>Stadium Light Fixtures Less Poles/Brackets - H.I.D (each Fixture)</b>	X				
	1000 Watt	X	4.00	5.00	6.25	E
	1500 Watt	X	5.00	6.25	7.81	E
	2000 Watt	X	6.00	7.50	9.38	E
	**** Note Add Additional Labor for Lowering Device Assembly	X				
	**** Note Add Additional Labor for Remote Ballast Installation	X				
	**** Note Add Additional Labor for Special Support Brackets	X				
	**** Note Add Additional Labor for Spotting and Aiming	X				
	<b>Steel Poles with Factory Assembled Arms or Brackets</b>	X				
	40 Ft.	X	10.00	12.50	15.63	E
	50 Ft.	X	16.00	20.00	25.00	E
	60 Ft.	X	20.00	25.00	31.25	E
	70 Ft.	X	30.00	37.50	46.88	E
	80 Ft.	X	40.00	50.00	62.50	E
	90 Ft.	X	50.00	62.50	78.13	E
	100 Ft.	X	75.00	93.75	117.19	E
	120 Ft.	X	75.00	93.75	117.19	E
150 Ft.	X	100.00	125.00	156.25	E	
	<b>Steel Pole Fixture Mounting Support Arms - Field Installed</b>	X				
	40 Lb	X	6.00	7.50	9.38	E
	60 Lb	X	7.00	8.75	10.94	E
	80 Lb	X	8.00	10.00	12.50	E
	100 Lb	X	9.00	11.25	14.06	E
	125 Lb	X	10.00	12.50	15.63	E
	150 Lb	X	12.00	15.00	18.75	E
	<b>Street Lighting Steel or Aluminum Poles</b>					
	20'		4.00	4.80	5.76	E
	25'		4.50	5.40	6.48	E
	30'		5.00	6.00	7.20	E
	35'		5.50	6.60	7.92	E
	40'		6.00	7.20	8.64	E
	50'		8.00	9.60	11.52	E
	60'		12.00	14.40	17.28	E
	<b>Street Lighting Concrete Poles</b>					
	20'		6.00	7.20	8.64	E
	25'		8.00	9.60	11.52	E
	30'		10.00	12.00	14.40	E
	35'		12.00	14.40	17.28	E
	40'		14.00	16.80	20.16	E
	<b>Street Lighting Class 3 Wood Pole</b>					
	20'		3.60	4.32	5.18	E
	25'		4.00	4.80	5.76	E
	30'		4.50	5.40	6.48	E
	35'		5.00	6.00	7.20	E
	40'		5.50	6.60	7.92	E
	50'		7.00	8.40	10.08	E
	60'		10.00	12.00	14.40	E
	<b>Street Light Poles - Mast Arm</b>					
	8'		1.50	1.80	2.16	E
	10'		2.00	2.40	2.88	E
	12'		2.50	3.00	3.60	E
	15'		3.00	3.60	4.32	E
	20'		5.00	6.00	7.20	E
	25'		6.00	7.20	8.64	E
	30'		8.00	9.60	11.52	E
	<b>Street Light Fixtures - Cobra Head</b>					
	Up to 1000 Watt		2.50	3.00	3.60	E
	<b>Steel or Aluminum Traffic Poles Foundations and Anchor Bolts Not Included</b>					
	10'		4.00	4.80	5.76	E
	15'		5.00	6.00	7.20	E
	20'		6.00	7.20	8.64	E
	25'		8.00	9.60	11.52	E
	30'		10.00	12.00	14.40	E
	35'		12.00	14.40	17.28	E

Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Steel or Aluminum Mast Arms</b>						
 20'		6.00	7.20	8.64		E
25'		7.00	8.40	10.08		E
30'		8.00	9.60	11.52		E
35'		9.00	10.80	12.96		E
40'		12.00	14.40	17.28		E
45'		13.00	15.60	18.72		E
50'		14.00	16.80	20.16		E
60'		16.00	19.20	23.04		E
65'		18.00	21.60	25.92		E
70'		20.00	24.00	28.80		E
<b>Pole Pedestals</b>						
Breakaway Steel or Aluminum		4.00	4.80	5.76		E
<b>High Mast Lighting - Per Head</b>						
Up to 1000 Watt		3.00	3.60	4.32		E
Up to 2000 Watt		4.00	4.80	5.76		E
<b>High Mast Steel Poles With Fixture Raising &amp; Lowering Device (Does not include lighting control)</b>						
40'		10.00	12.00	14.40		E
60'		24.00	28.80	34.56		E
80'		48.00	57.60	69.12		E
120'		72.00	86.40	103.68		E
150'		80.00	96.00	115.20		E
<b>Miscellaneous</b>						
Time Switches for Street Lighting		4.00	4.80	5.76		E
Photo Cell		1.00	1.20	1.44		E
<b>Airport Runway Lighting-200 Watt HID</b>						
with Transformer in Base Housing		1.97	2.46	2.96		E
200 Watt Recessed Fixture		2.96	3.64	4.43		E
45 Watt Taxi Fixture Mounted on 1" Pipe		1.97	2.46	2.96		E
Base Housing with Cover Only		1.50	1.87	2.25		E
<b>Aircraft Lighted Guide Signs</b>						
1-Section		3.94	4.93	5.91		E
2-Section		4.93	6.11	7.39		E
3-Section		5.91	7.39	8.87		E
4-Section		6.90	8.37	9.85		E
10" Dia 300 Watt Approach Light 2C/#12		2.96	3.64	4.43		E
500 Watt Threshold Light-#8/5KW Conductor		3.94	4.93	5.91		E
Lighted Wind Tee-Free Floating		5.91	7.39	8.87		E
Lighted Wind Tee-Remote Controlled		7.88	9.85	11.82		E
<b>Obstruction Lights</b>						
116 Watt 120 Volt Obstruction Light		1.97	2.46	2.96		E
700 Watt 120 Volt Obstruction Light		2.36	3.64	4.43		E
116 Watt 120 Volt Twin Obstruction Light		2.36	2.96	3.55		E
<b>Rotating Beacons-120 Volts</b>						
500 Watt 24" Dia 400 Lb		31.52	39.52	47.28		E
1000 Watt 30" Dia 670 Lb		35.46	44.33	53.19		E
1500 Watt 36" 800 Lb		39.40	49.25	59.10		E
<b>Obstruction Twin Light &amp; Tower - Factory Assembled</b>						
10' high		3.94	4.93	5.91		E
15' high		4.93	6.11	7.39		E
20' high		5.91	7.39	8.87		E
25' high		6.90	8.57	10.34		E
30' high		7.88	9.85	11.82		E
35' high		8.87	11.03	13.30		E
40' high		9.85	12.31	14.78		E
45' high		10.84	13.49	16.25		E
50' high		11.82	14.78	17.73		E


## Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>Obstruction Twin Light &amp; Tower - Field Assembled</b> 10' high 15' high 20' high 25' high 30' high 35' high 40' high 50' high		7.88	9.85	11.82		E
		9.85	12.31	14.78		E
		11.82	14.78	17.73		E
		13.79	17.24	20.69		E
		15.76	19.70	23.64		E
		17.73	22.16	26.60		E
		19.70	24.63	29.55		E
		23.64	29.55	35.46		E
 <b>Trimmed-Out Pole in Place with 1-Cross Arm, 3-Pin Insulators, Hdwe &amp; Pwr Augered Hose</b> 20' 25' 30' 35' 40' 45' 50' 55' 60' 65' 70' 75' 80' 90' 100'		8.00	10.00	12.00		E
		8.20	10.20	12.30		E
		8.40	10.50	12.60		E
		8.70	10.80	13.00		E
		9.00	11.20	13.50		E
		9.50	11.80	14.20		E
		10.00	12.50	15.00		E
		11.00	13.70	16.50		E
		12.00	15.00	18.00		E
		13.00	16.20	19.50		E
		14.00	17.50	21.00		E
		15.00	18.70	22.50		E
		16.00	20.00	24.00		E
		18.00	22.50	27.00		E
		20.00	25.00	30.00		E
 <b>Trimmed Out Pole with 2 Cross Arms, 3-HV, Ins., Hdwe, &amp; Power Augered Hole</b> 20' 25' 30' 35' 40' 45' 50' 55' 60' 65' 70' 75' 80' 90' 100'		10.00	12.50	15.00		E
		10.50	13.10	15.70		E
		11.00	13.70	16.50		E
		11.50	14.30	17.20		E
		12.00	15.00	18.00		E
		12.50	15.60	18.70		E
		13.00	16.20	19.50		E
		14.00	17.50	21.00		E
		15.00	18.70	22.50		E
		16.00	20.00	24.00		E
		17.00	21.20	25.50		E
		18.00	22.50	27.00		E
		19.00	23.70	28.50		E
		21.00	26.50	32.00		E
		24.00	30.00	36.00		E
 <b>Hand Dug Post Holes</b> <b>Sandy Soil 3'</b> 4' 5' 6' 7' 8' <b>Soft Clay 3'</b> 4' 5' 6' 7' 8' <b>Hard Clay 3'</b> 4' 5' 6' 7' 8' <b>Shale 3'</b> 4' 5' 6' 7' 8'		3.00	3.70	4.50		E
		4.00	5.00	6.00		E
		5.00	6.20	7.50		E
		6.50	8.10	9.70		E
		8.00	10.00	12.00		E
		10.00	12.50	15.00		E
		4.00	5.00	6.00		E
		5.00	6.20	7.50		E
		6.00	7.50	9.00		E
		7.50	9.30	11.20		E
		9.00	11.20	13.50		E
		11.00	13.70	16.50		E
		5.00	6.20	7.50		E
		6.00	7.50	9.00		E
		7.00	8.70	10.50		E
		8.50	10.60	12.70		E
		10.00	12.50	15.00		E
		12.00	15.00	18.00		E
		6.00	7.50	9.00		E
		7.00	8.70	10.50		E
		8.00	10.00	12.00		E
		10.00	12.50	15.00		E
		12.00	15.00	18.00		E
		14.00	17.50	21.00		E


## Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Post Hole Excavation With Truck Auger</b>						
Sandy Soil 3'						
4'		0.70	0.85	1.00		E
5'		0.80	1.00	1.20		E
6'		0.90	1.12	1.35		E
7'		1.00	1.25	1.50		E
8'		1.20	1.50	1.80		E
10'		1.50	1.85	2.25		E
Soft Clay 3'						
4'		2.10	2.60	3.15		E
5'		0.80	1.00	1.20		E
6'		0.90	1.12	1.35		E
7'		1.00	1.25	1.50		E
8'		1.10	1.37	1.65		E
10'		1.30	1.65	2.00		E
Hard Clay 3'						
4'		1.60	2.00	2.40		E
5'		2.20	2.75	3.30		E
6'		0.90	1.12	1.35		E
7'		1.00	1.25	1.50		E
8'		1.15	1.43	1.75		E
10'		1.30	1.65	2.00		E
Shale 3'						
4'		1.60	2.00	2.40		E
5'		2.20	2.75	3.30		E
6'		0.90	1.12	1.35		E
7'		1.00	1.25	1.50		E
8'		1.15	1.43	1.75		E
10'		1.30	1.65	2.00		E
<b>Wood Pole Installation</b>						
25'		4.00	5.00	6.00		E
30'		4.50	5.60	6.70		E
35'		5.00	6.20	7.50		E
40'		5.50	6.80	8.20		E
45'		6.00	7.50	9.00		E
50'		7.00	8.70	10.50		E
55'		8.00	10.00	12.00		E
60'		10.00	12.50	15.00		E
65'		12.00	15.00	18.00		E
70'		14.00	17.50	21.00		E
75'		17.00	21.20	25.50		E
80'		20.00	25.00	30.00		E
90'		28.00	35.00	42.00		E
100'		38.00	48.00	58.00		E
<b>Steel or Aluminum Pole Installation</b>						
25'		4.50	5.60	6.70		E
30'		5.00	6.20	7.50		E
35'		5.50	6.80	8.20		E
40'		6.00	7.50	9.00		E
45'		7.00	8.70	10.50		E
50'		8.00	10.00	12.00		E
55'		10.00	12.50	15.00		E
60'		12.00	15.00	18.00		E
65'		14.00	17.50	21.00		E
70'		16.00	20.00	24.00		E
75'		19.00	23.00	28.00		E
80'		22.00	27.00	33.00		E
90'		30.00	37.00	45.00		E
100'		40.00	50.00	60.00		E
<i>Note: Excludes Template and Anchor Bolt Setting</i>						
<b>Concrete Pole Installation</b>						
25'		5.00	6.20	7.50		E
30'		5.50	6.80	8.20		E
35'		6.00	7.50	9.00		E
40'		6.50	8.20	10.00		E
45'		7.20	9.00	11.00		E
50'		8.00	10.00	12.00		E
55'		9.00	11.20	13.50		E
60'		10.00	12.50	15.00		E
65'		11.00	13.70	16.50		E
70'		12.00	15.00	18.00		E
75'		14.00	17.50	21.00		E
80'		16.00	20.00	24.00		E
<b>Single Wooden Cross Arms</b>						
3'		1.00	1.20	1.50		E
4'		1.10	1.30	1.60		E
5'		1.20	1.40	1.70		E
6'		1.30	1.50	1.90		E
7'		1.40	1.70	2.10		E
8'		1.50	1.90	2.30		E
10'		1.70	2.10	2.60		E

## Section 11 - Outdoor Overhead and Underground Systems



Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Double Wooden Cross Arms</b>						
 3'		2.00	2.50	3.00		E
4'		2.20	2.70	3.30		E
5'		2.40	2.90	3.60		E
6'		2.60	3.20	3.90		E
7'		2.80	3.50	4.20		E
8'		3.00	3.80	4.50		E
10'		3.40	4.20	5.10		E
<b>Single Steel Cross Arms</b>						
3'		1.30	1.50	1.90		E
4'		1.40	1.60	2.00		E
5'		1.50	1.80	2.20		E
6'		1.60	2.00	2.40		E
7'		1.70	2.20	2.60		E
8'		1.80	2.40	2.80		E
10'		2.00	2.60	3.00		E
<b>Cross Arm Pins</b>						
Shank Type		0.25	0.31	0.37		E
Saddle Type		0.30	0.37	0.45		E
Pole Top Type		0.40	0.50	0.60		E
<b>Porcelain Spool Insulators</b>						
2" Dia		0.10	0.12	0.15		E
3" Dia		0.12	0.15	0.18		E
4" Dia		0.15	0.18	0.22		E
<b>Porcelain LV Pin Insulators</b>						
4" Dia		0.15	0.18	0.22		E
5" Dia		0.20	0.25	0.30		E
7" Dia		0.30	0.37	0.45		E
<b>Porcelain Screw Type Wireholders</b>						
1 1/2" Dia		0.20	0.25	0.30		E
2" Dia		0.22	0.27	0.33		E
2 1/2" Dia		0.25	0.31	0.37		E
<b>Wood Pole Butt Plates</b>						
Wood Pole Butt Plates		0.40	0.50	0.60		E
<b>Grounding Rods</b>						
8 Ft Grounding Rod with Clamp		1.00	1.25	1.50		E
<b>Bare Copper Grounding Conductors</b>						
25'		0.50	0.60	0.70		E
30'		0.60	0.70	0.80		E
35'		0.70	0.80	0.90		E
40'		0.80	0.90	1.10		E
45'		0.90	1.00	1.30		E
50'		1.00	1.20	1.50		E
60'		1.20	1.40	1.80		E
70'		1.40	1.70	2.10		E
80'		1.60	2.00	2.40		E
90'		1.80	2.20	2.70		E
100'		2.00	2.50	3.00		E
<b>Wood or Plastic Molding Over Grounding Conductors</b>						
10 Ft or Shorter Sections		0.50	0.60	0.70		E
<b>Secondary Racks</b>						
2 Spools		0.80	1.00	1.20		E
3 Spools		0.90	1.10	1.35		E
4 Spools		1.00	1.25	1.50		E
<b>Plate or Bladed Anchors (Excavation Add'l)</b>						
Plate or Bladed Anchors (Excavation Add'l)		1.00	1.25	1.50		E

## Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>Screw Type Anchors-Power Driven</b> Screw Type Anchors-Power Driven		2.00	2.50	3.00		E
<b>Threaded Anchor Rods</b>						
5'		0.20	0.25	0.30		E
6'		0.22	0.27	0.35		E
7'		0.25	0.31	0.40		E
8'		0.30	0.37	0.45		E
<b>Threaded Eye Bolts</b>						
8"		0.20	0.25	0.30		E
10"		0.22	0.27	0.33		E
12"		0.24	0.29	0.36		E
14"		0.26	0.31	0.39		E
16"		0.28	0.34	0.42		E
18"		0.30	0.37	0.45		E
20"		0.32	0.40	0.48		E
<b>Cross Arm Braces 26" to 32" Long</b> Cross Arm Braces 26" to 32" Long		0.30	0.37	0.45		E
<b>Alley Braces 5' to 7' Long</b> Alley Braces 5' to 7' Long		0.40	0.50	0.60		E
<b>Steel Anchoring Cable with One Insulator</b>						
20'		2.00	2.50	3.00		E
25'		2.50	3.10	3.70		E
30'		3.00	3.80	4.50		E
40'		4.00	5.00	6.00		E
50'		5.00	6.20	7.50		E
60'		6.00	7.50	9.00		E
70'		7.00	8.70	10.50		E
80'		8.00	10.00	12.00		E
<b>1/C ACSR Cable on Outdoor Poles</b>						
#6		12.00	15.00	18.00		M
#4		13.00	16.20	19.50		M
#2		14.00	17.50	21.00		M
#1		15.00	18.70	22.50		M
1/0		16.00	20.00	24.00		M
2/0		18.00	22.50	27.00		M
3/0		20.00	25.00	30.00		M
4/0		22.00	27.50	33.00		M
<b>1/C 600 Volt Copper Polyethylene Cable on Pole</b>						
#6		14.00	17.50	21.00		M
#4		16.00	20.00	24.00		M
#2		18.00	22.50	27.00		M
#1		20.00	25.00	30.00		M
1/0		24.00	30.00	36.00		M
2/0		28.00	35.00	42.00		M
3/0		32.00	40.00	48.00		M
4/0		36.00	45.00	54.00		M
<b>1/C 600 Volt Alum Polyethylene Cable on Poles</b>						
#6		12.00	15.00	18.00		M
#4		14.00	17.50	21.00		M
#2		16.00	20.00	24.00		M
#1		18.00	22.50	27.00		M
1/0		20.00	25.00	30.00		M
2/0		22.00	27.50	33.00		M
3/0		24.00	30.00	36.00		M
4/0		26.00	32.50	39.00		M
<b>1/C Bare Copper Cable On Outdoor Poles</b>						
#6		14.00	17.50	21.00		M
#4		16.00	20.00	24.00		M
#2		18.00	22.50	27.00		M
#1		20.00	25.00	30.00		M
1/0		24.00	30.00	36.00		M
2/0		28.00	35.00	42.00		M
3/0		32.00	40.00	48.00		M
4/0		36.00	45.00	54.00		M

Section 11 - Outdoor Overhead and Underground Systems


Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>3/C 600 Volt Copper Primary Cable with Messenger Wire Support</b>						
#6		28.00	35.00	42.00		M
#4		32.00	40.00	48.00		M
#2		36.00	45.00	54.00		M
#1		40.00	50.00	60.00		M
1/0		48.00	60.00	72.00		M
2/0		56.00	70.00	84.00		M
3/0		64.00	80.00	96.00		M
4/0		72.00	90.00	108.00		M
<b>3/C 600 Volt Alum Primary Cable with Messenger Wire Support</b>						
#6		24.00	30.00	36.00		M
#4		28.00	35.00	42.00		M
#2		32.00	40.00	48.00		M
#1		36.00	45.00	5.00		M
1/0		40.00	50.00	60.00		M
2/0		44.00	55.00	66.00		M
3/0		48.00	60.00	72.00		M
4/0		52.00	65.00	78.00		M
<b>Pole Mounted Single Phase Transformers</b>						
5 KVA		6.00	7.50	9.00		E
10 KVA		7.00	8.50	10.00		E
15 KVA		8.00	10.00	12.00		E
25 KVA		10.00	12.50	15.00		E
37 1/2 KVA		12.00	15.00	18.00		E
50 KVA		15.00	17.50	22.50		E
75 KVA		18.00	22.50	27.00		E
100 KVA		22.00	27.50	33.00		E
167 KVA		26.00	33.00	40.00		E
250 KVA		32.00	40.00	48.00		E
333 KVA		40.00	50.00	60.00		E
500 KVA		52.00	65.00	78.00		E
<b>Pole Mounted Three Phase Transformers</b>						
30 KVA		30.00	37.50	45.00		E
45 KVA		34.00	42.00	51.00		E
75 KVA		38.00	47.00	57.00		E
112 1/2 KVA		43.00	54.00	64.00		E
150 KVA		48.00	60.00	72.00		E
225 KVA		54.00	67.00	80.00		E
300 KVA		60.00	75.00	90.00		E
500 KVA		72.00	90.00	110.00		E
<b>Pole Mounted Capacitors</b>						
25 KVAR		8.00	10.00	14.00		E
50 KVAR		10.00	12.00	16.00		E
100 KVAR		16.00	18.00	20.00		E
<b>Pole Mounted Air Break Switches</b>						
5KV Pole Mounted Air Break Switches		36.00	45.00	54.00		E
15KV Pole Mounted Air Break Switches		40.00	50.00	60.00		E
<b>5-15KV Single Phase Pole Mounted Oil Switches</b>						
1-Switch Remote Operated		10.00	12.50	15.00		E
1-Switch Manual Operated		20.00	25.00	30.00		E
2-Switch Manual Operated		30.00	37.50	45.00		E
3-Switch Manual Operated		40.00	50.00	60.00		E
<b>5-15KV Three Phase Pole Mounted Oil Switches</b>						
3-Switch Remote Operated		40.00	50.00	60.00		E
3-Switch Manual Operated		60.00	75.00	90.00		E
<b>Pole Mounted Lightning Arrestors</b>						
20 KV		5.00	6.20	7.50		E
35 KV		6.00	7.50	9.00		E
50 KV		7.00	8.70	10.50		E
70 KV		8.00	10.00	12.00		E
100 KV		9.00	11.20	13.50		E
120 KV		10.00	12.50	15.00		E
160 KV		12.00	15.00	18.00		E
200 KV		14.00	17.50	21.00		E
<b>Circuit Reclosures</b>						
Single Phase Circuit Reclosure		12.00	15.00	18.00		E
Three Phase Circuit Reclosures		24.00	30.00	36.00		E










## Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Transformers Outdoor Type Up to 15 KV Primary, Unload, Inspect and Handling Labor Only</b>	X					
25 KVA	X	6.00	7.50	9.00		E
50 KVA	X	7.00	8.75	10.50		E
75 KVA	X	8.00	10.00	12.00		E
100 KVA	X	9.00	11.25	13.50		E
150 KVA	X	10.00	12.50	15.00		E
200 KVA	X	11.00	13.75	16.50		E
225 KVA	X	12.00	15.00	18.00		E
250 KVA	X	13.00	16.25	19.50		E
300 KVA	X	14.00	17.50	21.00		E
400 KVA	X	15.00	18.75	22.50		E
500 KVA	X	16.00	20.00	24.00		E
600 KVA	X	18.00	22.50	27.00		E
750 KVA	X	20.00	25.00	30.00		E
1000 KVA	X	22.00	27.50	33.00		E
1500 KVA	X	24.00	30.00	36.00		E
2000 KVA	X	26.00	32.50	39.00		E
2500 KVA	X	29.00	36.25	43.50		E
3000 KVA	X	32.00	40.00	48.00		E
<i>Note: Labor Units Do Not Include</i>	X					
1) Housekeeping Pad	X					
2) Vibration Isolator	X					
3) Seismic Supports	X					
4) Larger Sized Equipment Will Require Special Handling And/Or Rigging						
<b>600 Amp Sectional Switches, Pad Mounted, Outdoor Type Up to 15 KV Primary, Unload, Inspect and Handling Labor Only</b>	X					
2 Section	X	21.00	27.00	32.00		E
4 Section	X	40.00	48.00	56.00		E
<i>Note: Labor Units do not Include</i>	X					
1) Housekeeping Pad	X					
2) Remote Supervisory	X					
3) Remote Source Transfer	X					
4) Fuses or Fusing	X					
<b>600-1200 Amp Pad Mounted Switchgear, Outdoor Type Up to 15 KV Primary, Unload, Inspect and Handling Labor Only</b>	X					
Radial System:	X					
3 Section	X	64.00	81.00	97.00		E
4 Section	X	79.00	99.00	118.00		E
5 Section	X	99.00	124.00	148.00		E
6 Section	X	140.00	175.00	210.00		E
Common Bus, Primary-Selective	X					
6 Section	X	140.00	175.00	210.00		E
7 Section	X	189.00	236.00	284.00		E
8 Section	X	216.00	270.00	324.00		E
9 Section	X	236.00	285.00	335.00		E
Split-Bus, Primary-Selective	X					
6 Section	X	140.00	175.00	210.00		E
7 Section	X	189.00	236.00	284.00		E
8 Section	X	216.00	270.00	324.00		E
9 Section	X	236.00	285.00	335.00		E
<i>Note: Labor Units do not Include</i>	X					
1) Housekeeping Pad	X					
2) Remote Supervisory	X					
3) Remote Source Transfer	X					
4) Fuses or Fusing	X					
<b>Hand Excavation of Small Trenches</b>						
Sandy Soil - 6" x 18" Deep		4.00	5.00	6.00		C
9" x 18" Deep		5.00	6.20	7.50		C
12" x 18" Deep		6.00	7.50	9.00		C
12" x 24" Deep		9.00	11.20	13.50		C
12" x 30" Deep		12.00	15.00	18.00		C
18" x 36" Deep		20.00	25.00	30.00		C
Clay Soil - 6" x 18" Deep		6.00	7.50	9.00		C
9" x 18" Deep		8.00	10.00	12.00		C
12" x 18" Deep		10.00	12.50	15.00		C
12" x 24" Deep		15.00	18.70	22.50		C
12" x 30" Deep		20.00	25.00	30.00		C
18" x 36" Deep		34.00	42.00	50.00		C
Loose Shale 6" x 18" Deep		8.00	10.00	12.00		C
9" x 18" Deep		10.00	12.50	15.00		C
12" x 18" Deep		13.00	16.00	19.00		C
12" x 24" Deep		18.00	22.00	27.00		C
12" x 30" Deep		24.00	30.00	36.00		C
18" x 36" Deep		40.00	50.00	60.00		C
Rocky Soil 6" x 18" Deep		10.00	12.50	15.00		C
9" x 18" Deep		14.00	17.50	21.00		C
12" x 18" Deep		18.00	22.00	27.00		C
12" x 24" Deep		24.00	30.00	36.00		C
12" x 30" Deep		32.00	40.00	48.00		C
18" x 36" Deep		56.00	70.00	84.00		C












Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Hand Trim Bottom of Machine Excavated Trenches</b>						
12" Wide - Sandy Soil		2.00	2.50	3.00		C
18" Wide - Sandy Soil		3.00	3.70	4.50		C
24" Wide - Sandy Soil		4.00	5.00	6.00		C
36" Wide - Sandy Soil		6.00	7.50	9.00		C
48" Wide - Sandy Soil		8.00	10.00	12.00		C
60" Wide - Sandy Soil		10.00	12.50	15.00		C
12" Wide - Soft Clay		3.00	3.70	4.50		C
18" Wide - Soft Clay		4.00	5.00	6.00		C
24" Wide - Soft Clay		5.00	6.20	7.50		C
36" Wide - Soft Clay		8.00	10.00	12.00		C
48" Wide - Soft Clay		10.00	12.50	15.00		C
60" Wide - Soft Clay		13.00	16.00	19.00		C
12" Wide - Hard Clay		4.00	5.00	6.00		C
18" Wide - Hard Clay		5.00	6.20	7.50		C
24" Wide - Hard Clay		6.00	7.50	9.00		C
36" Wide - Hard Clay		9.00	11.20	13.50		C
48" Wide - Hard Clay		12.00	15.00	18.00		C
60" Wide - Hard Clay		15.00	18.70	22.50		C
12" Wide - Shale		5.00	6.20	7.50		C
18" Wide - Shale		6.00	7.50	9.00		C
24" Wide - Shale		8.00	10.00	12.00		C
36" Wide - Shale		10.00	12.50	15.00		C
48" Wide - Shale		14.00	17.50	21.00		C
60" Wide - Shale		18.00	22.00	27.00		C
12" Wide - Rocky Soil		6.00	7.50	9.00		C
18" Wide - Rocky Soil		7.00	8.70	10.50		C
24" Wide - Rocky Soil		9.00	11.20	13.50		C
36" Wide - Rocky Soil		12.00	15.00	18.00		C
48" Wide - Rocky Soil		16.00	20.00	24.00		C
60" Wide - Rocky Soil		20.00	25.00	30.00		C
<b>Inst. &amp; Removal of Trench Shoring -</b>						
<b>3/4" Plywood Shoring Both Sides &amp;</b>						
<b>Steel Trench Jacks Bracing</b>						
4' Deep		0.40	0.50	0.60		LF
6' Deep		0.45	0.56	0.67		LF
8' Deep		0.50	0.62	0.75		LF
10' Deep		0.55	0.68	0.82		LF
<b>Inst. &amp; Removal of Trench Shoring -</b>						
<b>3/4" Plywood Both Sides -</b>						
<b>2x8 Vert Planks &amp; Steel Trench Jacks</b>						
4' Deep		0.50	0.62	0.75		LF
6' Deep		0.55	0.68	0.82		LF
8' Deep		0.60	0.75	0.90		LF
10' Deep		0.65	0.81	0.97		LF
<b>Inst. &amp; Removal of Trench Shoring -</b>						
<b>2x12's Laid Horiz. Both Sides</b>						
<b>2x8 Vert Planks &amp; Steel Trench Jacks</b>						
4' Deep		0.50	0.62	0.75		LF
6' Deep		0.60	0.75	0.90		LF
8' Deep		0.70	0.87	1.05		LF
10' Deep		0.80	1.00	1.20		LF
<b>Inst. &amp; Removal of Trench Shoring -</b>						
<b>Vert 2x12's Both Sides -</b>						
<b>2x8 Horiz Headers &amp; Steel Trench Jacks</b>						
4' Deep		0.80	1.00	1.20		LF
6' Deep		0.85	1.06	1.27		LF
8' Deep		0.90	1.12	1.35		LF
10' Deep		1.00	1.25	1.50		LF
<b>Inst. &amp; Removal of Trench Shoring -</b>						
<b>Steel Shoring Both Sides</b>						
<b>w/ Either Steel Trench Jacks or</b>						
<b>4x4 Horiz. Wood Bracing</b>						
4' Deep		0.30	0.37	0.45		LF
6' Deep		0.35	0.43	0.52		LF
8' Deep		0.40	0.50	0.60		LF
10' Deep		0.50	0.62	0.75		LF
<b>Inst. &amp; Removal of Trench Shoring -</b>						
<b>2x12 Vert Planks Both Sides &amp;</b>						
<b>Two Steel Trench Jacks or</b>						
<b>Two 4 x 4 Wood Braces</b>						
4' Deep		0.25	0.31	0.34		E
6' Deep		0.30	0.37	0.45		E
8' Deep		0.35	0.43	0.52		E
10' Deep		0.40	0.50	0.60		E




Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>3" Deep Sand Bedding in Trenches</b>						
 12" Wide		8.00	10.00	12.00		C
18" Wide		10.00	12.50	15.00		C
24" Wide		12.00	15.00	18.00		C
36" Wide		15.00	18.70	22.00		C
48" Wide		18.00	22.00	27.00		C
60" Wide		22.00	27.00	33.00		C
<b>3" Deep Concrete Bedding in Trenches</b>						
 12" Wide		6.00	8.00	10.00		C
18" Wide		7.00	9.00	11.00		C
24" Wide		8.00	10.00	12.00		C
36" Wide		9.00	11.00	13.00		C
48" Wide		10.00	12.00	14.00		C
60" Wide		12.00	14.00	16.00		C
<b>Backfill &amp; Compaction of Trenches</b>						
 6" x 18" Deep		4.00	5.00	6.00		C
6" x 24" Deep		5.00	6.20	7.50		C
6" x 30" Deep		6.00	7.50	9.00		C
12" x 24" Deep		8.00	10.00	12.00		C
12" x 30" Deep		10.00	12.50	15.00		C
12" x 36" Deep		12.00	15.00	18.00		C
18" x 24" Deep		10.00	12.50	15.00		C
18" x 30" Deep		12.00	15.00	18.00		C
18" x 36" Deep		14.00	17.50	21.00		C
24" x 24" Deep		16.00	20.00	24.00		C
24" x 30" Deep		18.00	22.50	27.00		C
24" x 36" Deep		20.00	25.00	30.00		C
30" x 30" Deep		24.00	30.00	36.00		C
30" x 36" Deep		28.00	35.00	42.00		C
30" x 48" Deep		36.00	45.00	54.00		C
36" x 36" Deep		32.00	40.00	48.00		C
36" x 48" Deep		40.00	50.00	60.00		C
36" x 60" Deep		48.00	60.00	72.00		C
48" x 48" Deep		50.00	62.00	75.00		C
48" x 60" Deep		60.00	75.00	90.00		C
48" x 72" Deep		70.00	85.00	100.00		C
<b>3/4" Plywood Forms for Duct Bank Concrete Encasement - One Side Only</b>						
 12" Deep		10.00	12.50	15.00		C
18" Deep		12.00	15.00	18.00		C
24" Deep		14.00	17.50	21.00		C
30" Deep		16.00	20.00	24.00		C
36" Deep		18.00	22.50	27.00		C
48" Deep		20.00	25.00	30.00		C
60" Deep		24.00	30.00	36.00		C
<b>3/4" Plywood Forms for Duct Bank Concrete Encasement - Forms on Both Sides</b>						
 12" Deep		20.00	25.00	30.00		C
18" Deep		24.00	30.00	36.00		C
24" Deep		28.00	35.00	42.00		C
30" Deep		32.00	40.00	48.00		C
36" Deep		36.00	45.00	54.00		C
48" Deep		40.00	50.00	60.00		C
60" Deep		48.00	60.00	72.00		C
<b>Plastic Spacers in Duct Bank for Conduit</b>						
 2" - 6" Wide		12.00	14.00	16.00		C
<i>Note: Add for tie-wire</i>						
<b>Pouring Concrete Directly From Ready Mix Trucks Into Duct Banks - Per Cubic Yard (CY)</b>						
 Pouring Concrete Directly From Ready Mix Trucks Into Duct Banks		0.50	0.75	1.00		CY
<i>Note: Excludes Rebar</i>						
<b>Wood Forms For Concrete Slabs</b>						
 6" High		0.60	0.75	0.90		LF
8" High		0.65	0.80	0.95		LF
10" High		0.70	0.85	1.00		LF
12" High		0.80	1.00	1.20		LF
18" High		1.00	1.25	1.50		LF
24" High		1.20	1.50	1.80		LF
<b>Rented Steel Forms For Concrete Slabs</b>						
 6" High		0.50	0.62	0.75		LF
8" High		0.55	0.68	0.82		LF
10" High		0.60	0.75	0.90		LF
12" High		0.70	0.85	1.00		LF
18" High		0.85	1.05	1.25		LF
24" High		1.00	1.25	1.50		LF







## Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Sonotube Pole Foundation Forms - 48" High</b>						
 8" Dia		0.60	0.75	0.90		E
12" Dia		0.65	0.80	0.95		E
16" Dia		0.70	0.85	1.00		E
20" Dia		0.80	1.00	1.20		E
24" Dia		0.90	1.12	1.35		E
30" Dia		1.00	1.25	1.50		E
<b>Plywood Pole Foundation Forms - 48" High</b>						
8" x 8"		3.00	3.75	4.50		E
12" x 12"		3.50	4.35	5.25		E
16" x 16"		4.00	5.00	6.00		E
20" x 20"		5.00	6.25	7.50		E
24" x 24"		6.00	7.50	9.00		E
<b>Wire Reinforcing Mesh In Concrete Slabs</b>						
Wire Reinforcing Mesh In Concrete Slabs		0.40	0.50	0.60		SF
<b>Steel Reinforcing Bars In Concrete Slabs</b>						
2 to 5 #/SF		0.40	0.50	0.60		SF
6 to 10 #/SF		0.50	0.62	0.75		SF
11 to 15 #/SF		0.60	0.75	0.90		SF
16 to 20 #/SF		0.70	0.85	1.00		SF
<b>Steel Reinforcing Bars in Pole Foundations</b>						
2 to 5 #/CY		1.00	1.25	1.50		CY
6 to 10 #/CY		1.50	1.85	2.25		CY
11 to 15 #/CY		2.25	2.80	3.35		CY
16 to 20 #/CY		3.00	3.75	4.50		CY
<b>Pour Concrete Slabs At Grade Elevation</b>						
<b>Directly From Ready Mix Trucks</b>						
6" Thick		0.10	0.12	0.15		SF
8" Thick		0.12	0.15	0.18		SF
10" Thick		0.14	0.17	0.21		SF
12" Thick		0.16	0.20	0.24		SF
18" Thick		0.18	0.22	0.27		SF
24" Thick		0.20	0.25	0.30		SF
<b>Pouring Concrete In 48" High Pole Foundations</b>						
	X					
8" Dia	X	0.50	0.62	0.75		E
12" Dia	X	0.55	0.68	0.82		E
16" Dia	X	0.60	0.75	0.90		E
20" Dia	X	0.70	0.85	1.00		E
24" Dia	X	0.85	1.05	1.25		E
30" Dia	X	1.00	1.25	1.50		E
<b>Hand Finish Concrete Slabs At Grade</b>						
Hand Finish Concrete Slabs At Grade		0.10	0.12	0.15		SF
<b>Hand Finish Pole Foundations Above Grade</b>						
Hand Finish Pole Foundations Above Grade		0.20	0.25	0.30		SF
<b>HDPE Polyethylene Plastic Laid In Trenches -</b>						
<b>Per LF With O-Rings</b>						
1"		4.00	5.00	6.00		C
1 1/2"		4.25	5.30	6.35		C
2"		4.50	5.60	6.75		C
3"		4.75	5.90	7.10		C
4"		5.00	6.25	7.50		C
5"		5.25	6.50	7.75		C
6"		5.50	6.75	8.00		C
<b>HDPE Coupling O-Ring Type</b>						
1"		10.00	12.50	15.00		C
1 1/2"		12.00	15.00	18.00		C
2"		14.00	17.50	21.00		C
3"		17.00	21.00	25.00		C
4"		20.00	25.00	30.00		C
5"		23.00	27.00	32.00		C
6"		25.00	30.00	35.00		C
<b>HDPE Conduit Adapter</b>						
1"		15.00	18.70	22.50		C
1 1/2"		20.00	25.00	30.00		C
2"		25.00	31.00	37.00		C
3"		30.00	37.00	45.00		C
4"		35.00	43.00	52.00		C
5"		40.00	49.00	59.00		C
6"		45.00	55.00	65.00		C

Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 PVC EB/DB Plastic Conduit Laid In Trenches - 10Ft & 20Ft Lengths With Glued Couplings						
2"		4.00	5.00	6.00		C
3"		4.25	5.30	6.35		C
3 1/2"		4.50	5.60	6.75		C
4"		4.75	5.90	7.10		C
5"		5.00	6.25	7.50		C
6"		5.40	6.75	8.00		C
<i>Note: Reduce Labor Units for 20Ft Lengths by 10%</i>						
PVC EB/DB Plastic Conduit Laid In Trenches - Couplings - Glued Type						
2"		15.00	18.70	22.50		C
3"		20.00	25.00	30.00		C
3 1/2"		25.00	31.00	37.00		C
4"		30.00	37.00	45.00		C
5"		35.00	43.00	52.00		C
6"		40.00	50.00	60.00		C
PVC EB/DB Plastic Conduit Laid In Trenches - 90 Degree Elbows						
2"		30.00	37.00	45.00		C
3"		35.00	43.00	52.00		C
3 1/2"		40.00	50.00	60.00		C
4"		45.00	56.00	67.00		C
5"		50.00	62.00	75.00		C
6"		58.00	73.00	87.00		C
PVC EB/DB Plastic Conduit Laid In Trenches - Threaded End Conduit Adapters						
2"		20.00	25.00	30.00		C
3"		25.00	31.00	37.00		C
3 1/2"		30.00	37.00	45.00		C
4"		35.00	43.00	52.00		C
5"		40.00	50.00	60.00		C
6"		46.00	58.00	70.00		C
PVC Duct Bank Conduit Spacers						
1/2" - 2"		12.00	14.00	16.00		C
2 1/2" - 6"		20.00	25.00	30.00		C
Sch 40 PVC Conduit Laid In Trenches - 10Ft & 20Ft Len. w/ Glued Couplings						
3/4"		3.50	4.50	5.50		C
1"		3.75	4.75	5.75		C
1 1/4"		4.00	5.00	6.00		C
1 1/2"		4.25	5.30	6.35		C
2"		4.50	5.60	6.75		C
2 1/2"		4.75	5.90	7.10		C
3"		5.00	6.25	7.50		C
3 1/2"		5.25	6.55	7.85		C
4"		5.50	6.85	8.25		C
5"		5.75	7.15	8.60		C
6"		6.00	7.50	9.00		C
<i>Note: Reduce Labor Units for 20Ft Lengths by 10%</i>						
Sch 40 PVC Conduit Laid In Trenches - 90 Degree Elbows Add 20% for Wide Sweep Elbows						
1/2"		0.20	0.25	0.30		E
3/4"		0.22	0.28	0.33		E
1"		0.25	0.31	0.38		E
1 1/4"		0.32	0.40	0.48		E
1 1/2"		0.40	0.48	0.60		E
2"		0.50	0.63	0.75		E
2 1/2"		0.60	0.75	0.90		E
3"		0.70	0.84	1.05		E
3 1/2"		0.85	1.06	1.28		E
4"		1.00	1.25	1.50		E
5"		1.25	1.56	1.88		E
6"		1.50	1.88	2.25		E
Sch 40 PVC Conduit Laid In Trenches - Threaded Adapters						
1/2"		0.14	0.17	0.21		E
3/4"		0.16	0.20	0.24		E
1"		0.18	0.22	0.27		E
1 1/4"		0.20	0.25	0.30		E
1 1/2"		0.25	0.31	0.37		E
2"		0.30	0.37	0.45		E
2 1/2"		0.40	0.50	0.60		E
3"		0.50	0.62	0.75		E
3 1/2"		0.65	0.81	0.97		E
4"		0.80	1.00	1.20		E
5"		1.00	1.25	1.50		E
6"		1.25	1.55	1.85		E

Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Sch 40 PVC Conduit Laid In Trenches - Expansion Couplings</b>						
 1/2"		0.50	0.62	0.75		E
3/4"		0.60	0.75	0.90		E
1"		0.70	0.87	1.05		E
1 1/4"		0.80	1.00	1.20		E
1 1/2"		0.90	1.12	1.35		E
2"		1.00	1.25	1.50		E
2 1/2"		1.15	1.43	1.72		E
3"		1.30	1.62	1.95		E
3 1/2"		1.50	1.85	2.25		E
4"		1.75	2.15	2.60		E
5"		2.00	2.50	3.00		E
6"		2.25	2.75	3.25		E
<b>Field Bend Sch 40 PVC Conduit &amp; Installation</b>						
<b>Add 10% for each field cut &amp; ream</b>						
 1/2"		0.40	0.50	0.60		E
3/4"		0.50	0.60	0.75		E
1"		0.60	0.75	0.90		E
1 1/4"		0.65	0.81	0.98		E
1 1/2"		0.80	1.00	1.20		E
2"		1.00	1.25	1.50		E
2 1/2"		1.20	1.50	1.80		E
3"		1.40	1.75	2.10		E
3 1/2"		1.70	2.13	2.55		E
4"		2.00	2.50	3.00		E
5"		3.15	3.94	4.73		E
6"		4.20	5.25	6.30		E
<b>Sch 80 PVC Conduit Laid In Trenches - 10Ft &amp; 20Ft Lengths w/ Glued Couplings</b>						
 1/2"		4.00	5.00	6.00		C
3/4"		4.20	5.20	6.20		C
1"		4.50	5.50	6.50		C
1 1/4"		4.80	5.80	6.80		C
1 1/2"		5.10	6.10	7.10		C
2"		5.40	6.40	7.40		C
2 1/2"		5.70	6.70	7.70		C
3"		6.00	7.00	8.00		C
4"		6.60	7.60	8.60		C
5"		6.90	7.90	8.90		C
6"		7.20	8.20	9.20		C
<b>Sch 80 PVC Conduit Laid In Trenches - 90 Degree Elbows</b>						
<b>Add 20% for Wide Sweep Elbows</b>						
 1/2"		0.22	0.27	0.32		E
3/4"		0.24	0.29	0.34		E
1"		0.28	0.33	0.38		E
1 1/4"		0.35	0.40	0.45		E
1 1/2"		0.46	0.56	0.66		E
2"		0.58	0.73	0.88		E
2 1/2"		0.69	0.89	1.09		E
3"		0.84	1.09	1.34		E
4"		1.20	1.70	2.20		E
5"		1.50	2.00	2.50		E
6"		1.80	2.30	2.80		E
<b>Sch 80 PVC Conduit Laid In Trenches - Threaded Adapters</b>						
 1/2"		0.16	0.19	0.23		E
3/4"		0.18	0.22	0.26		E
1"		0.20	0.24	0.28		E
1 1/4"		0.22	0.27	0.32		E
1 1/2"		0.30	0.35	0.40		E
2"		0.35	0.42	0.47		E
2 1/2"		0.45	0.55	0.65		E
3"		0.60	0.70	0.80		E
4"		0.70	0.85	1.00		E
5"		0.85	1.15	1.35		E
6"		1.20	1.40	1.70		E
<b>Sch 80 PVC Conduit Laid In Trenches - Expansion Couplings</b>						
 1/2"		0.25	0.30	0.35		E
3/4"		0.30	0.36	0.41		E
1"		0.40	0.48	0.55		E
1 1/4"		0.50	0.60	0.70		E
1 1/2"		0.65	0.78	0.90		E
2"		0.75	0.90	1.05		E
2 1/2"		0.85	1.02	1.17		E
3"		1.05	1.26	1.45		E
4"		1.40	1.68	1.93		E
5"		1.65	1.98	2.28		E
6"		1.90	2.28	2.62		E

## Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Field Bend Sch 80 PVC Conduit &amp; Installation</b>						
Add 10% for each field cut & ream						
1/2"		0.50	0.60	0.70		E
3/4"		0.60	0.70	0.80		E
1"		0.70	0.85	1.00		E
1 1/4"		0.80	0.96	1.12		E
1 1/2"		1.00	1.20	1.40		E
2"		1.25	1.50	1.75		E
2 1/2"		1.50	1.75	2.00		E
3"		1.75	2.00	2.25		E
4"		2.00	2.25	2.50		E
5"		2.40	2.90	3.40		E
6"		3.65	4.44	5.23		E
<b>600 Volt Direct Burial Copper Cable</b>						
1/C #12 TO #8		18.00	22.00	27.00		M
1/C #6 to #3		20.00	25.00	30.00		M
1/C #2 to 2/0		22.00	27.00	33.00		M
1/C 3/0 to 250		24.00	30.00	36.00		M
1/C 300 to 500		28.00	35.00	42.00		M
1/C 600 to 750		32.00	40.00	48.00		M
2/C #12 to #8		23.00	28.00	34.00		M
2/C #6 to #3		25.00	31.00	37.00		M
2/C #2 to 2/0		27.00	33.00	41.00		M
2/C 3/0 to 250		30.00	37.00	45.00		M
2/C 300 to 500		35.00	43.00	52.00		M
2/C 600 to 750		40.00	50.00	60.00		M
3/C #12 to #8		27.00	33.00	41.00		M
3/C #6 to #3		30.00	37.00	45.00		M
3/C #2 to 2/0		33.00	41.00	49.00		M
3/C 3/0 to 250		36.00	45.00	54.00		M
3/C 300 to 500		42.00	52.00	63.00		M
3/C 600 to 750		48.00	60.00	72.00		M
<b>600 Volt Direct Burial Aluminum Cable</b>						
1/C #12 TO #8		16.00	20.00	24.00		M
1/C #6 to #3		17.00	21.00	25.00		M
1/C #2 to 2/0		18.00	23.00	27.00		M
1/C 3/0 to 250		20.00	25.00	30.00		M
1/C 300 to 500		23.00	28.00	34.00		M
1/C 600 to 750		26.00	32.00	39.00		M
2/C #12 to #8		20.00	25.00	30.00		M
2/C #6 to #3		22.00	27.00	33.00		M
2/C #2 to 2/0		24.00	30.00	36.00		M
2/C 3/0 to 250		26.00	32.00	39.00		M
2/C 300 to 500		29.00	36.00	43.00		M
2/C 600 to 750		32.00	40.00	48.00		M
3/C #12 to #8		23.00	28.00	34.00		M
3/C #6 to #3		25.00	31.00	37.00		M
3/C #2 to 2/0		27.00	33.00	41.00		M
3/C 3/0 to 250		30.00	37.00	45.00		M
3/C 300 to 500		35.00	43.00	52.00		M
3/C 600 to 750		40.00	50.00	60.00		M
<b>5 KV Direct Burial Copper Cable</b>						
1/C #12 TO #8		20.00	25.00	30.00		M
1/C #6 to #3		22.00	27.00	33.00		M
1/C #2 to 2/0		24.00	30.00	36.00		M
1/C 3/0 to 250		26.00	32.00	39.00		M
1/C 300 to 500		30.00	37.00	45.00		M
1/C 600 to 750		34.00	42.00	51.00		M
2/C #12 to #8		25.00	31.00	37.00		M
2/C #6 to #3		27.00	33.00	41.00		M
2/C #2 to 2/0		30.00	37.00	45.00		M
2/C 3/0 to 250		33.00	41.00	49.00		M
2/C 300 to 500		37.00	46.00	55.00		M
2/C 600 to 750		42.00	52.00	63.00		M
3/C #12 to #8		30.00	37.00	45.00		M
3/C #6 to #3		33.00	41.00	49.00		M
3/C #2 to 2/0		36.00	45.00	54.00		M
3/C 3/0 to 250		39.00	48.00	58.00		M
3/C 300 to 500		43.00	53.00	64.00		M
3/C 600 to 750		48.00	60.00	72.00		M

## Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>5 KV Direct Burial Aluminum Cable</b>						
1/C #12 TO #8		18.00	22.00	27.00		M
1/C #6 to #3		20.00	25.00	30.00		M
1/C #2 to 2/0		22.00	27.00	33.00		M
1/C 3/0 to 250		24.00	30.00	36.00		M
1/C 300 to 500		26.00	32.00	39.00		M
1/C 600 to 750		30.00	37.00	45.00		M
2/C #12 to #8		23.00	28.00	34.00		M
2/C #6 to #3		25.00	31.00	37.00		M
2/C #2 to 2/0		27.00	33.00	40.00		M
2/C 3/0 to 250		30.00	37.00	45.00		M
2/C 300 to 500		34.00	42.00	51.00		M
2/C 600 to 750		38.00	47.00	57.00		M
3/C #12 to #8		25.00	31.00	37.00		M
3/C #6 to #3		27.00	33.00	40.00		M
3/C #2 to 2/0		30.00	37.00	45.00		M
3/C 3/0 to 250		33.00	41.00	49.00		M
3/C 300 to 500		37.00	46.00	55.00		M
3/C 600 to 750		42.00	52.00	63.00		M
<b>15 KV Direct Burial Copper Cable</b>						
1/C #12 TO #8		24.00	30.00	36.00		M
1/C #6 to #3		26.00	32.00	39.00		M
1/C #2 to 2/0		28.00	35.00	42.00		M
1/C 3/0 to 250		30.00	37.00	45.00		M
1/C 300 to 500		33.00	41.00	49.00		M
1/C 600 to 750		36.00	45.00	54.00		M
2/C #12 to #8		30.00	37.00	45.00		M
2/C #6 to #3		32.00	40.00	48.00		M
2/C #2 to 2/0		34.00	42.00	51.00		M
2/C 3/0 to 250		36.00	45.00	54.00		M
2/C 300 to 500		39.00	48.00	58.00		M
2/C 600 to 750		43.00	53.00	64.00		M
3/C #12 to #8		32.00	40.00	48.00		M
3/C #6 to #3		35.00	43.00	52.00		M
3/C #2 to 2/0		38.00	47.00	57.00		M
3/C 3/0 to 250		41.00	51.00	61.00		M
3/C 300 to 500		45.00	56.00	67.00		M
3/C 600 to 750		50.00	62.00	75.00		M
<b>15 KV Direct Burial Aluminum Cable</b>						
1/C #12 TO #8		20.00	25.00	30.00		M
1/C #6 to #3		22.00	27.00	33.00		M
1/C #2 to 2/0		24.00	30.00	36.00		M
1/C 3/0 to 250		26.00	32.00	39.00		M
1/C 300 to 500		28.00	35.00	42.00		M
1/C 600 to 750		30.00	37.00	45.00		M
2/C #12 to #8		25.00	31.00	37.00		M
2/C #6 to #3		27.00	33.00	40.00		M
2/C #2 to 2/0		30.00	37.00	45.00		M
2/C 3/0 to 250		33.00	41.00	49.00		M
2/C 300 to 500		36.00	45.00	54.00		M
2/C 600 to 750		40.00	50.00	60.00		M
3/C #12 to #8		30.00	37.00	45.00		M
3/C #6 to #3		32.00	40.00	48.00		M
3/C #2 to 2/0		34.00	42.00	51.00		M
3/C 3/0 to 250		36.00	45.00	54.00		M
3/C 300 to 500		40.00	50.00	60.00		M
3/C 600 to 750		44.00	55.00	66.00		M
<b>25 KV 1/C Direct Burial Copper Cable w/ Concentric Wire Neutral</b>						
#4		27.00	33.00	40.00		M
#2		28.00	35.00	42.00		M
#1		29.00	36.00	43.00		M
1/0		30.00	37.00	45.00		M
2/0		31.00	38.00	46.00		M
3/0		32.00	40.00	48.00		M
4/0		34.00	42.00	51.00		M
250 kcmil		36.00	45.00	54.00		M
350 kcmil		38.00	47.00	57.00		M
500 kcmil		40.00	50.00	60.00		M
750 kcmil		42.00	52.00	63.00		M
<b>25 KV 1/C Direct Burial Aluminum Cable w/ Concentric Wire Neutral</b>						
#4		25.00	31.00	37.00		M
#2		26.00	32.00	38.00		M
#1		27.00	33.00	40.00		M
1/0		28.00	35.00	42.00		M
2/0		29.00	36.00	43.00		M
3/0		30.00	37.00	45.00		M
4/0		32.00	40.00	48.00		M
250 kcmil		34.00	42.00	51.00		M
350 kcmil		36.00	45.00	54.00		M
500 kcmil		38.00	47.00	57.00		M
750 kcmil		40.00	50.00	60.00		M







Section 11 - Outdoor Overhead and Underground Systems



Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>35 KV 1/C Direct Burial Copper Cable</b>						
<b>w/ Concentric Wire Neutral</b>						
#1		30.00	37.00	45.00		M
1/0		31.00	38.00	46.00		M
2/0		32.00	40.00	48.00		M
3/0		33.00	41.00	49.00		M
4/0		35.00	43.00	52.00		M
250 kcmil		37.00	46.00	55.00		M
350 kcmil		39.00	48.00	58.00		M
500 kcmil		41.00	51.00	61.00		M
750 kcmil		44.00	55.00	66.00		M
1000 kcmil		48.00	60.00	72.00		M
<b>35 KV 1/C Direct Burial Aluminum Cable</b>						
<b>w/ Concentric Wire Neutral</b>						
#1		27.00	33.00	40.00		M
1/0		28.00	34.00	41.00		M
2/0		29.00	35.00	43.00		M
3/0		30.00	37.00	45.00		M
4/0		31.00	38.00	46.00		M
250 kcmil		32.00	40.00	48.00		M
350 kcmil		34.00	42.00	51.00		M
500 kcmil		36.00	45.00	54.00		M
750 kcmil		39.00	48.00	58.00		M
1000 kcmil		42.00	52.00	63.00		M
<b>600 Volt Copper Cable Pulled Into Buried Conduit</b>						
1/C #12 TO #8		40.00	50.00	60.00		M
1/C #6 to #3		42.00	52.00	63.00		M
1/C #2 to 2/0		44.00	55.00	66.00		M
1/C 3/0 to 250		46.00	57.00	69.00		M
1/C 300 to 500		48.00	60.00	72.00		M
1/C 600 to 750		50.00	62.00	75.00		M
2/C #12 to #8		44.00	55.00	66.00		M
2/C #6 to #3		46.00	57.00	69.00		M
2/C #2 to 2/0		48.00	60.00	72.00		M
2/C 3/0 to 250		50.00	62.00	75.00		M
2/C 300 to 500		53.00	66.00	79.00		M
2/C 600 to 750		56.00	70.00	84.00		M
3/C #12 to #8		48.00	60.00	72.00		M
3/C #6 to #3		50.00	62.00	75.00		M
3/C #2 to 2/0		52.00	65.00	78.00		M
3/C 3/0 to 250		54.00	67.00	81.00		M
3/C 300 to 500		57.00	71.00	85.00		M
3/C 600 to 750		60.00	75.00	90.00		M
<b>600 Volt Aluminum Cable Pulled Into Buried Conduit</b>						
1/C #12 TO #8		36.00	45.00	54.00		M
1/C #6 to #3		38.00	47.00	57.00		M
1/C #2 to 2/0		40.00	50.00	60.00		M
1/C 3/0 to 250		42.00	52.00	63.00		M
1/C 300 to 500		44.00	55.00	66.00		M
1/C 600 to 750		46.00	57.00	69.00		M
2/C #12 to #8		40.00	50.00	60.00		M
2/C #6 to #3		42.00	52.00	63.00		M
2/C #2 to 2/0		44.00	55.00	66.00		M
2/C 3/0 to 250		46.00	57.00	69.00		M
2/C 300 to 500		49.00	61.00	73.00		M
2/C 600 to 750		52.00	65.00	78.00		M
3/C #12 to #8		44.00	55.00	66.00		M
3/C #6 to #3		46.00	57.00	69.00		M
3/C #2 to 2/0		48.00	60.00	72.00		M
3/C 3/0 to 250		50.00	62.00	75.00		M
3/C 300 to 500		53.00	66.00	79.00		M
3/C 600 to 750		56.00	70.00	84.00		M
<b>5KV Copper Cable Pulled Into Buried Conduit</b>						
1/C #12 TO #8		42.00	52.00	63.00		M
1/C #6 to #3		44.00	55.00	66.00		M
1/C #2 to 2/0		46.00	57.00	69.00		M
1/C 3/0 to 250		48.00	60.00	72.00		M
1/C 300 to 500		50.00	62.00	75.00		M
1/C 600 to 750		53.00	66.00	79.00		M
2/C #12 to #8		46.00	57.00	69.00		M
2/C #6 to #3		48.00	60.00	72.00		M
2/C #2 to 2/0		50.00	62.00	75.00		M
2/C 3/0 to 250		52.00	65.00	78.00		M
2/C 300 to 500		54.00	67.00	81.00		M
2/C 600 to 750		57.00	71.00	85.00		M
3/C #12 to #8		50.00	62.00	75.00		M
3/C #6 to #3		52.00	65.00	78.00		M
3/C #2 to 2/0		54.00	67.00	81.00		M
3/C 3/0 to 250		56.00	70.00	84.00		M
3/C 300 to 500		59.00	73.00	88.00		M
3/C 600 to 750		62.00	77.00	93.00		M

Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>5KV Aluminum Cable Pulled Into Buried Conduit</b>						
 1/C #12 TO #8		39.00	48.00	58.00		M
1/C #6 to #3		41.00	51.00	61.00		M
1/C #2 to 2/0		43.00	53.00	64.00		M
1/C 3/0 to 250		45.00	56.00	67.00		M
1/C 300 to 500		47.00	58.00	70.00		M
1/C 600 to 750		50.00	62.00	75.00		M
2/C #12 to #8		44.00	55.00	66.00		M
2/C #6 to #3		46.00	57.00	69.00		M
2/C #2 to 2/0		48.00	60.00	72.00		M
2/C 3/0 to 250		50.00	62.00	75.00		M
2/C 300 to 500		52.00	65.00	78.00		M
2/C 600 to 750		55.00	68.00	82.00		M
3/C #12 to #8		46.00	57.00	69.00		M
3/C #6 to #3		48.00	60.00	72.00		M
3/C #2 to 2/0		50.00	62.00	75.00		M
3/C 3/0 to 250		52.00	65.00	78.00		M
3/C 300 to 500		54.00	68.00	81.00		M
3/C 600 to 750		57.00	71.00	85.00		M
<b>15KV Copper Cable Pulled Into Buried Conduit</b>						
 1/C #12 TO #8		44.00	55.00	66.00		M
1/C #6 to #3		46.00	57.00	69.00		M
1/C #2 to 2/0		48.00	60.00	72.00		M
1/C 3/0 to 250		50.00	62.00	75.00		M
1/C 300 to 500		52.00	65.00	78.00		M
1/C 600 to 750		54.00	68.00	81.00		M
2/C #12 to #8		48.00	60.00	72.00		M
2/C #6 to #3		50.00	62.00	75.00		M
2/C #2 to 2/0		52.00	65.00	78.00		M
2/C 3/0 to 250		54.00	68.00	81.00		M
2/C 300 to 500		56.00	70.00	84.00		M
2/C 600 to 750		58.00	72.00	87.00		M
3/C #12 to #8		51.00	63.00	76.00		M
3/C #6 to #3		53.00	66.00	79.00		M
3/C #2 to 2/0		55.00	69.00	82.00		M
3/C 3/0 to 250		57.00	71.00	85.00		M
3/C 300 to 500		59.00	74.00	88.00		M
3/C 600 to 750		62.00	78.00	93.00		M
<b>15KV Aluminum Cable Pulled Into Buried Conduit</b>						
 1/C #12 TO #8		40.00	50.00	60.00		M
1/C #6 to #3		42.00	52.00	63.00		M
1/C #2 to 2/0		44.00	55.00	66.00		M
1/C 3/0 to 250		46.00	57.00	69.00		M
1/C 300 to 500		48.00	60.00	72.00		M
1/C 600 to 750		50.00	62.00	75.00		M
2/C #12 to #8		46.00	57.00	69.00		M
2/C #6 to #3		48.00	60.00	72.00		M
2/C #2 to 2/0		50.00	62.00	75.00		M
2/C 3/0 to 250		52.00	65.00	78.00		M
2/C 300 to 500		54.00	68.00	81.00		M
2/C 600 to 750		56.00	70.00	84.00		M
3/C #12 to #8		48.00	60.00	72.00		M
3/C #6 to #3		50.00	62.00	75.00		M
3/C #2 to 2/0		52.00	65.00	78.00		M
3/C 3/0 to 250		54.00	68.00	81.00		M
3/C 300 to 500		56.00	70.00	84.00		M
3/C 600 to 750		58.00	72.00	87.00		M
<b>25 KV 1/C Direct Burial Copper Cable w/ Concentric Neutral Pulled Into Buried Conduit</b>						
 #4		47.00	59.00	70.00		M
#2		48.00	60.00	71.00		M
#1		49.00	61.00	72.00		M
1/0		50.00	62.00	73.00		M
2/0		51.00	63.00	74.00		M
3/0		52.00	64.00	76.00		M
4/0		53.00	65.00	78.00		M
250 kcmil		54.00	66.00	80.00		M
350 kcmil		55.00	68.00	82.00		M
500 kcmil		56.00	70.00	84.00		M
750 kcmil		58.00	72.00	88.00		M
<b>25 KV 1/C Direct Burial Aluminum Cable w/ Concentric Neutral Pulled Into Buried Conduit</b>						
 #4		44.00	56.00	67.00		M
#2		45.00	57.00	68.00		M
#1		46.00	58.00	69.00		M
1/0		47.00	59.00	70.00		M
2/0		48.00	60.00	71.00		M
3/0		49.00	61.00	72.00		M
4/0		50.00	62.00	73.00		M
250 kcmil		51.00	63.00	74.00		M
350 kcmil		52.00	64.00	76.00		M
500 kcmil		53.00	65.00	78.00		M
750 kcmil		54.00	66.00	80.00		M



Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>35 KV 1/C Direct Burial Copper Cable w/ Concentric Neutral Pulled Into Buried Conduit</b>						
#1		50.00	62.00	73.00		M
1/0		51.00	63.00	74.00		M
2/0		52.00	64.00	76.00		M
3/0		53.00	65.00	78.00		M
4/0		54.00	66.00	80.00		M
250 kcmil		55.00	68.00	82.00		M
350 kcmil		56.00	70.00	84.00		M
500 kcmil		57.00	72.00	86.00		M
750 kcmil		58.00	74.00	88.00		M
1000 kcmil		60.00	76.00	90.00		M
<b>35 KV 1/C Direct Burial Aluminum Cable w/ Concentric Neutral Pulled Into Buried Conduit</b>						
#1		47.00	59.00	70.00		M
1/0		48.00	60.00	71.00		M
2/0		49.00	61.00	72.00		M
3/0		50.00	62.00	73.00		M
4/0		51.00	63.00	74.00		M
250 kcmil		52.00	64.00	76.00		M
350 kcmil		53.00	65.00	78.00		M
500 kcmil		54.00	66.00	80.00		M
750 kcmil		55.00	68.00	82.00		M
1000 kcmil		56.00	70.00	84.00		M
<b>Excavation, Backfilling, &amp; Soil Compaction For Manholes</b>						
6' X 6' X 6' Deep - Sandy Soil		8.00	10.00	12.00		E
6' X 6' X 8' Deep - Sandy Soil		9.00	11.00	13.00		E
6' X 6' X 10' Deep - Sandy Soil		10.00	12.00	14.00		E
6' X 6' X 6' Deep - Clay Soil		9.00	11.00	13.00		E
6' X 6' X 8' Deep - Clay Soil		10.00	12.00	14.00		E
6' X 6' X 10' Deep - Clay Soil		11.00	13.00	15.00		E
6' X 6' X 6' Deep - Loose Shale		10.00	14.00	16.00		E
6' X 6' X 8' Deep - Loose Shale		11.00	15.00	17.00		E
6' X 6' X 10' Deep - Loose Shale		12.00	16.00	18.00		E
<b>8" Thick Concrete Foundation For Manholes</b>						
5' x 5'		5.00	7.00	9.00		E
6' x 6'		6.00	8.00	10.00		E
7' x 7'		7.00	9.00	11.00		E
8' x 8'		8.00	10.00	12.00		E
<b>Hand Holes-Open Bottom</b>						
Pre-Cast Concrete 11" x 16"		2.00	2.50	3.00		E
Pre-Cast Concrete 18" x 24"		3.00	3.50	3.90		E
Composite 11" x 16"		1.50	1.75	2.00		E
Composite 18" x 24"		2.00	2.30	2.60		E
<b>Concrete Man Holes Base, Cover and Riser - Excludes Excavation and Gravel Base</b>						
36" x 36" x 36" Base		3.00	4.00	5.00		E
48" x 48" x 48" Base		5.00	6.00	7.00		E
48" x 60" x 48" Base		6.00	7.00	8.00		E
36" x 36" LID		1.25	1.75	1.25		E
48" x 48" LID		2.00	2.50	3.00		E
48" x 60" LID		3.50	3.00	3.50		E
24" Covers		1.00	1.25	1.50		E
36" Covers		1.00	1.25	1.50		E
4' x 6' Base		6.00	8.00	10.00		E
6' x 8' Base		8.00	10.00	12.00		E
8' x 10' Base		10.00	12.00	14.00		E
4' x 4' x 6' Riser		4.00	6.00	8.00		E
6' x 6' x 8' Riser		5.00	7.00	8.00		E
6' x 8' x 10' Riser		6.00	8.00	9.00		E
4' x 6' LID		2.00	3.00	4.00		E
6' x 8' LID		3.00	4.00	5.00		E
8' x 10' LID		4.00	6.00	8.00		E
<b>Manhole Racks Install in Manholes</b>						
4'L with Saddle and Arms		2.00	2.50	3.00		E
6'L with Saddle and Arms		3.00	3.75	4.50		E
8'L with Saddle and Arms		4.00	5.00	6.00		E



## Section 11 - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>3-Section Prefabricated Concrete Manholes</b>						
 4' Dia X 6' Deep		8.00	10.00	12.00		E
4' Dia X 8' Deep		9.00	11.00	13.00		E
4' Dia x 10' Deep		10.00	12.00	14.00		E
4' Dia X 12' Deep		11.00	13.00	15.00		E
5' Dia X 6' Deep		9.00	11.00	13.00		E
5' Dia X 8' Deep		10.00	12.00	14.00		E
5' Dia x 10' Deep		11.00	13.00	15.00		E
5' Dia X 12' Deep		12.00	14.00	16.00		E
6' Dia X 6' Deep		10.00	12.00	14.00		E
6' Dia X 8' Deep		11.00	13.00	15.00		E
6' Dia x 10' Deep		12.00	14.00	16.00		E
6' Dia X 12' Deep		13.00	15.00	17.00		E
<b>Trench Duct</b>						
<i>Does not include excavation, trench preparation, joint sealing</i>						
9000 lb Pedestrian	X	0.40	0.60	0.70		LF
16,000/Axel	X	0.60	0.90	1.05		LF
32,000/Axel	X	0.80	1.20	1.40		LF
Double Wide	X	0.90	1.35	1.58		LF
Lids/Covers	X	0.50	0.75	0.95		LF
Blank Ends	X	0.35	0.50	0.60		LF
<b>Hydro Excavation</b>						
<i>Including set up and backfill, final surface restoration not included</i>						
Based on 2' * 2' * 6'D in Dirt	X	5.00	6.00	7.00		E
<b>Jacking Steel Pipe Under Driveways</b>						
2" Dia - Sandy Soil		0.20	0.25	0.30		LF
4" Dia		0.25	0.30	0.35		LF
6" Dia		0.30	0.35	0.40		LF
8" Dia		0.40	0.45	0.50		LF
2" Dia - Clay Soil		0.25	0.30	0.35		LF
4" Dia		0.30	0.35	0.40		LF
6" Dia		0.35	0.40	0.45		LF
8" Dia		0.45	0.50	0.55		LF
2" Dia - Loose Shale		0.30	0.35	0.40		LF
4" Dia		0.35	0.40	0.45		LF
6" Dia		0.40	0.45	0.50		LF
8" Dia		0.50	0.55	0.60		LF
2" Dia - Packed Shale		0.40	0.45	0.50		LF
4" Dia		0.45	0.50	0.55		LF
6" Dia		0.50	0.55	0.60		LF
8" Dia		0.60	0.65	0.70		LF
<b>Equipment Set-Up Labor For Jacking Pipe</b>						
Equipment Set-Up Labor For Jacking Pipe (*)		4.00	5.00	6.00		E



Section 11 (A) - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Installation of Items</b>						
<b>Wood Poles - Cedar or Pine</b>						
25'		4.00	5.00	6.25		E
30'		4.50	5.63	7.03		E
35'		5.00	6.25	7.81		E
40'		5.50	6.88	8.59		E
45'		6.00	7.50	9.38		E
50'		7.00	8.75	10.94		E
55'		8.00	10.00	12.50		E
60'		10.00	12.50	15.63		E
65'		12.00	15.00	18.75		E
70'		14.00	17.50	21.88		E
75'		17.00	21.25	26.56		E
80'		20.00	25.00	31.25		E
85'		24.00	30.00	37.50		E
90'		28.00	35.00	43.75		E
95'		33.00	41.25	51.56		E
100'		38.00	47.50	59.38		E
<b>Wood Poles - Adder for Setting In Rock</b>						
25'		1.30	1.63	2.03		E
30'		1.40	1.75	2.19		E
35'		1.50	1.88	2.34		E
40'		1.60	2.00	2.50		E
45'		1.70	2.13	2.66		E
50'		1.80	2.25	2.81		E
55'		1.90	2.38	2.97		E
60'		2.00	2.50	3.13		E
65'		2.10	2.63	3.28		E
70'		2.20	2.75	3.44		E
75'		2.40	3.00	3.75		E
80'		2.60	3.25	4.06		E
85'		2.80	3.50	4.38		E
90'		3.00	3.75	4.69		E
95'		3.20	4.00	5.00		E
100'		3.40	4.25	5.31		E
<b>Straighten Existing Poles</b>						
Up To 40 Ft		1.25	1.56	1.95		E
45 To 55 Ft		1.50	1.88	2.34		E
60 To 75 Ft		2.25	2.81	3.52		E
80 To 100 Ft		3.00	3.75	4.69		E
<b>Add For Pole Set In Sidewalk or Pavement</b>						
Add For Pole Set In Sidewalk or Pavement		1.50	1.88	2.34		E
<b>Key Pole - Lof or Plank Key</b>						
New Pole		0.65	0.81	1.02		E
Existing Pole		1.20	1.50	1.88		E
<b>Key Pole - Bottom Of Hole</b>						
Key Pole - Bottom Of Hole		0.40	0.50	0.63		E
<b>Re-Roof Pole</b>						
Re-Roof Pole		1.60	2.00	2.50		E
<b>Dig Poles Holes &amp; Not Used</b>						
Dig Poles Holes & Not Used		1.40	1.75	2.19		E
<b>Haul Poles or Pick Up &amp; Return To Storage</b>						
25 To 35 Ft		2.00	2.50	3.13		E
40 To 55 Ft		3.00	3.75	4.69		E
60 To 75 Ft		4.00	5.00	6.25		E
80 To 100 Ft		5.00	6.25	7.81		E
<b>Barrel Holes - Per Pole</b>						
25 To 35 Ft		4.00	5.00	6.25		E
40 To 55 Ft		5.00	6.25	7.81		E
60 To 75 Ft		7.00	8.75	10.94		E
80 To 100 Ft		9.00	11.25	14.06		E



Section 11 (A) - Outdoor Overhead and Underground Systems




Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Cross Arms With Braces &amp; Pins</b>						
2 To 6 Ft		1.00	1.25	1.56		E
7 To 8 Ft		1.50	1.88	2.34		E
9 To 11 Ft		2.00	2.50	3.13		E
12 To 16 Ft		3.00	3.75	4.69		E
17 To 24 Ft		4.00	5.00	6.25		E
<b>Replace Steel Braces With Wood Braces</b>						
Replace Steel Braces With Wood Braces		0.60	0.75	0.94		E
<b>Conductor Attachments</b>						
Shank Pins		0.10	0.13	0.16		E
Pole Top Pins		0.40	0.50	0.63		E
Stud Bolts, Clevis, or Side Pins		0.40	0.50	0.63		E
20 KV Insulator		0.10	0.13	0.16		E
25 KV Post Insulator		0.40	0.50	0.63		E
3-Wire Section Rack		0.60	0.75	0.94		E
Riser Brackets		0.40	0.50	0.63		E
<b>Down Guys</b>						
Dig Anchor Holes		1.50	1.88	2.34		E
10 Ft Swamp Anchor		7.00	8.75	10.94		E
20 Ft Swamp Anchor		7.40	9.25	11.56		E
2 Ft Anchor In Rock		3.00	3.75	4.69		E
3 Ft Anchor In Rock		3.50	4.38	5.47		E
4 Ft Anchor In Rock		4.00	5.00	6.25		E
Replace Guy Wire		2.75	3.44	4.30		E
Transfer Guy Wire End		2.00	2.50	3.13		E
Add Guy Wire		2.40	3.00	3.75		E
Add Guy Wire Guard		2.75	3.44	4.30		E
Bond Existing Guy Wire		0.60	0.75	0.94		E
<b>Complete Guy With Anchor, Rod, Wire &amp; Guard</b>						
Complete Guy With Anchor, Rod, Wire & Guard		5.00	6.25	7.81		E
<b>Complete Overhead Guy</b>						
Complete Overhead Guy		3.00	3.75	4.69		E
<b>Bond Existing Overhead Guy</b>						
Bond Existing Overhead Guy		0.60	0.75	0.94		E
<b>Transformer Platform</b>						
One Pole		5.60	7.00	8.75		E
Two Pole		10.00	12.50	15.63		E
Three Pole		18.00	22.50	28.13		E
Two Pole With Stub Pole		16.00	20.00	25.00		E
Railing On One Side		2.30	2.88	3.59		E
<b>Primary Attachment</b>						
Primary Clevis		0.50	0.63	0.78		E
Bells & D/E Clamp		0.75	0.94	1.17		E
Neutral Suspension or D/E Clamp		0.40	0.50	0.63		E
<b>1/C Copper or Aluminum Cable - Bare or Insulated (Labor units are per span)</b>						
#4 to #1		1.50	1.88	2.34		E
1/0 To 2/0		2.00	2.50	3.13		E
3/0 To 4/0		2.50	3.13	3.91		E
250 To 400		3.00	3.75	4.69		E
500 To 750		4.00	5.00	6.25		E
800 To 1000		5.50	6.88	8.59		E
<b>Re-sag 1/C Copper or Aluminum Cable</b>						
#4 to #1		0.50	0.63	0.78		E
1/0 To 2/0		0.70	0.88	1.09		E
3/0 To 4/0		1.00	1.25	1.56		E
250 To 400		1.50	1.88	2.34		E
500 To 750		2.00	2.50	3.13		E
800 To 1000		2.50	3.13	3.91		E
<b>3/C Triplex Secondary Cable</b>						
#1 and Smaller		2.30	2.88	3.59		E
1/0 To 2/0		3.00	3.75	4.69		E
3/0 To 4/0		4.00	5.00	6.25		E
250 To 350		5.00	6.25	7.81		E

Section 11 (A) - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Re-sag 3/C Triplex Secondary Cable</b>						
#1 and Smaller		0.90	1.13	1.41		E
1/0 To 2/0		1.30	1.63	2.03		E
3/0 To 4/0		1.80	2.25	2.81		E
250 To 350		2.20	2.75	3.44		E
<b>Copperweld Conductors</b>						
#8A To #6A		1.70	2.13	2.66		E
#4A To #2A		1.90	2.38	2.97		E
Larger Than #2A		2.20	2.75	3.44		E
<b>Re-sag Copperweld Conductors</b>						
#8A To #6A		0.90	1.13	1.41		E
#4A To #2A		1.00	1.25	1.56		E
Larger Than #2A		1.10	1.38	1.72		E
<b>2/C Duplex Secondary Cable</b>						
Up To #1		1.50	1.88	2.34		E
1/0 To 2/0		1.60	2.00	2.50		E
<b>Re-sag 2/C Duplex Secondary Cable</b>						
Up To #1		0.60	0.75	0.94		E
1/0 To 2/0		0.70	0.88	1.09		E
<b>Aluminum Conductor Armor Rods</b>						
Aluminum Conductor Armor Rods		0.40	0.50	0.63		E
<b>1/C ACSR Cable - Bare or Insulated (Labor units are per span)</b>						
#1 and Smaller		2.40	3.00	3.75		E
1/0		2.80	3.50	4.38		E
2/0		3.20	4.00	5.00		E
3/0		3.60	4.50	5.63		E
4/0		4.10	5.13	6.41		E
336 kcmil		4.60	5.75	7.19		E
477 kcmil		5.10	6.38	7.97		E
556 kcmil		5.60	7.00	8.75		E
<b>Re-sag 1/C ACSR Cable</b>						
#1 and Smaller		1.10	1.38	1.72		E
1/0		1.30	1.63	2.03		E
2/0		1.50	1.88	2.34		E
3/0		1.70	2.13	2.66		E
4/0		1.90	2.38	2.97		E
336 kcmil		2.10	2.63	3.28		E
477 kcmil		2.40	3.00	3.75		E
556 kcmil		2.70	3.38	4.22		E
<b>Replace Sleeves In Existing Primary Cable</b>						
Up To #1 Copper		2.40	3.00	3.75		E
1/0 To 2/0 Copper		2.80	3.50	4.38		E
3/0 To 4/0 Copper		3.20	4.00	5.00		E
<b>Copperweld</b>						
Up To #6A Copperweld		2.40	3.00	3.75		E
#4A to 2A Copperweld		2.80	3.50	4.38		E
Up To #1 ACSR		3.80	4.75	5.94		E
1/0 To 2/0 ACSR		4.40	5.50	6.88		E
3/0 To 4/0 ACSR		5.20	6.50	8.13		E
336 ACSR		6.00	7.50	9.38		E
477 ACSR		7.00	8.75	10.94		E
556 ACSR		8.00	10.00	12.50		E
<b>Temporary Installations &amp; Cable Transfers</b>						
Up To #1		1.10	1.38	1.72		E
1/0		1.30	1.63	2.03		E
2/0		1.50	1.88	2.34		E
3/0		1.70	2.13	2.66		E
4/0		1.90	2.38	2.97		E
336 kcmil		2.10	2.63	3.28		E
477 kcmil		2.40	3.00	3.75		E
556 kcmil		2.70	3.38	4.22		E

Section 11 (A) - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Cross Arms &amp; Pins</b>						
Cross Arms & Pins		1.00	1.25	1.56		E
<b>Cutouts</b>						
Cutouts		0.80	1.00	1.25		E
<b>Arresters</b>						
Arresters		0.70	0.88	1.09		E
<b>Perch Guard</b>						
Perch Guard	X	0.25	0.30	0.40		E
<b>Primary Jumpers</b>						
Primary Jumpers		0.50	0.63	0.78		E
<b>Primary Dead Ends</b>						
Primary Dead Ends		0.60	0.75	0.94		E
<b>Neutral Dead Ends</b>						
Neutral Dead Ends		0.60	0.75	0.94		E
<b>Lightning Arrestors</b>						
Lightning Arrestors		0.70	0.88	1.09		E
<b>Complete Pole Grounding Systems</b>						
Complete Pole Grounding Systems		1.10	1.38	1.72		E
<b>Pole Grounding System Components</b>						
Each Additional Grounding Rod		0.60	0.75	0.94		E
Butt Wrapped Ground		0.80	1.00	1.25		E
Replace Grounding Wire		1.00	1.25	1.56		E
Extend Neutral To Primary Arm		0.50	0.63	0.78		E
<b>Disconnect Switches</b>						
Solid Blade or Bypass		1.60	2.00	2.50		E
3 Shot Enclosure		1.60	2.00	2.50		E
1 Phase Oil Circuit Enclosure		2.50	3.13	3.91		E
3 Phase Oil Circuit Enclosure		3.00	3.75	4.69		E
3 Phase GOAB Switch-Pole Top Mtd.		18.00	22.50	28.13		E
<b>Single Pole Mounted Transformers</b>						
10 KVA and Smaller		3.20	4.00	5.00		E
15 To 25 KVA		5.20	6.50	8.13		E
37 1/2 To 50 KVA		10.00	12.50	15.63		E
75 To 100 KVA		17.00	21.25	26.56		E
150 To 167 KVA		25.00	31.25	39.06		E
<b>Two Or More Pole Mounted Transformers</b>						
10 KVA and Smaller		2.20	2.75	3.44		E
15 To 25 KVA		3.60	4.50	5.63		E
37 1/2 To 50 KVA		7.00	8.75	10.94		E
75 To 100 KVA		12.00	15.00	18.75		E
150 To 167 KVA		18.00	22.50	28.13		E





Section 11 (A) - Outdoor Overhead and Underground Systems



Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Single Pad Mounted Transformers - Pole Type Transformers</b>						
75 To 100 KVA		15.00	18.75	23.44		E
150 To 167 KVA		22.00	27.50	34.38		E
200 To 250 KVA		27.00	33.75	42.19		E
333 To 500 KVA		43.00	53.75	67.19		E
<b>Two Or More Pad Mounted Transformers - Pole Type Transformers</b>						
75 To 100 KVA		13.00	16.25	20.31		E
150 To 167 KVA		16.00	20.00	25.00		E
200 To 250 KVA		19.00	23.75	29.69		E
333 To 500 KVA		40.00	50.00	62.50		E
<b>Brackets For Cluster Mounted Transformers</b>						
Brackets For Cluster Mounted Transformers		1.80	2.25	2.81		E
<b>Change Ratios on Dual Voltage Transformers</b>						
Before Mounting On Pole		2.00	2.50	3.13		E
After Mounting On Pole		4.00	5.00	6.25		E
<b>1/C Power Terminations on Transformers</b>						
<b>600 Volt Copper Cable</b>						
#4 To #1		0.25	0.31	0.39		E
1/0 To 2/0		0.30	0.38	0.47		E
3/0 To 4/0		0.40	0.50	0.63		E
250 kcmil		0.50	0.63	0.78		E
350 kcmil		0.60	0.75	0.94		E
500 kcmil		0.70	0.88	1.09		E
<b>Secondary Service - Two Copper Conductors (Reduce 10% for Aluminum)</b>						
#8		1.50	1.88	2.34		E
#6		1.70	2.13	2.66		E
#4		2.00	2.50	3.13		E
#2		2.30	2.88	3.59		E
#1		2.50	3.13	3.91		E
1/0		2.75	3.44	4.30		E
2/0		3.00	3.75	4.69		E
3/0		3.30	4.13	5.16		E
4/0		3.60	4.50	5.63		E
250		3.90	4.88	6.09		E
350		4.30	5.38	6.72		E
500		4.90	6.13	7.66		E
<b>Secondary Service - Three Copper Conductors (Reduce 10% for Aluminum)</b>						
#8		1.70	2.13	2.66		E
#6		2.00	2.50	3.13		E
#4		2.30	2.88	3.59		E
#2		2.60	3.25	4.06		E
#1		3.00	3.75	4.69		E
1/0		3.30	4.13	5.16		E
2/0		3.60	4.50	5.63		E
3/0		3.90	4.88	6.09		E
4/0		4.20	5.25	6.56		E
250		4.50	5.63	7.03		E
350		5.15	6.44	8.05		E
500		5.80	7.25	9.06		E
<b>Secondary Service - Four Copper Conductors (Reduce 10% for Aluminum)</b>						
#8		2.10	2.63	3.28		E
#6		2.50	3.13	3.91		E
#4		3.00	3.75	4.69		E
#2		3.50	4.38	5.47		E
#1		3.80	4.75	5.94		E
1/0		4.10	5.13	6.41		E
2/0		4.50	5.63	7.03		E
3/0		4.90	6.13	7.66		E
4/0		5.30	6.63	8.28		E
250		5.80	7.25	9.06		E
350		6.50	8.13	10.16		E
500		7.40	9.25	11.56		E

Section 11 (A) - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Secondary Service - Five Copper Conductors</b>						
<b>(Reduce 10% for Aluminum)</b>						
#8		3.00	3.75	4.69		E
#6		3.50	4.38	5.47		E
#4		4.00	5.00	6.25		E
#2		4.80	6.00	7.50		E
#1		5.20	6.50	8.13		E
1/0		5.70	7.13	8.91		E
2/0		6.20	7.75	9.69		E
3/0		6.70	8.38	10.47		E
4/0		7.20	9.00	11.25		E
250		7.80	9.75	12.19		E
350		8.90	11.13	13.91		E
500		10.00	12.50	15.63		E
<b>Secondary Copper Triplex Cable</b>						
<b>(Reduce 10% for Aluminum)</b>						
#4		1.50	1.88	2.34		E
#2		1.75	2.19	2.73		E
#1		2.00	2.50	3.13		E
1/0		3.00	3.75	4.69		E
4/0		4.00	5.00	6.25		E
<b>House Service</b>						
Residential Meter Socket Base						
		0.60	0.75	0.94		E
<b>House Service - 2/C Service Entrance Cable - 30FT Length</b>						
#8 To #4		1.30	1.63	2.03		E
#3 To #1		1.50	1.88	2.34		E
<b>House Service - 3/C Service Entrance Cable - 30FT Length</b>						
#8 To #4		1.50	1.88	2.34		E
#3 To #1		1.70	2.13	2.66		E
1/0 To 2/0		2.00	2.50	3.13		E
3/0 To 4/0		2.40	3.00	3.75		E
<b>House Service - 4/C Service Entrance Cable - 30FT Length</b>						
#8 To #4		1.70	2.13	2.66		E
#3 To #1		1.90	2.38	2.97		E
1/0 To 2/0		2.20	2.75	3.44		E
3/0 To 4/0		2.60	3.25	4.06		E
<b>House Service - Service Entrance Conduit Cap</b>						
3/4" To 1"		0.35	0.44	0.55		E
1 1/4" To 2"		0.40	0.50	0.63		E
<b>House Service - Threaded Steel Conduit &amp; Fasteners - 30Ft Length</b>						
3/4" & 1"		5.00	6.25	7.81		E
1 1/4" & 1 1/2"		5.50	6.88	8.59		E
2" & 2 1/2"		6.00	7.50	9.38		E
<b>House Service - EMT With Fasteners &amp; WP Couplings Up to 30 Ft Length</b>						
3/4" To 1"		4.50	5.63	7.03		E
1 1/4" To 1 1/2"		5.00	6.25	7.81		E
2" To 2 1/2"		5.50	6.88	8.59		E
<b>House Service - Three Single Conductors Pulled Into Conduit - Up To 30 Ft Length</b>						
#8 To #4		0.50	0.63	0.78		E
#3 To #1		0.60	0.75	0.94		E
1/0 To 2/0		0.70	0.88	1.09		E
3/0 To 4/0		1.00	1.25	1.56		E
<b>Apt &amp; Comm WP Svc - 3-Wire Solid Neutral Meter Center Modules w/ Main CB or Main Disc. Switch</b>						
400 Amp		20.00	25.00	31.25		E
600 Amp		22.00	27.50	34.38		E
800 Amp		25.00	31.25	39.06		E
1000 Amp		28.00	35.00	43.75		E
1200 Amp		32.00	40.00	50.00		E
1600 Amp		36.00	45.00	56.25		E
2000 Amp		40.00	50.00	62.50		E



Section 11 (A) - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Apt &amp; Comm WP Svc -</b>						
<b>Single Phase 125 Amp Meter Socket Modules</b>						
2 Meters		4.00	5.00	6.25		E
3 Meters		4.60	5.75	7.19		E
4 Meters		5.20	6.50	8.13		E
5 Meters		6.00	7.50	9.38		E
<b>Apt &amp; Comm WP Svc -</b>						
<b>Three Phase 125 Amp Meter Socket Modules</b>						
2 Meters		4.80	6.00	7.50		E
3 Meters		5.20	6.50	8.13		E
4 Meters		5.80	7.25	9.06		E
5 Meters		6.60	8.25	10.31		E
<b>Street Lighting Systems -</b>						
<b>Metal Poles With Internal Wiring - (Bolted metal bases with foundations &amp; anchor bolts by others)</b>						
20'		4.00	5.00	6.25		E
25'		4.50	5.63	7.03		E
30'		5.00	6.25	7.81		E
35'		5.50	6.88	8.59		E
40'		6.00	7.50	9.38		E
45'		7.00	8.75	10.94		E
50'		8.00	10.00	12.50		E
55'		10.00	12.50	15.63		E
60'		12.00	15.00	18.75		E
<b>Street Lighting Systems -</b>						
<b>Mast Arms Attached Before Pole Erection</b>						
8'		3.00	3.75	4.69		E
10'		3.50	4.38	5.47		E
12'		4.00	5.00	6.25		E
15'		5.00	6.25	7.81		E
20'		6.00	7.50	9.38		E
25'		7.00	8.75	10.94		E
30'		8.00	10.00	12.50		E
<b>Street Lighting Systems -</b>						
<b>Light Fixtures Attached Before Pole Erection</b>						
250 Watt		2.00	2.50	3.13		E
400 Watt		2.40	3.00	3.75		E
700 Watt		2.80	3.50	4.38		E
1000 Watt		3.20	4.00	5.00		E
<b>Street Lighting Systems - Upsweep Bracket On Pole</b>						
Upsweep Bracket On Pole		2.40	3.00	3.75		E
<b>Street Lighting Systems -</b>						
<b>Pull Cable In Pole &amp; Arm-Series Circuit</b>						
Pull Cable In Pole & Arm-Series Circuit		2.50	3.13	3.91		E
<b>Street Lighting Systems -</b>						
<b>Pole Mounted Photo Switch With Relay</b>						
Pole Mounted Photo Switch With Relay		1.20	1.50	1.88		E
<b>Street Lighting Systems -</b>						
<b>Metal Pole Transformer Base Housing</b>						
Metal Pole Transformer Base Housing		4.00	5.00	6.25		E
<b>Street Lighting Systems - Constant Current Transformers</b>						
5 KW		4.00	5.00	6.25		E
10 KW		5.00	6.25	7.81		E
15 KW		6.00	7.50	9.38		E
20 KW		7.50	9.38	11.72		E
25 KW		9.00	11.25	14.06		E
30 KW		11.00	13.75	17.19		E
<b>Street Lighting Systems - Street Lighting Transformers</b>						
Street Lighting Transformers		1.10	1.38	1.72		E
<b>Street Lighting Systems - Series Street Lighting Protectors</b>						
Series Street Lighting Protectors		1.50	1.88	2.34		E



Section 11 (A) - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Street Lighting Systems - Street Lighting Controllers</b>						
Street Lighting Controllers		3.00	3.75	4.69		E
<b>Street Lighting Systems - Capacitor Banks - Up To 50 KVR</b>						
3 Capacitors Per Bank		8.00	10.00	12.50		E
3 Capacitors Per Bank		12.00	15.00	18.75		E
3 Capacitors Per Bank		16.00	20.00	25.00		E
3 Capacitors Per Bank		22.00	27.50	34.38		E
<b>Street Lighting Systems - Spacer Cable Accessories</b>						
Spacers		0.75	0.94	1.17		E
Angle Brackets		2.40	3.00	3.75		E
Tangent Brackets		2.70	3.38	4.22		E
Dead End Brackets		2.40	3.00	3.75		E

Section 11 (A) - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Removal of Items</b>						
<b>Wood Poles - Cedar or Pine</b>						
25'		2.00	2.50	3.13		E
30'		2.20	2.75	3.44		E
35'		2.40	3.00	3.75		E
40'		2.70	3.38	4.22		E
45'		3.00	3.75	4.69		E
50'		3.50	4.38	5.47		E
55'		4.00	5.00	6.25		E
60'		5.00	6.25	7.81		E
65'		6.00	7.50	9.38		E
70'		7.00	8.75	10.94		E
75'		8.50	10.63	13.28		E
80'		10.00	12.50	15.63		E
85'		12.00	15.00	18.75		E
90'		14.00	17.50	21.88		E
95'		16.50	20.63	25.78		E
100'		19.00	23.75	29.69		E
<b>Cross Arms With Braces &amp; Pins</b>						
2 To 6 Ft		0.50	0.63	0.78		E
7 To 8 Ft		0.75	0.94	1.17		E
9 To 11 Ft		1.00	1.25	1.56		E
12 To 16 Ft		1.50	1.88	2.34		E
17 To 24 Ft		2.00	2.50	3.13		E
<b>Replace Steel Braces With Wood Braces</b>						
Replace Steel Braces With Wood Braces		0.80	1.00	1.25		E
<b>Conductor Attachments</b>						
Shank Pins		0.10	0.13	0.16		E
Pole Top Pins		0.20	0.25	0.31		E
Stud Bolts, Clevis, or Side Pins		0.20	0.25	0.31		E
20 KV Insulator		0.10	0.13	0.16		E
25 KV Post Insulator		0.20	0.25	0.31		E
3-Wire Section Rack		0.30	0.38	0.47		E
Riser Brackets		0.20	0.25	0.31		E
<b>Complete Guy With Anchor, Rod, Wire &amp; Guard</b>						
Complete Guy With Anchor, Rod, Wire & Guard		1.00	1.25	1.56		E
<b>Complete Overhead Guy</b>						
Complete Overhead Guy		1.00	1.25	1.56		E
<b>Transformer Platform</b>						
One Pole		1.70	2.13	2.66		E
Two Pole		3.80	4.75	5.94		E
Three Pole		6.70	8.38	10.47		E
Two Pole With Stub Pole		5.00	6.25	7.81		E
Railing On One Side		1.20	1.50	1.88		E
<b>Primary Attachment</b>						
Primary Clevis		0.25	0.31	0.39		E
Bells & D/E Clamp		0.30	0.38	0.47		E
Neural Suspension or D/E Clamp		0.20	0.25	0.31		E
<b>1/C Copper or Aluminum Cable - Bare or Insulated (Labor units are per span)</b>						
#4 to #1		0.50	0.63	0.78		E
1/0 To 2/0		0.70	0.88	1.09		E
3/0 To 4/0		0.90	1.13	1.41		E
250 To 400		1.20	1.50	1.88		E
500 To 750		1.50	1.88	2.34		E
800 To 1000		2.00	2.50	3.13		E
<b>3/C Triplex Secondary Cable</b>						
#1 and Smaller		0.80	1.00	1.25		E
1/0 To 2/0		1.20	1.50	1.88		E
3/0 To 4/0		1.50	1.88	2.34		E
250 To 350		2.00	2.50	3.13		E
<b>Copperweld Conductors</b>						
#8A To #6A		0.40	0.50	0.63		E
#4A To #2A		0.50	0.63	0.78		E
Larger Than #2A		0.60	0.75	0.94		E
<b>Re-sag Copperweld Conductors</b>						
#8A To #6A		0.70	0.88	1.09		E
#4A To #2A		0.80	1.00	1.25		E

Section 11 (A) - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>2/C Duplex Secondary Cable</b>						
Up To #1		0.60	0.75	0.94		E
1/0 To 2/0		0.70	0.88	1.09		E
<b>Aluminum Conductor Armor Rods</b>						
Aluminum Conductor Armor Rods		0.20	0.25	0.31		E
<b>1/C ACSR Cable - Bare or Insulated (Labor units are per span)</b>						
#1 and Smaller		1.10	1.38	1.72		E
1/0		1.20	1.50	1.88		E
2/0		1.30	1.63	2.03		E
3/0		1.50	1.88	2.34		E
4/0		1.70	2.13	2.66		E
336 kcmil		1.90	2.38	2.97		E
477 kcmil		2.10	2.63	3.28		E
556 kcmil		2.30	2.88	3.59		E
<b>Complete Pole Grounding Systems</b>						
Complete Pole Grounding Systems		0.40	0.50	0.63		E
<b>Disconnect Switches</b>						
Solid Blade or Bypass		0.50	0.63	0.78		E
3 Shot Enclosure		0.50	0.63	0.78		E
1 Phase Oil Circuit Enclosure		1.20	1.50	1.88		E
3 Phase Oil Circuit Enclosure		1.50	1.88	2.34		E
3 Phase GOAB Switch-Pole Top Mtd.		6.00	7.50	9.38		E
<b>Single Pole Mounted Transformers</b>						
10 KVA and Smaller		1.80	2.25	2.81		E
15 To 25 KVA		2.80	3.50	4.38		E
37 1/2 To 50 KVA		3.80	4.75	5.94		E
75 To 100 KVA		6.20	7.75	9.69		E
150 To 167 KVA		8.60	10.75	13.44		E
<b>Two Or More Pole Mounted Transformers</b>						
10 KVA and Smaller		1.40	1.75	2.19		E
15 To 25 KVA		2.20	2.75	3.44		E
37 1/2 To 50 KVA		3.00	3.75	4.69		E
75 To 100 KVA		5.00	6.25	7.81		E
150 To 167 KVA		8.00	10.00	12.50		E
<b>Single Pad Mounted Transformers - Pole Type Transformers</b>						
75 To 100 KVA		5.50	6.88	8.59		E
150 To 167 KVA		7.60	9.50	11.88		E
200 To 250 KVA		10.20	12.75	15.94		E
333 To 500 KVA		18.00	22.50	28.13		E
<b>Two Or More Pad Mounted Transformers - Pole Type Transformers</b>						
75 To 100 KVA		5.80	7.25	9.06		E
150 To 167 KVA		6.60	8.25	10.31		E
200 To 250 KVA		8.60	10.75	13.44		E
333 To 500 KVA		14.00	17.50	21.88		E
<b>Brackets For Cluster Mounted Transformers</b>						
Brackets For Cluster Mounted Transformers		0.80	1.00	1.25		E
<b>Secondary Service - Two Copper Conductors (Reduce 10% for Aluminum)</b>						
#8		0.90	1.13	1.41		E
#6		1.00	1.25	1.56		E
#4		1.10	1.38	1.72		E
#2		1.30	1.63	2.03		E
#1		1.50	1.88	2.34		E
1/0		1.65	2.06	2.58		E
2/0		1.80	2.25	2.81		E
3/0		2.00	2.50	3.13		E
4/0		2.20	2.75	3.44		E
250		2.40	3.00	3.75		E
350		2.60	3.25	4.06		E
500		3.00	3.75	4.69		E

Section 11 (A) - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Secondary Service - Three Copper Conductors</b>						
<b>(Reduce 10% for Aluminum)</b>						
#8		1.00	1.25	1.56		E
#6		1.10	1.38	1.72		E
#4		1.30	1.63	2.03		E
#2		1.50	1.88	2.34		E
#1		1.80	2.25	2.81		E
1/0		2.00	2.50	3.13		E
2/0		2.20	2.75	3.44		E
3/0		2.40	3.00	3.75		E
4/0		2.55	3.19	3.98		E
250		2.70	3.38	4.22		E
350		3.10	3.88	4.84		E
500		3.50	4.38	5.47		E
<b>Secondary Service - Four Copper Conductors</b>						
<b>(Reduce 10% for Aluminum)</b>						
#8		1.30	1.63	2.03		E
#6		1.50	1.88	2.34		E
#4		1.80	2.25	2.81		E
#2		2.10	2.63	3.28		E
#1		2.30	2.88	3.59		E
1/0		2.50	3.13	3.91		E
2/0		2.70	3.38	4.22		E
3/0		2.90	3.63	4.53		E
4/0		3.20	4.00	5.00		E
250		3.50	4.38	5.47		E
350		4.00	5.00	6.25		E
500		4.50	5.63	7.03		E
<b>Secondary Service - Five Copper Conductors</b>						
<b>(Reduce 10% for Aluminum)</b>						
#8		1.80	2.25	2.81		E
#6		2.10	2.63	3.28		E
#4		2.40	3.00	3.75		E
#2		2.80	3.50	4.38		E
#1		3.10	3.88	4.84		E
1/0		3.40	4.25	5.31		E
2/0		3.70	4.63	5.78		E
3/0		4.00	5.00	6.25		E
4/0		4.35	5.44	6.80		E
250		4.70	5.88	7.34		E
350		5.35	6.69	8.36		E
500		6.00	7.50	9.38		E
<b>Secondary Copper Triplex Cable</b>						
<b>(Reduce 10% for Aluminum)</b>						
#4		0.90	1.13	1.41		E
#2		1.00	1.25	1.56		E
#1		1.20	1.50	1.88		E
1/0		1.40	1.75	2.19		E
4/0		1.60	2.00	2.50		E
<b>Street Lighting Systems -</b>						
<b>Metal Poles With Internal Wiring - (Bolted metal bases</b>						
<b>with foundations &amp; anchor bolts by others)</b>						
20'		2.00	2.50	3.13		E
25'		2.25	2.81	3.52		E
30'		2.50	3.13	3.91		E
35'		2.75	3.44	4.30		E
40'		3.00	3.75	4.69		E
45'		3.50	4.38	5.47		E
50'		4.00	5.00	6.25		E
55'		5.00	6.25	7.81		E
60'		6.00	7.50	9.38		E
<b>Street Lighting Systems -</b>						
<b>Mast Arms Attached Before Pole Erection</b>						
8'		1.50	1.88	2.34		E
10'		1.70	2.13	2.66		E
12'		2.00	2.50	3.13		E
15'		2.50	3.13	3.91		E
20'		3.00	3.75	4.69		E
25'		3.50	4.38	5.47		E
30'		4.00	5.00	6.25		E

Section 11 (A) - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Street Lighting Systems -</b>						
<b>Light Fixtures Attached Before Pole Erection</b>						
250 Watt		1.00	1.25	1.56		E
400 Watt		1.20	1.50	1.88		E
700 Watt		1.40	1.75	2.19		E
1000 Watt		1.60	2.00	2.50		E
<b>Street Lighting Systems - Upsweep Bracket On Pole</b>						
Upsweep Bracket On Pole		1.20	1.50	1.88		E
<b>Street Lighting Systems -</b>						
<b>Pull Cable In Pole &amp; Arm-Series Circuit</b>						
Pull Cable In Pole & Arm-Series Circuit		1.25	1.56	1.95		E
<b>Street Lighting Systems -</b>						
<b>Pole Mounted Photo Switch With Relay</b>						
Pole Mounted Photo Switch With Relay		0.60	0.75	0.94		E
<b>Street Lighting Systems -</b>						
<b>Metal Pole Transformer Base Housing</b>						
Metal Pole Transformer Base Housing		2.00	2.50	3.13		E
<b>Street Lighting Systems - Constant Current Transformers</b>						
5 KW		1.60	2.00	2.50		E
10 KW		2.00	2.50	3.13		E
15 KW		2.40	3.00	3.75		E
20 KW		3.00	3.75	4.69		E
25 KW		3.60	4.50	5.63		E
30 KW		4.40	5.50	6.88		E
<b>Street Lighting Systems - Street Lighting Transformers</b>						
Street Lighting Transformers		0.50	0.63	0.78		E
<b>Street Lighting Systems - Series Street Lighting Protectors</b>						
Series Street Lighting Protectors		0.60	0.75	0.94		E
<b>Street Lighting Systems - Street Lighting Controllers</b>						
Street Lighting Controllers		1.20	1.50	1.88		E
<b>Street Lighting Systems - Capacitor Banks - Up To 50 KVR</b>						
3 Capacitors Per Bank		3.20	4.00	5.00		E
3 Capacitors Per Bank		4.80	6.00	7.50		E
3 Capacitors Per Bank		6.40	8.00	10.00		E
3 Capacitors Per Bank		8.80	11.00	13.75		E
<b>Street Lighting Systems - Spacer Cable Accessories</b>						
Spacers		0.30	0.38	0.47		E
Angle Brackets		1.00	1.25	1.56		E
Tangent Brackets		1.10	1.38	1.72		E
Dead End Brackets		1.00	1.25	1.56		E
<b>Remove Trees (Excluding Roots)</b>						
4" to 8" Dia		2.00	2.50	3.13		E
9" To 12" Dia		3.00	3.75	4.69		E
13" To 18" Dia		4.00	5.00	6.25		E
19" To 24" Dia		6.00	7.50	9.38		E
25" To 30" Dia		10.00	12.50	15.63		E
31" To 36" Dia		16.00	20.00	25.00		E
37" To 42" Dia		24.00	30.00	37.50		E
43" To 48" Dia		36.00	45.00	56.25		E
<b>Remove Larger Tree Limb - No Obstacles</b>						
Remove Larger Tree Limb - No Obstacles		2.00	2.50	3.13		E
<b>Remove Large Tree Limb Over Hot Wires or Over Other Obstacles</b>						
Remove Large Tree Limb		4.00	5.00	6.25		E
<b>Trim Tree For Lighting Fixture Installation</b>						
Trim Tree For Lighting Fixture Installation		2.00	2.50	3.13		E



Section 11 (A) - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Transfer of Items</b>						
<b>Wood Poles - Cedar or Pine</b>						
25'		5.00	6.25	7.81		E
30'		5.60	7.00	8.75		E
35'		6.20	7.75	9.69		E
40'		6.80	8.50	10.63		E
45'		7.60	9.50	11.88		E
50'		8.70	10.88	13.59		E
55'		10.00	12.50	15.63		E
60'		12.50	15.63	19.53		E
65'		15.00	18.75	23.44		E
70'		17.50	21.88	27.34		E
75'		21.20	26.50	33.13		E
80'		25.00	31.25	39.06		E
85'		30.00	37.50	46.88		E
90'		35.00	43.75	54.69		E
95'		41.00	51.25	64.06		E
100'		48.00	60.00	75.00		E
<b>Cross Arms With Braces &amp; Pins</b>						
2 To 6 Ft		1.50	1.88	2.34		E
7 To 8 Ft		2.25	2.81	3.52		E
9 To 11 Ft		3.00	3.75	4.69		E
12 To 16 Ft		4.50	5.63	7.03		E
17 To 24 Ft		6.00	7.50	9.38		E
<b>Conductor Attachments</b>						
Shank Pins		0.20	0.25	0.31		E
Pole Top Pins		0.60	0.75	0.94		E
Stud Bolts, Clevis, or Side Pins		0.60	0.75	0.94		E
20 KV Insulator		0.20	0.25	0.31		E
25 KV Post Insulator		0.60	0.75	0.94		E
3-Wire Section Rack		0.90	1.13	1.41		E
Riser Brackets		0.60	0.75	0.94		E
<b>Transfer One End Of Overhead Guy</b>						
Transfer One End Of Overhead Guy		2.20	2.75	3.44		E
<b>Transformer Platform</b>						
One Pole		7.30	9.13	11.41		E
Two Pole		13.80	17.25	21.56		E
Three Pole		24.70	30.88	38.59		E
Two Pole With Stub Pole		21.00	26.25	32.81		E
Railing On One Side		3.40	4.25	5.31		E
<b>Primary Attachment</b>						
Primary Clevis		0.75	0.94	1.17		E
Bells & D/E Clamp		1.00	1.25	1.56		E
Neural Suspension or D/E Clamp		0.60	0.75	0.94		E
<b>1/C Copper or Aluminum Cable - Bare or Insulated (Labor units are per span)</b>						
#4 to #1		1.00	1.25	1.56		E
1/0 To 2/0		1.40	1.75	2.19		E
3/0 To 4/0		1.80	2.25	2.81		E
250 To 400		2.20	2.75	3.44		E
500 To 750		3.70	4.63	5.78		E
800 To 1000		5.00	6.25	7.81		E
<b>3/C Triplex Secondary Cable</b>						
#1 and Smaller		1.70	2.13	2.66		E
1/0 To 2/0		2.20	2.75	3.44		E
3/0 To 4/0		3.70	4.63	5.78		E
250 To 350		5.00	6.25	7.81		E
<b>Copperweld Conductors</b>						
#8A To #6A		0.75	0.94	1.17		E
#4A To #2A		1.00	1.25	1.56		E
Larger Than #2A		1.20	1.50	1.88		E
<b>Re-sag Copperweld Conductors</b>						
#8A To #6A		1.40	1.75	2.19		E
#4A To #2A		1.70	2.13	2.66		E
<b>2/C Duplex Secondary Cable</b>						
Up To #1		1.10	1.38	1.72		E
1/0 To 2/0		1.20	1.50	1.88		E

Section 11 (A) - Outdoor Overhead and Underground Systems







Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Aluminum Conductor Armor Rods</b>						
Aluminum Conductor Armor Rods		0.60	0.75	0.94		E
<b>1/C ACSR Cable - Bare or Insulated (Labor units are per span)</b>						
#1 and Smaller		1.70	2.13	2.66		E
1/0		1.90	2.38	2.97		E
2/0		2.10	2.63	3.28		E
3/0		2.40	3.00	3.75		E
4/0		2.70	3.38	4.22		E
336 kcmil		3.00	3.75	4.69		E
477 kcmil		3.30	4.13	5.16		E
556 kcmil		3.60	4.50	5.63		E
<b>Disconnect Switches</b>						
Solid Blade or Bypass		1.80	2.25	2.81		E
3 Shot Enclosure		1.80	2.25	2.81		E
1 Phase Oil Circuit Enclosure		3.20	4.00	5.00		E
3 Phase Oil Circuit Enclosure		4.10	5.13	6.41		E
3 Phase GOAB Switch-Pole Top Mtd.		22.00	27.50	34.38		E
<b>Single Pole Mounted Transformers</b>						
10 KVA and Smaller		4.40	5.50	6.88		E
15 To 25 KVA		7.20	9.00	11.25		E
37 1/2 To 50 KVA		12.40	15.50	19.38		E
75 To 100 KVA		21.00	26.25	32.81		E
150 To 167 KVA		29.00	36.25	45.31		E
<b>Two Or More Pole Mounted Transformers</b>						
10 KVA and Smaller		3.10	3.88	4.84		E
15 To 25 KVA		5.00	6.25	7.81		E
37 1/2 To 50 KVA		8.50	10.63	13.28		E
75 To 100 KVA		14.00	17.50	21.88		E
150 To 167 KVA		22.00	27.50	34.38		E
<b>Single Pad Mounted Transformers - Pole Type Transformers</b>						
75 To 100 KVA		18.00	22.50	28.13		E
150 To 167 KVA		25.00	31.25	39.06		E
200 To 250 KVA		32.00	40.00	50.00		E
333 To 500 KVA		40.00	50.00	62.50		E
<b>Two Or More Pad Mounted Transformers - Pole Type Transformers</b>						
75 To 100 KVA		16.00	20.00	25.00		E
150 To 167 KVA		28.00	35.00	43.75		E
200 To 250 KVA		31.00	38.75	48.44		E
333 To 500 KVA		35.00	43.75	54.69		E
<b>Brackets For Cluster Mounted Transformers</b>						
Brackets For Cluster Mounted Transformers		2.50	3.13	3.91		E
<b>Secondary Service - Two Copper Conductors (Reduce 10% for Aluminum)</b>						
#8		1.40	1.75	2.19		E
#6		1.60	2.00	2.50		E
#4		1.90	2.38	2.97		E
#2		2.20	2.75	3.44		E
#1		2.40	3.00	3.75		E
1/0		2.60	3.25	4.06		E
2/0		2.85	3.56	4.45		E
3/0		3.10	3.88	4.84		E
4/0		3.40	4.25	5.31		E
250		3.70	4.63	5.78		E
350		4.10	5.13	6.41		E
500		4.60	5.75	7.19		E
<b>Secondary Service - Three Copper Conductors (Reduce 10% for Aluminum)</b>						
#8		1.60	2.00	2.50		E
#6		1.90	2.38	2.97		E
#4		2.20	2.75	3.44		E
#2		2.50	3.13	3.91		E
#1		2.85	3.56	4.45		E
1/0		3.10	3.88	4.84		E
2/0		3.40	4.25	5.31		E
3/0		3.70	4.63	5.78		E
4/0		4.00	5.00	6.25		E
250		4.30	5.38	6.72		E
350		4.90	6.13	7.66		E
500		5.50	6.88	8.59		E

Section 11 (A) - Outdoor Overhead and Underground Systems













Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Secondary Service - Four Copper Conductors</b>						
<b>(Reduce 10% for Aluminum)</b>						
#8		2.00	2.50	3.13		E
#6		2.40	3.00	3.75		E
#4		2.85	3.56	4.45		E
#2		3.30	4.13	5.16		E
#1		3.60	4.50	5.63		E
1/0		3.90	4.88	6.09		E
2/0		4.30	5.38	6.72		E
3/0		4.60	5.75	7.19		E
4/0		5.00	6.25	7.81		E
250		5.50	6.88	8.59		E
350		6.20	7.75	9.69		E
500		7.00	8.75	10.94		E
<b>Secondary Service - Five Copper Conductors</b>						
<b>(Reduce 10% for Aluminum)</b>						
#8		2.85	3.56	4.45		E
#6		3.30	4.13	5.16		E
#4		3.80	4.75	5.94		E
#2		4.50	5.63	7.03		E
#1		4.90	6.13	7.66		E
1/0		5.40	6.75	8.44		E
2/0		5.90	7.38	9.22		E
3/0		6.40	8.00	10.00		E
4/0		6.90	8.63	10.78		E
250		7.50	9.38	11.72		E
350		8.50	10.63	13.28		E
500		9.50	11.88	14.84		E
<b>Secondary Copper Triplex Cable</b>						
<b>(Reduce 10% for Aluminum)</b>						
#4		1.40	1.75	2.19		E
#2		1.65	2.06	2.58		E
#1		1.90	2.38	2.97		E
1/0		2.00	2.50	3.13		E
4/0		2.20	2.75	3.44		E
<b>Street Lighting Systems -</b>						
<b>Metal Poles With Internal Wiring - (Bolted metal bases</b>						
<b>with foundations &amp; anchor bolts by others)</b>						
20'		5.00	6.25	7.81		E
25'		5.60	7.00	8.75		E
30'		6.25	7.81	9.77		E
35'		6.80	8.50	10.63		E
40'		7.50	9.38	11.72		E
45'		8.75	10.94	13.67		E
50'		10.00	12.50	15.63		E
55'		12.50	15.63	19.53		E
60'		15.00	18.75	23.44		E
<b>Street Lighting Systems -</b>						
<b>Mast Arms Attached Before Pole Erection</b>						
8'		3.75	4.69	5.86		E
10'		4.35	5.44	6.80		E
12'		5.00	6.25	7.81		E
15'		6.25	7.81	9.77		E
20'		7.50	9.38	11.72		E
25'		8.75	10.94	13.67		E
30'		10.00	12.50	15.63		E
<b>Street Lighting Systems -</b>						
<b>Light Fixtures Attached Before Pole Erection</b>						
250 Watt		2.50	3.13	3.91		E
400 Watt		3.00	3.75	4.69		E
700 Watt		3.50	4.38	5.47		E
1000 Watt		4.00	5.00	6.25		E
<b>Street Lighting Systems - Upsweep Bracket On Pole</b>						
Upsweep Bracket On Pole		3.00	3.75	4.69		E
<b>Street Lighting Systems -</b>						
<b>Pull Cable In Pole &amp; Arm-Series Circuit</b>						
Pull Cable In Pole & Arm-Series Circuit		3.10	3.88	4.84		E
<b>Street Lighting Systems -</b>						
<b>Pole Mounted Photo Switch With Relay</b>						
Pole Mounted Photo Switch With Relay		1.50	1.88	2.34		E
<b>Street Lighting Systems -</b>						
<b>Metal Pole Transformer Base Housing</b>						
Metal Pole Transformer Base Housing		5.00	6.25	7.81		E



Section 11 (A) - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Maintenance and Protection of Traffic</b>						
Labor is for set up and breakdown - Labor for flagmen has to be addressed as actual time						
 Illuminated Arrow Sign	X	3.00	3.75	4.05		E
 Attenuator Barrels	X	2.00	2.50	2.70		E
Attenuator Truck		See section on utility trucks				
 Barricade Lights	X	1.00	1.25	1.35		E
Barricade Horse	X	1.00	1.25	1.35		E
 Roll-Up Signs						
Roll up work in progress alert signs - Road closed, detour, lane closed, shoulder closed, workmen ahead	X	2.00	2.50	2.70		E
Flag Man Flag		Use labor hours planned				
Flag Man Traffic Paddle		Use labor hours planned				
 Light Towers	X	4.00	5.00	5.40		E
Portable Traffic Light	X	4.00	5.00	5.40		E
Electric Message Boards	X	4.00	5.00	5.40		E
 Sign Stands	X	3.00	3.75	4.05		E
Folding Sign Stands						

Section 11 (A) - Outdoor Overhead and Underground Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Watershed Protection</b>						
 <b>Bio-Degradable Erosion Control Mat</b> 4'x112' roll (36lbs)	X	0.85	1.06	1.15		E
 <b>Coir Wattles</b> 6"x15' (10 lbs)	X	0.30	0.38	0.41		E
 <b>De-Watering Filter Bags</b> 6'x6' (set-up & removal)	X	0.75	0.94	1.01		E
 <b>De-Watering Tubes</b> 15'x50' Lengths (set-up & removal)	X	5.00	6.25	6.75		E
 <b>De-Watering Filter Sock</b> 1'x5'	X	0.50	0.63	0.68		E
 <b>Erosion Control Blankets</b> 8'x112' roll (150 lbs)	X	1.10	1.38	1.49		E
 <b>Filter Bags</b> 12'x50' (set-up & remove)	X	6.00	7.50	8.10		E
 <b>Sand Bags</b>	X	1.00	1.25	1.35		E
 <b>Silt Check</b> 15' lengths (38 lbs)	X	0.60	0.75	0.81		E
 <b>Silt Fence</b> (3'x100')	X	1.50	1.88	2.03		E
 <b>Straw Wattles</b> 10' lengths	X	0.30	0.38	0.41		E
 <b>Tree Trunk Protection</b>	X	0.55	0.69	0.74		E

# SECTION 12

## EQUIPMENT INSTALLATION AND CONNECTIONS

### General Information

The labor units in this section include installing and terminating power equipment, variable frequency drives, DC drives, motors, fixed and adjustable motor bases and similar equipment.

### Scope of These Labor Units

The Introduction section includes details on the scope of labor units across the manual. Some items included are:

- Material unloading, jobsite storage and delivery to the installation area
- Drawing and specification study
- Layout, measuring and marking the installation location
- Tool acquisition and return to storage
- Material assembly and installation
- Pulling cable
- Clean-up of electrical contractor furnished excess material
- Normal non-productive labor

### Work Operations Not Included In These Labor Units

- Field supervision
- Hoisting above three floors
- Grounding, bonding, welding or painting
- Testing of any type
- Grouting or anchoring
- Cutting holes or openings in walls, floors, cabinets, or panels
- Heavy equipment (crane) operator's time

### Labor Adjustments for Non-Typical Conditions

See the Introduction section for details.

### Application Instructions

- Labor units under the "Normal" column are for locations with good access, no obstructions and large quantities of equipment. Labor units under the "Difficult" column are for locations with less than good access, a few minor obstructions and large quantities of equipment. Labor units under the "Very Difficult" column are for locations with poor access or require the use of a ladder, numerous obstructions, limited space or small quantities of equipment.
- All the labor units in this section are based on using the most efficient tools and equipment available. When the anticipated jobsite conditions will prevent the optimum use of tools and equipment, an appropriate additional labor allowance in proportion to the anticipated difficulties is necessary.
- Labor units in this manual are for new work only and for a complete electrical installation. For remodeling or change order situations these labor units need to be substantially increased.










## Section 12 - Equipment Installation and Connections Table of Contents

Motor Handling - 280 - 550 Volt D.C.	12-5
Motor Handling - 0 - 600 Volt A.C.	12-5
1800 RPM Motor Mounting	12-5
Adjustable Base Plates for Motor Mounting	12-5
Motor Mounting Base Conversion Brackets	12-5
Motor Leveling and Rotation Test - 0 to 600 Volt A.C.	12-6
Motor Leveling and Rotation Test - 2300 to 5000 Volts	12-6
<b>Steel Flex</b>	12-6
2 Conductor + Ground - 600V Phase Wire Size	12-6
3 Conductor + Ground - 600V Phase Wire Size	12-6
3 conductor + Ground - 5KV Phase Wire Size	12-6
<b>Aluminum Flex</b>	12-7
2 Conductor + Ground - 600V Phase Wire Size	12-7
3 Conductor + Ground - 600V Phase Wire Size	12-7
3 conductor + Ground - 5KV Phase Wire Size	12-7
<b>Sealtite Flex</b>	12-7
2 Conductor + Ground - 600V Phase Wire Size	12-7
3 Conductor + Ground - 600V Phase Wire Size	12-8
3 conductor + Ground - 5KV Phase Wire Size	12-8
Standard Wire Conductor Terminations	12-8
Motor Stub Splice Insulators	12-8






## Section 12 - Equipment Installation and Connections

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Motor Handling - 280 - 550 Volt D.C.</b>						
<b>(Unload, Inspect, Install - Labor Only)</b>						
 Up to 5 H.P.		7.00	9.00	10.00		E
7 1/2 H.P.		7.50	9.50	10.50		E
10 H.P.		8.00	10.00	11.00		E
15 H.P.		10.00	12.00	13.50		E
20 H.P.		10.50	12.50	14.00		E
25 H.P.		11.00	12.50	14.50		E
30 H.P.		12.00	13.00	14.50		E
40 H.P.		13.00	15.50	18.50		E
50 H.P.		13.50	16.00	19.00		E
60 H.P.		16.00	19.00	22.50		E
75 H.P.		19.00	23.00	27.50		E
100 H.P.		23.00	29.00	35.00		E
125 H.P.		27.50	34.00	41.00		E
150 H.P.		30.00	37.00	44.00		E
200 H.P.		34.00	41.50	49.00		E
250 - 400 H.P.		38.00	47.00	56.00		E
500 - 600 H.P.		45.00	55.00	65.00		E
<b>Motor Handling - 0 - 600 Volt A.C.</b>						
<b>(Unload, Inspect, Install - Labor Only)</b>						
 Up to 5 H.P.		5.00	6.00	7.00		E
7 1/2 H.P.		5.50	6.50	7.50		E
10 H.P.		6.00	7.00	8.00		E
15 H.P.		6.50	8.00	9.00		E
20 H.P.		7.00	8.50	9.50		E
25 H.P.		8.00	9.50	11.00		E
30 H.P.		8.50	10.00	12.50		E
40 H.P.		10.00	12.00	14.00		E
50 H.P.		10.50	12.50	14.50		E
60 H.P.		13.00	15.50	18.00		E
75 H.P.		14.00	17.00	20.00		E
100 H.P.		18.00	22.50	27.00		E
125 H.P.		21.00	26.00	31.00		E
150 H.P.		24.00	30.00	35.00		E
200 H.P.		27.00	33.00	39.00		E
250 to 400 H.P.		36.00	45.00	54.00		E
500 to 750 H.P.		40.00	50.00	60.00		E
800 to 1000 H.P.		44.00	55.00	66.00		E
1200 to 1500 H.P.		48.00	60.00	72.00		E
<b>1800 RPM Motor Mounting</b>						
 Up to 1/2 H.P.		2.00	2.50	3.13		E
3/4 H.P.		2.00	2.50	3.13		E
1 H.P.		2.00	2.50	3.13		E
1 1/2 H.P.		2.00	2.50	3.13		E
2 H.P.		2.00	2.50	3.13		E
3 H.P.		3.50	4.38	5.47		E
5 H.P.		3.50	4.38	5.47		E
7 1/2 H.P.		3.50	4.38	5.47		E
10 H.P.		5.00	6.25	7.81		E
15 H.P.		5.00	6.25	7.81		E
20 H.P.		5.00	6.25	7.81		E
25 H.P.		8.00	10.00	12.50		E
30 H.P.		10.00	12.50	15.63		E
40 H.P.		12.00	15.00	18.75		E
50 H.P.		14.00	17.50	21.88		E
75 H.P.		16.00	20.00	25.00		E
100 H.P.		18.00	22.50	28.13		E
125 H.P.		20.00	25.00	31.25		E
150 H.P.		24.00	30.00	37.50		E
200 H.P.		34.00	42.50	53.13		E
<b>Adjustable Base Plates for Motor Mounting</b>						
 8" x 10" 5 lbs		2.00	2.50	3.00		E
10" x 12" 10 lbs		2.25	2.80	3.35		E
12" x 15" 15 lbs		2.50	3.10	3.75		E
16" x 20" 20 lbs		2.75	3.40	4.10		E
18" x 22" 30 lbs		3.00	3.75	4.50		E
20" x 25" 45 lbs		3.50	4.35	5.25		E
22" x 28" 60 lbs		4.00	5.00	6.00		E
24" x 30" 75 lbs		4.50	5.60	6.75		E
30" x 32" 90 lbs		5.00	6.25	7.50		E
32" x 34" 110 lbs		5.50	6.85	8.25		E
34" x 36" 130 lbs		6.00	7.50	9.00		E
<b>Motor Mounting Base Conversion Brackets</b>						
 8" long 4 lb per pair		1.00	1.25	1.50		E
10" Long 6 lb per pair		1.10	1.35	1.65		E
12" Long 10 lb per pair		1.20	1.50	1.80		E
14" Long 15 lb per pair		1.35	1.65	2.00		E
16" Long 20 lb per pair		1.50	1.85	2.25		E
18" Long 26 lb per pair		1.75	2.15	2.60		E
20" Long 40 lb per pair		2.00	2.50	3.00		E
22" long 44 lbs per pair		2.25	2.80	3.35		E
24" Long 50 lb per pair		2.50	3.10	3.75		E

## Section 12 - Equipment Installation and Connections





Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Motor Leveling and Rotation Test - 0 to 600 Volt A.C.</b>						
Up to 5 H.P.		1.50	2.00	3.00		E
7 1/2 H.P.		1.50	2.00	3.00		E
10 H.P.		1.50	2.00	3.00		E
15 H.P.		2.00	2.50	3.00		E
20 H.P.		2.00	2.50	3.00		E
25 H.P.		2.50	3.00	3.50		E
30 H.P.		2.50	3.00	3.50		E
40 H.P.		2.50	3.00	3.50		E
50 H.P.		2.50	3.00	3.50		E
60 H.P.		3.00	3.50	4.00		E
75 H.P.		3.00	3.50	4.00		E
100 H.P.		3.00	3.50	4.00		E
125 H.P.		3.25	3.75	4.25		E
150 H.P.		3.50	4.00	5.00		E
200 H.P.		4.00	4.50	5.00		E
<b>Motor Leveling and Rotation Test - 2300 to 5000 Volts</b>						
200 to 250 H.P.		3.00	4.00	4.50		E
250 to 400 H.P.		3.00	4.00	4.50		E
500 to 600 H.P.		3.00	4.00	5.00		E
750 to 1000 H.P.		4.00	5.00	6.00		E
1100 to 1200 H.P.		5.00	6.00	7.00		E
<b>Steel Flex</b>						
<i>Whips are based on 3ft length of flex plus labor for terminating</i>						
<b>2 Conductor + Ground - 600V</b>						
<b>Phase Wire Size</b>						
#14		1.17	1.46	1.75		E
#12		1.23	1.54	1.84		E
#10		1.33	1.66	1.99		E
#8		1.60	2.00	2.40		E
#6		1.74	2.17	2.61		E
#4		2.07	2.58	3.10		E
#3		2.33	2.91	3.49		E
#2		2.28	2.85	3.42		E
#1		2.45	3.07	3.68		E
<b>3 Conductor + Ground - 600V</b>						
<b>Phase Wire Size</b>						
#14		1.34	1.67	2.01		E
#12		1.44	1.80	2.16		E
#10		1.54	1.93	2.31		E
#8		1.80	2.25	2.70		E
#6		1.90	2.38	2.86		E
#4		2.41	3.01	3.62		E
#3		2.76	3.46	4.15		E
#2		2.62	3.28	3.93		E
#1		2.90	3.63	4.36		E
1/0		3.32	4.15	4.98		E
2/0		3.88	4.85	5.82		E
3/0		4.16	5.20	6.24		E
4/0		4.59	5.73	6.88		E
250		5.33	6.66	8.00		E
300		5.47	6.84	8.21		E
350		5.76	7.19	8.63		E
400		6.22	7.77	9.33		E
500		6.36	7.95	9.54		E
600		6.90	8.62	10.35		E
750		7.19	8.99	10.79		E
<b>3 conductor + Ground - 5KV</b>						
<b>Phase Wire Size</b>						
#14		1.81	2.26	2.71		E
#12		1.94	2.43	2.92		E
#10		2.09	2.62	3.14		E
#8		2.44	3.05	3.66		E
#6		2.60	3.25	3.90		E
#4		3.27	4.09	4.91		E
#3		3.73	4.66	5.59		E
#2		3.54	4.43	5.31		E
#1		3.96	4.96	5.95		E
1/0		4.45	5.57	6.68		E
2/0		5.15	6.44	7.73		E
3/0		5.58	6.97	8.36		E
4/0		6.21	7.76	9.32		E
250		7.13	8.92	10.70		E
300		7.35	9.18	11.02		E
350		7.77	9.71	11.65		E
400		8.27	10.34	12.40		E
500		8.48	10.60	12.72		E



Section 12 - Equipment Installation and Connections

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Aluminum Flex</b>						
<i>Whips are based on 3ft length of flex plus labor for terminating</i>						
<b>2 Conductor + Ground - 600V</b>						
<b>Phase Wire Size</b>						
#14		1.16	1.45	1.74		E
#12		1.22	1.53	1.83		E
#10		1.32	1.65	1.97		E
#8		1.59	1.98	2.38		E
#6		1.72	2.15	2.58		E
#4		2.02	2.53	3.04		E
#3		2.29	2.87	3.44		E
#2		2.25	2.81	3.37		E
#1		2.42	3.03	3.63		E
<b>3 Conductor + Ground - 600V</b>						
<b>Phase Wire Size</b>						
#14		1.33	1.66	1.99		E
#12		1.43	1.78	2.14		E
#10		1.53	1.91	2.29		E
#8		1.78	2.23	2.67		E
#6		1.89	2.36	2.83		E
#4		2.37	2.96	3.55		E
#3		2.73	3.41	4.10		E
#2		2.59	3.24	3.88		E
#1		2.87	3.59	4.31		E
1/0		3.27	4.09	4.91		E
2/0		3.82	4.77	5.72		E
3/0		4.10	5.12	6.15		E
4/0		4.52	5.65	6.78		E
250		5.25	6.57	7.88		E
300		5.39	6.74	8.09		E
350		5.68	7.10	8.51		E
400		6.12	7.65	9.18		E
500		6.26	7.83	9.40		E
600		6.84	8.56	10.27		E
750		7.07	8.83	10.60		E
<b>3 conductor + Ground - 5KV</b>						
<b>Phase Wire Size</b>						
#14		1.79	2.24	2.69		E
#12		1.93	2.41	2.89		E
#10		2.08	2.60	3.11		E
#8		2.42	3.03	3.63		E
#6		2.58	3.22	3.87		E
#4		3.23	4.03	4.84		E
#3		3.70	4.62	5.54		E
#2		3.51	4.39	5.26		E
#1		3.93	4.92	5.90		E
1/0		4.40	5.51	6.61		E
2/0		5.09	6.36	7.63		E
3/0		5.51	6.89	8.27		E
4/0		6.15	7.69	9.22		E
250		7.05	8.82	10.58		E
300		7.27	9.08	10.90		E
350		7.69	9.61	11.54		E
400		8.17	10.22	12.26		E
500		8.38	10.48	12.58		E
<b>Sealtite Flex</b>						
<i>Whips are based on 3ft length of flex plus labor for terminating</i>						
<b>2 Conductor + Ground - 600V</b>						
<b>Phase Wire Size</b>						
#14		1.24	1.55	1.86		E
#12		1.30	1.63	1.96		E
#10		1.40	1.75	2.10		E
#8		1.70	2.13	2.55		E
#6		1.84	2.30	2.76		E
#4		2.22	2.78	3.34		E
#3		2.58	3.22	3.86		E
#2		2.51	3.14	3.77		E
#1		2.69	3.36	4.03		E

Section 12 - Equipment Installation and Connections

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
 <b>3 Conductor + Ground - 600V</b> <b>Phase Wire Size</b>						
#14		1.41	1.76	2.11		E
#12		1.51	1.89	2.27		E
#10		1.61	2.01	2.42		E
#8		1.90	2.37	2.85		E
#6		2.00	2.50	3.00		E
#4		2.57	3.21	3.85		E
#3		3.01	3.77	4.52		E
#2		2.85	3.57	4.28		E
#1		3.14	3.92	4.71		E
1/0		3.58	4.47	5.37		E
2/0		4.16	5.20	6.24		E
3/0		4.44	5.55	6.66		E
4/0		4.87	6.08	7.30		E
250		5.52	6.90	8.28		E
300		5.66	7.07	8.49		E
350		5.94	7.43	8.91		E
400		6.45	8.06	9.68		E
500		6.59	8.24	9.89		E
600		7.47	9.34	11.21		E
750		7.50	9.38	11.26		E
 <b>3 conductor + Ground - 5KV</b> <b>Phase Wire Size</b>						
#14		1.88	2.35	2.81		E
#12		2.01	2.52	3.02		E
#10		2.16	2.70	3.24		E
#8		2.54	3.17	3.81		E
#6		2.70	3.37	4.04		E
#4		3.43	4.28	5.14		E
#3		3.98	4.97	5.97		E
#2		3.77	4.72	5.66		E
#1		4.20	5.25	6.30		E
1/0		4.71	5.89	7.06		E
2/0		5.43	6.79	8.15		E
3/0		5.86	7.32	8.78		E
4/0		6.49	8.11	9.74		E
250		7.32	9.15	10.98		E
300		7.53	9.42	11.30		E
350		7.96	9.95	11.93		E
400		8.50	10.63	12.75		E
500		8.71	10.89	13.07		E
 <b>Standard Wire Conductor Terminations</b>						
#12		0.15	0.19	0.23		E
#10		0.16	0.20	0.24		E
#8		0.18	0.23	0.27		E
#6		0.20	0.25	0.30		E
#4		0.22	0.27	0.33		E
#3		0.24	0.30	0.36		E
#2		0.27	0.33	0.40		E
#1		0.30	0.37	0.45		E
1/0		0.33	0.41	0.50		E
2/0		0.36	0.45	0.55		E
3/0		0.40	0.50	0.60		E
4/0		0.45	0.56	0.67		E
250 kcmil		0.50	0.62	0.75		E
300 kcmil		0.55	0.68	0.82		E
350 kcmil		0.60	0.75	0.90		E
400 kcmil		0.65	0.81	0.97		E
500 kcmil		0.70	0.87	1.05		E
600 kcmil		0.80	1.00	1.20		E
750 kcmil		0.90	1.12	1.35		E
1000 kcmil		1.00	1.25	1.50		E
 <b>Motor Stub Splice Insulators</b>						
#14 - #10 Motor Splice Insulator		0.15	0.20	0.25		E
#12 - #3 Motor Splice Insulator		0.18	0.23	0.28		E
#2 - #2/0 Motor Splice Insulator		0.22	0.27	0.32		E
#3/0 - #300 Motor Splice Insulator		0.25	0.30	0.32		E
#350 - #500 Motor Splice Insulator		0.30	0.35	0.40		E

# SECTION 13

## INDUSTRIAL CONTROL AND INSTRUMENTATION

### General Information

The labor units in this section include installing and terminating control and instrumentation equipment including temperature control cabinets and devices.

### Scope of These Labor Units

The Introduction section includes details on the scope of labor units across the manual. Some items included are:

- Material unloading, jobsite storage and delivery to the installation area
- Drawing and specification study
- Layout, measuring and marking the installation location
- Terminating conductors
- Tool acquisition and return to storage Material assembly and installation
- Clean-up of electrical contractor furnished excess material
- Normal non-productive labor

### Work Operations Not Included In These Labor Units

- Field supervision
- Hoisting above three floors
- Grounding, bonding, welding or painting
- Testing of any type
- Commissioning equipment
- Grouting or anchoring
- Cutting holes or openings in walls, floors, cabinets or panels
- Heavy equipment (crane) operator's time

### Labor Adjustments for Non-Typical Conditions

See the Introduction section for details.

### Application Instructions

- Labor units under the "Normal" column are for locations with good access, no obstructions and large quantities of equipment. Labor units under the "Difficult" column are for locations with less than good access, a few minor obstructions and large quantities of equipment. Labor units under the "Very Difficult" column are for locations with poor access or require the use of a ladder, numerous obstructions, limited space or small quantities of equipment.
- All the labor units in this section are based on using the most efficient tools and equipment available. When the anticipated jobsite conditions will prevent the optimum use of tools and equipment, an appropriate additional labor allowance in proportion to the anticipated difficulties is necessary.
- Labor units in this manual are for new work only and for a complete electrical installation. For remodeling or change order situations these labor units need to be substantially increased.





## Section 13 - Industrial Control and Instrumentation Table of Contents

Temperature Controls - Panel Enclosures - 19"H X 24" W Panel	13-5
Temperature Controls - Panel Enclosures - 23"H X 24" W Panel	13-5
Temperature Controls - Panel Enclosures - 38"H X 24" W Panel	13-5
Temperature Controls - Thermostatic Control Valves - Water, Straight Through	13-5
Temperature Controls - Thermostatic Control Valves - Water, 3 Way	13-5
Temperature Controls - Electrical Relays - 4 SPDT Outputs	13-5
Temperature Controls - Electrical Relays - E/P Relays	13-5
Temperature Controls - Electrical Relays - Water Flow Switch	13-5
Timers	13-5
Temperature Controls - Electrical Relays - Miscellaneous	13-6
Temperature Controls - Central Equipment	13-6
Temperature Controls - Central Equipment - Power Supply	13-6
Miscellaneous Controls	13-6
Temperature Controls - Central Equipment - Computer Systems	13-6
Modem Comm. Module	13-6
Temperature Controls - Temperature Sensors - Wall Mount Standard	13-6
Temperature Controls - Temperature Sensors - Space	13-6
Temperature Controls - Temperature Sensors - Duct	13-6
Temperature Controls - Temperature Sensors - Pipe	13-6
Temperature Controls - Temperature Sensors - Miscellaneous	13-6
Temperature Controls - Humidity Sensors - Wall Mount	13-6
Temperature Controls - Humidity Sensors - Duct	13-6
Temperature Controls - Humidity Sensors - Pressure	13-7
Temperature Controls - Actuators - Damper	13-7

**(Updated)**



Section 13 - Industrial Control and Instrumentation

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Temperature Controls - Panel Enclosures - 19"H X 24" W Panel</b>						
Rough-in Enclosure		1.00	1.50	2.00		E
Install Interior		0.50	0.75	1.00		E
Terminate Conductors		0.04	0.05	0.06		E
Test & Start-up Per Termination Point		0.05	0.06	0.08		E
<b>Temperature Controls - Panel Enclosures - 23"H X 24" W Panel</b>						
Rough-in Enclosure		1.00	1.50	2.00		E
Install Interior		0.50	0.75	1.00		E
Terminate Conductors		0.04	0.05	0.06		E
Test & Start-up Per Termination Point		0.05	0.06	0.08		E
<b>Temperature Controls - Panel Enclosures - 38"H X 24" W Panel</b>						
Rough-in Enclosure		1.50	2.00	2.50		E
Install Interior		0.75	1.00	1.25		E
Terminate Conductors		0.04	0.05	0.06		E
Test & Start-up Per Termination Point		0.05	0.06	0.08		E
<b>Temperature Controls - Thermostatic Control Valves - Water, Straight Through: Installation Only in Existing Fitting</b>						
1/2"		1.50	2.00	2.50		E
3/4"		1.50	2.00	2.50		E
1"		1.50	2.00	2.50		E
1 1/4"		2.00	2.50	3.00		E
1 1/2"		2.00	2.50	3.00		E
2"		2.00	2.50	3.00		E
2 1/2"		2.50	3.00	3.50		E
3"		2.50	3.00	3.50		E
Terminate Conductors		0.50	0.75	1.00		E
<i>Note: Conduit, Conductors, Box Installation not included</i>						
<b>Temperature Controls - Thermostatic Control Valves - Water, 3 Way Installation Only in Existing Fitting</b>						
1/2"		1.50	2.00	2.50		E
3/4"		1.50	2.00	2.50		E
1"		1.50	2.00	2.50		E
1 1/4"		2.00	2.50	3.00		E
1 1/2"		2.00	2.50	3.00		E
2"		2.00	2.50	3.00		E
2 1/2"		2.50	3.00	3.50		E
3"		2.50	3.00	3.50		E
Terminate Conductors		0.50	0.75	1.00		E
<i>Note: Conduit, Conductors, Box Installation not included</i>						
<b>Install Temperature Controls - Electrical Relays - 4 SPDT Outputs</b>						
Floating Control		1.50	2.00	2.50		E
2 SPDT, 1 SPST		1.50	2.00	2.50		E
DPDT 24VAC, General Pur		1.50	2.00	2.50		E
DPDT 24VAC, Pilot Duty		1.50	2.00	2.50		E
1-SPDT 12A, 1 SPDT pilot		1.50	2.00	2.50		E
DPDT 12A, 120Vac, Gen		1.50	2.00	2.50		E
DPDT pilot duty 120 Vac		1.50	2.00	2.50		E
SPDT for XL 100/80		1.50	2.00	2.50		E
Relay Base, HOA		0.50	0.75	1.00		E
Relay Base		0.50	0.75	1.00		E
Terminate Conductors		0.04	0.05	0.06		E
<b>Install Temperature Controls - Electrical Relays - E/P Relays</b>						
2W Pneu. Xducer		1.00	1.50	2.00		E
3W Pneu. Xducer		1.00	1.50	2.00		E
120V/60HZ, Field Mounted		1.00	1.50	2.00		E
120V/60HZ, Panel Mounted		1.00	1.50	2.00		E
24V/60HZ, Field Mounted		1.00	1.50	2.00		E
24V/60HZ, Panel Mounted		1.00	1.50	2.00		E
Terminate Conductors		0.50	0.75	1.00		E
<b>Temperature Controls - Electrical Relays - Water Flow Switch Installation Only</b>						
PENN NEMA-1 1" NPT		1.50	2.00	2.50		E
PENN NEMA-4 1" NPT		1.50	2.00	2.50		E
Terminate Conductors		0.50	0.75	1.00		E
<b>Timers</b>						
Install and connect:						
Timer: Wall Mounted		1.00	1.50	2.00		E
Timer: Panel Mounted		1.00	1.50	2.00		E

Section 13 - Industrial Control and Instrumentation

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Temperature Controls - Electrical Relays - Miscellaneous</b>						
<b>Installation Only in Existing Fitting</b>						
 Air Flow DP Switch .05-12"		1.00	1.50	2.00		E
Air Quality Sensor -		1.00	1.50	2.00		E
Kele Wall Mount CO2		0.75	1.25	1.75		E
Kele Duct Mount CO2		1.50	2.00	2.50		E
Freeze Stat		1.00	1.50	2.00		E
Terminate Conductors		0.75	1.00	1.50		E
<b>Temperature Controls - Central Equipment</b>						
Controller		1.00	1.20	1.50		E
Panel Mounting Kit		0.50	0.60	0.75		E
Terminate Conductors		0.04	0.05	0.06		E
<b>Temperature Controls - Central Equipment - Power Supply</b>						
Std. + 24 Vac		2.50	3.00	3.75		E
Std. + 24 Vac & 24 Vdc		2.50	3.00	3.75		E
120/24 VAC Transformer		2.50	3.00	3.75		E
Uninterrupted Power Sup.		3.50	4.00	5.00		E
<b>Miscellaneous Controls</b>						
Connect Controls at Furnace		0.75	1.25	1.50		E
Connect Controls at Condensor		1.00	1.50	2.00		E
Connect Controls at Roof Top HVAC		1.00	1.50	2.00		E
Connect Thermostat		0.75	1.25	1.50		E
Interlock to Fan		0.75	1.25	1.50		E
Interlock to Damper		0.75	1.25	1.50		E
Connect VAV Unit		1.00	1.50	2.00		E
Connect Fan/Coil Unit		1.00	1.50	2.00		E
<b>Temperature Controls - Central Equipment - Computer Systems</b>						
Personal Computer System w/Programming Pre-Installed		4.00	5.00	7.00		E
Modem		2.00	2.50	3.00		E
<b>Modem Comm. Module</b>						
Area Control Module		3.00	3.50	4.00		E
Main Control Module		3.00	3.50	4.00		E
Terminate to Computer		3.00	3.50	4.00		E
Test / Start-up		0.50	0.75	1.00		E
<i>You Must Include All Components: Stats, Sensors, Dampers, Equip., Etc.</i>						
<b>Temperature Controls - Temperature Sensors - Wall Mount Standard</b>						
Install and Connect		1.50	2.00	2.50		E
<b>Temperature Controls - Temperature Sensors - Space</b>						
Wall Mount Install and Connect		1.00	1.50	2.00		E
<b>Temperature Controls - Temperature Sensors - Duct</b>						
<b>Installation Only in Existing Fitting</b>						
Install Duct Sensor		2.00	3.00	4.00		E
Terminate Conductor		1.00	1.30	1.50		E
<b>Temperature Controls - Temperature Sensors - Pipe</b>						
<b>Installation Only in Existing Fitting</b>						
20K NTC, Nipple-in		1.50	2.00	2.50		E
20K NTC, Strap-on		1.00	1.50	2.00		E
Terminate Conductors		0.75	1.00	1.25		E
<b>Temperature Controls - Temperature Sensors - Miscellaneous</b>						
<b>Installation Only in Existing Fitting</b>						
PT 3000, Bulb, 24" leads		1.50	2.00	2.50		E
PT 3000, Bulb, 180" leads		1.75	2.25	2.75		E
C7 170 Duct Bulb Holder	X	0.50	0.75	1.00		E
Terminate Conductors		0.75	1.00	1.25		E
<b>Temperature Controls - Humidity Sensors - Wall Mount</b>						
Typical, Install and Connect		1.00	1.50	2.00		E
<b>Temperature Controls - Humidity Sensors - Duct</b>						
<b>Installation Only in Existing Fitting</b>						
Typical, Install		2.00	3.00	4.00		E
Terminate Conductors		0.75	1.00	1.25		E

### Section 13 - Industrial Control and Instrumentation

	Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
	<b>Temperature Controls - Humidity Sensors - Pressure</b>						
	<b>Installation Only in Existing Fitting</b>						
	4-20 MA, 0-5" WC, Panel		1.00	1.50	2.00		E
	4-20 MA, 0-5" WC, Duct		2.00	3.00	4.00		E
	Terminate Conductors		0.75	1.00	1.25		E
	<b>Temperature Controls - Actuators - Damper</b>						
	Damper Motor		0.75	1.00	1.25		E
	Mounting Base		1.00	1.25	1.50		E
	Control Linkage		1.00	1.25	1.50		E
	Terminate Conductors		0.75	1.00	1.25		E



# SECTION 14

## ALTERNATIVE ENERGY SYSTEMS

### General Information

This section includes labor units for installing and terminating generating equipment and the related controls and instrumentation, including photovoltaic modules, wind turbines, gas fired cogeneration and fuel cell technologies.

### Scope of These Labor Units

The Introduction section includes details on the scope of labor units across the manual. Some items included are:

- Material unloading, jobsite storage and delivery to the installation area
- Drawing and specification study
- Layout, measuring and marking the installation location
- Terminating and quick connect splices of conductors
- Tool acquisition and return to storage Material assembly and installation
- Clean-up of electrical contractor furnished excess material
- Normal non-productive labor

### Work Operations Not Included In These Labor Units

- Field supervision
- Hoisting above two floors
- Grounding, bonding, welding or painting
- Testing of any type unless specifically listed
- Grouting or anchoring
- Cutting holes or openings in walls, floors, cabinets, or panels
- Heavy equipment (crane) operator's time
- Roof sealing or roofing sub-contracts as may be needed
- Pre-engineering or design
- Slabs or foundations for gear, inverters, power generating equipment
- Any and all engineering, electrical, mechanical, or structural

### Labor Adjustments for Non-Typical Conditions

See the Introduction section for details.

### Application Instructions

- Labor units for roof mounted photovoltaic solar arrays are based on a single story structure with less than a 15 degree slope to the roof line and use of a stationary extension ladder up to a single story structure. If roof slope is more than 15 degrees these labor units need to be substantially increased.
- Labor units under the "Normal" column are for locations with good access, no obstructions and large quantities of equipment. Labor units under the "Difficult" column are for locations with less than good access, a few minor obstructions, two story structure and large quantities of equipment. Labor units under the "Very Difficult" column are for locations with poor access or require the use of a scaffold or scissor-lift, etc., numerous obstructions, limited space or small quantities of equipment, above a two story structure and may require the use of cranes etc.
- All the labor units in this section are based on using the most efficient tools and equipment available. When the anticipated jobsite conditions will prevent the optimum use of tools and equipment, an appropriate additional labor allowance in proportion to the anticipated difficulties is necessary.
- Labor units in this manual are for new work only and for a complete electrical installation. For remodeling or change order situations these labor units need to be substantially increased.





## Section 14 - Alternate Energy Systems Table of Contents

Photovoltaic Solar Modules - Standard Frame, Front Hardware Mounted	14-5
Photovoltaic Solar Modules - Standard Frame, Rear Hardware Mounted	14-5
Photovoltaic Solar - Solar Roofing Shingles	14-5
Photovoltaic Solar - Solar Laminate	14-5
Multi-Contact Quick Connector	14-5
Sunlight Resistant Wire/Cable, Type USE-2	14-5
Photovoltaic Solar Inverters	14-5
Photovoltaic Solar Micro Inverters	14-5
Micro Inverters Accessories	14-5
Alternative Energy, Data Acquisition Systems (DAS)	14-5
Photovoltaic Solar Inverters	14-6
Photovoltaic Solar Roof Mounting Systems	14-6
Sunlink Racking	14-6
Unirack Mono-Pole	14-6
Tile Trac	14-6
Photovoltaic Solar Roof Mounting Systems	14-6
Commercial & Residential Stations	14-6
Roof Flashings	14-6
Solar Railing	14-6
Solar Module Clamping Assemblies	14-6
Wind Generation	14-7
Foundations	14-7
Erection	14-7
Pole / Tower Interior	14-7
Equipment	14-7
Prepackaged Fuel Cell Generator	14-7
300KW Fuel Cell CHP Generator	14-7
1.5MW Fuel Cell CHP Generator	14-7
3.0MW Fuel Cell CHP Generator	14-7
Bloom Energy Fuel Cell	14-7
100KW Fuel Cell Generator	14-7
Foundations	14-8
Prepackaged Co-Gen	14-8
<b>Electric Vehicle Charging Stations</b>	14-9
Wall Mount Electric Vehicle Supply Equipment (EVSE)	14-9
Ceiling Mount Electric Vehicle Supply Equipment (EVSE)	14-9
Pedestal Mount Electric Vehicle Supply Equipment (EVSE)	14-9



## Section 14 - Alternate Energy Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
	<b>Photovoltaic Solar Modules</b>					
<b>Standard Frame, Front Hardware Mounted</b>						
<b>Factory Installed Whip w/ MC Quick Connector</b>						
Up to 50 Watt		0.30	0.38	0.45		E
51 to 100 Watt		0.40	0.50	0.60		E
101 to 240 Watt		0.50	0.63	0.75		E
241 to 380 Watt		0.60	0.75	0.90		E
	<b>Photovoltaic Solar Modules</b>					
<b>Standard Frame, Rear Hardware Mounted</b>						
<b>Factory Installed Whips w/ MC Quick Connector</b>						
Up to 50 Watt		0.35	0.44	0.53		E
51 to 100 Watt		0.45	0.56	0.68		E
101 to 240 Watt		0.65	0.81	0.98		E
241 to 380 Watt		0.85	1.06	1.28		E
	<b>Photovoltaic Solar</b>					
<b>Solar Roofing Shingles</b>						
up to 20 Watts		0.90	1.22	1.44		E
<i>**Note: roofing underlayment not included</i>						
	<b>Photovoltaic Solar</b>					
<b>Solar Laminate</b>						
up to 150 Watts		0.15	0.20	0.24		LF
<i>**Note: roofing underlayment not included</i>						
	<b>Multi-Contact Quick Connector</b>					
<b>MC-3 Connectors</b>						
MC-4 Connectors		0.40	0.50	0.60		E
<i>**Note: Includes time for crimping</i>						
MC-3 Parallel Connector		0.20	0.25	0.30		E
	<b>Sunlight Resistant Wire/Cable, Type USE-2</b>					
#12 Copper Conductor, Type USE-2		4.80	6.00	7.20		M
#10 Copper Conductor, Type USE-2		7.00	8.75	10.50		M
#8 Copper Conductor, Type USE-2		9.00	11.25	13.50		M
#12 Aluminum Conductor, Type USE-2		3.85	4.80	5.78		M
#10 Aluminum Conductor, Type USE-2		5.60	7.00	8.40		M
#8 Aluminum Conductor, Type USE-2		7.20	9.00	10.80		M
	<b>Photovoltaic Solar Inverters</b>					
<b>Grid-Tied Rated, 208-240vAC, Single Phase</b>						
<b>Up to 600vDC</b>						
Up to 3000 Watts		2.60	3.25	3.90		E
3001 to 7000 Watts		3.70	4.63	5.55		E
	<b>Photovoltaic Solar Micro Inverters</b>					
<b>Grid-Tied Rated, 120-240vAC, Single Phase and Three Phase</b>						
M190 Watt Inverter		0.25	0.31	0.38		E
M210 Watt Inverter		0.25	0.31	0.38		E
D380 Watt Inverter (Twin Pack)		0.30	0.38	0.45		E
	<b>Micro Inverters Accessories</b>					
6 foot cable extension		0.25	0.31	0.38		E
20 foot cable extension		0.31	0.39	0.47		E
12 foot extension cable for D380 only		0.29	0.36	0.43		E
6 foot AC Interconnect cable		0.25	0.31	0.38		E
12 foot AC Interconnect cable		0.29	0.36	0.43		E
20 foot AC Interconnect cable		0.31	0.39	0.47		E
Mounting bracket		0.20	0.25	0.30		E
Sealing end caps		0.15	0.19	0.23		E
240 VAC AC branch circuit Installation Kit		0.25	0.31	0.38		E
	<b>Alternative Energy, Data Acquisition Systems (DAS)</b>					
<b>Enlighten</b>						
Energy Management Unit, with indoor enclosure		1.50	1.88	2.25		E
Line Communication Filter		0.50	0.63	0.75		E

Section 14 - Alternate Energy Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
						
<b>Photovoltaic Solar Inverters</b>						
<b>Grid-Tied Rated, 208-480vAC, Three Phase</b>						
<b>Up to 600vDC</b>						
30 kW		8.00	10.00	12.00		E
45 kW		10.00	12.50	15.00		E
50 kW		11.00	13.75	16.50		E
75 kW		13.00	16.25	19.50		E
100 kW		11.00	13.75	16.50		E
150 kW		14.00	17.50	21.00		E
225 kW		21.00	26.25	31.50		E
250 kW		23.00	28.75	34.50		E
375 kW		28.00	35.00	42.00		E
500 kW		34.00	42.50	51.00		E
1 mW		50.00	62.50	75.00		E
<b>Photovoltaic Solar Roof Mounting Systems</b>						
<i>* Note: for racking and mounting hardware, go to the following websites for additional information</i>						
1) <a href="http://www.prosolar.com">www.prosolar.com</a> (primarily for residential)						
2) <a href="http://www.unirac.com">www.unirac.com</a>						
3) <a href="http://www.sunlink.com">www.sunlink.com</a>						
						
<b>Sunlink Racking</b>						
Non-Penetrating and Minimal Penetrations for Seismic		0.25	0.31	0.38		E
<i>* Note: Labor is based per PV module</i>						
<i>* Note: Labor for ballasting is not included</i>						
						
<b>Unirack Mono-Pole</b>						
Mono-Pole install only (does not include caisson)		5.00	6.25	7.50		E
						
<b>Tile Trac</b>						
Composite Shingled Roof Hardware Assembly		0.15	0.19	0.23		E
Concrete Tile Roof Hardware Assembly		0.31	0.39	0.47		E
<i>*Note: If installing on clay tile roof, suggest removing the tiles in the array area and applying a torch down or 3-tab shingle roofing material, under the array</i>						
						
<b>Photovoltaic Solar Roof Mounting Systems</b>						
<b>Commercial &amp; Residential Stations</b>						
Mounting base, Station & Hardware Assembly		0.20	0.25	0.30		E
						
<b>Roof Flashings</b>						
Up to 1"		0.20	0.25	0.30		E
1-1/4" up to 2"		0.25	0.31	0.38		E
						
<b>Solar Railing</b>						
Residential Rated		6.00	7.50	9.00		C
Commercial Rated		7.20	9.00	10.80		C
						
<b>Solar Module Clamping Assemblies</b>						
Intermediate or End Clamping Assemblies		0.15	0.19	0.23		E

Section 14 - Alternate Energy Systems


Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Wind Generation</b>						
1.5MW, 2.5MW, 3.6MW Size						
<b>Foundations</b>						
Grounding						
reference Section 8 - Grounding & Lightning Protection of the MLU						
U.G. Conduit						
reference Section 11 - Outdoor Overhead & Underground Systems						
** Does not include civil / concrete work						
<b>Erection</b>						
** Does not include setting of pole or tower on base						
** Does not include erection of pole or tower sections						
** Does not include setting of generator on pole or tower						
<b>Pole / Tower Interior</b>						
Tower Climbing - Unproductive Labor (/tower)		15.00	18.75	22.50		E
average 13.25 feet per minute						
Control Cable - Uncoil & Lower Cable (/foot)		8.00	10.00	12.00		M
Control Cable - Lacing (Ty-Raps every 3')(/cable)		7.50	9.38	11.25		C
Power Cable Splice - Compression Type (up to 500 kcmil)		0.75	0.94	1.13		E
Power Cable Splice - Compression Type (500 kcmil and larger)		1.00	1.25	1.50		E
Power Cable Splice - Heat Shrink (/Cable)		0.75	0.94	1.13		E
Compression Tool Test & Log (Daily per Tool)		1.50	1.88	2.25		E
Power Busduct - Flexible Splice		4.00	5.00	6.00		E
Power Busduct - Torque Flexible Splice		3.00	3.75	4.50		E
Power Busduct - Heat Shrink (/splice)		1.00	1.25	1.50		E
Cable Tray Splice at Tower Section (/pair)		1.50	1.88	2.25		E
Cable Tray Grounding - Ground Jumper		0.75	0.94	1.13		E
Ladder - Ground Jumper		0.75	0.94	1.13		E
FAA Obstruction Light (on top of generator)		2.00	2.50	3.00		E
Anomometer		2.00	2.50	3.00		E
Overtwist Limit Switch		2.00	2.50	3.00		E
Pole Interior Safety Lighting Connection (/section)		1.00	1.25	1.50		E
<b>Equipment</b>						
Down Terminal Assembly (DTA)(Switchgear Package)		24.00	30.00	36.00		E
Pad Mount Transformer - See Section 4						
<b>Prepackaged Fuel Cell Generator</b>						
The work outlined below is to accommodate offloading, setting and mounting to existing pad or foundation. (Directly from truck to pad)						
** Does not include civil / concrete work						
** Does not include mechanical process piping						
<b>300KW Fuel Cell CHP Generator</b>						
Fuel Cell Module		6.00	7.50	9.00		E
Mechanical Balance of Plant		6.00	7.50	9.00		E
Electrical Balance of Plant		6.00	7.50	9.00		E
<b>1.5MW Fuel Cell CHP Generator</b>						
Fuel Cell Module		12.00	15.00	18.00		E
Mechanical Balance of Plant		12.00	15.00	18.00		E
Electrical Balance of Plant		12.00	15.00	18.00		E
<b>3.0MW Fuel Cell CHP Generator</b>						
Fuel Cell Module		24.00	30.00	36.00		E
Mechanical Balance of Plant		24.00	30.00	36.00		E
Electrical Balance of Plant		24.00	30.00	36.00		E
** For all other work associated with the installation please refer to the respective section of the MLU						
<b>Bloom Energy Fuel Cell</b>						
<b>100KW Fuel Cell Generator</b>						
Fuel Cell Module		10.00	12.50	15.00		E
** For all other work associated with the installation please refer to the respective section of the MLU						





### Section 14 - Alternate Energy Systems

Description	Rev	Normal	Difficult	Very Difficult	Company Experience	Unit
<b>Electric Vehicle Charging Stations</b>						
<b>Wall Mount Electric Vehicle Supply Equipment (EVSE)</b>						
<i>Factory Warranty Requires Certified Installers</i>						
<i>Verify Installation Instructions</i>						
<i>Verify Manufacture Recommendations</i>						
<i>Branch Wiring Not Included</i>						
<i>Layout Not Included</i>						
30 AMP 2 Pole Unit		1.50	1.90	2.40		E
40/2 AMP 2 Pole Unit		2.00	2.50	3.10		E
<b>Ceiling Mount Electric Vehicle Supply Equipment (EVSE)</b>						
<i>Factory Warranty Requires Certified Installers</i>						
<i>Verify Installation Instructions</i>						
<i>Verify Manufacture Recommendations</i>						
<i>Branch Wiring Not Included</i>						
<i>Backing and Layout not Included</i>						
30 AMP 2 Pole Unit		2.50	3.00	4.00		E
40/2 AMP 2 Pole Unit		3.00	3.80	4.70		E
<b>Pedestal Mount Electric Vehicle Supply Equipment (EVSE)</b>						
<i>Factory Warranty Requires Certified Installers</i>						
<i>Verify Installation Instructions</i>						
<i>Verify Manufacture Recommendations</i>						
<i>Branch Wiring Not Included</i>						
<i>Base and Layout not Included</i>						
30 AMP 2 Pole Unit		3.00	3.80	4.70		E
70/2 AMP 2 Pole Unit		4.00	5.00	6.25		E







# ELECTRICAL CONSTRUCTION ABBREVIATIONS

3W	3-Way	Occ.	Occupancy (As in occupancy sensor)
4s	4-Square (As in 4" square box)	O&M	Operations and Maintenance
4W	4-Way	PIV	Post Indicating Valve
A	Amps	PNL	Panel or Panel Board
AFF	Above Finished Floor	PVC	Plastic conduit (Also known as polyvinyl chloride)
AHU	Air Handling Unit	Recp.	Receptacle
AIA	The American Institute of Architects	RFI	Request for Information
AL	Aluminum	RMC	Rigid Metallic Conduit
Alt	Alternate	R/R	Remove and Relocate
AWG	American Wire Gauge	RTU	Roof Top Unit
BCW	Branch Circuit Wiring	SD	Smoke Detector
Conc.	Concrete	SP	Single Pole
CU	Copper	STE	Switch with Thermal Element
CUH	Cabinet Unit Heater	Stl.	Steel
CWP	Chilled Water Pump	SW	Switch
DEMO	Demolition	SWBD	Switch Board
DJE	Direct Job Expenses	TAB	Terminal Air Blender (Electric or pneumatic device to regulate air temperature cooling or heating)
EF	Exhaust Fan	T&BF	Trench and backfill (Or T&B)
EMT	Electrical Metallic Tubing	TBB	Telephone Back Board
Equip.	Equipment	TC	Time Clock
EWC	Electric Water Cooler (Drinking fountain)	T/D	Telephone/Data
Exc.	Excavation	Tele	Telephone
FA	Fire Alarm	U.G.	Under Ground
FACP	Fire Alarm Control Panel	V	Volts
FCU	Fan Coil Unit	VAV	Variable Air Volume (Electric or pneumatic device to regulate air temperature cooling or heating)
GFI	Ground Fault Interrupter	VDV	Voice/Data/Video
GFCI	Ground Fault Circuit Interrupter	W	Watts
GRC	Galvanized Rigid Conduit	WP	Weatherproof
GRS	Galvanized Rigid Steel	XFMR	Transformer
HD	Heat Detector		
Hdwr.	Hardware		
HP	Horse Power		
HWP	Hot Water Pump		
kW	Kilowatt		
LF	Lineal Foot		
Ltg.	Lighting		
MAU	Make Up Air Unit		
MBCW	Motor Branch Circuit Wiring		
Misc.	Miscellaneous		
MSB	Main Switchboard/Main Service Board		
Mtg.	Mounting		
NEC	National Electric Code		
NECA	National Electrical Contractors Association		
NF	Non-Fused		
NFPA	National Fire Protection Agency		

## Manufacturer Abbreviations

C-H	Cutler Hammer
GE	General Electric
Sie	Siemens
SQ D	Square D

# ELECTRICAL CONSTRUCTION DEFINITIONS

**Addendum** – A written change or clarification issued, typically by the architect or general contractor, prior to bid, which becomes part of the contract documents.

**Alternate** – An additive or deductive price option to the base bid price submitted. Usually pertains to an alternate manufacturer of materials or additional or reduction in project scope.

**Approved Equal** – Equipment, material or means of construction approved by the architect or engineer as being of equal attributes to those described in the contract documents.

**Arbitration Clause** – A provision that may be included in certain construction, insurance, labor or sale contracts, requiring settlement of disputes through arbitration instead of litigation, and often providing the procedure to be followed.

**As-Built Drawings** – As specified drawings of installations, including circuit numbers and conduit routing, either submitted as hand-drawn, generated, marked-up red-line drawings or as CAD/BIM generated drawings in specified format.

**Beneficial Occupancy** – The stage of construction of a building or facility, before final completion, at which its owner can occupy it for the purpose it was constructed.

**Bid** – 1) An offer or proposal of a price. 2) The amount offered or proposed. 3) To tender a price for work.

**Bid Bond** – A written form of security executed by the bidder as principal and by a surety for the purpose of guaranteeing that the bidder will sign the contract, if awarded the contract, for the stated bid amount.

**Bid Documents** – The drawings and specifications and addendums for a project that are provided to potential bidders.

**Bid Rigging** – A form of price fixing and market allocation collusion, in which an agreement is illegally made among two or more bidders to allow one party to win the bid.

**Bid Shopping** – A practice in which a contractor uses the lowest subcontract bid as a tool in negotiating lower bids from other subcontractors prior to award of the contract.

**Building Information Modeling (BIM)** – A process involving the generation and management of digital representations of physical and functional characteristics of a structure. The resulting building information models become shared resources that can support decision-making about a facility from earliest conceptual stages to eventual demolition.

**Cash Allowance** – A dollar amount described in the contract documents to be included in the bid to cover the cost for a scope of work not specified in detail.

**Change Order** – A written order, agreed upon by the owner, contractor and designer, authorizing changes to the scope of work, the contract sum, and/or the contract time.

**Closeout Documents** – Material cut sheets of equipment used, warranties and as-built drawings that are required for final payment.

**Contract Documents** – The legally binding, written agreement to perform work. May include drawings, specifications and addendums for a project. A construction project may have many levels of contract documents.

**Cost Breakdown** – A statement furnished by the contractor to the architect or engineer reflecting the portions of the contract sum allotted for the various parts of the work that is used as the basis for reviewing the contractor's applications for progress payments. Also known as a Schedule of Values.

**Cost Codes** – A numbering system given to specific kinds of work for the purpose of organizing the cost control process of a specific project.

**Design/Bid/Build** – A project delivery method in which design and construction are separate contracts. The contract for construction is awarded based on bids provided in response to the design.

**Design/Build** – A project delivery method in which design and construction contracts are combined.

**Direct Job Expenses (DJE)** – Expenses attributed to a specific project that end once the project ends. Some examples are field supervision, engineering, equipment rental, insurance, permits and travel. Sometimes confused with general overhead. (See also Overhead)

**Estimating** – Determining the accurate cost of proposed work through reviewing and analyzing construction documents, economic conditions, the physical location of the work, and the parties involved.

**Field authorization** – Order to perform a change issued by the owner's representative in the field, made directly to the contractor's field personnel. This process requires significant extra transfers of information from the field to management.

**General Conditions** – Contract conditions, usually included in the book of specifications (or in the accompanying architectural drawings) of a contract, which set the minimum performance requirements for the contractor. These conditions also include the rights and responsibilities of the parties involved.

**Greenfield** – Flexible metal conduit, steel or aluminum.

**Guaranteed Maximum Price (GMP)** – A type of project contract where the contractor is compensated for actual costs incurred, plus a fixed fee, to a ceiling price. The contractor is responsible for cost over runs, unless the GMP has been increased due to a change order. Savings resulting from cost under runs are returned to the owner. This is also known as Not-to-Exceed Price.

**Integrated Project Delivery (IPD)** – A project delivery approach that emphasizes increased stakeholder involvement from the beginning of the project to increase project efficiency, increase value to the owner, reduce waste and improve design quality. IPD projects typically have characteristics such as multi-party contractual agreements, shared risk/reward incentives, and buyout processes.

**Letter of Intent** – An agreement between two or more parties prior to an agreement on the final contract.

**Liens** – A charge upon real or personal property for the satisfaction of some debt or duty ordinarily arising by operation of law.

**Liquidated Damages** – Damages that can be collected by the injured party as compensation in the event of a specific breach. The amount may be specified in the contract or to agreed to or determined by a court of tribunal in the event of a breach. Also know as liquidated and ascertained damages.

**Notice To Proceed (NTP)** – Letter from a principal to a contractor stating the date the contractor can begin work subject to the conditions of the contract. The performance time of the contract starts from the NTP date.

**Order to Proceed** – A directive from the customer (or customer's representative) to perform a specific task or tasks. Not necessarily an approval of a change order.

**Overhead** – Items or expenses that cannot be attributed to one specific project. Overhead is the cost

of running your company, such as building lease, utility bills, office salaries, warehouse, legal and accounting fees, etc. Sometimes confused with direct job expenses. (See also Direct Job Expenses)

**Performance Bond** – A written form of security from a surety (bonding) company to the owner, on behalf of an acceptable prime contractor or subcontractor, guaranteeing payment to the owner in the event the contractor fails to perform all labor, materials, equipment, or services in accordance with the contract.

**Prefabrication** – The process by which components are assembled or prepared, in whole or in part, before reaching their final location.

**Prime Contractor** – Contractor who has a contract with the owner of a project and has the full responsibility for its completion. A prime contractor undertakes to perform a complete contract, and may employ, and manage, one or more subcontractors to carry out specific parts of the contract. Also called main or general contractor.

**Profit** – The excess revenue after all expenditures including direct job cost and overhead are considered.

**Raceway** – Generic term describing material used to contain electrical wiring. This could include conduit, cable tray, wire way, etc.

**Request for Information (RFI)** – A written request to the owner, architect or engineer for guidance on a job condition prior to bidding or during the project. A good tool to let others make a decision without taking the responsibility.

**Retainage** – A portion of a contractor's payment that is withheld until the contract is satisfactorily completed.

**Rough Order of Magnitude (ROM)** – An estimate of costs and time provided in the early stages of a project when its scope and requirements has not been fully defined. An ROM is used to reduce the uncertainty of cost outcomes for both parties when project details have yet to be identified.

**Schedule of Values** – A statement furnished by the contractor to the architect or engineer reflecting the portions of the contract sum allotted for the various parts of the work and used as the basis for reviewing the contractor's applications for progress payments.

**Scope Letter** – A letter or statement submitted with a contractor's bid listing inclusions and exclusions they make to their bid.

**Special Conditions** – Provisions of a contract that are peculiar to the project under consideration and do not fall under the general conditions or supplementary conditions.

**Subcontractor** – A contractor who has a contractual relationship to perform work with an entity other than the owner of a project, typically a general or prime contractor, although there can be multiple tiers of subcontractors. The lower-tier subcontractor completes a portion of the higher-tier contractor's work.

**Submittal** – Documents of equipment or procedures needing approval prior to implementation.

**Substantial Completion** – Stage in the progress of the work when the work is sufficiently complete in accordance with a contract so the owner can occupy or utilize the work for its intended use.

**Supplemental Conditions** – Special provisions in a contract that modify or qualify its general provisions. Also called supplementary conditions.

**Time and Material (T&M)** – Contracted construction work paid-for on the basis of time taken and material consumed. Also known as force account.

**Unit Price** – A predetermined price for a measurement or quantity of work to be performed within a

specific contract. The designated unit price would include all labor materials, equipment or services associated with the measurement or quantity established.

**Work directive** – Generally an authorization to perform a specific task or tasks, with the payment to be negotiated at a later date.

# APPENDIX A: TECHNICAL DATA TABLES

**Table 1: Conversion Of Minutes To Decimal Hours**

Minutes	Hours	Minutes	Hours	Minutes	Hours	Minutes	Hours
1	0.017	16	0.267	31	0.517	46	0.767
2	0.033	17	0.283	32	0.533	47	0.783
3	0.050	18	0.300	33	0.550	48	0.800
4	0.067	19	0.317	34	0.567	49	0.817
5	0.083	20	0.333	35	0.583	50	0.833
6	0.100	21	0.350	36	0.600	51	0.850
7	0.117	22	0.367	37	0.617	52	0.867
8	0.133	23	0.383	38	0.633	53	0.883
9	0.150	24	0.400	39	0.650	54	0.900
10	0.167	25	0.417	40	0.667	55	0.917
11	0.183	26	0.433	41	0.683	56	0.933
12	0.200	27	0.450	42	0.700	57	0.950
13	0.217	28	0.467	43	0.717	58	0.967
14	0.233	29	0.483	44	0.733	59	0.983
15	0.250	30	0.500	45	0.750	60	1.000

**Table 2: Metric Conversions**

1 meter = 39.37 inches
1 centimeter = 0.39 inch
1 millimeter = 0.04 inch
1 inch = 0.025 meter
1 inch = 2.564 centimeters
1 inch = 25.641 millimeters

**Table 3: Rigid Metal Conduit Inside Diameters**

Trade Size	Inches	Millimeters	Trade Size	Inches	Millimeters
½	0.632	16.1	2 ½	2.489	63.2
¾	0.836	21.2	3	3.090	78.5
1	1.063	27.0	3 ½	3.570	90.7
1 ¼	1.394	35.4	4	4.050	102.9
1 ½	1.624	41.2	5	5.073	128.9
2	2.083	52.9	6	6.093	154.8

**Table 4: Electrical Conductor Areas**

United States		
Size (AWG)	Area	
	Circular Mils	Square Millimeter
18	1,620	0.82
16	2,580	1.30
14	4,110	2.08
12	6,530	3.30
10	10,380	5.25
8	16,510	8.36
6	26,240	13.29
4	41,740	21.14
3	52,620	26.65
2	66,360	33.61
1	83,690	42.39
1/0	105,600	53.49
2/0	133,100	67.42
3/0	167,800	85.00
4/0	211,600	107.19
250	250,000	126.64
300	300,000	151.97
350	350,000	177.30
400	400,000	202.63
500	500,000	253.29

Closest European Sizes	
Size	Area
Square Millimeter	Circular Mils
0.75	1,480
1.00	1,974
1.50	2,961
2.50	4,935
4.00	7,896
6.00	11,844
10.00	19,740
16.00	31,584
25.00	49,350
—	—
35.00	69,090
50.00	98,700
—	—
70.00	138,180
95.00	187,530
120.00	236,880
150.00	296,100
—	—
185.00	365,190
240.00	473,760

**Table 5: Conduit Weight Comparisons (All Weights Are Per 100 Feet Of Conduit\*\*)**

Size	Rigid Steel	IMC	Rigid Aluminum	EMT	PVC Sch 40	PVC Sch 80	PVC Coated* Rigid Steel
½"	80	60	28	29	16	21	87
¾"	108	82	37	45	22	29	115
1"	160	116	55	65	33	42	166
1 ¼"	208	150	72	96	46	61	217
1 ½"	254	182	89	111	56	71	262
2"	344	242	119	141	74	98	267
2 ½"	550	401	188	215	117	149	557
3"	710	493	246	260	153	200	724
3 ½"	855	571	296	365	185	246	917
4"	1000	638	350	390	219	292	1056
5"	1335	—	479	—	298	400	1535
6"	1845	—	630	—	385	510	2025

\*20 mil thickness

\*\*The above weights were taken from several manufacturers' catalogues, include the threaded coupling when applicable, and have been rounded off to the closest whole number.



**Table 6: Estimating the Effects of Extended Duration Beyond a Normal Job Period**

Extra Labor Hours Consumed						
Base Estimated Electrical Contract Time		Optimum Average Crew	Crew Weeks **	Normal Related Construction Project Duration	Effect of Extended Duration Increase of Base Estimated Labor Per Month of Extended Duration	
Labor-Hours	Labor-Days*	Workers		Months	%	Labor-Hours
500	62	2	6	2	8.00	40
1,000	125	3	8	3	6.50	65
1,250	156	4	8	3	6.50	81
2,500	313	5	10	4	5.00	125
5,000	625	8	16	5	4.00	200
10,000	1,250	11	23	7	3.50	350
15,000	1,875	14	27	8	2.75	415
20,000	2,500	15	34	10	2.25	450
30,000	3,750	17	44	12	1.75	525
45,000	5,625	25	45	12	1.75	785
60,000	7,500	30	50	14	1.45	870
75,000	9,400	35	54	15	1.35	1,010
100,000	12,500	38	65	18	1.25	1,250
125,000	15,650	40	78	21	1.15	1,445
150,000	18,750	45	83	22	1.00	1,500
200,000	25,000	58	86	23	.95	1,900
250,000	33,000	70	90	24	.85	2,120
300,000	37,500	80	94	26	.84	2,520

\*Based on 8 Hour Day

\*\*Based on 40 Hour Week

**Example:**

A labor estimate based on normal project duration (7 months) = 10,000 hours

Project extension past normal duration = 2.5 months

$10,000 \times 3.50\% \times 2.5 = 875$  hours additional time

Therefore: A typical 10,000 hour project that extends to 9.5 months for completion would require a total of 10,875 hours due to the abnormal project duration time.



## APPENDIX B: ELECTRICAL FORMULAS

To Find:	Single Phase	Three Phase	Direct Current
Ampere when KVA is known	$\frac{KVA \times 1000}{E}$	$\frac{KVA \times 1000}{E \times 1.73}$	Not Applicable
Amperes when Horsepower is known	$\frac{HP \times 1000}{E \times \%Eff. \times PF}$	$\frac{HP \times 746}{E \times 1.73 \times \%Eff. \times PF}$	$\frac{HP \times 746}{E \times \%Eff.}$
Amperes when Kilowatts are known	$\frac{kW \times 1000}{E \times PF}$	$\frac{kW \times 1000}{E \times 1.73 \times PF}$	$\frac{kW \times 1000}{E}$
Kilowatts	$\frac{I \times E \times PF}{1000}$	$\frac{1 \times E \times 1.73 \times PF}{1000}$	$\frac{I \times E}{1000}$
Kilovolt/Amperes	$\frac{I \times E}{1000}$	$\frac{I \times E \times 1.73}{1000}$	Not Applicable
Horsepower	$\frac{I \times E \times \%Eff. \times PF}{746}$	$\frac{I \times E \times 1.73 \times \%Eff. \times PF}{746}$	$\frac{I \times E \times \%Eff}{746}$
Watts	$E \times I \times PF$	$E \times I \times 1.73 \times PF$	$E \times I$

### Key

I = Amperes  
 E = Volts  
 kW = Kilowatts  
 KVA = Kilovolt/Amperes  
 HP = Horsepower  
 %Eff. = Percent Efficiency  
 PF = Power Factor

### Voltage Drop

Single Phase  $VD = \frac{2K \times L \times I}{D}$

Three Phase  $VD = \frac{2K \times L \times I}{D} (0.8666)$

### Key

VD = Voltage Drop  
 L = Length of Circuit  
 I = Current  
 D = Circular Mills of Conductor  
 K = Resistivity of Conductor (Copper = 12, Aluminum = 18)

# APPENDIX C: ADDITIONAL COSTS OF CHANGE ORDERS

## Change Orders Cost More

One should not be deceived by the illusion that all change orders make money. The majority of change orders have adverse impacts to the base contract, and in the long run cause the contractor to experience detrimental conditions and increased costs. There are many reasons for this adversity, some of them are:

- **Additional management time.** When critical project information must be transferred from one person to another, a substantial amount of time is required, usually this time is the company's most expensive time—that of top managers, supervisors, and executives. The information handoffs are numerous with the request for changes being transferred from the superintendent to the estimator; the estimator discussing the change with the project manager and/or owner; the estimator explaining the accepted project to the project manager (this information transfer must be slow and careful, so that nothing is lost); the project manager discussing changes with the foreman; supervision of additional or extended contracts; and more complex job accounting information going both ways. In addition to this, there may be additional discussions with the owner or owner's representative while the changes are being considered. All of this adds hours of extra work by management personnel, even for a fairly modest change order. The contractor must either recover these costs from the change order, or absorb the cost in the project.
- **Redirecting the workforce.** Any change order is disruptive to the flow of work at the jobsite. The obvious costs are the extra hours needed for the foreman and lead installers to read the new plans, interpret them, and pass the information along to the field workers. In addition to this, there are other, less obvious, costs:
  - Material quantities must be verified and more materials ordered, received and stored if necessary.
  - New or increased numbers of tools may be necessary and will have to be procured and distributed.
  - Sections of the workforce may be reassigned. This is an expensive process, as each worker must stop what he or she is doing, move their tools and/or equipment and familiarize themselves with new tasks and a new work area before they begin any actual installation.
  - When it is known that changes may be coming in one portion of the project, workers tend to “work around” that area, rather than installing equipment that they will have to remove later. This inhibits the streamlining of the workflow and reduces efficiency, sometimes substantially.

All of these things are in addition to the “put down what you're doing and do something else” losses that the contractor will incur because of a change in the work.

- **Incorrect installation based on untimely information.** In almost every case there is an “approval gap” in the change order process—the time between when the change is requested and when it is finally approved. During this gap, it is quite likely that a good deal of the electrical system will be incorrectly routed. The routing will be correct according to the original plans, but incorrect according to the change. This requires the field workers to reroute, and sometimes deconstruct their previous work. Not only does this take extra time, but also it is demoralizing to many workers, thus harming long-term productivity. The longer the “approval gap” is, the more likely it is that the contractor will encounter excessive losses.
- **Finance costs on extra cash flow.** The financing of large change orders is a serious matter to the electrical contractor. On average, an electrical contractor is required to finance about one third of the projects they perform. Thus a change order that increases a contract amount by

20% will require the contractor to finance an extra 7% of the contract amount. Not only is this an extra expense by itself, but it may also require the contractor to spend time negotiating (or renegotiating) a loan. If the contractor takes on a large change, and associated financing, there is also the possibility that the firm may not be able to obtain that extra financing, at least not without great difficulty.

- **Compressed job schedule.** Because of project delays, and due to the fact that change orders are often approved at the last minute, a high concentration of workers in the changed areas is usually necessary. This obviously reduces the electrical contractor's efficiency, since his workers are putting down one set of tasks and picking up others; but it also causes losses from too many workers in too small an area. Additionally, there are usually several other trades involved with change and each of them will also be putting a large number of workers into the area. This causes problems, not only of too many electricians running pipe past each other, but too many different trades working on top of each other. Disputes easily break out, and morale almost always suffers. If no contract time is made for a large change, the contractor is likely to see significant losses. For this reason, it is prudent for the electrical contractor to include a clause in a change proposal that reads something like:

A time extension of \_\_\_\_\_ days will be necessary for the satisfactory completion of these changes. Furthermore, this price is subject to change if not accepted within \_\_\_\_\_ days.

- **Extended overhead costs.** The longer and more complex a project is, the greater the contractor's overhead expenses will be. The time of overhead employees is required for the oversight of tools, storage trailers, support facilities, telephone and electrical service, electronic and computer equipment and jobsite offices. All support personnel such as CAD/BIM operators, office help and the like are direct overhead expenses.
- **Additional estimating costs.** Estimating expenses for change orders are very high, for several reasons. First of all, the change order is a new project, and must be estimated from scratch. The estimator will likely have to call a variety of suppliers for accurate quotes on material costs and will have to spend time factoring the labor for the expected conditions.

The estimator will have to account for not only material and labor expenses, but must also account for job costs and for the full impact that the change will make on the existing portion of the project. This process takes quite a bit of thought and project review. For an estimator to spend several hours on a \$1,000.00 change order may not be out of line.

A second reason for high estimating costs to the contractor on changes is that not all change estimates are accepted. The estimator may price two, three, or more proposed changes before one is accepted. One way or another, the contractor must find a way of recovering these estimating costs.

- **Updating as-built drawings.** This requires not only the time of draftspersons and/or CAD/BIM operators, but also a great deal of information transfer between the jobsite and the office. Information transfer monopolizes the time of at least two highly paid persons, and is far more costly than is commonly supposed.
- **Updating operations and maintenance manuals.** The use of new types of materials under a change requires the contractor to modify the operations and maintenance manuals that are required under the base contract. This requires not only replication expenses of reworking the books, but also a potentially significant amount of time securing the necessary new information and graphic representations.
- **Revised and/or additional testing.** New items required by the change may have different testing requirements, and may also affect other items, requiring them to be tested differently or repetitively. A particular hazard is the coordination of over-current interrupting capacities.

- **Revising and/or updating project schedules.** For both contractual and project management reasons, schedules must be revised for significant changes. Even if time delays are not given, the work must flow and must be reconfigured. Someone on the contractor's payroll will be required to perform this coordination and rescheduling. On a complex project, this task may require multiple conversations with field personnel, transferring information back and forth, which is very expensive.
- **Processing revised shop drawings.** If there are changes in specified materials, submittals and shop drawings required under the base contract may have to be modified and expanded.
- **Additional rental expenses for tools.** For example, a second conduit bender may be required to do both the change and the base contract work concurrently. Extra lifts may be required, etc.
- **Additional rental expenses for equipment.** Cranes, lifts and similar items may have to be left on the site longer than originally planned, or will have to be returned to the site. This may result in not only time charges, but in mobilization costs as well.
- **Additional safety costs.** Not only are safety equipment costs significant, but safety training may be necessary as well. These expenses are related to the extra workers who are required for the most change orders, as most changes are performed concurrent with the base contract, not consecutive to it.
- **Freight charges on rushed material orders.** "Hurry-up" items necessary for changes may not meet freight minimums, may not be available in time, or may require the contractor to send a man and a truck to pick it up. All of these situations result in extra costs.
- **Restocking and return freight charges for credited items.** Changes in the work may render some materials ordered under the base contract unnecessary. In these cases, the materials may be returned to the supplier for only partial credit due to restocking and/or freight charges.
- **Extended warrantee exposure.** Changes often involve equipment that has been placed in service prior to the beginning of the contractor's warrantee period. Unless the manufacturer's warrantee is longer than the contractor's warrantee, the contractor has a liability exposure for this warrantee period. For example, a switchgear manufacturer will typically guarantee equipment one year from date of energizing. The contractor's warrantee, however, is one year from date of acceptance, which may be months after the initial energizing. If the equipment fails during this gap, the contractor will have to replace the equipment at his or her own expense. Change orders can greatly increase the contractor's exposure to these risks.
- **Additional financing on extended retainage.** If a project, the closeout of a project, or the final payment on a project is delayed due to changes, the contractor will have to wait for the final retainage payment. Thus the contractor is forced to finance this dollar amount for an extended period of time. The cost of money is significant, whether borrowed from one's self or from others. Depending on the contract terms, a change order that increases the total amount of a contract may also be subject to retainage, therefore, the amount of total retainage on the project is increased.
- **Extra bond, permit, tax, and insurance costs.** On a bonded project, a fee must be paid to increase the amount of coverage due to the increased contract amount.
- **Additional non-working foremen.** If a change increases the necessary workforce beyond a certain limit, additional non-working personnel may be required.
- **Reductions in the quality of the workforce.** New electricians hired to rush the work are almost never up to the efficiency of the contractor's continuing workforce. This not only reduces the productivity immediately, but due to decreased morale reduces long-term productivity.

It is important to note that all of these items are prime costs to the electrical contractor. None of these items are covered in the contractor's standard overhead percentages. These are purely job-related impacts.

It is strongly recommended that you use a copy of the following **Change Order Costs Form** for each change order you estimate. If you hope to recover these very significant costs, you will most certainly have to document them.

## Change Orders Supplemental Material

Questions regarding change orders are some of the more complex issues that electrical contractors face. When bidding a project, the contractor should check the contract documents to see what requirements are given regarding the change orders. Usually, these requirements will be very detailed.

One of the first things that will usually be specified is the percentages of mark-up that will be allowed on changes. In most contracts these percentages are very low and the contractor will lose money doing change orders this way.

Another primary question is this: What is an extra? As you will often find, you may be required to move several lights, outlets, etc., without ever being able to charge for this work. Carefully research these details, and also the time requirements for them. Contract documents should never require moving items after they have been roughed-in.

A very critical matter regarding changes is contract time extension. *The contractor should be allowed time extensions for substantial or numerous change orders.* If there is no time extension allowed for extra work, the contractor will be in serious danger of paying liquidated damages. It is the owner's prerogative to request extra work, but it is not the contractor's responsibility to do the additional work without the allowance of additional time. A contract is for a certain amount of work (that which is shown in the contract documents) to be performed in a certain amount of time and it is the contractor's responsibility to meet these conditions. If, however, more work is added to the original contract, the contractor should be entitled to more time to perform that work. The contractor must make sure that time extensions are a part of significant extras; to fail to do so is to court disaster.

## Change Order Requirements

The requirements covering change orders are of extreme importance, especially if the project looks like it will have numerous changes. (The contractor can usually count on numerous changes if there are incomplete plans, large numbers of addenda, parts of the job that aren't clearly defined, or if there are other gaps in the design.) The following questions need to be answered:

- Who has the authority to issue change orders?
- Do change orders need to be put in writing?
- How will payment for change orders be handled?
- Who approves payment?
- How do you verify extensions of time for changes?
- What percentages of overhead and profit can you charge?
- Do you need signed work tickets to verify the labor hours?
- Will you have to submit copies of invoices to verify your material costs?

Make sure all of these questions are answered; every one of them is very important to the profitability of the project. There can be a great deal of money contained in change orders; and probably more money is lost by contractors in disallowed change orders than by any other means. Protect profits by making sure all of these questions are clearly answered. To do otherwise can be disastrous. Be very cautious about change order requirements. Clarity in this part of your contract is can pay dividends in the overall performance of the project.

## Change Order Costs Form

Cost*	Amount	Notes
Additional management time		
Redirecting the workforce		
Incorrect installation based on untimely information		
Finance costs on extra cash flow		
Compressed job schedule		
Extended overhead costs		
Additional estimating costs		
Updating as-built drawings		
Updating operating and maintenance manuals		
Revised or additional testing		
Revising and/or updating CPM and other schedules		
Processing revised shop drawings		
Additional rental expenses for tools		
Additional rental expenses for equipment		
Additional safety costs		
Freight charges on rushed material orders		
Restocking and return freight charges for credited items		
Extended warranty exposure		
Additional financing on extended retainage		
Extra bond, permit, tax, and insurance costs		
Additional non-working foreman		
Reductions in the quality of the workforce		
<b>TOTAL</b>		

\*This list is not to be construed as complete and should be modified as needed per project.

The best way to argue these pitfalls is to prepare an accurate change order estimate with the real costs itemized in detail and accompanying documentation outlining these costs. Through the use of the charts and information in this manual you can strengthen your negotiating position and a pre-construction change order meeting should help you recover these hidden costs associated with change orders.

Several publications are available to provide additional information on change orders and are included Appendix G.

## APPENDIX D: ESTIMATING THE COST OF SUPERVISION

The labor units in this manual **do not** include any labor for supervision of any type. All electrical construction requires more than one level of supervision, and the magnitude of supervision depends on the complexity, type, and size of each project. In addition, many labor agreements include special requirements related to supervision. Because each project is unique, it is the opinion of most electrical contractors that the labor for supervision is best estimated as a separate cost item and that no part of the supervision labor be included in the material installation labor units.

For estimating, accounting and cost control purposes, the direct and indirect costs of supervision are usually separated into home office supervision costs and field supervision costs.

- **Home Office Supervision Costs** – These direct (payroll) costs and indirect (fringe benefits, insurance, taxes, etc.) costs are usually included in the cost category of home office overhead. The owner’s salary is usually not included in the home office supervision category, but other salaried employees such as project managers are included when they supervise more than one project simultaneously. When an electrical contractor’s project manager supervises only one project, these direct and indirect supervision costs are more appropriately included in the field supervision cost category.
- **Field Supervision Costs** – These direct and indirect costs are usually separated into two separate categories for ease of calculations:
  - **Salaried Supervision Costs.** These direct and indirect costs include all supervisory personnel assigned full time to a single project whose pay is based on an annual salary.
  - **Non-Salaried Supervision Costs.** These direct and indirect costs include all supervisory personnel assigned full time to a single project whose pay is based on an hourly wage rate.

The calculation of supervisory costs is usually accomplished by the multiplication of each supervisor’s cost per hour, day, week or month and the quantity of the time required.

The most frequent area of dispute is in change order cost negotiations. Owners are often reluctant to allow supervisory costs in the estimating of change order costs. The owner’s reluctance is usually based on the incorrect assumption that the electrical contractor’s supervisory personnel are already on the construction site and that their costs were already included in the original contract price. This is an incorrect assumption because each change, whether an add-on change order or a deduct change order, will require additional supervisory labor to examine, estimate the cost or credit, administrate, document, complete the change (if approved), and other requirements of the supervisor’s time as a direct result of any change order. The supervisor’s labor spent on change orders is not included in the scope of work defined in the bid contract documents, and therefore the electrical contractor is clearly entitled to additional reimbursement for the supervisory labor regardless of the change order being approved or rejected.

In the interest of expediency and fair play, many electrical contractors negotiate fixed rates for supervision, overhead and profit for all change orders shortly after each construction contract is awarded or at the time that the first change order is presented. One of the many advantages of this early settlement of future change order cost calculations is that they are resolved before an uncooperative or antagonistic relationship can develop.

## APPENDIX E: SUGGESTED LABOR FACTOR PERCENTAGE TO USE WITH MULTIPLE RUNS

Labor Factor Description	Raceway	Support Channel and Fittings	Pull Boxes	Wire
Parallel 2 Runs @ 10'	90	90	100	90
Parallel 4 Runs @ 10'	80	80	100	85
Parallel 6 Runs @ 10'	78	78	100	80
Parallel 8 Runs @ 10'	76	76	100	75
Parallel 10 Runs @ 10'	75	75	100	70
Parallel 2 Runs @ 15'	96	96	110	90
Parallel 4 Runs @ 15'	90	90	110	85
Parallel 6 Runs @ 15'	86	86	110	80
Parallel 8 Runs @ 15'	84	84	110	75
Parallel 10 Runs @ 15'	82	82	110	70
Parallel 2 Runs @ 20'	113	113	125	90
Parallel 4 Runs @ 20'	100	100	125	85
Parallel 6 Runs @ 20'	98	98	125	80
Parallel 8 Runs @ 20'	95	95	125	75
Parallel 10 Runs @ 20'	94	94	125	70
Parallel 2 Runs @ 25'	117	117	130	90
Parallel 4 Runs @ 25'	104	104	130	85
Parallel 6 Runs @ 25'	101	101	130	80
Parallel 8 Runs @ 25'	98	98	130	75
Parallel 10 Runs @ 25'	96	96	130	70
Parallel 2 Runs @ 30'	126	126	140	90
Parallel 4 Runs @ 30'	112	112	140	85
Parallel 6 Runs @ 30'	109	109	140	80
Parallel 8 Runs @ 30'	106	106	140	75
Parallel 10 Runs @ 30'	104	104	140	70
Parallel 2 Runs @ 40'	135	135	150	90
Parallel 4 Runs @ 40'	120	120	150	85
Parallel 6 Runs @ 40'	117	117	150	80
Parallel 8 Runs @ 40'	114	114	150	75
Parallel 10 Runs @ 40'	111	111	150	70

Note: The above table does not take into account specific jobsite conditions, ease of access to installation location, hanging or strapping material, congestion of work area, conflict with other trades, and other items that may impact overall crew productivity. The table also assumes the parallel runs are like type and size of material.

R

Table courtesy of AccuBid



# APPENDIX F: EQUIPMENT STARTUP CHECKLIST RESOURCES

The *National Electrical Installation Standards (NEIS)* are the first and only quality and performance standards for electrical construction. Developed by NECA, in partnership with several industry organizations, these standards clearly define the actions needed to perform an installation in a “neat and workmanlike manner,” as often referenced in the National Electrical Code (NEC).

The following publications represent a sample of the *NEIS* available and all can be viewed at [www.neca-neis.org](http://www.neca-neis.org) or purchased through the NECA Store at [www.necanet.org/store](http://www.necanet.org/store) or by emailing [orderdesk@necanet.org](mailto:orderdesk@necanet.org) or calling (301) 215-4504.

<b>Title</b>	<b>NECA Index Number</b>
Recommended Practice for Commissioning Building Electrical Systems	NECA90-09
Standard for Installing and Maintaining Switchboards	NECA400-07
Standard for Installing and Maintaining Motor Control Centers	NECA402-14

## APPENDIX G: ADDITIONAL NECA RESOURCES

The following publications, referenced throughout the *Manual of Labor Units*, are available through the NECA Store at [www.necanet.org/store](http://www.necanet.org/store) or by emailing [orderdesk@necanet.org](mailto:orderdesk@necanet.org) or calling (301) 215-4504.

<b>Title</b>	<b>NECA Index Number</b>
Change Order Guidelines for Electrical and Low Voltage Contractors	F3405a
The Effect of Multi-Story Buildings on Productivity	5071-04
The Effect of Temperature on Productivity	5072-04
Factors Affecting Labor Productivity for Electrical Contractors	F3000(R-07)
Impact of Change Orders on Labor Efficiency for Electrical Construction	F9901
Impact of Overtime on Electrical Labor Productivity: A Measured Mile Approach	F3101
Rate of Manpower Consumption	5075-04
Normal Project Duration	5076-04
Project Peak Workforce	5074-04
Quantifying the Cumulative Impact of Change Orders for Electrical Contractors	F2004

## Index

"C" Compression Ground Tap Connector	8-10
1.5MW Fuel Cell CHP Generator	14-7
1/C 600 Volt Alum Polyethylene Cable on Poles	11-17
1/C 600 Volt Copper Polyethylene Cable on Pole	11-17
1/C ACSR Cable - Bare or Insulated	11-33
1/C ACSR Cable on Outdoor Poles	11-17
1/C Bare Copper Cable On Outdoor Poles	11-17
1/C Copper or Aluminum Cable - Bare or Insulated	11-32
1/C Hand Wrapped Stress Relief Cones 15KV	3-28
1/C Hand Wrapped Stress Relief Cones 25KV	3-28
1/C Hand Wrapped Stress Relief Cones 5KV	3-27
1/C Heat Shrink & Premolded Shielded Cable Splices - 15KV	3-33
1/C Heat Shrink & Premolded Shielded Cable Splices - 25KV	3-33
1/C Heat Shrink & Premolded Shielded Cable Splices - 5KV	3-33
1/C Power Terminations on Transformers - 600 Volt Copper Cable	11-35
1/C Shielded Cable Splices-15KV Cold Shrink	3-32
1/C Shielded Cable Splices-25KV Cold Shrink	3-32
1/C Shielded Cables Splices-5KV Cold Shrink	3-32
100 Ft Extension Cord	10-6
100KW Fuel Cell Generator	14-7
125 Volt and 250 Volt Unit Heaters with Blowers	9-7
125 Volt Duct Heaters	9-6
15KV Aluminum Cable Pulled Into Buried Conduit	11-28
15KV Copper Cable Pulled Into Buried Conduit	11-28
15KV Direct Burial Aluminum Cable	11-26
15KV Direct Burial Copper Cable	11-26
15KV Interlocked Armored Cable - 3/C Shielded - Aluminum Conductors	3-21
15KV Interlocked Armored Cable - 3/C Shielded - Copper Conductors	3-21
15KV Loadbreak Cable Elbows	3-31
15KV Porcelain Terminators	3-27
15KV Power Cable-1/C Shielded - Copper - XLP - PVC Jacketed	3-12
15KV Power Cable-3/C-w/o ground Shielded - Copper - XLP PVC Jacketed	3-13
15KV Single Conductor Potheads	3-29
15KV Three Conductor Potheads	3-30
15KV Two Conductor Potheads	3-30
1800 RPM Motor Mounting	12-5
1-Pole Circuit Breakers with Spin Top Covers	7-8
2 Conductor + Ground - 600V Phase Wire Size	12-6
2 Conductor + Ground - 600V Phase Wire Size	12-7
2 Conductor + Ground - 600V Phase Wire Size	12-7
2 Pole Ltg & Motor Busway up to 240 Volt	3-35
2/C Armored Cable Terminators - Weatherproof - Gland Type	3-26
2/C Armored Cable to Conduit Terminators - Compound Filled	3-27
2/C Armored Sheathed - Cable Terminators With Sealing Bushing	3-24
2/C Duplex Secondary Cable	11-33
2/C Jacketed Cable to Conduit Terminators - Compound Filled	3-25
2/C Jacketed Cable to Conduit Terminators With Sealing Bushings	3-24
2/C Sheathed Armored Cable Terminators - Compound Filled	3-26
2/C Wire Armored Cable Terminators - Compound Filled	3-25
208 & 240 Volt 3 Phase Power Capacitors	4-30
240 Volt Portable Electric Heaters	10-8
240/120 Volt Meter Socket	4-26
250 Volt Duct Heaters	9-7
25KV 1/C Direct Burial Aluminum Cable w/ Concentric Neutral Pulled Into Buried Conduit	11-28
25KV 1/C Direct Burial Aluminum Cable w/ Concentric Wire Neutral	11-26
25KV 1/C Direct Burial Copper Cable w/ Concentric Neutral Pulled Into Buried Conduit	11-28
25KV 1/C Direct Burial Copper Cable w/ Concentric Wire Neutral	11-26
25KV Loadbreak Cable Elbows	3-31

## Index

25KV Porcelain Terminators	3-27
25KV Single Conductor Potheads	3-30
25KV Three Conductor Potheads	3-31
25KV Two Conductor Potheads	3-30
2-Hub Round Junction Boxes	7-6
2-Pole Circuit Breakers with Spin Top Covers	7-8
2-Pole Trolleys	3-36
2x12 Vert Planks Both Sides & Two Steel Trench Jacks or Two 4 x 4 Wood Braces	11-20
2x12's Laid Horiz. Both Sides - 2x8 Vert Planks & Steel Trench Jacks	11-20
3 1/4" x 1 1/4" Flushduct	2-55
3 conductor + Ground - 5KV Phase Wire Size	12-6
3 conductor + Ground - 5KV Phase Wire Size	12-7
3 conductor + Ground - 5KV Phase Wire Size	12-8
3 Conductor + Ground - 600V Phase Wire Size	12-6
3 Conductor + Ground - 600V Phase Wire Size	12-7
3 Conductor + Ground - 600V Phase Wire Size	12-8
3 Phase 3P Bus Duct-Fire & Weather Stops	3-43
3 Phase 3P Bus Duct-Wall & Floor Flanges	3-42
3 Phase 3P Copper Bus Duct Plug-In Type	3-37
3 Phase 3P Copper Bus Duct-Cable Tap Boxes	3-38
3 Phase 3P Copper Bus Duct-Crosses	3-37
3 Phase 3P Copper Bus Duct-Elbows	3-37
3 Phase 3P Copper Bus Duct-End Closures	3-38
3 Phase 3P Copper Bus Duct-Expansion Fittings	3-38
3 Phase 3P Copper Bus Duct-Feeder Type	3-40
3 Phase 3P Copper Bus Duct-Offset Elbows	3-38
3 Phase 3P Copper Bus Duct-Offset Fittings	3-37
3 Phase 3P Copper Bus Duct-Panelboard Fittings	3-38
3 Phase 3P Copper Bus Duct-Tees	3-37
3 Phase 3P Copper Bus Duct-Transformer Fittings	3-39
3 Phase 3P Copper Bus Duct-Unfused Reducers	3-38
3 Phase 3P Feeder Bus Duct-Cable Tap Boxes	3-42
3 Phase 3P Feeder Bus Duct-Cross Fittings	3-41
3 Phase 3P Feeder Bus Duct-Elbows	3-40
3 Phase 3P Feeder Bus Duct-End Closures	3-42
3 Phase 3P Feeder Bus Duct-Expansion Fittings	3-41
3 Phase 3P Feeder Bus Duct-Offset Elbows	3-41
3 Phase 3P Feeder Bus Duct-Offset Fittings	3-41
3 Phase 3P Feeder Bus Duct-Panelboard Fittings	3-42
3 Phase 3P Feeder Bus Duct-Tee Fittings	3-41
3 Phase 3P Feeder Bus Duct-Transformer Fittings	3-42
3 Phase 3P Feeder Bus Duct-Unfused Reducers	3-41
3 Pole Ltg & Motor Busway up to 480 Volt	3-35
3" Deep Concrete Bedding in Trenches	11-21
3" Deep Sand Bedding in Trenches	11-21
3.0MW Fuel Cell CHP Generator	14-7
3/4" Perforated Grounding Strap with Compression Lugs	8-7
3/4" Plywood Both Sizes - 2x8 Vert Planks & Steel Trench Jacks	11-20
3/4" Plywood Forms for Duct Bank Concrete Encasement - Forms on Both Sides	11-21
3/4" Plywood Forms for Duct Bank Concrete Encasement - One Side Only	11-21
3/4" Plywood Shoring Both Sides & Steel Trench Jacks Bracing	11-20
3/C 600 Volt Alum Primary Cable with Messenger Wire Support	11-18
3/C 600 Volt Copper Primary Cable with Messenger Wire Support	11-18
3/C Armored Cable Terminators - Weatherproof - Gland Type	3-26
3/C Armored Cable to Conduit Terminators - Compound Filled	3-27
3/C Armored Sheathed - Cable Terminators With Sealing Bushing	3-24
3/C Cable Splices-15KV Cold Shrink	3-32
3/C Cable Splices-25KV Cold Shrink	3-33

## Index

3/C Cable Splices-5KV Cold Shrink	3-32
3/C Hand Wrapped Stress Relief Cones 15KV	3-28
3/C Hand Wrapped Stress Relief Cones 25KV	3-28
3/C Hand Wrapped Stress Relief Cones 5KV	3-28
3/C Heat Shrink Cable Splices - 15KV	(Updated) 3-34
3/C Heat Shrink Cable Splices - 25KV	3-34
3/C Heat Shrink Cable Splices - 5KV	3-33
3/C I.A.C. Splices-15KV-Compound Filled	3-35
3/C I.A.C. Splices-5KV-Compound Filled	3-35
3/C Interlocked Armored Cable Splices 15KV	3-34
3/C Interlocked Armored Cable Splices 25KV	3-34
3/C Interlocked Armored Cable Splices-5KV	3-34
3/C Jacketed Cable to Conduit Terminators - Compound Filled	3-25
3/C Jacketed Cable to Conduit Terminators With Sealing Bushings	3-25
3/C Sheathed Armored Cable Terminators - Compound Filled	3-26
3/C Triplex Secondary Cable	11-32
3/C Wire Armored Cable Terminators - Compound Filled	3-25
300 Volt Service Entrance Cable - Type SEU 3/C Aluminum Conductors	3-21
300 Volt Service Entrance Cable - Type SEU 3/C Copper Conductors	3-21
300 Volt Solid Connector Plenum Cable	3-17
300KW Fuel Cell CHP Generator	14-7
35KV 1/C Direct Burial Aluminum Cable w/ Concentric Neutral Pulled Into Buried Conduit	11-29
35KV 1/C Direct Burial Aluminum Cable w/ Concentric Wire Neutral	11-27
35KV 1/C Direct Burial Copper Cable w/ Concentric Neutral Pulled Into Buried Conduit	11-29
35KV 1/C Direct Burial Copper Cable w/ Concentric Wire Neutral	11-27
3-Cell Duct Support & Couplings	2-54
3-Cell Elbows	2-54
3-Cell Junction Boxes	2-54
3-Hub Round Junction Boxes	7-6
3-Pole Circuit Breakers with Spin Top Covers	7-8
3-Pole Trolleys	3-36
3-Section Prefabricated Concrete Manholes	11-30
4/C Armored Cable Terminators - Weatherproof - Gland Type	3-26
4/C Armored Cable to Conduit Terminators - Compound Filled	3-27
4/C Armored Sheathed - Cable Terminators With Sealing Bushing	3-24
4/C Jacketed Cable to Conduit Terminators - Compound Filled	3-25
4/C Jacketed Cable to Conduit Terminators With Sealing Bushings	3-25
4/C Sheathed Armored Cable Terminators - Compound Filled	3-26
4/C Wire Armored Cable Terminators - Compound Filled	3-26
48" Vaportite Fluorescent Fixtures	10-8
48" Weatherproof Fluorescent Fixtures	10-8
480 & 600 Volt 3 Phase Power Capacitors	4-31
5-15KV Single Phase Pole Mounted Oil Switches	11-18
5-15KV Three Phase Pole Mounted Oil Switches	11-18
5KV Aluminum Cable Pulled Into Buried Conduit	11-28
5KV Copper Cable Pulled Into Buried Conduit	11-27
5KV Direct Burial Aluminum Cable	11-26
5KV Direct Burial Copper Cable	11-25
5KV Interlocked Armored Cable 3/C Aluminum	3-20
5KV Interlocked Armored Cable 3/C Copper	3-20
5KV Porcelain Terminators	3-27
5KV Power Cable-3/C-w/o Ground Shielded Copper - XLP - PVC Jacketed	3-12
5KV Power Cable-3/C-with Ground Shielded - Copper - XLP - PVC Jacketed	3-12
5KV Power Cable-Shielded-1/C Copper - XLP Insulated - PVC Jacketed	3-12
5KV Power Cable-Unshielded-1/C Copper - XLP Insulated - PVC Jacketed	3-11
5KV Single Conductor Potheads	3-29
5KV Three Conductor Potheads	3-30
5KV Two Conductor Potheads	3-30

## Index

600 Amp Sectional Switches, Pad Mounted, Outdoor Type Up to 15 KV Primary	<b>(Updated)</b>	11-19
600 Volt AC Cable with Alum. or Steel Armor - Copper		3-13
600 Volt Aluminum Cable Pulled Into Buried Conduit		11-27
600 Volt Bldg Wire-1/C-Copper Type RHW-Use		3-7
600 Volt Bldg Wire-1/C-Copper Type THHN & THWN		3-7
600 Volt Copper Cable Pulled Into Buried Conduit		11-27
600 Volt Direct Burial Aluminum Cable		11-25
600 Volt Direct Burial Copper Cable		11-25
600 Volt Fixture Wire-1/C-Copper Type TF, TFF, TFN, & TFFN		3-10
600 Volt High Temp Wire-1/C Copper-Type XHHW		3-10
600 Volt High Temp Wire-1/C-Copper Type XHHW		3-7
600 Volt Interlocked Armor Cable 3/C Copper		3-20
600 Volt Interlocked Armored Cable 3/C Aluminum		3-20
600 Volt MC Cable - Homerun Cables - Copper		3-13
600 Volt MC Cable with Alum. or Steel Armor - Copper		3-13
600 Volt Mineral Insulated Cable Terminators		3-16
600 Volt Mineral Insulated Cable Type MI Non-Heating		3-16
600 Volt Non-Metallic Sheathed Cable Copper - Type NM and UF w/o Ground		3-15
600 Volt Non-Metallic Sheathed Cable Copper - Type NM and UF with Ground		3-16
600 Volt Power Cable-3/C-Copper Cross Linked Poly Ins PVC Jack w/o Gnd		3-10
600 Volt Power Cable-4/C-Copper Cross Linked Poly Ins PVC Jacketed w Gnd		3-10
600 Volt Power Cable-Multi Conductor Stranded Copper - XLP Insulated		3-11
600 Volt Power Cable-Type USE RHW Insulation Copper		3-10
600 Volt Service Entrance Cable - Type SER 3/C Aluminum Conductors		3-21
600 Volt Service Entrance Cable - Type SER 3/C Copper Conductors		3-21
600 Volt Service Entrance Cable - Type SER 4/C Copper Conductors		3-22
600 Volt Stranded Copper Control Cable		3-17
600 Volt Tape Wrapped Cable Splices 1/C		3-31
600 Volt Tape Wrapped Cable Splices 2/C		3-31
600 Volt Tape Wrapped Cable Splices 3/C		3-31
600 Volt Type FCC Flat Under Carpet Wiring Junction Box		3-18
600 Volt Type S-SJ-SO Flexible Cord		3-19
600 Volt Type TC Copper Tray Cable THHN		3-19
600-1200 Amp Pad Mounted Switchgear, Outdoor Type Up to 15 KV Primary	<b>(Updated)</b>	11-19
8" Thick Concrete Foundation For Manholes		11-29
Access Control		1-9
Access Control - Misc. Items		1-9
Access Field Devices		1-9
Accessories		4-40
Add For Pole Set In Sidewalk or Pavement		11-31
Addressable Control Panels - Modules Mounted in Control Panel		1-7
Adhesive Cable Holder		8-11
Adhesive Point Base		8-13
Adjustable Base Plates for Motor Mounting		12-5
Adjustable Ring Hangers		2-94
Aircraft Lighted Guide Signs		11-13
Airport Runway Lighting-200 Watt HID		11-13
AL Bus Bar		8-10
AL Flat Conductor		8-11
AL Flexible Braid Conductor		8-6
AL Flexible Braid Conductor		8-6
AL Points		8-12
AL Rod Conductor		8-6
Alley Braces 5' to 7' Long		11-17
Alternative Energy, Data Acquisition Systems (DAS)		14-5
Aluminum - 45 Degree Elbow - 3" Depth		2-65
Aluminum - 45 Degree Elbow - 4" Depth		2-67
Aluminum - 45 Degree Elbow - 6" Depth		2-69

## Index

Aluminum - 45 Degree Elbow - Solid Covers	2-71
Aluminum - 90 Degree Elbow - 3" Depth	2-65
Aluminum - 90 Degree Elbow - 4" Depth	2-67
Aluminum - 90 Degree Elbow - 6" Depth	2-69
Aluminum - 90 Degree Elbow - Solid Covers	2-71
Aluminum - Cross - 3" Depth	2-65
Aluminum - Cross - 6" Depth	2-69
Aluminum - Cross - Solid Covers	2-71
Aluminum - Enclosure Connectors	2-72
Aluminum - End Plates	2-72
Aluminum - Ladder Drop-Outs	2-72
Aluminum - Reducer - 3" Depth	2-65
Aluminum - Reducer - 4" Depth	2-68
Aluminum - Reducer - 6" Depth	2-70
Aluminum - Reducer - Solid Covers	2-71
Aluminum - Splice Plates Pair	2-72
Aluminum - Tee - 3" Depth	2-65
Aluminum - Tee - 4" Depth	2-67
Aluminum - Tee - 6" Depth	2-69
Aluminum - Tee - Solid Covers	2-71
Aluminum - Vertical 45 Degree Elbow - 3" Depth	2-66
Aluminum - Vertical 45 Degree Elbow - 4" Depth	2-68
Aluminum - Vertical 45 Degree Elbow - 6" Depth	2-70
Aluminum - Vertical 45 Degree Elbow - Solid Covers	2-71
Aluminum - Vertical 90 Degree Elbow - 3" Depth	2-66
Aluminum - Vertical 90 Degree Elbow - 4" Depth	2-68
Aluminum - Vertical 90 Degree Elbow - 6" Depth	2-70
Aluminum - Vertical 90 Degree Elbow - Solid Covers	2-72
Aluminum - Vertical Tee - 3" Depth	2-66
Aluminum - Vertical Tee - 4" Depth	2-68
Aluminum - Vertical Tee - 6" Depth	2-70
Aluminum - Vertical Tee - Solid Covers	2-72
Aluminum Cable Tray - Solid Cover Clamps (Per Pair)	2-71
Aluminum Cable Tray - Solid Covers	2-71
Aluminum Cable Tray Barrier Strips	2-72
Aluminum Cable Tray Fitting Barrier Strips	2-72
Aluminum Cable Tray Fittings & Accessories	2-71
Aluminum Chase Nipples	2-27
Aluminum Compression Couplings	2-27
Aluminum Conductor Armor Rods	11-33
Aluminum Conduit To Cable Tray Adapters	2-72
Aluminum- Cross - 4" Depth	2-67
Aluminum Erickson Couplings	2-28
Aluminum Expansion Couplings	2-28
Aluminum Factory Cut Nipples	2-27
Aluminum Female Threaded Reducers	2-27
Aluminum Field Cut Nipples and Installation	2-27
Aluminum Flex	12-7
Aluminum FS & FD Threaded 1-Gang Boxes	2-30
Aluminum FS & FD Threaded 2-Gang Boxes	2-30
Aluminum Ladder Cable Tray - 12" Rung Spacing - 3" Depth	2-65
Aluminum Ladder Cable Tray - 12" Rung Spacing - 4" Depth	2-67
Aluminum Ladder Cable Tray - 12" Rung Spacing - 6" Depth	2-69
Aluminum Ladder Cable Tray - 18" Rung Spacing - 3" Depth	2-65
Aluminum Ladder Cable Tray - 18" Rung Spacing - 4" Depth	2-67
Aluminum Ladder Cable Tray - 18" Rung Spacing - 6" Depth	2-69
Aluminum Ladder Cable Tray - 6" Rung Spacing - 3" Depth	2-65
Aluminum Ladder Cable Tray - 6" Rung Spacing - 4" Depth	2-67

## Index

Aluminum Ladder Cable Tray - 6" Rung Spacing - 6" Depth	2-69
Aluminum Ladder Cable Tray - 9" Rung Spacing - 3" Depth	2-65
Aluminum Ladder Cable Tray - 9" Rung Spacing - 4" Depth	2-67
Aluminum Ladder Cable Tray - 9" Rung Spacing - 6" Depth	2-69
Aluminum Lock Nut & Bushing Sets	2-26
Aluminum Lock Nut & Ground Bushing Sets	2-26
Aluminum Mogul Conduit Bodies-Three Hubs	2-30
Aluminum Mogul Conduit Bodies-Two Hubs	2-29
Aluminum Offset Nipples	2-27
Aluminum Pipe Caps or Capped Bushings	2-29
Aluminum Split Couplings	2-28
Aluminum Threaded Capped Elbows	2-29
Aluminum Threaded Conduit Bodies-Four Hubs	2-29
Aluminum Threaded Conduit Bodies-One Hub	2-29
Aluminum Threaded Conduit Bodies-Three Hubs	2-29
Aluminum Threaded Conduit Bodies-Two Hubs	2-29
Aluminum Threaded Entrance Elbows	2-28
Aluminum Threaded Service Entrance Caps	2-28
Aluminum Threadless Box Connectors	2-28
Aluminum Tray 3" Depth	2-65
Aluminum Tray 4" Depth	2-67
Aluminum Tray 6" Depth	2-69
Anchor Bolts (Set of 4) With Template	11-11
Anchor Bolts Set in Concrete	2-92
Apt & Comm WP Svc - 3-Wire Solid Neutral Meter Center Modules w/ Main CB or Main Disc. Switch	11-36
Apt & Comm WP Svc - Single Phase 125 Amp Meter Socket Modules	11-37
Apt & Comm WP Svc - Three Phase 125 Amp Meter Socket Modules	11-37
Arresters	11-34
Attenuator Barrels	<b>(Updated)</b> 11-47
Attenuator Truck	11-47
Audio Visual	1-11
Audio Visual Systems - Interface Devices	1-13
Audio Visual Systems - Miscellaneous	1-13
Audio Visual Systems - Patching	1-13
Audio Visual Systems - Playback	1-13
Audio Visual Systems - Programming and Switching	1-13
Audio Visual Systems - Remote Control	1-13
Audio Visual Systems - Roll Down Screens	1-13
Audio Visual Systems - Source Equipment	1-12
Audio Visual Systems - Teleconference	1-13
Automatic Transfer & Bypass Isolation Switches: Drawout Type 3 Pole 600 Volt	4-33
Automatic Transfer & Bypass Isolation Switches: Drawout Type 4 Pole 600 Volt	4-33
Automatic Transfer Switch: Enclosed - 600 Volt 2 Pole Double Throw Wall Mounted	4-32
Automatic Transfer Switch: Enclosed - 600 Volt 3 Pole Double Throw Wall Mounted	4-32
Automatic Transfer Switch: Enclosed - 600 Volt 4 Pole Double Throw Wall Mounted	4-32
Auxiliary Contacts NO/NC	4-15
Backfill & Compaction of Trenches	11-21
Bare and Insulated Copper Grounding Conductors - Indoors - Exposed or In Cable Trays	8-5
Bare Copper Grounding Conductors	11-16
Bare Copper Grounding Conductors - Buried - Outdoors	8-5
Bare Copper Grounding up to Wire-6 Ft Long	10-6
Barrel Holes - Per Pole	11-31
Barricade Horse	<b>(Updated)</b> 11-47
Barricade Lights	<b>(Updated)</b> 11-47
Baseboard Heaters	9-5
Baseboard Section - Electrical Accys	9-5
Basket Type Wire Tray-Steel	2-91
Battery Spacesaver System	4-40



## Index

Beam Clamps		2-95
Bio-Degradable Erosion Control Mat	<b>(Updated)</b>	11-48
Blank Baseboard Section		9-5
Bloom Energy Fuel Cell		14-7
Bollard Lights 36 Inch High (Round or Square)		5-14
Bollard Lights 42 Inch High (Round or Square)	<b>(Updated)</b>	5-14
Bolt, Washer, and Nut		2-96
Bolt-On Fuse 600 Volt		4-10
Bolt-On Fuse 600V		4-19
Bolt-On Fuse 600V		4-24
Bond Existing Overhead Guy		11-32
Bonding Jumpers		2-64
Bonding Jumpers		2-72
Bonding Jumpers		2-85
Bonding Jumpers		2-90
Bonding Lug		8-11
Bonding Plates		8-11
Box Connected Pigtail, Lamp & Guard		10-7
Bracket Mount - Wall Mounted		5-10
Brackets For Cluster Mounted Transformers		11-35
Braided Copper Bonding Jumpers		8-8
Breather/Drain Fittings		7-5
Bus Duct 3P4W Fusible Switches		3-40
Bus Duct-2P2W Fusible Switches		3-39
Bus Duct-2P2W Molded Case Circuit Breakers		3-40
Bus Duct-2P2W Nonfusible Switches		3-39
Bus Duct-2P3W Fusible Switches		3-39
Bus Duct-2P3W Molded Case Circuit Breakers		3-40
Bus Duct-2P3W Nonfusible Switches		3-39
Bus Duct-3P3W Fusible Switches		3-40
Bus Duct-3P3W Molded Case Circuit Breakers		3-40
Bus Duct-3P3W Nonfusible Switches		3-39
Bus Duct-3P4W Nonfusible Switches		3-39
Busway Center Power Feeds		3-36
Busway End Power Feeds		3-36
Busway Expansion Joints		3-37
Cable Clamps		2-91
Cable Fastener (Masonry)		8-11
Cable Fasteners		8-11
Cable Prep of Fiber - Fanouts		1-19
Cable Prep of Fiber - Gel Filled		1-19
Cable Prep of Fiber - Unfilled		1-19
Cable Protectors CU		8-14
Cable Protectors Galv Steel		8-14
Cable Protectors PVC Pipe		8-14
Cable Protectors Strap Pipe		8-14
Cable Protectors Wood		8-14
Cable Pulleys/Bull Wheels-Setup		2-91
Cable Rollers For Tray Setup		2-91
Cable Splicers		8-11
Cable Supports		1-25
Cable Tray		2-57
Cable Tray Fire Barrier		2-91
Cable Tray Insulator Blocks		2-91
Cable Tray Lay-in Ground Clamp		2-91
Cabling System		1-18
Cadweld Bare Copper Wire To Rebar		8-9
Cadweld To Ground Rod		8-9

## Index

Cast Iron Junction Boxes		2-21
Cathodic Protection	<b>(Updated)</b>	8-15
CCTV Systems - Controllers and Recorders		1-17
Ceiling Fans	<b>(Updated)</b>	5-10
Ceiling Fans - Low Velocity	<b>(Updated)</b>	5-10
Ceiling Mount Electric Vehicle Supply Equipment (EVSE)		14-9
Cellular Trench Duct		2-56
Cellular Underfloor Duct-3 Cell		2-54
Center-R-Rail Spline Cable Tray- Aluminum		2-91
Chandelier - Incandescent or Similar		5-13
Chanel Cable Tray		2-91
Change Ratios on Dual Voltage Transformers		11-35
Channel Type Raceways & Fixture Supports		2-53
Circuit Reclosures		11-18
Clevis Ring Hangers		2-94
Clock		1-10
Clock Systems		1-10
Closed Circuit Television		1-17
Coaxial Cable - Indoor In Conduit PVC / Plenum		1-21
Coaxial Cable - Indoor Not In Conduit PVC / Plenum		1-21
Code Blue Systems		1-14
Coir Wattles	<b>(Updated)</b>	11-48
Cold Shrink Cable Termination with 15KV Stress Cone and Compression Lug		3-29
Cold Shrink Cable Termination with 25KV Stress Cone and Compression Lug		3-29
Cold Shrink Cable Termination with 5KV Stress Cone and Compression Lug		3-29
Colored Lamps In Stage Troughs or Stage Borderlights		5-13
Comb. Point Base		8-13
Combination Hold - Down Clamp and Expansion Guide		2-71
Combination Hold-Down Clamp and Expansion Guide		2-63
Combination Hold-Down Clamp and Expansion Guide		2-79
Commercial & Residential Stations		14-6
Commercial Grade Wall or Cove Mounted	<b>(Updated)</b>	5-7
Commercial Indoor Fixtures - Wall Mounted - Up To 150 Watt	<b>(Updated)</b>	5-8
Complete Guy With Anchor, Rod, Wire & Guard		11-32
Complete Overhead Guy		11-32
Complete Pole Grounding Systems		11-34
Compression Ground Rod with 1ea Tap Connectors		8-9
Compression Ground Rod with 2ea Tap Connectors		8-9
Compression Ground Rod with 3ea Tap Connectors		8-9
Compression Splice Connectors		3-22
Compression Tails - Copper to Aluminum		3-24
Compression Terminal Lugs-Four Hole		3-22
Compression Terminal Lugs-One Hole		3-22
Compression Terminal Lugs-Two Hole		3-22
Computer Equipment		1-15
Computer Equipment		1-15
Computer Equipment - Miscellaneous		1-15
Computer Equipment - Network Devices	<b>(Updated)</b>	1-15
Computer Equipment - Printers		1-15
Computerized Traffic Controller - Modules Wiring Harness Interconnected		11-11
Concrete Anchor Bolts		2-92
Concrete Bases for Bollards:		5-14
Concrete Channel End Plates		2-93
Concrete Channel Inserts		2-93
Concrete Channel Nuts		2-93
Concrete Channel Studs	<b>(Updated)</b>	2-93
Concrete Man Holes Base, Cover and Riser - Excludes Excavation and Gravel Base		11-29
Concrete Pole Installation		11-15

## Index

Concrete Sawing For Loop Detector Wire	11-11
Conductor Attachments	11-32
Conductor Grounding Clamps	8-5
Conductor to Steel - Cadweld	8-9
Conduit and Box Supports	2-94
Conduit Clamps	2-94
Conduit Grounding Bushings or Locknuts	8-5
Conduit Grounding Clamps	8-6
Conduit Grounding Wedges	8-5
Conduit Ring Hangers	2-94
Conduit Riser Clamps	2-94
Conduit Seal Fittings with or without Drain Fittings	7-5
Cone Vent Point Base	8-13
Cones	2-97
Control & Instrument Enclosures 2-Hubs	7-6
Control & Instrument Enclosures 3-Hub	7-6
Control Switch Factory Mounted	4-16
Control Transformer Termination - Factory Mounted in MCC's	4-15
Control Wire Terminations	4-16
Controls	4-38
Copper Cable - STP - PVC / Plenum Indoor In Conduit	1-21
Copper Cable - STP - PVC / Plenum Indoors w/o Conduit	1-21
Copper Cable - UTP - PVC / Plenum Indoor w/o Conduit	1-21
Copper Cable - UTP - PVC / Plenum Indoor In Conduit	1-20
Copper Labeling	1-25
Copper Splice Enclosures	1-22
Copper Termination Hardware	1-22
Copper Testing	1-25
Copperweld	11-33
Copperweld Conductors	11-33
Copperweld Conductors	11-43
Cord Bodies	3-19
Core-Drill Concrete With Lay-out	<b>(Updated)</b> 2-98
Coupling and Adapters for Point AL	<b>(Updated)</b> 8-13
Coupling and Adapters for Point CU	8-14
Crimp Terminations - Ring Type	3-18
Crimp Terminations - Spade Type	3-18
Cross (4 Way) Cadwelds	8-9
Cross Arm Braces 26" to 32" Long	11-17
Cross Arm Pins	11-16
Cross Arms & Pins	11-34
Cross Arms With Braces & Pins	11-32
Cross Connects	1-24
Cross Run Splicer	8-11
CT Cabinets	<b>(Updated)</b> 2-41
CU Bus Bar	8-10
CU Flat Conductor	8-11
CU Flexible Braid Conductor	8-6
CU Points	8-12
CU Rod Conductor	8-6
Custom Made #10 Gage Steel Pull Boxes WxHxD	2-41
Custom Made Steel Pull Boxes	4-9
Cutouts	11-34
Decorative Outdoor Fixture - Wall Mounted	5-13
Decorative Outdoor Fixtures - Pendant or Chain Supported	5-14
Device boxes for 2700/2800/2900	2-46
Device boxes for 400/800/2300 Selected Series	2-47
Device boxes for NM2000	2-47

## Index

Device boxes for PN05A/PN10A series raceways		2-48
Device boxes for PN20A series raceways		2-48
De-Watering Filter Bags	<b>(Updated)</b>	11-48
De-Watering Filter Sock	<b>(Updated)</b>	11-48
De-Watering Tubes	<b>(Updated)</b>	11-48
Dig Poles Holes & Not Used		11-31
Dimmer Switch		6-7
Disconnect Safety Switches - Fused 2-Pole		4-20
Disconnect Safety Switches - Fused 3-Pole		4-20
Disconnect Safety Switches - Fused 4-Pole		4-20
Disconnect Safety Switches - Nonfused 2-Pole		4-20
Disconnect Safety Switches - Nonfused 3-Pole		4-20
Disconnect Safety Switches - Nonfused 4-Pole		4-20
Disconnect Switches		11-34
Double H-Tap Connector		8-10
Double Throw Switches - Maintained Contact 2 Circuit 3 Position		6-7
Double Wooden Cross Arms		11-16
Down Guys		11-32
Drill and Tap for Hubs		7-6
Drill Holes in Steel (up to 1/4" Thick)		2-95
Drill Holes in Wood Stud	<b>(Updated)</b>	2-95
Drive Units - 200 - 550 Volt DC		4-17
Drive Units - Variable Frequency A.C.		4-18
Drop-in Anchors		2-92
Duct End Closures		2-54
Duct Marker Items		2-55
Duplex Receptacle - Straight Blade	<b>(Updated)</b>	6-5
Egress / Emergency Fixtures		5-10
Electric 120 Volt Wall Heaters		9-5
Electric 240 Volt Wall Heaters		9-5
Electric Message Boards	<b>(Updated)</b>	11-47
Electric Snow Melting Mats-12" Wide		9-6
Electric Snow Melting Mats-24" Wide		9-6
Electric Snow Melting Mats-36" Wide		9-6
Electric Snow Melting Mats-48" Wide		9-6
Electric Snow Melting Mats-60" Wide		9-6
Electric Vehicle Charging Stations		14-9
Electrical Metallic Tubing (EMT)	<b>(Updated)</b>	2-22
Electrical Metallic Tubing (EMT) and Fittings		2-22
Electrical Non-Metallic Flexible Tubing (ENT)		2-39
Electrolytic Grd Rod		8-7
Electronic Air Filters-120 Volt		9-7
Electronic Equipment		1-25
Electronic Equipment - Miscellaneous Components - Jacks, Wall Plates		1-16
Electronic Equipment - Miscellaneous Components - Jacks, Wall Plates		1-25
Electronic Equipment - Miscellaneous Components - Meters		1-25
Electronic Equipment - Miscellaneous Components - Power Supplies		1-13
Electronic Equipment - Miscellaneous Components - Speakers		1-13
Electronic Equipment - Miscellaneous Components - Switches		1-25
Electronic Equipment - Miscellaneous Components - Terminals		1-25
Electronically Activated Streamer Emission Air Terminal		8-14
Emergency Generator & 2-Source Auto Transfer Switch in Single Enclosure - 208 Volt Service		4-34
Emergency Generator & 2-Source Auto Transfer Switch in Single Enclosure - 220 Volt Service		4-34
Emergency Generator & 2-Source Auto Transfer Switch in Single Enclosure - 480 Volt Service		4-34
Emergency Generator & 2-Source Auto Transfer Switch in Single Enclosure - 600 Volt Service		4-34
Emergency Generator & 3-Source Auto Transfer Switch in Four Enclosures - 208 Volt Service		4-35
Emergency Generator & 3-Source Auto Transfer Switch in Four Enclosures - 220 Volt Service		4-35
Emergency Generator & 3-Source Auto Transfer Switch in Four Enclosures - 480 Volt Service		4-36

## Index

Emergency Generator & 3-Source Auto Transfer Switch in Four Enclosures - 600 Volt Service	4-36
Emergency Generator & 3-Source Auto Transfer Switch in Two Enclosures - 208 Volt Service	4-35
Emergency Generator & 3-Source Auto Transfer Switch in Two Enclosures - 220 Volt Service	4-35
Emergency Generator & 3-Source Auto Transfer Switch in Two Enclosures - 480 Volt Service	4-35
Emergency Generator & 3-Source Auto Transfer Switch in Two Enclosures - 600 Volt Service	4-35
Emergency Generator Fused 2-Pole Switch Distribution Section in Single Enclosure	4-36
Emergency Generator Fused 3-Pole Switch Distribution Section in Single Enclosure	4-36
Emergency Generator Fused 4-Pole Switch Distribution Section in Single Enclosure	4-36
Emergency Generator Master Control - Single Enclosure	4-37
Emergency Generator Selective Load Transfer Switches in Single Enclosure	4-37
Emergency Lighting Inverter Panels - up to 5000W	5-10
Emergency Power Off System	<b>(Updated)</b> 4-41
Emergency Preemption	11-11
EMT Compression Box Connectors	2-22
EMT Compression Couplings	2-23
EMT Expansion/Deflection Coupling	<b>(Updated)</b> 2-23
EMT Factory Elbows	2-22
EMT Service Elbows	2-23
EMT Service Entrance Caps	2-23
EMT Set Screw Box Connectors	2-22
EMT Set Screw Couplings	2-22
EMT to EMT Reducing Couplings	2-23
EMT to Flexible Conduit Couplings	2-23
EMT to Rigid Conduit Adapters	2-23
Enclosed 600 Volt Overload Relays - NEMA 1 Enclosure 600 Volt	4-24
Enclosed Circuit Breakers, Wall Mounted - 2-Pole (or 1-Pole and Neutral)	4-21
Enclosed Circuit Breakers, Wall Mounted - 3-Pole (or 2-Pole and Neutral)	4-21
Enclosed Circuit Breakers, Wall Mounted - 4-Pole (or 3-Pole and Neutral)	4-21
Enclosed Lighting & Heating Contactors - NEMA 1 Enclosure up to 600 Volt AC	4-24
Enclosed Magnetic Motor Starter, Wall Mounted, Non-Reversing 2-Pole	4-21
Enclosed Magnetic Motor Starter, Wall Mounted, Non-Reversing 3-Pole	4-22
Enclosed Magnetic Motor Starter, Wall Mounted, Non-Reversing 4-Pole	4-22
Enclosed Magnetic Motor Starter, Wall Mounted, Reversing 2-Pole	4-22
Enclosed Magnetic Motor Starter, Wall Mounted, Reversing 3-Pole	4-22
Enclosed Magnetic Motor Starter, Wall Mounted, Reversing 4-Pole	4-22
Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Non-Reversing 2-Pole	4-22
Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Non-Reversing 3-Pole	4-23
Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Non-Reversing 4-Pole	4-23
Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Reversing 2-Pole	4-23
Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Reversing 3-Pole	4-23
Enclosed Multi-Speed Magnetic Motor Starter, Wall Mounted, Reversing 4-Pole	4-23
ENT Box Connectors-Snap In Type	2-39
ENT Box Connectors-Threaded Elbows	2-39
ENT Box Connectors-Threaded Type	2-39
ENT Conduit	2-39
ENT Couplings	2-39
EPO Emergency Power Off Systems	4-39
Equipment	14-7
Equipment Set-Up Labor For Jacking Pipe	11-30
Erection	14-7
Erosion Control Blankets	<b>(Updated)</b> 11-48
Excavation per Vert. Ft.	11-11
Excavation, Backfilling, & Soil Compaction For Manholes	11-29
Exit Fixtures	5-10
Exit Fixtures - Edge Lit	5-10
Exit Sign - Self Powered	5-10
Expansion Shields	2-92
Explosion Proof 2-Wire Safety Switches	7-7

## Index

Explosion Proof 3-Wire Safety Switches	7-8
Explosion Proof 4-Wire Safety Switches	7-8
Explosion Proof Conduit Bodies 2-Hub	7-5
Explosion Proof Conduit Bodies 3-Hub	7-5
Explosion Proof Fixtures: Fluorescent	5-15
Explosion Proof Fixtures: Guards	5-16
Explosion Proof Fixtures: H.I.D.	
Explosion Proof Fixtures: Incandescent	5-15
Explosion Proof Junction Boxes with Hubs Up to 10 x 10"	7-6
Explosion Proof Junction Boxes with Hubs up to 12 x 12"	7-6
Explosion Proof Junction Boxes with Hubs Up to 5" x 5"	7-6
Explosion Proof Large Junction Boxes	7-6
Explosion Proof Polarized Pin Receptacles	7-7
Explosion Proof Receptacle Male Attachment Cap	7-7
Explosion Proof Receptacles with Interlocked Switches	7-7
Explosion Proof Single Receptacles	7-6
Explosion Proof Single Receptacles with Factory Seal	7-7
Explosion Proof Snap Switches	7-7
Explosion Proof Snap Switches with Factory Seal	7-7
Fabric Inter Duct	1-18
Factory Cut Rigid Steel Nipples	2-16
Factory Mounted Disconnect/Circuit Breaker - Termination Labor Only	4-15
Factory Mounted Push Button Stations	4-16
Factory Mounted Variable Frequency Drive - Termination Labor Only	4-15
Fasteners / Hangers / Supports	2-92
Fiber & Plastic Anchors	2-92
Fiber Optic Cable - Fiber Labeling	1-20
Fiber Optic Cable - Fiber Testing (one wave length)	1-20
Fiber Optic Cable - Patch Cords (Premade)	1-20
Fiberglass - 45 Degree Elbow - 3" Depth	2-73
Fiberglass - 45 Degree Elbow - 4" Depth	2-75
Fiberglass - 45 Degree Elbow - 6" Depth	2-77
Fiberglass - 45 Degree Elbow - Solid Covers	2-79
Fiberglass - 90 Degree Elbow - 3" Depth	2-73
Fiberglass - 90 Degree Elbow - 4" Depth	2-75
Fiberglass - 90 Degree Elbow - 6" Depth	2-77
Fiberglass - 90 Degree Elbow - Solid Covers	2-79
Fiberglass - Cross - 3" Depth	2-73
Fiberglass - Cross - 4" Depth	2-75
Fiberglass - Cross - 6" Depth	2-77
Fiberglass - Cross - Solid Covers	2-79
Fiberglass - End Plates	2-80
Fiberglass - Ladder Drop-Outs	2-80
Fiberglass - Reducer - 3" Depth	2-74
Fiberglass - Reducer - 4" Depth	2-76
Fiberglass - Reducer - 6" Depth	2-78
Fiberglass - Reducer - Solid Covers	2-79
Fiberglass - Splice Plates Pair	2-80
Fiberglass - Tee - 3" Depth	2-73
Fiberglass - Tee - 4" Depth	2-75
Fiberglass - Tee - 6" Depth	2-77
Fiberglass - Tee - Solid Covers	2-79
Fiberglass - Vertical 45 Degree Elbow - 3" Depth	2-74
Fiberglass - Vertical 45 Degree Elbow - 4" Depth	2-76
Fiberglass - Vertical 45 Degree Elbow - 6" Depth	2-78
Fiberglass - Vertical 45 Degree Elbow - Solid Covers	2-79
Fiberglass - Vertical 90 Degree Elbow - 3" Depth	2-74
Fiberglass - Vertical 90 Degree Elbow - 4" Depth	2-76

## Index

Fiberglass - Vertical 90 Degree Elbow - 6" Depth	2-78
Fiberglass - Vertical 90 Degree Elbow - Solid Covers	2-80
Fiberglass - Vertical Tee - 3" Depth	2-74
Fiberglass - Vertical Tee - 4" Depth	2-76
Fiberglass - Vertical Tee - 6" Depth	2-78
Fiberglass - Vertical Tee - Solid Covers	2-80
Fiberglass Cable Tray - 12" Rung Spacing - 3" Depth	2-73
Fiberglass Cable Tray - 12" Rung Spacing - 4" Depth	2-75
Fiberglass Cable Tray - 12" Rung Spacing - 6" Depth	2-77
Fiberglass Cable Tray - 18" Rung Spacing - 3" Depth	2-73
Fiberglass Cable Tray - 18" Rung Spacing - 4" Depth	2-75
Fiberglass Cable Tray - 18" Rung Spacing - 6" Depth	2-77
Fiberglass Cable Tray - 6" Rung Spacing - 3" Depth	2-73
Fiberglass Cable Tray - 6" Rung Spacing - 3" Depth	2-73
Fiberglass Cable Tray - 6" Rung Spacing - 4" Depth	2-75
Fiberglass Cable Tray - 6" Rung Spacing - 6" Depth	2-77
Fiberglass Cable Tray - 9" Rung Spacing - 4" Depth	2-75
Fiberglass Cable Tray - 9" Rung Spacing - 6" Depth	2-77
Fiberglass Cable Tray - Solid Covers	2-79
Fiberglass Cable Tray - Solid Covers Clamps (Per Pair)	2-79
Fiberglass Cable Tray Barrier Strips	2-80
Fiberglass Cable Tray Fitting Barrier Strips	2-80
Fiberglass Cable Tray Fittings & Accessories	2-79
Fiberglass Conduit	2-38
Fiberglass Conduit - 10Ft & 20Ft Len. w/ Glued Couplings	2-38
Fiberglass Conduit 90 Degree Elbows	2-38
Fiberglass Conduit Expansion Couplings	2-38
Fiberglass Conduit Glued Couplings	2-38
Fiberglass Conduit Threaded Adapters	2-38
Fiberglass Conduit to Cable Tray Adapters	2-80
Fiberglass Tray 3" Depth	2-73
Fiberglass Tray 4" Depth	2-75
Fiberglass Tray 6" Depth	2-77
Field Bend Sch 40 PVC Conduit & Installation	11-24
Field Bend Sch 80 PVC Conduit & Installation	11-25
Field Bending EMT Conduit and Installation	2-22
Field Bending IMC Conduit and Installation	2-25
Field Bending Rigid Aluminum Conduit and Installation	2-26
Field Bending Steel Conduit & Installation	2-15
Field Bent PVC Conduit and Installation	2-35
Field Bent Schedule 80 PVC Conduit and Installation	2-36
Field Cut Knockouts in J-Boxes & Pull Boxes	(Updated) 2-41
Field Cut Rigid Steel Nipples & Installation	2-16
Field Cut Strut Hanger Channels	2-93
Field Installed Preset Inserts	2-54
Field Mounted Control Switch	4-18
Field Mounted Disconnect/Circuit Breaker - Includes Termination Labor	4-18
Field Mounted in MCC's - Auxiliary Contacts NO/NC	4-18
Field Mounted in MCC's - Single Speed Non-Reversing 2-Pole	4-16
Field Mounted in MCC's - Single Speed Non-Reversing 3-Pole	4-16
Field Mounted in MCC's - Single Speed Non-Reversing 4-Pole	4-16
Field Mounted in MCC's - Single Speed Reversing 2-Pole	4-16
Field Mounted in MCC's - Single Speed Reversing 3-Pole	4-16
Field Mounted in MCC's - Single Speed Reversing 4-Pole	4-16
Field Mounted in MCC's - Variable Speed Non-Reversing 2-Pole	4-17
Field Mounted in MCC's - Variable Speed Non-Reversing 3-Pole	4-17
Field Mounted in MCC's - Variable Speed Non-Reversing 4-Pole	4-17
Field Mounted in MCC's - Variable Speed Reversing 2-Pole	4-17

## Index

Field Mounted in MCC's - Variable Speed Reversing 3-Pole		4-17
Field Mounted in MCC's - Variable Speed Reversing 4-Pole		4-17
Field Mounted in MCC's MCC Control Relays		4-18
Field Mounted in MCC's MCC Control Transformers		4-18
Field Mounted Push Button Switches		4-18
Field Mounted Variable Frequency Drive - Includes Termination Labor		4-18
Field-cut All-thread Hanger Rods		2-93
Filter Bags	<b>(Updated)</b>	11-48
Fire Alarm		1-7
Fire Alarm - Aspirating Smoke Detection	<b>(Updated)</b>	1-7
Fire Alarm - Miscellaneous Devices		1-7
Fire Alarm - Signaling		1-7
Fire Alarm Control Panels Hardwired		1-7
Fire Alarm Initiating Devices		1-7
Fire Alarm Wire-Solid-Copper		3-11
Fire Alarm/Control MC Cable with Alum. or Steel Armor - Copper		3-14
Fire Proof Tape		3-35
Fire Proof Wall Penetrations		2-98
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 208 to 240 Volt Full Voltage Starting		4-25
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 208 to 240 Volt Part Winding Starting		4-26
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 208 to 240 Volt Reduced Voltage Starting		4-26
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 208 to 240 Wye Delta Starting		4-26
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 380 to 600 Volt Full Voltage Starting		4-27
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 380 to 600 Volt Part Winding Starting		4-27
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 380 to 600 Volt Reduced Voltage Starting		4-27
Fire Pump Controller, Free Standing NEMA 1 Enclosure - 380 to 600 Volt Wye Delta Starting		4-27
Fire Stop Pillows		2-98
Firestop Collar		2-98
Firestop Material		2-98
Firestopping		1-25
Fittings		10-5
Fittings	<b>(Updated)</b>	2-91
Fixture Cleaning		5-17
Fixture Mounting Accessories	<b>(Updated)</b>	5-8
Flag Man Flag		11-47
Flag Man Traffic Paddle		11-47
Flanged End Wireways with Knockouts		2-51
Flanged End Wireways with Knockouts - Brackets		2-52
Flanged End Wireways with Knockouts - Connectors		2-52
Flanged End Wireways with Knockouts - End Caps		2-52
Flanged End Wireways with Knockouts - Fittings		2-52
Flanged End Wireways with Knockouts - Miscellaneous		2-52
Flat Surface Point Base		8-13
Flat Undercarpet - Tee-Tap / X Tap / Change of direction		3-18
Flexible Braid Connectors		4-30
Flexible Braid Grounding Strap		8-6
Flexible Steel Conduit (FSC or Greenfield) and Fittings		2-31
Flexible Steel Conduit (FSC)		2-31
Flexible Steel Conduit 30" to 60" Long		4-30
Flexible Steel Couplings		7-5
Floor Box Device Cover Plates		6-8
Floor Boxes		2-21
Floor Firestop		2-98
Floor Mount (Assemble and Mount)		1-23
Floor Mount Power Pedestal -Single or Double Duplex - Mount Pedestal and Terminate		3-18
Floor Mount Telephone or Data		3-19
Floor Springload Factory Hanger		3-43
Flue Liner Point Base		8-12



## Index

Fluorescent Ballast	<b>(Updated)</b>	5-16
Fluorescent High Bay Fixture Ultra- Efficient 6 Lamp HO		5-11
Fluorescent Lay-in Parabolic Fixtures		5-6
Fluorescent Lay-in Paracube Fixtures		5-6
Foundations		14-7
Foundations		14-8
Free Standing Bolted Press. Switches - Installation & 2P3W Conductor Term.		4-19
Free Standing Bolted Press. Switches - Installation & 3P4W Conductor Term.		4-19
Free Standing Temporary Light Standard		10-7
FSC Duplex Box Converters		2-31
FSC to Box Connectors		2-31
FSC to EMT Couplings		2-31
FSC to Rigid Steel Conduit Couplings		2-31
Fuse Installation in Fused Switch in Safety Switches and MCC's - Cartridge Fuse (250 V or 600V)		4-19
Fuse Installation in Fused Switch in Safety Switches and MCC's - Cartridge Fuse (250 V or 600V)		4-24
Fuse Installation in Fused Switch in Safety Switches and MCC's Cartridge Fuse (250V - 600V)		4-10
Generator Accessories		4-38
Generator Sets		4-34
Generator w/o Fuel Tank - Over 60KW		4-38
Generator w/o Fuel Tank Up to 60KW		4-37
Generators - Permanent Outdoor Loadbank Units - Installed on Grade Level		4-41
Generators - Portable Loadbank Units - Installed on Grade Level		4-41
Ground Bar Assembly		8-7
Ground Grid Cross Connector		8-9
Ground Pigtail for Boxes		8-8
Ground Rod for Down Spout		8-14
Grounding Plate Insert for Concrete		8-10
Grounding Rods		8-6
Grounding Rods		10-6
Grounding Rods		11-16
Grounding Wire Connectors		8-8
Hammer Drive Anchors		2-92
Hand Dug Post Holes		11-14
Hand Excavation of Small Trenches		11-19
Hand Finish Concrete Slabs At Grade		11-22
Hand Finish Pole Foundations Above Grade		11-22
Hand Holes-Open Bottom		11-29
Hand Trim Bottom of Machine Excavated Trenches		11-20
Hanger Channel Conduit Clamps		2-93
Hardwire Annunciator		1-7
Haul Poles or Pick Up & Return To Storage		11-31
HDPE Conduit Adapter		11-22
HDPE Coupling O-Ring Type		11-22
HDPE Polyethylene Plastic Laid In Trenches - Per LF With O-Rings		11-22
Header Items		2-55
Header Sections		2-54
Health Care Lighting	<b>(Updated)</b>	5-9
Heat Shrink Cable Termination with 15KV Stress Cone and Compression Lug		3-28
Heat Shrink Cable Termination with 25KV Stress Cone and Compression Lug		3-29
Heat Shrink Cable Termination with 5KV Stress Cone and Compression Lug		3-28
Heat Tape and Accessories		9-5
Heating Controls		9-7
HID Temporary Light Fixture		10-7
HID Temporary Light Fixtures		10-7
High Bay Fixture Ultra- Efficient 2x4	<b>(Updated)</b>	5-10
High Bay Fixtures - Multi Vapor H.I.D Fixtures - 1000 Watt - With Lens		5-11
High Bay Fixtures - Multi Vapor H.I.D Fixtures - 250 Watt - With Lens		5-11
High Bay Fixtures - Multi Vapor H.I.D Fixtures - 250 Watt - Without Lens		5-11

## Index

High Bay Fixtures - Multi Vapor H.I.D Fixtures - 400 Watt - With Lens	5-11
High Bay Fixtures - Multi Vapor H.I.D Fixtures - 400 Watt - Without Lens	5-11
High Bay with Prismatic Lens - Pendant Mounted	5-12
High Mast Fixtures Less Poles - H.I.D Fixtures (each Fixture)	<b>(Updated)</b> 11-11
High Mast Lighting - Per Head	11-13
High Mast Steel Poles With Fixture Raising & Lowering Device	11-13
Hinged Cover Lay-In Wireways	2-50
Hinged Cover Lay-In Wireways - Accessories	2-50
Hinged Cover Lay-In Wireways - Brackets	2-50
Hinged Cover Lay-In Wireways - Fittings	2-50
Hinged Cover Lay-In Wireways - Miscellaneous	2-50
Hole Drilling and Coring	2-98
Hollow Wall Anchors	2-92
Hot Melt / Heat Cure / UV	1-20
House Service	11-36
House Service - 2/C Service Entrance Cable - 30FT Length	11-36
House Service - 3/C Service Entrance Cable - 30FT Length	11-36
House Service - 4/C Service Entrance Cable - 30FT Length	11-36
House Service - EMT With Fasteners & WP Couplings Up to 30 Ft Length	11-36
House Service - Service Entrance Conduit Cap	11-36
House Service - Threaded Steel Conduit & Fasteners - 30Ft Length	11-36
House Service - Three Single Conductors Pulled Into Conduit - Up To 30 Ft Length	11-36
Hydro Excavation	11-30
Illuminated Arrow Sign	<b>(Updated)</b> 11-47
IMC Factory Elbows	2-25
IMC Field Cut Nipples and Installation	2-25
Industrial - Chain Hung Suspended from Ceiling	<b>(Updated)</b> 5-7
Industrial Vaportite Pendant Mounted Lampholders	5-16
Industrial Vaportite Surface Mounted Lampholders	5-16
In-Line Splices-Cadweld Splices	8-8
Innerduct	1-18
Innerduct in Conduit - Indoor PVC/Plenum	1-18
Innerduct in Conduit - Outdoor PVC/Plenum	1-18
Innerduct: Not In Conduit - Indoor PVC / Plenum	1-18
Innerduct: Not In Conduit - Outdoor Aerial	1-18
Innerduct: Not In Conduit - Outdoor Buried (Reels) (Not Including Trenching)	1-18
Innerduct: Not In Conduit -Multi Duct (Not Incl. Trenching)	1-18
Inst. & Removal of Trench Shoring -	11-20
Install Flat To Round Cable Transition Block in Junction Box - All Types	3-18
Install Floor Pedestal - Install Flat Cable to Modular Ass.	3-19
Install Round To Flat Cable - Transition Block - In Junction Box	3-18
Install Telephone an Data	3-19
Installation of Items	11-31
Integrated Power Centers	4-19
Intermediate Metal Conduit (IMC) and Fittings	2-25
Intermediate Metal Conduit (IMC) with Couplings	2-25
Iron FS & FD Box Covers	2-20
Iron FS & FD Threaded 1-Gang Boxes	2-19
Iron FS & FD Threaded 2-Gang Boxes	2-19
Iron FS & FD Threaded 3-Gang Boxes	2-20
Irreversible Compression Ground System	8-9
J.I.C. Type Wireways without Knockouts	2-53
J.I.C. Type Wireways without Knockouts - Connectors & Brackets	2-53
Jacking Steel Pipe Under Driveways	11-30
Kellems Grips up to 1"	3-19
Key Pole - Bottom Of Hole	11-31
Key Pole - Lof or Plank Key	11-31
Knockout Type Steel Boxes	<b>(Updated)</b> 2-20

## Index

Knockout Type Steel Boxes		2-21
Knockout Type Steel Boxes - Accessories		2-20
Knockout Type Steel Boxes - Masonry		2-20
Knockout Type Steel Boxes - Wall Boxes		2-20
Labor Units - 3 Conductor - Aluminum MC Cable with Alum. or Steel Armor		3-14
Labor Units - 4 Conductor - Aluminum MC Cable with Alum. or Steel Armor		3-14
Lamps	<b>(Updated)</b>	5-16
Landscape Lighting - DC & AC Voltages	<b>(Updated)</b>	5-14
Lay-in (T-Bar) Fixtures - w/ Lens		5-5
Lens Cleaning		5-17
Lens Replacement	<b>(Updated)</b>	5-17
LFSC to Box Connectors		2-32
LFSC to EMT Couplings		2-32
LFSC to Rigid Steel Conduit Couplings		2-32
Light Towers	<b>(Updated)</b>	11-47
Light Track	<b>(Updated)</b>	5-9
Lighting Control Systems		1-26
Lighting Controls		1-25
Lighting Fixtures 2' x 2' Surface Mount		5-5
Lighting Fixtures 2' x 4' Surface Mount		5-5
Lighting Flex Whips - Pre-assembled		5-8
Lightning Arrestors		11-34
Lightning Protection		8-11
Limit Switch		4-24
Linear : Pendant, Stem or Aircraft Cable Mounted		5-6
Liquidtight Flexible Steel Conduit (LFSC)		2-32
Liquidtight Non-Metallic Flexible Tubing (LNT)		2-40
Liquid-Tight Steel Conduit 30" to 60" Long		4-30
LNT Box Connectors-Threaded Elbows		2-40
LNT Box Connectors-Threaded Type		2-40
LNT Conduit		2-40
Lock Nut & Ground Bushing Sets - Field Cut & Thread Included		2-16
Low Bay - Multi Vapor H.I.D. Fixtures - 250 Watt With Lens		5-11
Low Bay - Multi Vapor H.I.D. Fixtures - 400 Watt With Lens		5-11
Low Voltage Lighting Control		1-26
Low Voltage Power Grid Lighting System	<b>(Updated)</b>	5-9
Machine Screw-Drill & Tap		2-97
Main and Secondary Conductor AL		8-10
Main and Secondary Conductor CU		8-10
Maintenance and Protection of Traffic		11-47
Manhole Racks Install in Manholes		11-29
Manual Motor Starter 115/230 Volt AC - NEMA-1 Enclosure Toggle Switch		4-24
Manual Motor Starter 120/230 Volt AC - Box Mounted Toggle Switch W/O Enclosure		6-7
Manual Motor Starter W/ Enclosure		6-7
Manual Transfer Switch: Enclosed - 600 Volt 2 Pole Double Throw Wall Mounted		4-31
Manual Transfer Switch: Enclosed - 600 Volt 3 Pole Double Throw Wall Mounted		4-31
Manual Transfer Switch: Enclosed - 600 Volt 4 Pole Double Throw Wall Mounted		4-32
MC Connector for Aluminum MC - General Duty		3-15
MC Connector for Copper MC - General Duty		3-15
MCC Control Relay Termination - Factory Mounted in MCC's		4-15
MCC: Anchoring to Concrete Pad		4-14
MCC: Multiple Section Bolting Connections		4-14
MCC: Multiple Section Bus Bar Connections - Per Bus Bar		4-14
Mechanical Terminal Lugs-Four Hole		3-23
Mechanical Terminal Lugs-One Hole		3-23
Mechanical Terminal Lugs-Two Cable		3-23
Mechanical Terminal Lugs-Two Hole		3-23
Metal Mount Point Base		8-13

## Index

Metal Wireway	2-50
Metallic Sheathed Cable Box Connectors	3-24
Meter Center NEMA 1 & 3R (Typ) Enclosure - 3 Wire Solid Neutral Main Circuit Breaker or Fused Switch	4-25
Meter Center NEMA 1 & 3R (Typ) Enclosure - 3 Wire Solid Neutral MLO or Tap Box Module	4-25
Meter Center NEMA 1 & 3R (Typ) Enclosure - 4 Wire Solid Neutral Main Circuit Breaker or Fused Switch	4-25
Meter Center NEMA 1 & 3R (Typ) Enclosure - 4 Wire Solid Neutral MLO or Tap Box Module	4-25
Meter Center NEMA 1 & 3R Single Phase - 125 Amp Meter Socket Modules	4-25
Meter Center NEMA 1 & 3R Single Phase - 200 Amp Meter Socket Modules	4-25
Meter Center NEMA 1 & 3R Three Phase - 125 Amp Meter Socket Modules	4-25
Meter Center NEMA 1 & 3R Three Phase - 200 Amp Meter Socket Modules	4-26
Micro Inverters Accessories	14-5
Minerallc Straps	2-94
Misc Bolts, Washers, Nuts & Screws	2-96
Miscellaneous	4-38
Miscellaneous	11-13
Miscellaneous Connectors	1-24
Miscellaneous Controls	13-6
Modem Comm. Module	13-6
Modular Wiring System (MWS) Components - Pre-manufactured	5-8
Motor Control Centers: Receiving, Handling and Set In Place	4-13
Motor Handling - 0 - 600 Volt A.C.	12-5
Motor Handling - 280 - 550 Volt D.C.	12-5
Motor Leveling and Rotation Test - 0 to 600 Volt A.C.	12-6
Motor Leveling and Rotation Test - 2300 to 5000 Volts	12-6
Motor Mounting Base Conversion Brackets	12-5
Motor Starters Mounted in MCC's - Multi - Multi Speed Reversing 2-Pole	4-15
Motor Starters Mounted in MCC's - Multi - Multi Speed Reversing 3-Pole	4-15
Motor Starters Mounted in MCC's - Multi - Multi Speed Reversing 4-Pole	4-15
Motor Starters Mounted in MCC's - Multi - Speed Non-Reversing 2-Pole	4-14
Motor Starters Mounted in MCC's - Multi - Speed Non-Reversing 3-Pole	4-15
Motor Starters Mounted in MCC's - Multi - Speed Non-Reversing 4-Pole	4-15
Motor Starters Mounted in MCC's - Single Speed Non-Reversing 2-Pole	4-14
Motor Starters Mounted in MCC's - Single Speed Non-Reversing 3-Pole	4-14
Motor Starters Mounted in MCC's - Single Speed Non-Reversing 4-Pole	4-14
Motor Starters Mounted in MCC's - Single Speed Reversing 2-Pole	4-14
Motor Starters Mounted in MCC's - Single Speed Reversing 3-Pole	4-14
Motor Starters Mounted in MCC's - Single Speed Reversing 4-Pole	4-14
Motor Stub Splice Insulators	12-8
Multi Cable/Tray Firestop	2-98
Multi Speed Non-Reversing Combination Motor Starters - 2-Pole	7-9
Multi Speed Non-Reversing Combination Motor Starters - 3-Pole	7-9
Multi Speed Non-Reversing Combination Motor Starters - 4-Pole	7-9
Multi Speed Reversing Combination Motor Starters - 2-Pole	7-9
Multi Speed Reversing Combination Motor Starters - 3-Pole	7-9
Multi Vapor H.I.D. Fixtures - Twin Mounted	5-11
Multi-Contact Quick Connector	14-5
NEMA 1 Screw cover J-Boxes & Pull Boxes with Knockouts	<b>(Updated)</b> 2-40
NEMA 12 Hinged Cover J-Boxes & Pull Boxes	<b>(Updated)</b> 2-40
NEMA 13 J-Boxes & Pull Boxes	<b>(Updated)</b> 2-41
NEMA 3R Rain-tight J-Boxes & Pull Boxes	<b>(Updated)</b> 2-40
NEMA 4 J-Boxes & Pull Boxes	<b>(Updated)</b> 2-40
Neutral Dead Ends	11-34
New Installations	3-8
Non-Metallic Sheathed Cable Box Connectors	3-24
Nonmetallic Surface Raceways	2-46
Nurse Call	1-14
Nurse Call System - Field Devices	1-14
Nurse Call System - Head End	1-14

## Index

Obstruction Lights	11-13
Obstruction Twin Light & Tower - Factory Assembled	11-13
Obstruction Twin Light & Tower - Field Assembled	11-14
Occupancy Sensors	6-8
Offset Wall Point Base	8-13
One Conductor 600 Volt Heating Cable	9-5
One Hole Conduit Straps	2-93
One Pole Crane Hoist & Monorail Busway	3-36
One Speed Non-Reversing Combination Motor Starters - 2-Pole	7-8
One Speed Non-Reversing Combination Motor Starters - 3-Pole	7-9
One Speed Non-Reversing Combination Motor Starters - 4-Pole	7-9
One Speed Reversing Combination Motor Starters - 2-Pole	7-9
One Speed Reversing Combination Motor Starters - 3-Pole	7-9
One Speed Reversing Combination Motor Starters - 4-Pole	7-9
One-shot Conductor to Ground Rod-Cadweld	8-8
Optical Fiber Cable - Indoor in Conduit	1-18
Optical Fiber Cable - Indoor W/O Conduit	1-18
Optical Fiber Cable - Outdoor Aerial	1-19
Optical Fiber Cable - Outdoor Direct Burial (Not Including Trenching)	1-19
Optical Fiber Cable - Outdoor Underground in Conduit	1-19
Outdoor Ground Mtd Fixture W/ Spikes	5-12
Panelboard 600 Volt Feed Conductor Terminations	4-12
Panelboard Class 1 Div 1 up to 30 Circuits Style LP-1	7-8
Panelboard Class 1 Div 2 up to 30 Circuit Breakers Style D2L	7-8
Panelboard Empty Enclosure, Recessed Mounting - 100 Amp Rating	4-11
Panelboard Empty Enclosure, Recessed Mounting - 1200 Amp Rating	4-12
Panelboard Empty Enclosure, Recessed Mounting - 125 Amp Rating	4-11
Panelboard Empty Enclosure, Recessed Mounting - 150 Amp Rating	4-11
Panelboard Empty Enclosure, Recessed Mounting - 225 Amp Rating	4-11
Panelboard Empty Enclosure, Recessed Mounting - 400 Amp Rating	4-11
Panelboard Empty Enclosure, Recessed Mounting - 600 Amp Rating	4-12
Panelboard Empty Enclosure, Recessed Mounting - 800 Amp Rating	4-12
Panelboard Empty Enclosure, Surface Mounted - 100 Amp Rating	4-10
Panelboard Empty Enclosure, Surface Mounted - 1200 Amp Rating	4-11
Panelboard Empty Enclosure, Surface Mounted - 125 Amp Rating	4-10
Panelboard Empty Enclosure, Surface Mounted - 150 Amp Rating	4-10
Panelboard Empty Enclosure, Surface Mounted - 225 Amp Rating	4-10
Panelboard Empty Enclosure, Surface Mounted - 400 Amp Rating	4-10
Panelboard Empty Enclosure, Surface Mounted - 600 Amp Rating	4-10
Panelboard Empty Enclosure, Surface Mounted - 800 Amp Rating	4-11
Panelboard Grounding Conductor Terminations	4-12
Panelboard Terminations: Single Pole Circuit Breaker	<b>(Updated)</b> 4-13
Panelboard Terminations: Three Pole Circuit Breaker	<b>(Updated)</b> 4-13
Panelboard Terminations: Two Pole Circuit Breaker	<b>(Updated)</b> 4-13
Parking Lot Lighting - Cast-In-Place Base	5-14
Parking Lot Lighting - Post Top	5-15
Parking Lot Lighting - Pre-Cast Concrete Bases w/ Hole and Gravel Fill	5-14
Parking Lot Lighting - Shoe Box	5-15
Parking Lot Lighting - Steel and Aluminum Poles	5-15
Parking Lot Lighting Accessories	5-15
Patch Cords	1-24
Patch Panel Mounting Only	1-23
Patch Panel Termination	1-23
Patient Monitoring System	<b>(Updated)</b> 1-14
Pedestal Grounding Clamp-Raised Floor	8-6
Pedestal Mount Electric Vehicle Supply Equipment (EVSE)	14-9
Pedestal Receptacle Outlet	6-6
Pedestrian Signal Lights	11-11

## Index

Pendant Mount - Up to 150 Watt		5-8
Pendant Mount - Up to 300 Watt		5-8
Pendant Mounted Incandescent		5-14
Pendent Mount	<b>(Updated)</b>	5-9
Perch Guard	<b>(Updated)</b>	11-34
Photocell		6-8
Photovoltaic Solar - Solar Laminate		14-5
Photovoltaic Solar - Solar Roofing Shingles		14-5
Photovoltaic Solar Inverters		14-5
Photovoltaic Solar Inverters		14-6
Photovoltaic Solar Micro Inverters		14-5
Photovoltaic Solar Modules - Standard Frame, Front Hardware Mounted		14-5
Photovoltaic Solar Modules - Standard Frame, Rear Hardware Mounted		14-5
Photovoltaic Solar Roof Mounting Systems		14-6
Photovoltaic Solar Roof Mounting Systems		14-6
Pin Type Circuit Breaking Polarized Receptacles		6-6
Pin Type Convenience Single Receptacle Outlet		6-6
Plastic Bushing Only		2-15
Plastic Spacers in Duct Bank for Conduit		11-21
Plate or Bladed Anchors (Excavation Add'l)		11-16
Plugtail Connectors		6-5
Plugtail Wired Receptacles-Straight Blade	<b>(Updated)</b>	6-5
Plugtail Wired Switches	<b>(Updated)</b>	6-5
Plywood Pole Foundation Forms - 48" High		11-22
Pole / Tower Interior		14-7
Pole Grounding System Components		11-34
Pole Mounted Air Break Switches		11-18
Pole Mounted Capacitors		11-18
Pole Mounted Lightning Arrestors		11-18
Pole Mounted Single Phase Transformers		11-18
Pole Mounted Three Phase Transformers		11-18
Pole Pedestals		11-13
Porcelain Enamel Reflector - Vaportite - Pendant Mounted		5-12
Porcelain Enamel Reflector - Vaportite - Surface Mounted		5-12
Porcelain Enamel Reflector With Lens - Pendant Mounted		5-11
Porcelain LV Pin Insulators		11-16
Porcelain Screw Type Wireholders		11-16
Porcelain Spool Insulators		11-16
Portable Electric Generators		10-8
Portable Lighting Panelboards with 20 Amp 1 Pole S/N Branch Circuit Breakers		10-6
Portable Lighting Panelboards With Up to 30 Amp 2-Pole S/N Branch CB's		10-6
Portable Lighting Panelboards with up to 60 Amp 2-Pole S/N Branch CB's		10-6
Portable Post Mounted 3-Wire Safety Switches		10-6
Portable Post Mounted Lighting Fixtures - Indoor Grade		10-7
Portable Post Mounted Lighting Fixtures - Outdoors		10-7
Portable Power Distribution Center		10-8
Portable Traffic Light	<b>(Updated)</b>	11-47
Post Hole Excavation With Truck Auger		11-15
Post Top Mounted	<b>(Updated)</b>	5-13
Pour Concrete Slabs At Grade Elevation Directly From Ready Mix Trucks		11-22
Pouring Concrete Directly From Ready Mix Trucks Into Duct Banks - Per Cubic Yard (CY)		11-21
Pouring Concrete In 48" High Pole Foundations	<b>(Updated)</b>	11-22
Powder Activated Fasteners - All Types		2-92
Power Connections to Equipment Installed by Others - Aluminum 600 Volt Cond.		9-8
Power Connections to Equipment Installed by Others - Copper 600 Volt Cond.	<b>(Updated)</b>	9-8
Power Pack w/ Dual Heads		5-10
Pre-cut Hanger Rods		2-93
Pre-cut Strut Hanger Channels	<b>(Updated)</b>	2-93

## Index

Prefabbed Light Strings With Bulbs		10-6
Prepackaged Co-Gen		14-8
Prepackaged Fuel Cell Generator		14-7
Primary Attachment		11-32
Primary Dead Ends		11-34
Primary Jumpers		11-34
PT/CT Components		4-26
Push Button Station - Wall Mounted - 120 Volt - Explosion Proof Enclosure		7-7
Push Button Station NEMA-1 Enclosure, Factory Assembled		4-23
Push Button Station NEMA-1 Non Assembled		6-7
Push Button Station NEMA-3 Enclosure, Factory Assembled		4-23
Push Button Station NEMA-4 Non Assembled		6-7
PVC Bell Ends-Sch 40		2-36
PVC Boxes		2-37
PVC Coated Couplings		2-34
PVC Coated Expansion Couplings		2-34
PVC Coated Rigid Steel Conduit		2-33
PVC Coated Rigid Steel Elbows		2-33
PVC Coated Rigid Steel Elbows - 48" Radius		2-33
PVC Coated Steel Factory Nipples		2-33
PVC Coated Steel Field Cut Nipples		2-34
PVC Coated Steel Offset Nipples		2-34
PVC Coated Steel Split Couplings		2-34
PVC Coated Termination Sets		2-33
PVC Conduit Adapters-All Types		2-35
PVC Conduit Bodies		2-37
PVC Conduit End Caps-Sch 40		2-36
PVC Duct Bank Conduit Spacers		11-23
PVC EB/DB Plastic Conduit Laid In Trenches - 90 Degree Elbows		11-23
PVC EB/DB Plastic Conduit Laid In Trenches - 10Ft & 20Ft Lengths With Glued Couplings		11-23
PVC EB/DB Plastic Conduit Laid In Trenches - Couplings - Glued Type		11-23
PVC EB/DB Plastic Conduit Laid In Trenches - Threaded End Conduit Adapters		11-23
PVC Expansion Couplings-Sch 40		2-35
PVC Expansion Couplings-Sch 80		2-37
PVC Factory Elbows-Sch 40		2-35
PVC Factory Elbows-Sch 80		2-36
PVC Handy Boxes		2-37
PVC Junction Boxes & Pull Boxes		2-37
PVC Rigid Conduit		2-35
PVC Rigid Conduit - Schedule 40 with Couplings		2-35
PVC Rigid Conduit - Schedule 80 with Couplings	<b>(Updated)</b>	2-36
Radiant Heat Panel Frames		9-5
Radiant Heat Panels		9-5
Recess Mounted Gyp Bd Ceiling		5-6
Recessed Fountain Fixtures	<b>(Updated)</b>	5-12
Recessed H.I.D.		5-11
Recessed Heating Fixtures		9-7
Recessed Mounted Vaportite Gyp Bd Ceiling	<b>(Updated)</b>	5-6
Recessed Prewired Hi-Hat Fixt, Can Light or Downlight	<b>(Updated)</b>	5-9
Reglet Mount Point Base		8-13
Remote Ballast		5-16
Removal of Items		11-39
Removal of 1/C ACSR Cable - Bare or Insulated		11-40
Removal of 1/C Copper or Aluminum Cable - Bare or Insulated		11-39
Removal of 2/C Duplex Secondary Cable		11-40
Removal of 3/C Triplex Secondary Cable		11-39
Removal of Aluminum Conductor Armor Rods		11-40
Removal of Brackets For Cluster Mounted Transformers		11-40

## Index

Removal of Complete Guy With Anchor, Rod, Wire & Guard	11-39
Removal of Complete Overhead Guy	11-39
Removal of Complete Pole Grounding Systems	11-40
Removal of Conductor Attachments	11-39
Removal of Copperweld Conductors	11-39
Removal of Cross Arms With Braces & Pins	11-39
Removal of Disconnect Switches	11-40
Removal of Primary Attachment	11-39
Removal of Secondary Copper Triplex Cable	11-41
Removal of Secondary Service - Five Copper Conductors	11-41
Removal of Secondary Service - Four Copper Conductors	11-41
Removal of Secondary Service - Three Copper Conductors	11-41
Removal of Secondary Service - Two Copper Conductors	11-40
Removal of Single Pad Mounted Transformers - Pole Type Transformers	11-40
Removal of Single Pole Mounted Transformers	11-40
Removal of Street Lighting Systems - Capacitor Banks - Up To 50 KVR	11-42
Removal of Street Lighting Systems - Constant Current Transformers	11-42
Removal of Street Lighting Systems - Light Fixtures Attached Before Pole Erection	11-42
Removal of Street Lighting Systems - Mast Arms Attached Before Pole Erection	11-41
Removal of Street Lighting Systems - Metal Pole Transformer Base Housing	11-42
Removal of Street Lighting Systems - Metal Poles With Internal Wiring	11-41
Removal of Street Lighting Systems - Pole Mounted Photo Switch With Relay	11-42
Removal of Street Lighting Systems - Pull Cable In Pole & Arm-Series Circuit	11-42
Removal of Street Lighting Systems - Series Street Lighting Protectors	11-42
Removal of Street Lighting Systems - Spacer Cable Accessories	11-42
Removal of Street Lighting Systems - Street Lighting Controllers	11-42
Removal of Street Lighting Systems - Street Lighting Transformers	11-42
Removal of Street Lighting Systems - Upsweep Bracket On Pole	11-42
Removal of Transformer Platform	11-39
Removal of Two Or More Pad Mounted Transformers - Pole Type Transformers	11-40
Removal of Two Or More Pole Mounted Transformers	11-40
Removal of Wood Poles - Cedar or Pine	11-39
Remove and Package for Disposal	5-17
Remove Large Tree Limb Over Hot Wires or Over Other Obstacles	11-42
Remove Larger Tree Limb - No Obstacles	11-42
Remove Trees (Excluding Roots)	11-42
Rented Steel Forms For Concrete Slabs	11-21
Replace Sleeves In Existing Primary Cable	11-33
Replace Steel Braces With Wood Braces	11-32
Replace Steel Braces With Wood Braces	11-39
Re-Roof Pole	11-31
Re-sag 1/C ACSR Cable	11-33
Re-sag 1/C Copper or Aluminum Cable	11-32
Re-sag 2/C Duplex Secondary Cable	11-33
Re-sag 3/C Triplex Secondary Cable	11-33
Re-sag Copperweld Conductors	11-33
Re-sag Copperweld Conductors	11-39
Re-sag Copperweld Conductors	11-43
Retro-Fit	5-16
Retrofit Installations	3-9
RFI Filters	5-16
Ridge or Flat Point Base	8-12
Rigid Aluminum Conduit and Fittings	2-26
Rigid Aluminum Conduit with Couplings	2-26
Rigid Aluminum Factory Elbows	2-26
Rigid Conduit Locknut Only	2-16
Rigid Steel Conduit (GRC or GRS) and Fittings	2-15
Rigid Steel Conduit with Threaded Couplings	2-15



## Index

Rigid Steel Expansion / Deflection Couplings	<b>(Updated)</b>	2-17
Rigid Steel Factory Elbows		2-15
Roll up work in progress alert signs	<b>(Updated)</b>	11-47
Roof Flashings		14-6
Rotating Beacons-120 Volts		11-13
Roto-Hammer Concrete		2-98
Sand Bags	<b>(Updated)</b>	11-48
Sch 40 PVC Conduit Laid In Trenches - 10Ft & 20Ft Len. w/ Glued Couplings		11-23
Sch 40 PVC Conduit Laid In Trenches - 90 Degree Elbows		11-23
Sch 40 PVC Conduit Laid In Trenches - Expansion Couplings		11-24
Sch 40 PVC Conduit Laid In Trenches - Threaded Adapters		11-23
Sch 80 PVC Conduit Laid In Trenches - 10Ft & 20Ft Lengths w/ Glued Couplings		11-24
Sch 80 PVC Conduit Laid In Trenches - 90 Degree Elbows		11-24
Sch 80 PVC Conduit Laid In Trenches - Expansion Couplings		11-24
Sch 80 PVC Conduit Laid In Trenches - Threaded Adapters		11-24
Schedule 80 PVC Conduit Adapters-All Types		2-36
Screw Type Anchors-Power Driven		11-17
Screwed Cover Lay-In Wireways		2-50
Screwed Cover Lay-In Wireways - Adapters		2-51
Screwed Cover Lay-In Wireways - Brackets		2-51
Screwed Cover Lay-In Wireways - Fittings		2-51
Screwed Cover Lay-In Wireways - Miscellaneous		2-51
Sealing Compound		7-5
Sealing Hub Listed by Female Hub Size		7-5
Sealtite Flex		12-7
Sealtite Flexible Conduit and Fittings		2-32
Secondary Copper Triplex Cable		11-36
Secondary Racks		11-16
Secondary Service - Five Copper Conductors		11-36
Secondary Service - Four Copper Conductors		11-35
Secondary Service - Three Copper Conductors		11-35
Secondary Service - Two Copper Conductors		11-35
Sectional Ground Rods		8-6
Security & Access Control		1-8
Security Systems - Control Panels		1-8
Security Systems - Detection Devices		1-8
Security Systems - Peripherals		1-8
Security Systems - Signaling Devices		1-8
Security Systems - Wireless		1-8
Seismic Hold-Down Clamp and Expansion Guide		2-84
Seismic Hold-Down Clamp and Expansion Guide		2-89
Self Drill Anchors		2-92
Self Tapping Screws		2-97
Sheet Metal Screw		2-97
Showroom Stage & Auditorium Fixtures - Hardware		5-13
Showroom Stage & Auditorium Fixtures - Recessed Fixtures Hi-Ceiling		5-13
Showroom Stage & Auditorium Fixtures - Stage Footlight Troughs - 3 Color		5-13
Showroom Stage & Auditorium Fixtures - Stage Hanging Borderlights - 3 Color		5-13
Showroom Stage & Auditorium Fixtures - Surface Mounted Spot or Flood	<b>(Updated)</b>	5-13
Side Ridge Point Base		8-12
Sidewalk Cover Lighting		10-7
Sign Stands	<b>(Updated)</b>	11-47
Signal Hangers		11-11
Silt Check	<b>(Updated)</b>	11-48
Silt Fence	<b>(Updated)</b>	11-48
Single Conductor to Ground Rod		8-8
Single Pad Mounted Transformers - Pole Type Transformers		11-35
Single Pole Mounted Transformers		11-34

## Index

Single Receptacle - Straight Blade or Twist Lock	6-5
Single Steel Cross Arms	11-16
Single Wooden Cross Arms	11-15
Socket Replacement	5-17
Solar Module Clamping Assemblies	14-6
Solar Railing	14-6
Solid Bottom Trench Duct	2-56
Solid TFFN Conductors	3-14
Solid THHN Conductors	3-14
Solid/Ventilated Aluminum - 45 Degree Elbow - 3" Depth	2-86
Solid/Ventilated Aluminum - 45 Degree Elbow - 4" Depth	2-87
Solid/Ventilated Aluminum - 45 Degree Elbow - 6" Depth	2-88
Solid/Ventilated Aluminum - 45 Degree Elbow - Solid Covers	2-89
Solid/Ventilated Aluminum - 90 Degree Elbow - 3" Depth	2-86
Solid/Ventilated Aluminum - 90 Degree Elbow - 4" Depth	2-87
Solid/Ventilated Aluminum - 90 Degree Elbow - 6" Depth	2-88
Solid/Ventilated Aluminum - 90 Degree Elbow - Solid Covers	2-89
Solid/Ventilated Aluminum - Cable Tray - 3" Depth	2-86
Solid/Ventilated Aluminum - Cable Tray - 4" Depth	2-87
Solid/Ventilated Aluminum - Cable Tray - 6" Depth	2-88
Solid/Ventilated Aluminum - Cross - 3" Depth	2-86
Solid/Ventilated Aluminum - Cross - 4" Depth	2-87
Solid/Ventilated Aluminum - Cross - 6" Depth	2-88
Solid/Ventilated Aluminum - Cross - Solid Covers	2-89
Solid/Ventilated Aluminum - Enclosure Connectors	2-90
Solid/Ventilated Aluminum - End Plates	2-90
Solid/Ventilated Aluminum - Ladder Drop - Outs	2-90
Solid/Ventilated Aluminum - Reducer - 3" Depth	2-86
Solid/Ventilated Aluminum - Reducer - 4" Depth	2-87
Solid/Ventilated Aluminum - Reducer - 6" Depth	2-88
Solid/Ventilated Aluminum - Reducer - Solid Covers	2-89
Solid/Ventilated Aluminum - Splice Plates Pair	2-90
Solid/Ventilated Aluminum - Tee - 3" Depth	2-86
Solid/Ventilated Aluminum - Tee - 4" Depth	2-87
Solid/Ventilated Aluminum - Tee - 6" Depth	2-88
Solid/Ventilated Aluminum - Tee - Solid Covers	2-89
Solid/Ventilated Aluminum - Vertical 45 Degree Elbow - 3" Depth	2-86
Solid/Ventilated Aluminum - Vertical 45 Degree Elbow - 4" Depth	2-87
Solid/Ventilated Aluminum - Vertical 45 Degree Elbow - 6" Depth	2-88
Solid/Ventilated Aluminum - Vertical 45 Degree Elbow - Solid Covers	2-89
Solid/Ventilated Aluminum - Vertical 90 Degree Elbow - 3" Depth	2-86
Solid/Ventilated Aluminum - Vertical 90 Degree Elbow - 4" Depth	2-87
Solid/Ventilated Aluminum - Vertical 90 Degree Elbow - 6" Depth	2-88
Solid/Ventilated Aluminum - Vertical 90 Degree Elbow - Solid Covers	2-89
Solid/Ventilated Aluminum - Vertical Tee - 3" Depth	2-86
Solid/Ventilated Aluminum - Vertical Tee - 4" Depth	2-87
Solid/Ventilated Aluminum - Vertical Tee - 6" Depth	2-88
Solid/Ventilated Aluminum - Vertical Tee- Solid Covers	2-90
Solid/Ventilated Aluminum Cable Tray - Solid Cover Clamps (Per Pair)	2-89
Solid/Ventilated Aluminum Cable Tray - Solid Covers	2-89
Solid/Ventilated Aluminum Cable Tray Barrier Strips	2-90
Solid/Ventilated Aluminum Cable Tray Fitting Barrier Strips	2-90
Solid/Ventilated Aluminum Cable Tray Fittings & Accessories	2-89
Solid/Ventilated Aluminum Conduit to Cable Tray Adapters	2-90
Solid/Ventilated Aluminum Tray 3" Depth	2-86
Solid/Ventilated Aluminum Tray 4" Depth	2-87
Solid/Ventilated Aluminum Tray 6" Depth	2-88
Solid/Ventilated Steel - 45 Degree Elbow - 3" Depth	2-81

## Index

Solid/Ventilated Steel - 45 Degree Elbow - 4" Depth	2-82
Solid/Ventilated Steel - 45 Degree Elbow - 6" Depth	2-83
Solid/Ventilated Steel - 45 Degree Elbow - Solid Covers	2-84
Solid/Ventilated Steel - 90 Degree Elbow - 3" Depth	2-81
Solid/Ventilated Steel - 90 Degree Elbow - 4" Depth	2-82
Solid/Ventilated Steel - 90 Degree Elbow - 6" Depth	2-83
Solid/Ventilated Steel - 90 Degree Elbow - Solid Covers	2-84
Solid/Ventilated Steel - Cable Tray - 3" Depth	2-81
Solid/Ventilated Steel - Cable Tray - 4" Depth	2-82
Solid/Ventilated Steel - Cable Tray - 6" Depth	2-83
Solid/Ventilated Steel - Cross - 3" Depth	2-81
Solid/Ventilated Steel - Cross - 4" Depth	2-82
Solid/Ventilated Steel - Cross - 6" Depth	2-83
Solid/Ventilated Steel - Cross - Solid Covers	2-84
Solid/Ventilated Steel - Enclosure Connectors	2-85
Solid/Ventilated Steel - End Plates	2-85
Solid/Ventilated Steel - Ladder Drop-Outs	2-85
Solid/Ventilated Steel - Reducer - 3" Depth	2-81
Solid/Ventilated Steel - Reducer - 4" Depth	2-82
Solid/Ventilated Steel - Reducer - 6" Depth	2-83
Solid/Ventilated Steel - Reducer - Solid Covers	2-84
Solid/Ventilated Steel - Splice Plates Pair	2-85
Solid/Ventilated Steel - Tee - 3" Depth	2-81
Solid/Ventilated Steel - Tee - 4" Depth	2-82
Solid/Ventilated Steel - Tee - 6" Depth	2-83
Solid/Ventilated Steel - Tee - Solid Covers	2-84
Solid/Ventilated Steel - Vertical 45 Degree Elbow - 3" Depth	2-81
Solid/Ventilated Steel - Vertical 45 Degree Elbow - 4" Depth	2-82
Solid/Ventilated Steel - Vertical 45 Degree Elbow - 6" Depth	2-83
Solid/Ventilated Steel - Vertical 45 Degree Elbow - Solid Covers	2-84
Solid/Ventilated Steel - Vertical 90 Degree Elbow - 3" Depth	2-81
Solid/Ventilated Steel - Vertical 90 Degree Elbow - 4" Depth	2-82
Solid/Ventilated Steel - Vertical 90 Degree Elbow - 6" Depth	2-83
Solid/Ventilated Steel - Vertical 90 Degree Elbow - Solid Covers	2-84
Solid/Ventilated Steel - Vertical Tee - 3" Depth	2-81
Solid/Ventilated Steel - Vertical Tee - 4" Depth	2-82
Solid/Ventilated Steel - Vertical Tee - 6" Depth	2-83
Solid/Ventilated Steel - Vertical Tee - Solid Covers	2-85
Solid/Ventilated Steel Cable Tray - Solid Cover Clamps (Per Pair)	2-84
Solid/Ventilated Steel Cable Tray - Solid Covers	2-84
Solid/Ventilated Steel Cable Tray Barrier Strips	2-85
Solid/Ventilated Steel Cable Tray Fitting Barrier Strips	2-85
Solid/Ventilated Steel Cable Tray Fittings & Accessories	2-84
Solid/Ventilated Steel Conduit to Cable Tray Adapters	2-85
Solid/Ventilated Steel Tray 3" Depth	2-81
Solid/Ventilated Steel Tray 4" Depth	2-82
Solid/Ventilated Steel Tray 6" Depth	2-83
Sonotube Pole Foundation Forms - 48" High	11-22
Sound Systems - Pro-Sound - Theatrical Systems	1-11
Sound Systems - Pro-Sound - Theatrical Systems - Consoles, Mixers	1-12
Sound Systems - Pro-Sound - Theatrical Systems - Electronics	1-12
Sound Systems - Pro-Sound - Theatrical Systems - Patch Bays	1-12
Sound Systems - Signal Generators	1-11
Sound Systems - Signal Processing Equip.	1-11
Sound Systems - Sound Generating Equip.	1-11
Sound Systems - Sound Masking	1-12
Specific Use Items	1-16
Speed Sleeve	2-98

## Index

Splice Cables - Outdoor	1-19
Splice Enclosure Indoor	1-19
Splice Enclosures	1-22
Splicing	1-19
Split Bolt Connectors-Tape Wrapped	3-23
Split Wired Receptacle - Straight Blade	6-5
Stadium Light Fixtures Less Poles/Brackets - H.I.D (each Fixture)	<b>(Updated)</b> 11-12
Standard Wire Conductor Terminations	12-8
Steel - 45 Degree Elbow - 3" Depth	2-57
Steel - 45 Degree Elbow - 4" Depth	2-59
Steel - 45 Degree Elbow - 6" Depth	2-61
Steel - 45 Degree Elbow - Solid Covers	2-63
Steel - 90 Degree Elbow - 3" Depth	2-57
Steel - 90 Degree Elbow - 4" Depth	2-59
Steel - 90 Degree Elbow - 6" Depth	2-61
Steel - 90 Degree Elbow - Solid Covers	2-63
Steel - Cross - 3" Depth	2-57
Steel - Cross - 4" Depth	2-59
Steel - Cross - 6" Depth	2-61
Steel - Cross - Solid Covers	2-63
Steel - Enclosure Connectors	2-64
Steel - End Plates	2-64
Steel - Ladder Drop-Outs	2-64
Steel - Reducer - 3" Depth	2-58
Steel - Reducer - 4" Depth	2-60
Steel - Reducer - 6" Depth	2-62
Steel - Reducer - Solid Covers	2-63
Steel - Splice Plates Pair	2-64
Steel - Tee - 3" Depth	2-57
Steel - Tee - 4" Depth	2-59
Steel - Tee - 6" Depth	2-61
Steel - Tee - Solid Covers	2-63
Steel - Vertical 45 Degree Elbow - 3" Depth	2-58
Steel - Vertical 45 Degree Elbow - 4" Depth	2-60
Steel - Vertical 45 Degree Elbow - 6" Depth	2-62
Steel - Vertical 45 Degree Elbow - Solid Covers	2-63
Steel - Vertical 90 Degree Elbow - 3" Depth	2-58
Steel - Vertical 90 Degree Elbow - 4" Depth	2-60
Steel - Vertical 90 Degree Elbow - 6" Depth	2-62
Steel - Vertical 90 Degree Elbow - Solid Covers	2-64
Steel - Vertical Tee - 3" Depth	2-58
Steel - Vertical Tee - 4" Depth	2-60
Steel - Vertical Tee - 6" Depth	2-62
Steel - Vertical Tee - Solid Covers	2-64
Steel Anchoring Cable with One Insulator	11-17
Steel Cable Tray - Solid Cover Clamps (Per Pair)	2-63
Steel Cable Tray - Solid Covers	2-63
Steel Cable Tray Barrier Strips	2-64
Steel Cable Tray Fitting Barrier Strips	2-64
Steel Cable Tray Fittings & Accessories	2-63
Steel Channels Embedded in Concrete	4-9
Steel Chase Nipples - Includes Locknut & Bushing	2-16
Steel Compression Couplings	2-17
Steel Conduit To Cable Tray Adapters	2-64
Steel Conduit Unions	7-5
Steel Erickson Couplings	2-17
Steel Flex	12-6
Steel Ladder Cable Tray - 12" Rung Spacing - 3" Depth	2-57

## Index

Steel Ladder Cable Tray - 12" Rung Spacing - 6" Depth		2-61
Steel Ladder Cable Tray - 18" Rung Spacing - 3" Depth		2-57
Steel Ladder Cable Tray - 18" Rung Spacing - 4" Depth		2-59
Steel Ladder Cable Tray - 18" Rung Spacing - 6" Depth		2-61
Steel Ladder Cable Tray - 6" Rung Spacing - 3" Depth		2-57
Steel Ladder Cable Tray - 6" Rung Spacing - 4" Depth		2-59
Steel Ladder Cable Tray - 6" Rung Spacing - 6" Depth		2-61
Steel Ladder Cable Tray - 9" Rung Spacing - 3" Depth		2-57
Steel Ladder Cable Tray - 9" Rung Spacing - 4" Depth		2-59
Steel Ladder Cable Tray - 9" Rung Spacing - 6" Depth		2-61
Steel Ladder Cable Tray- 12" Rung Spacing - 4" Depth		2-59
Steel Mogul Conduit Bodies-Four Hubs		2-19
Steel Mogul Conduit Bodies-Three Hubs		2-19
Steel Mogul Conduit Bodies-Two Hubs		2-19
Steel Offset Nipples - Includes Locknut & Bushings		2-16
Steel or Aluminum Mast Arms		11-13
Steel or Aluminum Pole Installation		11-15
Steel or Aluminum Traffic Poles Foundations and Anchor Bolts Not Included		11-12
Steel Pipe Caps or Capped Bushings		2-18
Steel Pole Fixture Mounting Support Arms - Field Installed	<b>(Updated)</b>	11-12
Steel Poles with Factory Assembled Arms or Brackets	<b>(Updated)</b>	11-12
Steel Reinforcing Bars In Concrete Slabs		11-22
Steel Reinforcing Bars in Pole Foundations		11-22
Steel Set Screw Conduit Bodies		2-24
Steel Shoring Both Sides w/ Either Steel Trench Jacks or 4x4 Horz. Wood Bracing		11-20
Steel Split Couplings		2-17
Steel Structural Compression Connector		8-10
Steel Threaded Box Connectors (Myers Hub)		2-18
Steel Threaded Capped Elbows		2-18
Steel Threaded Conduit Bodies-Four Hubs		2-19
Steel Threaded Conduit Bodies-One Hub		2-18
Steel Threaded Conduit Bodies-Three Hubs		2-19
Steel Threaded Conduit Bodies-Two Hubs		2-18
Steel Threaded Entrance Elbows		2-17
Steel Threaded Reducers		2-17
Steel Threaded Service Entrance Caps		2-18
Steel Threadless Box Connectors		2-17
Steel Tray 3" Depth		2-57
Steel Tray 3" Depth		2-57
Steel Tray 4" Depth		2-59
Steel Tray 6" Depth		2-61
Steel Underfloor Duct & Fittings		2-54
Stem Mounted Vaportite Suspended from Ceiling	<b>(Updated)</b>	5-7
Step Controllers-20 Amp per Step		9-8
Straight Point Base		8-13
Straight Splicer		8-11
Straighten Existing Poles		11-31
Straps for MC Cable		3-15
Straw Wattles	<b>(Updated)</b>	11-48
Street Light Fixtures - Cobra Head		11-12
Street Light Poles - Mast Arm		11-12
Street Lighting Class 3 Wood Pole		11-12
Street Lighting Concrete Poles		11-12
Street Lighting Steel or Aluminum Poles		11-12
Street Lighting Systems - Capacitor Banks - Up To 50 KVR		11-38
Street Lighting Systems - Constant Current Transformers		11-37
Street Lighting Systems - Light Fixtures Attached Before Pole Erection		11-37
Street Lighting Systems - Mast Arms Attached Before Pole Erection		11-37

## Index

Street Lighting Systems - Metal Pole Transformer Base Housing		11-37
Street Lighting Systems - Metal Poles With Internal Wiring		11-37
Street Lighting Systems - Pole Mounted Photo Switch With Relay		11-37
Street Lighting Systems - Pull Cable In Pole & Arm-Series Circuit		11-37
Street Lighting Systems - Series Street Lighting Protectors		11-37
Street Lighting Systems - Spacer Cable Accessories		11-38
Street Lighting Systems - Street Lighting Controllers		11-38
Street Lighting Systems - Street Lighting Transformers		11-37
Street Lighting Systems - Upsweep Bracket On Pole		11-37
Submerged Fountain Fixtures	<b>(Updated)</b>	5-12
Sunlight Resistant Wire/Cable, Type USE-2		14-5
Sunlink Racking		14-6
Surface Ceiling Mounted		5-10
Surface Metal Raceways		2-42
Surface Mount - Up to 300 Watt Ceiling Mounted	<b>(Updated)</b>	5-8
Surface Mount Strip	<b>(Updated)</b>	5-8
Surface Mount Vaportite - Indoor / Outdoor	<b>(Updated)</b>	5-5
Surface Mounted Light Fixture		5-5
Swimming Pool & Fountain Lighting - Dry Niche Fixtures	<b>(Updated)</b>	5-12
Swimming Pool & Fountain Lighting - Wet Niche Fixtures	<b>(Updated)</b>	5-12
Switch and Receptacle Combination - 20 Amp		6-7
Switchboard 2 Pole Copper Cond. Term. On Circuit Breakers & Switches	<b>(Updated)</b>	4-9
Switchboard 3 Pole Copper Cond. Term. On Circuit Breakers & Switches	<b>(Updated)</b>	4-9
Switchboard 600 Volt Feed Conductor Terminations		4-8
Switchboard Bus Bar Splice Connections - 3 Phase 4 Wire W/ Copper Ground		4-9
Switchboard Grounding Conductor Terminations		4-8
Switchboard Heater	<b>(Updated)</b>	4-8
Switchboard Section Handling Labor Only		4-7
Switchboard/Gear Sections		4-7
Switches, General Use Toggle Switches, Keyed Switches		6-6
Swivel Adapt AL		8-12
Swivel Adapt CU		8-12
Teck Cable 14AWG		3-45
Teck Cable 16AWG		3-45
Teck Cable 18AWG		3-46
Teck Cable 1Kv 1C		3-44
Teck Cable 1Kv 3C		3-43
Teck Cable 1Kv 4C		3-43
Teck Cable 20AWG		3-46
Teck Cable 5Kv 3c		3-43
Teck Cable 600v 12AWG		3-44
Teck Cable 600v mh/1000 FT		3-44
Teck Connectors		3-47
Tee Cable Splicers		8-11
Tee Conductor to Ground Rod		8-8
Tee or Wye Cadwelds		8-8
Tee Point Base		8-12
Telephone / Television		1-16
Telephone Equipment		1-16
Telephone Equipment - Small System Programming		1-16
Telephone Equipment Paging System		1-16
Television System		1-16
Television Systems - Camera and Enclosure		1-17
Television Systems - Camera Lenses		1-17
Temp Svc - 16 to 20 Ft Dim Lumber Pole		10-5
Temp Svc - 20 to 30 ft Std Pole & Arms		10-5
Temp Svc - Undergnd Feed 12-16Ft Pole		10-5
Temperature Controls - Actuators - Damper		13-7

## Index

Temperature Controls - Central Equipment	13-6
Temperature Controls - Central Equipment - Computer Systems	13-6
Temperature Controls - Central Equipment - Power Supply	13-6
Temperature Controls - Electrical Relays - 4 SPDT Outputs	13-5
Temperature Controls - Electrical Relays - E/P Relays	13-5
Temperature Controls - Electrical Relays - Miscellaneous	13-6
Temperature Controls - Electrical Relays - Water Flow Switch	13-5
Temperature Controls - Humidity Sensors - Duct	13-6
Temperature Controls - Humidity Sensors - Pressure	13-7
Temperature Controls - Humidity Sensors - Wall Mount	13-6
Temperature Controls - Panel Enclosures - 19"H X 24" W Panel	13-5
Temperature Controls - Panel Enclosures - 23"H X 24" W Panel	13-5
Temperature Controls - Panel Enclosures - 38"H X 24" W Panel	13-5
Temperature Controls - Temperature Sensors - Duct	13-6
Temperature Controls - Temperature Sensors - Miscellaneous	(Updated) 13-6
Temperature Controls - Temperature Sensors - Pipe	13-6
Temperature Controls - Temperature Sensors - Space	13-6
Temperature Controls - Temperature Sensors - Wall Mount Standard	13-6
Temperature Controls - Thermostatic Control Valves - Water, 3 Way	13-5
Temperature Controls - Thermostatic Control Valves - Water, Straight Through	13-5
Temporary Installations & Cable Transfers	11-33
Terminal Blocks - Excludes Terminations	3-18
Termination Boxes / Cabinets - Misc	1-20
Termination Boxes / Cabinets - Rack Mount	1-20
Termination Boxes / Cabinets - Wall Mounted	1-20
Terminations Anaerobic	1-20
Thermostat Wire-Copper	3-11
Thermostats	9-7
Threaded Anchor Rods	11-17
Threaded Cast Floor Boxes	2-21
Threaded Cast Round Outlet Boxes	2-21
Threaded Concrete Inserts	2-93
Threaded Eye Bolts	11-17
Threadless Conduit Bodies for EMT & Rigid Steel Conduit	2-24
Three Phase 3P Feeder Bus Duct - Service Heads	3-42
Three Pole Heavy Duty Trolley Busway	3-36
Three Way Splicer	8-11
Thru Roof Point Adapt	8-12
Thru Wall or Roof Cable Connector	8-12
Tile Trac	14-6
Time Clocks and Lighting Contactors	(Updated) 6-8
Timers	13-5
Toggle Bolts	2-92
Traffic Signal Lights	11-11
Transfer of 1/C ACSR Cable - Bare or Insulated	11-44
Transfer of 1/C Copper or Aluminum Cable - Bare or Insulated	11-43
Transfer of 2/C Duplex Secondary Cable	11-43
Transfer of 3/C Triplex Secondary Cable	11-43
Transfer of Aluminum Conductor Armor Rods	11-44
Transfer of Brackets For Cluster Mounted Transformers	11-44
Transfer of Conductor Attachments	11-43
Transfer of Cross Arms With Braces & Pins	11-43
Transfer of Disconnect Switches	11-44
Transfer of Items	11-43
Transfer of Primary Attachment	11-43
Transfer of Secondary Copper Triplex Cable	11-45
Transfer of Secondary Service - Five Copper Conductors	11-45
Transfer of Secondary Service - Four Copper Conductors	11-45

## Index

Transfer of Secondary Service - Three Copper Conductors	11-44
Transfer of Secondary Service - Two Copper Conductors	11-44
Transfer of Single Pad Mounted Transformers - Pole Type Transformers	11-44
Transfer of Single Pole Mounted Transformers	11-44
Transfer of Street Lighting Systems - Capacitor Banks - Up To 50 KVR	11-46
Transfer of Street Lighting Systems - Constant Current Transformers	11-46
Transfer of Street Lighting Systems - Light Fixtures Attached Before Pole Erection	11-45
Transfer of Street Lighting Systems - Mast Arms Attached Before Pole Erection	11-45
Transfer of Street Lighting Systems - Metal Pole Transformer Base Housing	11-45
Transfer of Street Lighting Systems - Metal Poles With Internal Wiring	11-45
Transfer of Street Lighting Systems - Pole Mounted Photo Switch With Relay	11-45
Transfer of Street Lighting Systems - Pull Cable In Pole & Arm-Series Circuit	11-45
Transfer of Street Lighting Systems - Series Street Lighting Protectors	11-46
Transfer of Street Lighting Systems - Spacer Cable Accessories	11-46
Transfer of Street Lighting Systems - Street Lighting Controllers	11-46
Transfer of Street Lighting Systems - Street Lighting Transformers	11-46
Transfer of Street Lighting Systems - Upsweep Bracket On Pole	11-45
Transfer of Transformer Platform	11-43
Transfer of Two Or More Pad Mounted Transformers - Pole Type Transformers	11-44
Transfer of Two Or More Pole Mounted Transformers	11-44
Transfer of Wood Poles - Cedar or Pine	11-43
Transfer One End Of Overhead Guy	11-43
Transformer Lightning Arrestors	4-30
Transformer Platform	11-32
Transformers Indoor Type Up to 15 KV Primary	4-28
Transformers Indoor Type Up to 600 V Primary	4-28
Transformers Outdoor Type Up to 15 KV Primary	4-28
Transformers Outdoor Type Up to 15 KV Primary, Unload, Inspect and Handling Labor Only	<b>(Updated)</b> 11-19
Transformers Single Phase Floor Mounted Up to 600 V Primary	4-29
Transformers Single Phase Wall Mounted Up to 600 V Primary	4-29
Transformers Three Phase Floor Mounted Up to 600 V Primary	4-29
Transformers Three Phase Wall Mounted Up to 600 V Primary	4-29
Trapeze Hangers without Beam Clamps or Inserts	2-95
Tree Trunk Protection	<b>(Updated)</b> 11-48
Trench Duct	2-56
Trench Duct	<b>(Updated)</b> 11-30
Trench Duct Cover Plates	2-56
Trench Duct Crosses	2-56
Trench Duct Elbows	2-56
Trench Duct Tees	2-56
Trench Duct Wall Elbows & Panel Risers	2-56
Tri-line Conductor to Ground Rod	8-8
Trim Tree For Lighting Fixture Installation	11-42
Trimmed Out Pole with 2 Cross Arms, 3-HV, Ins., Hdwe, & Power Augered Hole	11-14
Trimmed-Out Pole in Place with 1-Cross Arm, 3-Pin Insulators, Hdwe & Pwr Augered Hose	11-14
Trolley Busway	3-35
Trolley Busway Curve Sections	3-36
Trolley Busway Feed Boxes	3-36
Trolley Busway Track Switches	3-36
TVSS - Serviceable Unit - Disconnect Type	4-39
TVSS - Serviceable Unit - Lug Type	4-39
TVSS Includes Nipples/Knock Outs/Mounting Brackets/Terminations	4-39
TVSS Self Contained Unit - Lug Type	4-39
Twisted Pair Cable - Outdoor Aerial (OSP)	1-22
Twisted Pair Cable - Outdoor Direct Burial (OSP) Not Including Trenching	1-22
Twisted Pair Cable - Outdoor Underground In Conduit (OSP)	1-22
Twisted Pair Cable - Riser Cable (Metal Jacket in Conduit)	1-22
Twisted Pair Cable - Riser Cable Metal Jacket w/o Conduit	1-22



## Index

Two Hole Conduit Straps	2-93
Two Or More Pad Mounted Transformers - Pole Type Transformers	11-35
Two Or More Pole Mounted Transformers	11-34
U-Bolts	2-94
Under Counter Lights	<b>(Updated)</b> 5-7
Undercarpet Telephone and Data Flat Cable - Junction Box	3-18
Underfloor Duct	2-54
Underfloor Duct Accessories	2-55
Underfloor Duct Outlet Receptacles	2-55
Uninterruptible Power Supply Up to 600 Volt Self Contained	4-39
Unirack Mono-Pole	14-6
UPS Systems - Battery Charging Unit - Rack Mounted	4-40
UPS Systems - Battery Cycle Monitor	4-40
UPS Systems - Battery Disconnect Switch	4-40
UPS Systems - Battery Monitoring System	4-41
UPS Systems - Battery Racks	4-40
UPS Systems - Control Cabinet	4-40
UPS Systems - Hydrogen Detection System	4-41
UPS Systems - Power Distribution Units - PDU's 208/480V Input	4-41
UPS Systems - Remote Distribution Cabinets - RDC's / RPP's	4-41
UPS Systems - Remote Status Panel	4-41
UPS Systems - Single Phase 120V	4-39
UPS Systems - Spill Containment System	4-40
UPS Systems - Static Transfer Switch & PDU Combined	4-41
UPS Systems - Static Transfer Switches	4-41
UPS Systems - Three Phase 120/208V with Internal batteries	4-39
UPS Systems - Three Phase 208V - System Control Cabinet w/o Internal Batteries	4-39
UPS Systems - Three Phase Maintenance Bypass Cabinet (MBC)	4-39
UPS Systems - Three Phase Sealed Battery Cabinets on a maximum battery time of 30 minutes	4-40
UPS Systems - Three Phase Single Module Systems	4-40
UPS Systems - Three Phase System Control Cabinets - 208V or 480V	4-39
UPS Systems - Wet-Cell Battery	4-40
Vehicle Detection	11-11
Vert 2x12's Both Sides - 2x8 Horiz Headers & Steel Trench Jacks	11-20
Walk Way Lighting	5-15
Walk Way Lighting - Concrete Posts - Direct Bury	5-15
Walk Way Lighting - Hollow Wood Posts - Direct Bury	5-15
Walk Way Lighting - Post Mounted H.I.D. Fixture	5-15
Walkway Lighting - Steel and Aluminum Poles	5-14
Wall Mount Electric Vehicle Supply Equipment (EVSE)	14-9
Wall Mounted Incandescent	5-14
Wall Mounted Racks / Cabinets (Assemble and Mount)	1-23
Wall Mounted Watthour Meter & Main Breaker	10-5
Wall Mounted Watthour Meter with 20 Amp Branch Circuit Breakers	10-5
Wall Mounted Watthour Sockets & Meters	10-5
Wall Mounted WP Box & 20 Amp Snap Switch	10-8
Wall Packs - Wall Mounted	5-10
Wall Sconce / Vanity Light	<b>(Updated)</b> 5-9
Water Radiator	4-38
Waterproof Covers	6-8
Watershed Protection	11-48
Weatherproof Aluminum Boxes 1-Gang	2-30
Weatherproof Fluorescent Fixture - Outdoor	5-8
Wind Generation	14-7
Wire Connectors (Wire Nuts)	3-18
Wire Identification	3-18
Wire Managers	1-23
Wire Reinforcing Mesh In Concrete Slabs	11-22

## Index

Wiremold Product - 5' lengths only	2-46
Wiremold Product - 8' Lengths only	2-47
Wiremold Product - 8' Lengths only	2-47
Wiremold Product - Available in 6' and 8' lengths	2-46
Wiremold Product - Cablesmart series for power and low voltage applications - 8' lengths only	2-48
Wiremold Product - Large cable capacity for power and low voltage applications - 8' lengths only	2-49
Wiremold Product - Power and low voltage applications - 8' lengths only	2-48
Wiremold Product - Power and low voltage applications - Available in 8' and 10' lengths	2-48
Wiring Device Cover Plates	6-7
Wiring Device Cover Plates - Decorative & Engraved	6-7
Wood Forms For Concrete Slabs	11-21
Wood or Plastic Molding Over Grounding Conductors	11-16
Wood Pole Butt Plates	11-16
Wood Pole Installation	11-15
Wood Poles - Adder for Setting In Rock	11-31
Wood Poles - Cedar or Pine	11-31
Work Area Terminations	1-24
Wrap Around Light Fixture	5-5

**(Updated)**